

Experimental methods

for engineers



J. P. Holman Associate Professor of Mechanical Engineering Southern Methodist University

INTERNATIONAL STUDENT EDITION

McGRAW-HILL BOOK COMPANY
new york st. louis san francisco tondon mexico sydney toronto
KÖGAKUSHA COMPANY, LTD.
tokyo

INTERNATIONAL STUDENT EDITION

Exclusive rights by Kōgakusha Co., Ltd. for manufacture and export from Japan. This book cannot be re-exported from the country to which it is consigned by Kōgakusha Co., Ltd. or by McGraw-Hill Book Company, Inc. or any of its subsidiaries.

Copyright © 1966 by McGraw-Hill, Inc. All Rights Reserved. This book, or parts thereof, may not be reproduced in any form without permission of the publishers. Library of Congress Catalog Card Number 65-25513



in a lecture session. The lectures would be concerned with the principles of instrumentation, whereas the laboratory periods would afford the student an opportunity to use some of the devices discussed in this text. The particular experiments, or the instruments used in the laboratory periods, will depend on the facilities available. A mathematical background through ordinary differential equations is assumed. Basic courses in thermodynamics, engineering mechanics, and electric-circuit theory should precede a course based on this text.

Whatever the course arrangement for which this text is applied, it is strongly recommended that the problems at the end of each chapter receive careful attention. These problems force the student to examine several instruments in order to determine their accuracy and the uncertainties which might result from faulty measurement techniques. In many instances the problems are very similar to numerical examples in the text. Other problems require the student to extend the text material through derivations, design of experiments, etc. The selection of problems for a typical course will depend, naturally, on the types of experiments and laboratory facilities available for use with the course.

A few remarks concerning the arrangement of the text material are in order. A brief presentation of all topics was desired, so that a rather broad range of experimental methods could be discussed within the framework of a book suitable in length for a one-semester course. Chapters 1 and 2 provide the mitial motivational remarks and some brief definitions of important terms common to all measurement systems. Next, a simple presentation of some of the principles of statistical data analysis is given in Chap. 3. Some of the concepts in Chap. 3 are used in almost every subsequent chapter in the book, particularly the concept of experimental uncertainty.

Chapter 4 discusses several simple electrical-measurement circuits and the principles of operation of typical electric transducers. Many of these transducers are applicable to specific measurement problems described in later chapters. Chapters 5 and 6, concerning dimensional and pressure measurements, offer fairly conventional presentations of their subject matter, except that numerical examples and problems are included to emphasize the importance of experimental uncertainty in the various devices. Flow measurement is discussed in Chap. 7 in a rather conventional manner. A notable feature of this chapter is the section on flow-visualization techniques. Again, the examples and problems illustrate some of the advantages and shortcomings of the various experimental techniques. Chapter 8 is quite specific in its discussion of temperature-measurement devices. Strong emphasis is placed on the errors

which may arise from conduction, convection, and radiation heat transfer between the temperature-sensing device and its thermal environment. Methods are given to correct for these effects.

Chapter 9 is brief but furnishes the reader with an insight into the problems associated with transport-properly measurements. The material in this chapter is dependent on the measurement techniques discussed in Chaps 6, 7, and 8. It may be noted that the material in Chap 9 could be dispersed through the three previous chapters and still achieve a balanced presentation, however, it was believed best to bring transport properties and thermal measurements into sharper focus by grouping them together in one chapter ments into sharper focus by grouping them together in one chapter.

Static force, torque, and strain measurements are discussed in Chap. 10. The atrain measurements are related to some elementary principles of experimental atress analysis, and the operation of the

electrical-resistance atrain gage is emphasized

Some of the elementary principles of motion- and vibrationmeasurement devices are discussed in Chap. 11 Included in this presentation is a discussion of sound waves and sound-pressure level The inclusion of the acoustics material in Chap 11 is somewhat arbitrary since this material would be equally pertinent in Chap 6

Chapter 12 discusses thermal and nuclear radiation measurements. These measurements are finding increasingly wide application in a number of industries. The presentation is birel; but some of the more important detection techniques are examined, and examples are given to illustrate the important principles. A short presentation of the statistics of counting illustrates the importance of background activity in nuclear radiation detection. The thermal radiation measurements are properly related to the material in Chap. 8. Chapter 13 gives a short, nonanalytical discussion is some typical industrial control arrangements. The discussion is a cursory one, but it serves to illustrate the important role of primary measurements in a control scheme and to familiarize the reader with some of the terminology of control systems.

Electronic data-acquisition and processing systems are being developed at a very rapid rate, so rapid in fact that the presentation in Chap, 14 had to be given in a very general manner of specific systems would be outdated in short order. A discussion of specific systems would be outdated in short order. Nevertheless, it is believed that this bird fisus uson will alert the reader to the importance of data-acquisition systems in modern experimental programs.

The author is particularly grateful to Professor S. J. Khine of Stanford University for reading the complete manuscript and making many helpful suggestions. Grateful acknowledgement is also extended to Dr. C. A. Albintton and the Science Information Insti-

Contents

Pr	eface	v		
1	Intro	duction 1		
2	Basic	concepts 7		
		Introduction		
	2-2	Definition of terms		
	2-3	Calibration		
		Standards		
	2-5	The generalized measurement system		1
		Basic concepts in dynamic measurements		,
	2-7	System response		2
	2-8	Distortion		2 2 2
	2-9	Impedance matching		2
	2-10	Experiment planning		2
3,	Analy	rsis of experimental data 33		
~	3-1	Introduction		3
		Causes and types of experimental errors		3
		Error analysis on a "commonsense" basis		
		Uncertainty analysis		3
		Statistical analysis of experimental data		4
		Probability distributions		4
	.3-7	The Gaussian or normal error distribution		4
	3-8	The Chi-square test of goodness of fit		5
	.3-9	Method of least squares		6
	3-10	Standard deviation of the mean		5
	3-11	Graphical analysis and curve fitting		6
4	Basic	electrical measurements and sensing devices	75	
	4-1	Introduction		7
	4-2	The measurement of current		7.
	4-3	Voltmeters		8
	4-4	Basic input circuitry		8
	4-5	Bridge circuits		8
	4-6	Filter eurcusts		9
	4-7	The vacuum-tube voltmeter (VTVM)		10
	4-8	The oscilloscope		10.

·	
4-9 Oscillographs	
4-10 Counters, time, and frequency measurements	
4-11 Transducers and electric sensing devices	
4-12 Variable-resistance transducer	
-4-13 The differential transformer :LVDT)	
4-14 Capacitive transducers	
4-15 Piczoelectrie transducers	
4-16 Photoelectric effects	
4-17 Photoconductive transducers	
4-18 Photovoltaic cells	
4-19 Ionization transducer	
4-20 Magnetometer search con	
4-21 Hall-effect transducers	
5 Displacement and area measurements 135	
5-1 Introduction	
5-2 Dimensional measurement.	
5-3 Gage blocks	
5-4 Optical methods	
5-5 Pneumatic displacement gage	
5-6 Area measurements	
5-7 The planumeter	
5-8 Graphical and numerical methods for area measurement	at
5-9 Surface areas	
6 / Pressure measurements 153	
6-1 Introduction	
6-2 Dynamic response considerations	
6-3 Mechanical pressure-measurement devices	
6-4 Dead-weight tester	
6-5 Bourdor-tube neesure gage	
8-6 Diaphy on and tollows gages	
6-7 The Bringman g-ge	
6-8 Low-pressure are, createst	
6-9 The McLead gage	
6-10 Pirani thermal-conductivity gage	
6-11 The Knudsen gage	
6-12 The ionization gage	
6-13 The Alphatron	
6-14 Summary	
7 Flow measurement 177	
7-1 Introduction	
7-2 Positive-displacement methods	
7-3 Flow-obstruction methods	
7-4 Practical considerations for obstruction meters	
7-5 The sonic nozzle	
7-6 Flow measurement by drag effects	
7-7 Hot-wire anemometer	

Contents

203

205

7-10 The shadowgraph	206
7-11 The Schlieren	209
7-12 The interferometer	211
7-13 Smoke methods	215
7-14 Pressure probes	216
7-15 Impact pressure in supersonse flow	221
7-16 Summary	222
The measurement of temperature 229	
8-1 Introduction	229
8-2 Temperature scales	229
8-3 Temperature measurement by mechanical effects	231
8-4 Temperature measurement by electrical effects	235
8-5 Temperature measurement by radiation	251
8-6 Effect of heat transfer on temperature measurement	257
8-7 Transient response of thermal systems	264
8-8 Thermocouple compensation	264
8-9 High-speed temperature measurements	269
8-10 Summary	270
9 Thermal- and transport-property measurements 27	3
9-1 Introduction	279
Thermal-conductivity measurements	280
38 Thermal conductivity of liquids and gases	255
Measurement of viscosity	297
9-5 Gas diffusion	293
9-6 Calorimetry	297
9-7 Convection heat-transfer measurements	302
10 Force, torque, and strain measurements 311	
10-1 Introduction	311
10-2 Mass balance measurements	312
10-3 Elastic elements for force measurements	316
194 Torque messurements	319
10-5 Stress and strain	322
10-6 Strain measurements	323
10-7 Electrical-resistance strain gages	325
10-8 Measurement of resustance strain-gage outputs	329
10-9 Temperature compensation	330
10-10 Strain-gage rosettes	332
10-11 The unbonded-resistance strain gage	335
11 Motion and vibration measurament 339	
11-1 Introduction	339
11-2 Two simple vibration instruments	339
11-3 Principles of the seismic instrument	342
11-4 Practical consuderations for seismic matruments	349

7-8 Magnetie flowmeters

7-9 Flow-visualization methods

12	Therr	nal and nuclear radiation measurements 359	
	12-1	Introduction	359
	12-2	Detection of thermal radiation	359
	12-3	Measurement of emissivity	365
	12-4	Nuclear radiation	367
	12-5	Detection of nuclear radiation	368
	12-6	The Geiger-Müller counter	368
	12-7	Ionization chambers	370
	12-8	Photographie detection methods	371
		The seintillation counter	371
	12-10	Neutron detection	372
	12-11	Statisties of counting	373
13	Basic	industrial control arrangements 381	
	13-1	Introduction	381
	13-2	On-off or two-position control	383
	13-3	Floating control	384
	13-4	Proportional control	384
	13-5	Rate netion .	387
14	Data	acquisition and processing 393	
	14-1	Introduction	393
	14-2	The general acquisition system	393
	14-3	Data processing	395
	14-4	Summary	397
Ap	pendix	399	
	A-1	Conversion factors	399
	A-2	Properties of metals at 70°F	400
	A-3	Thermal properties of some nonmetals at 70°F	400
	A-4	Properties of some saturated liquids at 68°F	400
	A~5	Properties of gases at atmospherie pressure and 65°F	401
	A-6	Properties of dry air at atmospheric pressure	401
	A-7	Properties of water (saturated liquid)	402
	A-8	Diffusion coefficients of some gases and vapors in air at 25°C and I atm	
	A-9		403
	M-3	Approximate total normal emissivities of various surfaces at 70°F	
	8.40		403
		Area moments of inertia for some common geometric shapes	404
no	iex	405	

:



Introduction

There is no such thing as an easy experiment, nor is there any substitute for careful experimentation in many areas of basic research and applied product development. Because experimentation is or important in all phases of engineering, there is a very definite need for the engineer to be familiar with methods of measurement as well as analysis techniques for nuterpeting experimental dats.

Experimental techniques have changed quite rapidly with the development of electronic devices for sensing prinary physical parameters and for controlling process variables. It imany instances more precision is now possible in the ineasitement of basic physical quantities through the use of these new devices. Further development in instrumentation techniques is certain to be very rapid breause of the increasing demand for measurement and control of physical variables in a wide variety of applications. To meet this demand the engineer must be familiar with the basic principles of instrumentation and the ideas which govern instrumentation development and usage.

Obviously, a sound knowledge of many engineering principles is necessary to perform successful experiments; it is for this reason that experimentation is so difficult. To design the experiment the engineer must be able to specify the physical variables which he needs to investigate and the role they will play in later analytical work. Then, to design or procure the instrumentation for the experiment he must have a knowledge of the governing principles of a broad range of instruments. Finally, to analyze his data the experimental engineer must have a combination of keen insight into the physical principles of the processes he is investigating and a knowledge of the limitations of his data.

Research involves a combination of analytical and experimental work. The theoretician strives to explain or predict the results of experiments on the basis of analytical models which are in accordance

error with very little analytical work as a preliminary to the experimentation. There are some older areas of engineering where this technique will still prevail, primarily where years of experience have built up a background knowledge to rely upon. But, in new fields, more emphases must be placed on a combination of theory and experimentation. To create a rather absurd example we might cit the development of a rocket engine. It would be possible to huild different axes of rockets and test them until a lucky combination of design parameters was found, however, the rost would be probabite. The proper approach is one of test and theoretical study where experimental data are constantly evaluated and compared with theoretical estimates. New theories are formulated on the lasts of the experimental measurements, and these theories help to guide further tests and the final desern

The engineer should know what he is looking for before beginmin experiments. The objective of the experiments will dietate
the accuracy required, expense justified, and level of luman effort
necessary. A simple calibration check of a microury-in-glass
thermometer would be a relatively simple matter requiring a limited
amount of equipment and time, however, the accurate measurement
of the temperature of a high-speed gas stream at 3000°F would
involve more thought and care. A test of an amphifier for a home
music system might be less exacting than a test of an amphifier to be
used as part of the electronic equipment in a satellite, and so on
The engineer is not only interested in the measurement of

physical variables but is also concerned with their control. The two functions are closely related, however, because one must be able to measure a variable such as temperature or flow in order to control! The accuracy of control is necessarily dependent on the accuracy of measurement. Hence, we see that a good knowledge of measurement techniques is necessary for the design of control systems. A detailed consideration of control systems is beyond the grope of our discussion, but the applicability of specific instruments and sensing devices to control systems will be indicated from time to time.

It is not enough for the engineer to be able to skillfully measure certain physical variables. For the data to have maximum rightscance he must be able to specify the precise degree of securary with which he has measured a certain variable. To specify this accuracy the limitations of the appearatus must be understood substitute accuracy the limitations of the appearatus must be understood substitute accuracy to the substitute of certain random and/or regular errors which may occur in the experimental data. Statistical techniques are available for analyzing data to determine expected errors and deviations from the true measurement. The engineer must be familiar with these techniques in order to analyze his data effectively

All too frequently the engineer embarks on an experimental program in a stumbling blind-faith manner. Data are collected at random, many of which are not needed for later analysis. Certain ranges of operation are not investigated thoroughly enough, resulting in the collection of data which may have limited correlative value. The engineer must be sure to take enough data, but he should not waste time and money by taking too many. point is that experiments should be carefully planned. experimentalists do indeed plan tests in respect to the range of certain variables that they will want to investigate. But they often neglect the fact that in certain ranges of operation more data points may be necessary than in others in order to ensure the same degree of accuracy in the final data evaluation. In other words, the anticipated methods of data analysis, statistical or otherwise, should be taken into account in planning the experiment, just as one would take into account certain variables in designing the physical size of the experimental apparatus. The engineer should always ask the question: How many data do I need to ensure that my data are not just the result of luck? We will have more to say about experiment planning throughout the book, and the reader should consider these opening remarks as only the initial motivation.

A few remarks concerning experimental research are in order at this point. It is very difficult to describe the atmosphere and technique of performing research. For, unlike standard performance testing where experiments are conducted according to some wellestablished procedure, in research there is seldom a clear-cut way of proceeding. Each problem is a different one, and if the research is worthwhile, it has not been attacked extensively before. This means that the engineer engaged in research must be prepared to face numerous experimental difficulties of varying complexities. Some desirable objectives of the research may have to be relaxed because of the unavailability of instrumentation to measure the variables involved. Many seemingly trivial details become significant problems before a new experimental apparatus is functioning properly. One of the most basic problems is that the engineer seldom gets to measure in a direct manner the variable he really wants. always corrections to apply to the measurements, and seldom do they fall in the category of "standard" corrections. detail piles on another until the whole experimental problem takes on a complexity which is usually not anticipated at the start of the research. Again we state the truism: there is no such thing as an casy experiment.


The neophyte experimentalist frequently assumes that a certain experiment will be easy to perform. All he need do is hook up the

apparatus, flip the awitch, and out will come reams of significant data which will startle his colleagues for supervisor). He does not realize that one simple instrument may not work, and thus spoil the experiment. Once this instrument is functioning properly, another may go bad, and so on. When the apparatus is functioning, the neophyte is then tempted to take data at random without giving much consideration to the results that he will want to derive from the data. It tries to solve all problems at once, vary many parameters at the same time, so that little control is exerted on the data, and it eventually becomes necessary to go back and do some of the work over. The important point, once again, is that careful planing is called for. In experimental research great care and patience will usually broduce the best results in the authers possible way.

All the above remarks may appear discouraging to the beginner for whom this book is written. On the contrary, they are intended to advise the beginner so that he can avoid some of the more obyous pitfalls. And, even more important, they are intended to let the beginner know that some troubles are to be expected and that perseverance in the face of these troubles combined with intelligent planning will almost always lead to the desired results—accurate and meanineful data.

The objective of the presentation in this book is to impart a broad knowledge of experimental methods and measurement techniques. To accomplish this objective a rather large number of instruments will be discussed from the standpoint of both theory of operation and specific functional characteristics. Emphasis will be placed on analytical calculations to familiarize the reader with important points in the theoretical development as well as in the descriptive information perfaming to operating characteristics. As a further means of emphasizing the discussions, the uncertainties which may arise in the various instruments are given particular attention.

The study of experimental methods is a necessary extension of analytical ambjects. A knowledge of the methods of verifying analytical work injects new his end vitably into the theories, and a clear understanding of the difficulties of experimental measurements creates a careful attitude in the theoretician which cannot be generated in any other way.



Basic concepts

2-1 INTRODUCTION

In this chapter we seek to explain some of the terminology used in experimental methods and to show the generalized arrangement of an experimental system. We shall also discuss briefly the clandards which are available and the importance of calibration in any experimental measurement. A major portion of the discussion on experimental errors is deferred until Chap. 3, and only the definition of certain terms is given here.

2-2 DEFINITION OF TERMS

We are frequently concerned with the readability of an instrument. This term indicates the closeness with which the scale of the instrument may be read, an instrument with a 12-m scale would have a higher readability than an instrument with a 6-m scale and the same range. The least count is the smallest difference between two indications that can be detected on the instrument scale. Both readability and least count are dependent on scale length, sparing of graduations, size of pointer (or pen if a recorder is used), and parallax effects.

The sensitivity of an instrument is the ratio of the linear covement of the pointer on the instrument to the charge in the resident variable caseing this motion. For example, a lent recorder right have a 10-in, seale length. Its sensitivity would be 10 in /rv assuming that the measurement was linear all arries the reale

An instrument is said to exhibit hydreness when there is a difference in readings depending on whether the value of the measured quantity is approached from above or below. Hydreness may be the result of mechanical friction, magnetic effects, clastic deformation, or thermal effects.

The accuracy of an instrument indicates the deviation of the reading from a known input. Accuracy is usually expressed as a percentage of full-scale reading so that a 100-psi pressure gage having an accuracy of 1 percent would be accurate within ±1 psi over the entire range of the gage.

The precision of an instrument indicates its ability to reproduce a certain reading with a given accuracy. As an example of the distinction between precision and accuracy, consider the measurement of a known voltage of 100 volts with a certain meter. readings are taken, and the indicated values are 104, 103, 105, 103, and 105 volts. From these values it is seen that the instrument could not be depended on for an accuracy of better than 5 percent (5 volts), while a precision of ±1 percent is indicated, since the maximum deviation from the mean reading of 104 volts is only 1 volt. It may be noted that the instrument could be calibrated so that it could be used to dependably measure voltages within ±1 volt. This simple example illustrates an important point. Accuracy can be improved up to but not beyond the precision of the instrument by calibration. The precision of an instrument is usually subject to many complicated factors and requires special techniques of analysis, which will be discussed in Chap. 3.

2-3 CALIBRATION

The ealibration of all instruments is important, for it affords the opportunity to check the instrument against a known standard and subsequently to reduce errors in accuracy. Calibration procedures involve a comparison of the particular instrument with either (1) a primary standard, (2) a secondary standard with a higher accuracy than the instrument to be ealibrated, or (3) a known input source. For example, a flowmeter might be calibrated by (1) comparing it with a standard flow-measurement facility of the National Bureau of Standards, (2) comparing it with another flowmeter of known accuracy, or (3) direct calibration with a primary measurement such as weighing a certain amount of water in a tank and recording the time clapsed for this quantity to flow through the meter. In item (2), the key words are "known accuracy." The meaning here is that the accuracy of the meter must be specified by a reputable source.

The importance of calibration cannot be overemphasized because it is calibration which firmly establishes the accuracy of the instruments. Rather than accept the reading of an instrument, it is insually best to make at least a simple calibration check to be sure of the validity of the measurements. Not even manufacturers' specifications or calibrations can always be taken at face value Most instrument manufacturers are reliable; some, alse, are not. We shall be able to give more information on calibration include throughout the book as various instruments and their accuracies are discussed.

2-4 STANDARDS

In order that investigators in different parts of the country and different parts of the world may compare the results of their experiments on a consistent basis, at is necessary to establish certain standard units of length, weight, time, temperature, and electrical quantities. The National Bureau of Standards has the primary responsibility or maintaining these standards in the United States.

The meter and the kilogram are considered fundamental units upon which, through appropriate conversion factors, the English system of length and mass is based. The standard meter is defined as the length of a platinum-indimin bar maintained at very accurate conditions at the International Bureau of Weights and Mesaures in Skyres, France. Similarly, the kilogram is defined in terins of a platinum-indium mass maintained at this same bureau. The conversion factors for the English and metire systems in the United States are fixed by faw as

1 meter = 39.37 inches 1 pound mass = 453.5921277 grams

Secondary standards of length and mass are maintained at the Normal Bureau of Standards for calibration purposes. In 1960 the General Conference on Weights and Measures defined the standard nieter in terms of the wavelength of the orange-red light of a krypton-86 lamp. The standard meter is thus.

1 meter = 1,650,763.73 wavelengths

The inch is exactly defined as

l inch = 254 centimeters

Standard units of time are established in terms of known frequencies of oscillation of certain devices. One of the simplest devices is a pendulum. A torsional vibrational system may also be used as a

standard of frequency. The torsional system is widely used in clocks and watches. Ordinary 69-cycle line voltage may be used as a frequency standard under certain circumstances. An electric clock uses this frequency as a standard because it operates from a synchronous electric motor whose speed depends on line frequency. A tuning fork is a suitable frequency source, as are piezoelectric crystals. Electronic oscillators may also be designed to serve as very precise frequency sources.

The fundamental unit of time, the second, is defined as 1/86,400 of a mean solar day. The solar day is measured as the time interval between two successive transits of the sun across a meridian of the earth. The time interval varies with location on the earth and time of year; however, the mean solar day for one year is constant. The solar year is the time required for the earth to make one revolution around the sun. The mean solar year is 365 days 5 hr 48 min 48 sec.

Very precise frequency and time standards are broadcast by the National Bureau of mandards' radio station, WWV. This station furnishes mandard time intervals, time signals, standard musical pitch, mandard radio frequencies, and radio-propagation forecasts. The entercy of the radio and audio frequencies as transmitted is better than 1 part in 100,000,000, and the time interval is accurate to 1 part in 100,000,000 \pm 1 pages.

Standard units of electrical quantities are derivable from the mechanical units of force, mass, length, and time. These units represent the absolute electrical units and differ eligibly from the international system of electrical units established in 1948. A detailed description of the international system is given in Refs. [1] and [2]. The main advantage of this system is that it affords the establishment of a standard cell, the output of which may be directly related to the absolute electrical units. The conversion from the international system is established by the following relations:

1 international ohm = 1.00049 absolute ohme 1 international volt = 1.000330 absolute volts 1 international ampere = 0.99335 absolute ampere

Laboratory calibration is usually made with the aid of secondary standards such as standard calls for voltage sources and standard resistors as standards of comparison for measurement of electrical resistance.

An absolute temperature scale was proposed by Lord Kelvin in 1854. It forms the basis for thermodynamic calculations. This absolute scale is so defined that particular meaning is given to the

Table 2-1 Primary points for the International temperature scale of 1948

Point al standard pressure = 14 6959 pera	Temperature			
Table person	·F	7.	**	
Oxygen point Temperature of equilibrium between oxygen and its vapor	~297 346	-182 970	90 19	
Ice point. Temperature at equilibrium between ice and air- saturated water	32 0	0	273 16	
Steam point. Temperature at equilibrium between liquid water and its copor	212 0	1000	373 16	
Sulfur point. Temperature at equilibrium between liquid rulfur and its sapor	832 29	444 6	717 76	
Silver point Temperature of equilibrium between solid and liquid either	1761 4	960 8	1233 96	
Gold point. Temperature of equilibrium between solid and liquid sold.	1945 4	1003 0	1336 16	

Table 2-2 Secondary fixed points for the International temperature scale of 1943

Point	Temperature, *C
Equilibrium between solid earbon dioxide and its caper	-78 5
Freezing mercury	-33 87
Equilibrium between see, water, and its espor (triple point)	+0 0100
Freezing lin	231 9
Freezing cadmium	320 9
Freezing lead	327 3
Equilibrium between mercury and its capor	356 55
Freezing zinc	419 5
Freezing antimony	630 S
Freezing aluminum	660 1
Preezing copper in a reducing atmosphere	1083
Freezing nickel	1453
Freezing cobalt	1492
Freezing platinum	1769
Freezing rhodium	1960
Freezing sridsum	2443
Melting tungsten	3950

second law of thermodynamies when this temperature scale is used. The International Temperature Scale of 1948 [6] furnishes an experimental basis for a temperature scale which approximates as closely as possible the absolute thermodynamic temperature scale. In the international scale, six primary points are established as shown in Table 2-1. Secondary fixed points are also established as given in Table 2-2. In addition to the fixed points, precise procedures are

Table 2-3 Interpolation procedures for the international temperature scale of 1948

Range definition	Temperature, °C	Procedure		
Between ice point and freezing point of anti- mony	0-630.5	Based on resistance of platinum resistance thermometer: $R_t = R_0(1 + AT + BT^2)$ $R_t = \text{resistance at temperature } T$, ohms $R_0 = \text{resistance at 0°C}$, ohms. $A, B = \text{constants determined from measured}$ values of R_t at steam and sulfur points $T = \text{temperature}$		
Between oxygen and ice points	182.97-0	Based on resistance of platinum resistance thermometer: $R_T \approx R_0[1 + AT + BT^2 + C(T - 100)T^3]$ $C \approx$ a constant determined from resistance at the oxygen point $A, B, R_0 \approx$ same constants as above		
Between freezing point of antimony and gold point	630 5~1063 0	Standard thermocouple of platinum and platinum-10% rhodium: E = a + bT + cT² E = emf of thermocouple when one junction is at 0°C and the other at temperature T T = temperature in specified range a, b, c = constants determined from emf data taken at antimony, silver, and gold points		
Abore gold point	Above 1063.0	Temperature defined by: $\frac{J_t}{J_{Au}} = \frac{e^{C_t h(T_{Au} + T_0)} - 1}{e^{C_t h(T_{Au} + T_0)} - 1}$ $J_t, J_{Au} = \text{radiant energy emitted per unit time, per unit area, and per unit wavelength at wavelength \lambda, at temperature T, and gold point temperature T_{Au} respectively. C_2 = 1.438 \text{ cm} - \text{°K} T_0 = 273.16 \text{°K} \lambda = \text{wavelength}$		

established for interpolating between these points. These interpolation procedures are given in Table 2-3.

Eshbaeh [3] gives a detailed discussion of various electrical and thermal units. The absolute thermodynamic temperature scale is discussed by Obert [4], and Constant [5] gives an excellent discussion of electromagnetic units and concepts.

1-5 THE GENERALIZED MEASUREMENT SYSTEM

How wereinguistic elegions and he have the training of the first angle

- 3. A forest terminalism state which drive to the television is not used and performs which a methanism courseless of the content of the content of the state of the content of the state of the content of the state of the content of the content
- 2. Some intermediate many within modifies the dipological by amplitudes directly of their means on the algorithm of the intermediate.
- & A final or terminating out which arise to the control of control the variable beautiful and defined.

As a example of a treatment of a low-voltage signs as a respectly 1 to the same may be just two when the consolidate signs as a respectly 1 to the same may be just two when the consolidate signs as the commands of the same to indicate or record the way as the promotes application. The same application of the same as the consolidate shows the final same application of the same as the consolidate in the same with the output voltage of the amplitude of the same as the consolidate of the same as the consolidate of the same same as the instrument by varying the input could not so the same for the instrument by varying the input, could not so to the amplifier.

Consider the simple bourdon-tube pressure gage shown in Fig. 2-1. This gage offers another excurate the pressure gage shown in Fig. 2-1. This gage offers another excurate the pressure sign desired in extractive ment system. In this case the luminon tube is the detection-trained duest stage because it converts the pressure sign desired a mechanical displacement of the tube for the tuber amplitus sine displacement of the rund of the tube so that a relatively small displacement at that point the tube so that a relatively small displacement at that point gear. The final indicator stage consists of the positive and the dial arrangement, which, when cabbrated with known pressure liquid, gives an indication of the pressure signal impressed on the boundon tube. A schematic diagram of the generalized measurement system is shown in Fig. 2-2.




Fig. 2-1. Bourdon-tube pressure gage as the generalized measurement system.

When a control device is used for the final measurement stage, it is necessary to apply some feedback signal to the input signal to accomplish the control objectives. The control stage compares the signal representing the measured variable with some other signal in the same form representing the assigned value the measured variable




Fig. 2-2. Schematic of the generalized measurement system.

abould hare. The assigned value is given by a predetermined setting of the controller. If the measured signal agrees with the predetermined setting, then the controller does nothing. If the signals do not agree, the controller issues a signal to a device which acts to alter the value of the measured variable. This device can be many things, depending on the variable which is to be controlled. If the measured variable is the flow rate of a fluid, the control device might be a motorized valve placed in the flow system. If the measured flow rate is too high, then the cootroller would cause the motorized valve to close, thereby reducing the flow rate. If the flow rate were too low, the valve would be opened. Eventually the operation would cease when the desired flow rate was achieved. The control feedback function is indicated in Fig. 2-2.

It is very important to realize that the accuracy of control cannot be any better than the accuracy of the measurement of the control variable. Therefore, one must be able to measure a physical variable accurately before he can hope to control the variable. In the flow system mentioned above, the most elaborate controller could not control the flow rate any more closely than the accuracy with which the primary sensing element measures the flow. We shall have more to say about some simple control systems in a later chapter. For the present we want to emphasize the importance of the measurement system in any control setup.

The overall achematic of the generalized measurement system is quite aimple, and as one might suspect, the difficult problems are encountered when suitable devices are sought to fill the requirements for each of the "boxes" on the schematic diagram. Most of the remaining chapters of the book are concerned with the types of detectors, transducers, modifying stages, etc., which may be used to fill these boxes.

2-6 BASIC CONCEPTS IN DYNAMIC MEASUREMENTS

Many experimental measurements are taken under such circumstances that simple time is available for the measurement system to reach steady state, and hence one need not be concerned with the behavior under non-steady-state conditions. In many other situations, however, it may be desirable to determine the behavior of a physical variable over a period of time. Sometimes the time interval is abort, and sometimes it may be rather extended. In any event, the measurement problem usually becomes more complicated when the traouent characteristics of a system need to be considered. In




Fig. 2-3. Simple spring-mass damper system.

this section we wish to discuss some of the more important characteristics and parameters applicable to a measurement system under dynamic conditions. To initiate the discussion let us consider a simple spring-mass damper system as shown in Fig. 2-3. We might consider this as a simple mechanical-measurement system where $x_1(t)$ is the input displacement variable which acts through the spring-mass damper arrangement to produce an output displacement $x_2(t)$. Both x_1 and x_2 vary with time. Suppose we wish to find $x_2(t)$, knowing $x_1(t)$, m, k, and the damping constant c. We assume that the damping force is proportional to velocity so that the differential equation governing the system is obtained from Newton's second law of motion as

$$k(x_1 - x_2) + c \left(\frac{dx_1}{dl} - \frac{dx_2}{dl}\right) = m \frac{d^2x_2}{dl^2}$$
 (2-1)

Written in another form,

$$m\frac{d^2x_2}{dt^2} + c\frac{dx_1}{dt} + kx_2 = c\frac{dx_1}{dt} + kx_1 \tag{2-2}$$

Now suppose that $x_1(t)$ is the harmonic function

$$x_1(t) = x_0 \cos \omega_1 t \tag{2-3}$$

where x_0 is the amplitude of the displacement and ω_1 is the frequency. We might imagine this simple vibrational system as being similar to a simple spring scale. The mass of the scale is m, the spring inside the scale is represented by the spring constant k, and whatever mechanical friction may be present is represented by c. We are subjecting the scale to an oscillating-displacement function and wish to know how the body of the scale will respond, i.e., we want to know $x_2(t)$. We might imagine that the spring scale is shaken by hand. When the oscillation $x_1(t)$ is very slow, we would note that the scale body very nearly follows the applied oscillation. When the frequency of the oscillation is increased, the scale body will react




Fig. 2-S. Frequency response of the system in Fig. 2-L.




Fig. 2-6. Phase-shift characteristics of the system in Fig. 2-4.

systems as well, and whenever time-varying measurements are made, due consideration must be given to these characteristics. Ideally, we should like to have a system with a linear frequency response over all ranges and with zero phase shift, but this is never completely attainable, although a certain instrument may be linear over a range of operation in which we are interested so that the behavior is good enough for the purposes intended. There are methods of providing compensation for the adverse frequency-response characteristics of an instrument, but these methods represent an extensive subject in themselves and cannot be discussed here. We shall have something to say about the dynamic characteristics of specific instruments in subsequent chapters.

2-7 SYSTEM RESPONSE

We have already discussed the meaning of frequency response and observed that in order for a system to have good response it must treat all frequencies the same within the range of application so that the ratio of output-to-input amplitude remains the same over the frequency range desired. We say that the system has linear frequency response if it follows this behavior.

Amplitude response pertains to the ability of the system to react in a linear way to various input amplitudes. In order for the system to have linear amplitude response, the ratio of output-to-input amplitude should remain constant over some specified range of input amplitudes. When this linear range is exceeded, the system is said to be overdriven, as in the case of a voltage amplifier where too high an input voltage is used.

We have already noted the significance of phase-shift response and its relation to frequency response. Phase shift is particularly important where complex waveforms are concerned because severe distortion may result if the system has poor phase-shift response.

Suppose a step or instantaneous input signal is applied to a system. In general there will be a slight delay in the output response, and this delay is called the rise time or delay of the system. This phenomenon is illustrated in Fig. 2-7.

Many systems exhibit an exponential decay type of behavior. When a capacitor is discharged through a resistance as shown in Fig. 2-8, the voltage varies with time according to

$$\frac{E(t)}{E_0} = e^{-(1/RC)t} {(2-11)}$$




Fig. 2-7. Effect of rise time on output response to a step input.

where R is the value of the external resistance and C is the capacitance. The voltage across the capacitor as a function of time is E(t), and the initial voltage is \mathcal{E}_{t} . Some types of thermal systems also display this same kind of response. The temperature of a hot block of metal allowed to cool in a room varies with approximately the same kind of relation as shown in Eq. (2-11). For systems which have this kind of behavior we may note that when

$$t \approx RC$$
 (2-12)

the ratio E/B_c has a value of 36 8 percent of its initial value. Since the terms of Eq. (2-12) have the units of time, they are described as the time constant of the system. This meaning of time constant is carried into all types of systems, even those which do not have a simple behavior like Eq. (2-11). Thus, the time constant is usually taken as the time for the system to attain a state of 63 2 percent of its steady-state value. In the capacitance system we speak of voltage, in a thermal system we speak of temperature, and in some mechanical systems we might speak of voltagive or displacements.



Fig. 2-8. Capacitor discharging through a resistance,

ment as the physical variables which change with time. The time constant would then be related to the steady-state values of these variables.

2-8 DISTORTION

Suppose a harmonic function of a complicated nature, i.e., composed of many frequencies, is transmitted through the mechanical system of Figs. 2-3 and 2-4. If the frequency spectrum of the incoming waveform is sufficiently broad, there would be different amplitude and phase-shift characteristics for each of the input-frequency components and the output waveform might bear little resemblance to the input. Thus, as a result of the frequency-response characteristics of the system, distortion in the waveform would be experienced.




Fig. 2-9. Effects of frequency response and phase-shift response on complex waveform.

Distortion is a very general term which may be used to describe the variation of a signal from its true form. Depending on the system, the distortion may result from either poor frequency response or poor phase-shift response. In electronic devices various circuits are employed to reduce distortion to very small values. For mechanical systems the dynamic response characteristics are not as easily controlled and remain a subject for further development. The effects of poor frequency and phase-shift response on a complex waveform are illustrated in Fig. 2-9.

2-9 IMPEDANCE MATCHING

In many experimental setups it is necessary to connect various items of electrical equipment in order to perform the overall measurement objective. When connections are made between electrical devices, proper care must be taken to avoid impedance mismatching. The output impedance of a two-terminal device may be illustrated as in Fig. 2-10. The device behaves as if the internal resistance R_i were connected in sense with the internal voltage source E. The connecting terminals for the instrument are designated as A and B_i , and the open-circuit voltage presented at these terminals is the internal voltage E. Now, if an external load R is connected to the device and the internal voltage E remains constant, the voltage presented at the output terminals A and B will be dependent on the value of R. The potential presented at the output terminals is

$$E_{AB} = E \frac{R}{R + R}, \qquad (2-13)$$

The larger the value of R, the more closely the terminal voltage approaches the internal voltage E. Thus, if the device is used as a voltage source with some internal impedance (or load) should be large enough that the voltage is essentially preserved at the terminals. Or, if we wish to measure the internal voltage E, the impedance of the measuring device connected to the terminals should be large compared with the internal impedance.

Now suppose that we wish to deliver power from the device to the external load R. The power is given by

$$P = \frac{E_A s^4}{R}$$
(2-14)

We ask for the value of the external load which will give the maximum power for a constant internal voltage E and internal impedance






Fig. 2-10. Two-terminal device with internal imponance P_{μ} .

Ri. Equation (2-14) is rewritten

$$P = \frac{E^2}{R} \left(\frac{R}{R + R_1} \right)^2 \tag{2-15}$$

and the maximizing condition

$$\frac{dP}{dR} = 0 ag{2-16}$$

is applied. There results

$$R = R, (2-17)$$

That is, the maximum amount of power r sy be drawn from the device when the impedance of the external load just matches the internal impedance. This is the essential principle of impedance matching in electric circuits.

Clearly, the miserial impedance and external load of a complicated electronic components which is the important in a ctransmission and dissipation. Neverthelic and the important in a ctransmission and dissipation. Neverthelic and the important in a ctransmission and dissipation. Neverthelic and the indicates the same. The general principles of matching and the circ the external impedance should match the internal impolation of the external impedance should be large compared with the internal impedance when a measurement of internal voltage of the device is desired. It is this latter principle which makes a vacuum-tube voltmeter essential for measurement of voltages in electronic circuits. The vacuum-tube voltmeter has a very high internal impedance (greater than 10 megohms) so that little current is drawn and the voltage presented to the terminals of the instrument is not altered appreciably by the measurement process.

Impedance-matching problems are usually encountered in electrical systems but can be important in mechanical systems as well. We might, for example, imagine the simple spring-mass sys-

tem of the previous section as a mechanical transmission system. From the curves describing the system behavior it is seen that frequencies below a certain value are transmitted through the system, i.e., the force is converted to displacement with little attenuation. Near the natural frequency, undesirable amphification of the signal is performed, and above this frequency, severe attenuation is present. We might say that this aystem exhibits a behavior characteristic of a variable impedance which is frequency-dependent. When it is desired to transmit mechanical motion through a system, the natural-frequency and damping characteristics must be taken into account so that good "matching" is present. The problem is an impedance-matching situation, although it is usually treated as a subject in mechanical vibrations.

2-10 EXPERIMENT PLANNING

The key to success in experimental work is to ask continually. What am I looking for? Why am I measuring this—does the measurement really answer any of my questions? What does the measurement tell me? These questions may seem rather elementary, but they should be asked frequently throughout the progress of any experimental program. Some particular questions which should be asked in the unital phases of experiment planning are.

- 1. What primary variables shall be investigated?
- 2. What control must be exerted on the experiment?
- What ranges of the primary variables will be necessary to describe the phenomena under study?
 - How many data points should be taken in the various ranges of operation to ensure good sampling of data considering instrument accuracy and other factors? (See Chap 3)
- ment accuracy and other factors? (See Chap 3)

 6 What instrument accuracy is required for each measurement?
- If a dynamic measurement is involved, what frequency response must the instruments have?
- Are the instruments available commercially, or must they be constructed especially for the particular experiment?
 What are the recognitions are necessary if some hind of hazardous
- 8. What safety precautions are necessary if some kind of hazardous operation is involved in the experiment?
- What financial resources are available to perform the experiment, and how do the various instrument requirements fit into the proposed budget?
- 10. What provisions have been made for recording the data?

The importance of control in any experiment should always be recognized. The physical principle, apparatus, or device under investigation will dietate the variables which must be controlled carefully. For example, a heat-transfer test of a particular apparatus might involve some heat loss to the surrounding air in the laboratory where the test equipment is located. Consequently, it would be wise to maintain (control) the surrounding temperature at a reasonably constant value. If one run is made with the room temperature at 90°F and another at 50°F, large unwanted effects may occur in the measurements. Suppose a test is to be made of the effect of cigarette smoke on the eating habits of mice. Clearly, we would want to control the concentration of smoke inhaled by the mice and also observe another group of nine which were not exposed to cigarette smoke at all. All other environmental variables should be the same if we are to establish the effect of the eigarette smoke on eating habits.

In the case of the horse transfer test we make a series of measurements of the characteristics of a device under certain specified operating conditions are comparison with other devices is made. For the smoke test with mice it is necessary to measure the performance of the mice under specified conditions and also to compare this performance with the performance of another group under different controlled conditions. For the heat-transfer test we establish an absolute measurement of performance, but for the mice a relative performance is all that can be ascertained. We have chosen two diverse examples of absolute and relative experiments, but the lesson is clear. Whenever a comparison test is performed to establish relative performance, control must be exerted over more than one experimental setup in order for the comparison to be significant.

It would seem obvious that very careful provisions should be made to record the data and all ideas and observations concerned with the experiment. Yet, many experimenters record data and important sketches on pieces of scratch paper or in such a disorganized manner that they may be lost or thrown away. In some experiments the readout instrument is a recording type so that a record is automatically obtained and there is little chance for loss. For most experiments, however, visual observations must be made and values recorded on an appropriate data sheet. This data sheet should be very carefully planned so that it may subsequently be used, if desired, for data reduction. Frequently, much time may be saved in the reduction process by eliminating unnecessary transferal of data from one sheet to another. If a computer is to be used for data reduction, then the primary data sheet should

be so designed that the data may be easily transferred to the input device of the computer. A bound notbook should be maintained to record sketches and rignificant observations of an unusual character which may occur during both the planning and the execution stages of the experiment. The notbook is also used for recording thoughts and observations of a theoretical nature as the experiment progresses. Upon the completion of the experimental program the well-kept notebook forms a clear and sequential record of the experiment planning, observations during the experiment, and where applicable, correspondence of important observations with theoretical predictions. Every experimenter should get into the habit of keeping a soud notebook

As a summary of our remarks on experimental planning we present the generalized experimental procedure given in Table 2-4. This procedure is, of course, a flexible one, and the reader should consider the importance of each item in relation to the entire experimental program. Notice particularly item 1a. The engineer should give eareful thought to the need for the experiment. Perhaps, after some sober thinking, he will decide that a previously planned experiment is really not necessary at all and that the could get the desired information from an analytical study or from the results of experiments which have already been conducted. Do not take this item lightly. A great amount of money is wasted by individuals who rush into a program only to discover later that the experiments were unnecessary for they own particular purposes.

Many books have been writen on the subject of report writing, and the author has no intention of competing with these works. The importance of good report writing and data presentation cannot be overemphasized. No matter how good an experiment or how brilliant a discovery, it is worthless unless the information is communicated to other people. Only a few general remarks will be made concerning stem 8 in Table 2-4.

Very good advice for those engaged in writing or speaking activities is contained in the appearam

A man who uses a great many words to express his meaning is like a bad marksman who instead of aiming a single stone at an object takes up a handful and throws at it in hopes be may hit

Samuel Johnson

In other words, say what you have to say end then shut up! Be succinct but not lacone: When graphs or tables will present the idea clearly, use then, but do not also include a wordy explanation which tells the reader what he could plainly see for himself by careful inspection of the graph.

verify theoretical reto make use of reto make use.	ા જા	such measurements	objec
ing of the project. wable. ance of production model	vious investibure, vious before and report en done before	ete.).	operature, and the number
ts, including time sequent	experiment (verify periors) experiment (verify periors) experiment (verify periors)	nat the work may him	ten
cdure	wer, and thing budget, manpower, and t	irly establish obsidite it	1, etc.,look the possium.
Generalized experimental procedure including time sequencing of the project.	ed for the experiment. ed for the experiment, manpo	f the experiment, eles	ing for the exp.
Heronoral	Tablo 2-4 Car	1. d. Establish the of	c. Modern

- analysis of particular physical phenomenon, etc.). If experiments are similar to those of previous investigato Begin detail planning for the experiment, clearly establish objectives of experiment (verify performal
 - લં
- Determine as nearly as possible the accounter which may be required in the primary measurements and the number of such measurements experience of the previous workers Nerer overlook the possibility that the work may have been done before and reported in the a. Establish the primary variable, which must be measured (force, strain, flow, pressure, temperature, etc.).
- Select instrumentation for the various measurements to match the anticipaled accuracy requirementation to d. Analyze the possible errors in the anticipated results, before the experiments were made and an in the anticipated results, before the experiments were analyze the possible errors in the anticipated results, before the experiments were analyze the possible errors in the anticipated results, before the experiments were analyzed the possible errors in the anticipated results, before the experiments were an analyzed the possible errors in the anticipated results, before the experiments were an analyzed the possible errors and an analyzed the experiments were an analyzed the possible errors and an analyzed the experiments were an analyzed the experiments which is a superior and an analyzed the experiments which is a superior and an analyzed the experiments which is a superior and an analyzed the experiments which is a superior and an analyzed the experiments which is a superior and a superior a c. Set up data reduction culculations before conducting the experiment. in his ure that adequate data are being collected to meet the object. Collect a few data points, and conduct, a preliminary analysis of these data to be suited that the experiment is going as plunned.
- Organize, discuss, and publish the finding gare for the experiments, being sure to include information pertuining to all items 1 to Modify the experimental apparatur and or more dure in accordance with the findings in item 5.
- spove.

Third-person past tense is generally accepted as the most formal granumatical style for technical reports, and it is seldom incorrect to use such a style. In some instances, first person may be employed in order to emphasize a point or to stress the fact that a statement is primarily the opinion of the writer. The usual scientific writing style is also in the passive mode. Examples of the two styles are:

Third person: Equation 5 is recommended for the final correlation in accordance with the limitations of the data as discussed above.

First person. We (1) recommend Equation 5 for the final correlation in accordance with the limitations of the data presented in our discussion above

In the first-person statement, the writer is making the recommendation on a much more personal basis than he is in the thirdperson statement. The selection of the proper statement is a matter of idiom which depends on many factors, including consideration of the person(s) who will read the report. For a formal paper in a scientific journal, the third-person statement might be more preferable, whereas the first-person usage might be desirable in an engineering report to an individual.

Engineers could learn a few lessons from politicians and busi-Have you ever noticed the difference in writing style in the annual reports of corporations? If the carnings situation is good, the point is brought forth very quickly and very clearly Wordiness is avoided in the presentation of good points so that the reader will not miss them. When the profit statement is poor, the discussion becomes more circumfocutious and clear graphical or labular presentations are seldom employed. The point is that a writer should make sure that the strong points of his report are not buried in excess words. The degree to which weak points are submerged depends upon the audience for which the report is intended and the circumstances under which the report is written The above comments should not be misconstrued. The engineer should not hury bad data in a presentation in hopes that no one will notice! On the other hand, one should recognize that some engineering reports are written for the layman, and it is extremely important for the presentation not to give conflicting or confusing results which may be misinterpreted. Of course, a paper for publication in the technical or seientific literature should be completely objective The purpose of these brief paragraphs has been to illustrate the fact that an engineer may, in some circumstances, find it necessary to do a bit of selling in his writing. Such writing

Experimental methods for engineers

requires a great amount of skill and experience in order to be effective.

Be specific if you have something to be specific about. Consider the following two statements:

- 1. An analysis of the experimental data showed that the average deviation from the theoretical values was less than 1 percent. Uncertainties in the primary data were shown to account for a deviation of 0.5 percent. In view of this excellent agreement between Eq. (42) and the experimental data, this relation is believed to be an adequate representation of the physical phenomena and is recommended for calculation purposes.
- 2. The experimental data are in good agreement with the theoretical development. In view of this favorable comparison the assumptions pertaining on the derivation are verified.

Note the difference between the two statements. The first statement is quite people and leaves the reader with a feeling of confidence in the experimental data and theoretical analysis. Upon examining the emond statement the reader will immediately ask: How good is "good", how favorable is "favorable"? The author has seen such statements applied to experimental data which differed from theoretical values by such a large factor that the veracity of the writer might be questioned by a careful reader.

A brief, general procedure for report writing might take the following form

- 1 Make a written outline of the report with as much detail as possible.
- 2. Let the outline "cool" for a period of time while you direct your thoughts to other matters.
- 8. Go back to the outline and make whatever changes you feel are necessary
- 4. Write the report in rough draft form as quickly as possible.
- 5. Let the report cool for a period of time, preferably a week or so.
- 6. Go back and make corrections on your draft. You will probably find that you did not say things quite the way you would like to, did not include as much information as you wanted to, or made reveral stupid mistakes in some of the data analysis.
- If possible, have a colleague scrutinize the report carefully.
 This person should be one whose competence you respect.
- 8. Consider your colleague's comments very carefully, and rewrite the report in its final form.

PROBLEMS

- 2-1 Consider an ordinary mercury-in-glass thermometer as a measurement system, and indicate which parts of the thermometer correspond to the boxes in the diagram of Fig. 2-2.
- 2-2 A thermometer is used for the range of 200 to 400°F, and it is stated that its accuracy is one-quarter of 1 percent. What does this mean in terms of temperature?
- 2-3 A sinusodal forcing function is impressed on the system in Fig. 2-4. The natural frequency is 100 cps, and the damping ratio cfc, is 0.7 Calculate the amplitude ratio and time lag of the system for an input frequency of 40 cps. (The time lag is the time interval between the maximum force input and maximum displacement output).
- 2-4 For a natural frequency of 100 cps and a damping ratio of 0.7, compute the input-frequency range for which the system in Fig. 2-4 will have an amplitude ratio of 1.00 ± 0.01.
- 2-5 A thermometer is initially at a temperature of 70°F and is suddenly placed in a liquid which is maintained at 300°F. The thermometer indicates 200 and 270°F after time intervals of 3 and 5 sec respectively. Estimate the time constant for the thermometer.
- 26 Plot the power output of the circuit in Fig. 2-10 as a function of R/R. Assume R, and E as constants, and show the plot in dimensionless form, i.e., use PR./E² as the ordinate for the curve.

REFERENCES

- Silsbee, F. B. Extension and Dissemination of the Electrical and Magnetic Units by the National Bureau of Standards, Natl. Bur. Std. (U.S.), Circ. 531, 1952.
- Silsbee, F. B. Fundamental Units and Standards, Instr. Control Systems, vol. 26, p. I,520, October, 1953
- Eshbach, O. N. "Handbook of Engineering Fundamentals," 2d ed. John Wiley & Sons, Inc., New York, 1952
- Obert, E. F. "Concepts of Thermodynamics," McGraw-Hill Book Company, New York, 1990
- Constant, F. W. "Theoretical Physics," vol. II, Addison-Wesley Publishing Company, Inc., Reading, Mass., 1958
- Stimson, H. F. The International Temperature Scale of 1948, J. Res. Natl. Bur. Std. (paper 1962), vol. 42, p. 211, March, 1919

	4			
,				
	-			

Analysis of experimental data

3-1 INTRODUCTION

Some form of analysis must be performed on all experimental data. The analysis may be a simple verbal appraisal of the test results, or it may take the form of a complex theoretical analysis of the errors involved in the experiment and matching of the data with fundamental physical principles. Even new principles may be developed in order to explain some unusual phenomenon. Our discussion in this chapter will consider the analysis of data to determine errors, precision, and general validity of experimental measurements. The correspondence of the measurements with physical principles is another matter, quite beyond the scope of our discussion. Some methods of graphical data presentation will also be discussed. The interested reader should consult the monograph by Wilson [4] for many interesting observations concerning correspondence of physical theory and experiment.

The experimentalist should always know the validity of his data. The automobile test engineer must know the accuracy of his speed-ometer and gas gage if he is to express the miles-per-gallon performance with confidence. A nuclear engineer must know the accuracy and precision of many instruments just to make some simple radio-activity measurements with confidence. In order for an electrical engineer to speedly the performance of an amplifier, he must know the accuracy with which he has conducted the appropriate measurements of voltage, distortion, etc. Many considerations enter into a final determination of the validity of the results of experimental data, and we wish to present some of these considerations in this chapter.

Errors will creep into all experiments regardless of the care which is exerted. Some of these errors are of a random nature, and some will be due to gross blunders on the part of the experimenter Bad data due to obvious blunders may be discarded immediately. But what of the data points that just "look" bad? We cannot throw out data because they do not conform with our hopes and expectations unless we see something obviously wrong. If such "bad" points fall outside the range of normally expected random deviations, they may be discarded on the basis of some consistent. statistical data analysis. The key word here is consistent. elimination of data points must be consistent and should not be dependent on human whims and bias based on what "ought to be." In many instances it is very difficult for the engineer to be consistent and unbiased. The pressure of a deadline, disgust with previous experimental failures, and normal impatience all can influence his rational thinking processes. However, the competent experimentalist will strive to maintain consistency in the primary data analysis. Our objective in this chapter is to show how one may go about maintaining this consistency.

3-2 CAUSES AND TYPES OF EXPERIMENTAL ERRORS

In this section we present a discussion of some of the types of errors which may be present in experimental data and begin to indicate the way these data may be handled. First, let us distinguish between

single-sample and multisample data.

Single-sample data are those in which some uncertainties may not be discovered by repetition. Multisample data are obtained in · those instances where enough experiments are performed so that the reliability of the results can be assured by statistics. Frequently, cost will prohibit the collection of multisample data, and the experimenter must be content with single-sample data and prepared to extract as much information as possible from such experiments. The reader is referred to Refs. [1] and [4] for further discussions on this subject, but we state a simple example at this time. If one measures pressure with a pressure gage and a single instrument is the only one used for the entire set of observations, then some of the crror which is present in the measurement will be sampled only once no matter how many times the reading is repeated. Consequently, such an experiment is a single-sample experiment. On the other hand, if more than one pressure gage is used for the same total set of observations, then we might say that a multisample experiment has been performed. The number of observations will then determine the success of this multisample experiment in accordance with accepted statistical principles.,

An experimental error is an experimental error. If the experimenter knew what the error was, he would correct it and it would no longer be an error. In other words, the real errors in experimental data are those factors which are always vague to some extent and earry some amount of uncertainty You task is to determine just how uncertain a particular observation may be and to device a consistent way of specifying the uncertainty in analytical form. A reasonable definition of experimental uncertainty may be taken as the possible value the error may have. This uncertainty may vary a great deal depending upon the circumstances of the experiment. Perhaps it is better to epeak of experimental uncertainty insited of experimental error, because the magnitude of an error is always uncertain? Both terms are used in practice, however, so the reader should be familiar with the meaning attached to the terms and the ways that the relate to each other

At this point we may mention some of the types of errors which may cause uncertainty in an experimental measurement. First, there can always be those gross blunders in apparatus or instrument construction which may invalidate the data. Hopefully, the careful experimenter will be able to eliminate most of these errors. Second, there may be certain fixed errors which will cause repeated readings to be in error by roughly the same amount, but for some unknown reason. These fixed errors are sometimes called systematic errors. Third, there are the random errors which may be caused by personal fluctuations, random electronic fluctuations in the apparatus or instruments, various influences of friction, etc. These random errors usually follow a certain statistical distribution, but not always. In many instances it is very difficult to distinguish between fixed errors and random errors.

The experimentalist may sometimes use theoretical methods to stimate the magnitude of a fixed error. For example, consider the measurement of the temperature of a hot gas stream flowing in a durt with a mercury-in-glass thermometer. It is well known that hear may be conducted from the stem of the thermometer, out of the glass body, and into the surroundings. In other words, the fact that part of the thermometer is exposed to the rurroundings at a lemperature different from the gas temperature to be measured in y influence the temperature of the stem of the thermometer. There is a heat flow from the gas to the stem dust the lower than the consequently, the temperature of the stem must be lower than the other hands of the hot gas. Therefore, the temperature we read on the thermometer is not the true temperature of the gas, and it will not rule under the stem of the stem must be lower than the difference how many readings are taken—we shall always have a term resulting from the best-transfer condition of the sense. Sense resulting from the best-transfer condition of the sense.

Bad data due to obvious blunders may be disearded immediately. But what of the data points that just "look" bad? We cannot throw out data because they do not conform with our hopes and expectations unless we see something obviously wrong. If such "bad" points fall outside the range of normally expected random deviations, they may be discarded on the basis of some consistent statistical data analysis. The key word here is consistent. elimination of data points must be consistent and should not be dependent on human whims and bias based on what "ought to be." In many instances it is very difficult for the engineer to be consistent and unbiased. The pressure of a deadline, disgust with previous experimental failures, and normal impatience all can influence his rational thinking processes. However, the competent experimentalist will strive to maintain consistency in the primary data analysis. Our objective in this chapter is to show how one may go about maintaining this consistency.

3-2 CAUSES AND TYPES OF EXPERIMENTAL ERRORS

In this section we present a discussion of some of the types of errors which may be present in experimental data and begin to indicate the way these data may be handled. First, let us distinguish between

single-sample and multisample data.

Single-sample data are those in which some uncertainties may not be discovered by repetition. Multisample data are obtained in · those instances where enough experiments are performed so that the reliability of the results can be assured by statistics. Frequently, cost will prohibit the collection of multisample data, and the experimenter must be content with single-sample data and prepared to extract as much information as possible from such experiments. The reader is referred to Refs. [1] and [4] for further discussions on this subject, but we state a simple example at this time. 'If one measures pressure with a pressure gage and a single instrument is the only one used for the entire set of observations, then some of the error which is present in the measurement will be sampled only once no matter how many times the reading is repeated. Consequently, such an experiment is a single-sample experiment. On the other hand, if more than one pressure gage is used for the same total set of observations, then we might say that a multisample experiment has been performed. The number of observations will then determine the success of this multisample experiment in accordance with accepted statistical principles.,

An experimental error is an experimental error. If the experimenter knew what the error was, be would correct it and it would no longer be an error. In other words, the real errors in experimental data are those factors which are always vague to some extent and carry some amount of uncertaioty. Our task is to determine just how uncertain a particular observation may be and to devise a consistent way of specifying the uncertainty in analytical form. A reasonable definition of experimental uncertainty may vary as the possible value the error may have. This uncertainty may vary a great deal depending upon the circumstances of the experiment Perhaps it is better to speak of experimental uncertainty instead of experimental error, because the magnitude of an error is always uncertain? Both terms are used in practice, however, so the reader should be familiar with the meaning attached to the terms and the ways that they relate to each other.

At this point we may mention some of the types of errors which may cause uncertainty in an experimental measurement. First, there can always be those gross blunders in apparatus or instrument construction which may invalidate the data. Hopefully, the careful experimenter will be able to eliminate most of these errors. Second, there may be certain fixed errors which will cause repeated readings to be in error by roughly the same amount, but for some unknown reason. These fixed errors are sometimes called systematic errors. Third, there are the random errors which may be caused by personal fluctuations, random electronic fluctuations in the apparatus or instruments, various influences of friction, etc. These random errors usually follow a certain statistical distribution, but not always. In many instances it is very difficult to distinguish between fixed errors and random errors.

The experimentalist may sometimes use theoretical methods to estimate the magnitude of a fixed error. For example, consider the measurement of the temperature of a hot gas stream flowing in a duct with a mercury-in-glass thermometer. It is well known that heat may be conducted from the stem of the thermometer, out of the glass body, and into the surroundings. In other words, the fact that part of the thermometer is exposed to the surroundings at a temperature different from the gas temperature to be measured may influence the temperature of the stem of the thermometer. There is a heat flow from the gas to the stem of the thermometer, and, consequently, the temperature of the stem must be lower than that of the hot gas. Therefore, the temperature we read on the thermometer is not the true temperature of the gas, and it will not make any difference how many readings are taken—we shall always have an error resulting from the heat-transfer condition of the stem of the

Experimental methods for engineers

thermometer. This is a fixed error, and its magnitude may be estimated with theoretical calculations based upon known thermal properties of the gas and the glass thermometer.

3-3 ERROR ANALYSIS ON A "COMMONSENSE" BASIS

We have already noted that it is somewhat more explicit to speak of experimental uncertainty rather than experimental error. Suppose that we have satisfied ourselves with the uncertainty in some basic experimental measurements, taking into consideration such factors as instrument accuracy, competence of the people using the instruments, etc. Eventually, the primary measurements must be combined to calculate a particular result which is desired. We shall be interested in knowing the uncertainty in the final result due to the uncertainties in the primary measurements. This may be done by a commonsense analysis of the data which may take many forms. One rule of thumb which could be used is that the error in the result is equal to the maximum error in any parameter used to calculate the result. Another commonsense analysis would combine all the errors in the most detrimental way in order to determine the maximum error in the final result. Consider the calculation of electric power from

$$P = EI$$

where E and I are measured as

$$E = 100 \text{ volts} \pm 2 \text{ volts}$$

$$I = 10 \text{ amp} \pm 0.2 \text{ amp}$$

The nominal value of the power is $100 \times 10 = 1,000$ watts. By taking the worst possible variations in voltage and current we could calculate

$$P_{\text{max}} = (100 + 2)(10 + 0.2) = 1040.4 \text{ watts}$$

$$P_{\min} = (100 - 2)(10 - 0.2) = 960.4 \text{ watts}$$

Thus, using this method of calculation the uncertainty in the power is ± 4.04 percent, -3.96 percent. It is quite unlikely that

the power would be in error by these amounts because the voltmeter variations would probably not correspond with the ammeter variations. When the voltmeter reads an extreme "high," there is no reason why the ammeter must also read an extreme "high" at that particular instant; indeed, this combination is most unlikely

The simple calculation applied to the electric-power equation above is a useful way of inspecting experimental data to determine what errors could result in a final ealculation; however, the test is too severe and should be used only for rough inspections of data. It is significant to note, however, that if the results of the experiments appear to be in error by more than the amounts indicated by the above calculation, then the experimenter had better examine his data more closely. In particular, he should look for certain fixed errors in the instrumentation which may be eliminated by applying either theoretical or empirical corrections.

The term "common sense" has many connotations and means different things to different people. In the brief example given above, it is intended as a quock and expedient vehicle which may be used to examine experimental data and results for gross errors and variations. In subsequent sections we shall present methods for determining experimental uncertainties in a more precise manner

3-4 UNCERTAINTY ANALYSIS

A more precise method of estimating unrertainty in experimental results has been presented by Kine and McClintock [1] The method is based on a careful specification of the uncertainties in the vanous primary experimental measurements. For example, a certain pressure reading might be expressed as

p = 100 psia ± 1 psia

When the plus or minus notation is used to designate the uncertainty, the person making this designation is stating in very precise terms the degree of accuracy with which he believes the measurement has been made. We may note that this specification is in itself uncertain because the experimenter is naturally uncertain about the accuracy of his measurements. To add a further specification of the uncertainty of a particular measurement, Kline and McClintock propose that the experimenter specify certain odds for the uncertainty. The above equation for pressure might thus be

written

$$p = 100 \text{ psia} \pm 1 \text{ psia} (20 \text{ to } 1)$$

In other words, the experimenter is willing to bet with 20 to 1 odds that his pressure measurement is within ± 1 psia. It is important to note that the specification of such odds can only be made by the experimenter himself based on his total laboratory experience.

Suppose a set of measurements is made and the uncertainty in each measurement may be expressed with the same odds. These measurements are then used to calculate some desired result of the experiments. We wish to estimate the uncertainty in the calculated result on the basis of the uncertainties in the primary measurements. The result R is a given function of the independent variables $x_1, x_2, x_2, \ldots, x_n$. Thus,

$$R = R(x_1, x_2, x_3 \ldots, x_n)$$
 (3-1)

Let w_R be the uncertainty in the result and w_1, w_2, \ldots, w_n be the uncertainties in the independent variables. If the uncertainties in the independent variables are all given with the same odds, then the uncertainty in the result having these odds is given in Ref. [1] as

$$w_R = \left[\left(\frac{\partial R}{\partial x_1} w_1 \right)^2 + \left(\frac{\partial R}{\partial x_2} w_2 \right)^2 + \cdots + \left(\frac{\partial R}{\partial x_n} w_n \right)^2 \right]^{\frac{1}{2}}$$
(3-2)

If this relation is applied to the electric-power relation of the previous section, the expected uncertainty is 2.83 percent instead of 4.04 percent.

Example 3-1

The resistance of a certain size of copper wire is given as

$$R = R_c[1 + \alpha(T - 20)]$$

where $R_0 = 6$ ohms ± 0.3 percent is the resistance at 20°C, $\alpha = 0.004$ °C⁻¹ ± 1 percent is the temperature coefficient of resistance, and the temperature of the wire is $T = 30 \pm 1$ °C. Calculate the resistance of the wire and its uncertainty.

Solution. The nominal resistance is

$$R = (6)[1 + (0.004)(30 - 20)] = 6.24$$
 ohms

The uncertainty in this value is calculated by applying Eq. (3-2). The various terms are:

$$\frac{\partial R}{\partial R_s} = 1 + \alpha(T - 20) = 1 + (0.004)(30 - 20) = 1.04$$

$$\frac{\partial R}{\partial \alpha} = R_s(T - 20) = (6)(30 - 20) = 60$$

$$\frac{\partial R}{\partial T} = R_s\alpha = (6)(0.004) = 0.024$$

$$w_{R_1} = (6)(0.003) = 0.018 \text{ shm}$$

Thus, the uncertainty in the resistance is

$$w_{A} = [(1.04)^{3}(0.018)^{3} + (60)^{3}(4 \times 10^{-4})^{3} + (0.024)^{3}(1)^{3}]^{4}$$

= 0.0305 ohm or 0.49%

Particular notice should be given to the fact that the uncertainty propagation in the result w_B predicted by Eq. (3-2) depends on the squares of the uncertainties in the independent variables w_c . This means that if the uncertainty in one variable is sgnifeantly larger than the uncertainties in the other variables, say by a factor of 5 or 10, then it is the largest uncertainty which predominates and the others may probably be neglected. To illustrate, suppose there are three variables with an uncertainty of magnitude 1 and one variable with an uncertainty of magnitude 5. The uncertainty in the result would be

$$(5^{2} + 1^{2} + 1^{2} + 1^{2})^{4} = \sqrt{28} = 5.29^{4}$$

The importance of this brief remark concerning the relative maxnitude of uncertainties is evident when one considers the despin of an experiment, procurement of instrumentation, etc. Very little is gained by trying to reduce the "small" uncertainties. Because of the square propagation it is the "large" ones that predominate and any improvement in the overall experimental result must be achieved by improving the instrumentation or experimental technique connected with these relatively large uncertainties. In the examples and problems which follow, both in this chapter and throughout the book, the reader should always note the relative effect of uncertainties in primary measurements on the final result.

In Sec. 2-10 (Table 2-4) the reader was cautioned to examine possible experimental errors before the experiment is conducted. Equation (3-2) may be used very effectively for such analyses, as we shall see in the sections and chapters which follow. A further word of caution may be added here. It is equally as unfortunate to overestimate uncertainty as to underestimate. An underestimate gives false security, while an overestimate may make one discard important results, miss a real effect, or buy much too expensive instruments. The purpose of this chapter is to indicate some of the methods for obtaining reasonable estimates of experimental uncertainty.

3-5 STATISTICAL ANALYSIS OF EXPERIMENTAL DATA

We shall not be able to give an extensive presentation of the methods of statistical analysis of experimental data; we may only indicate some of the more important methods currently employed. First, it is important to define some pertinent terms.

When a set of readings of an instrument is taken, the individual readings will vary somewhat from each other and the experimenter is usually concerned with the *mean* of all the readings. If each reading is denoted by x, and there are n readings, the arithmetic mean is given by

$$x_{m} = \frac{1}{n} \sum_{i=1}^{n} x_{i} \tag{3-3}$$

The deviation d, for each reading is defined by

$$d_i = x_i - x_m \tag{3-4}$$

We may note that the average of the deviations of all the readings is zero since

$$\overline{d}_i = \frac{1}{n} \sum_{i=1}^{n} d_i = \frac{1}{n} \sum_{i=1}^{n} (x_i - x_n)$$

$$= x_n - \frac{1}{n} (nx_n) = 0$$
(3-5)

The average of the absolute values of the deviations is given by

$$|\vec{d_i}| = \frac{1}{n} \sum_{i=1}^{n} |\vec{d_i}| = \frac{1}{n} \sum_{i=1}^{n} |x_i - x_n|$$
 (3-6)

Note that this quantity is not necessarily zero.

The standard deviation or roof-mean-square deviation is defined by

$$\sigma = \left[\frac{1}{n}\sum_{n=1}^{n}(x_{i}-x_{n})^{2}\right]^{i}$$
(3-7)

and the square of the standard deviation of is called the ranance.
We shall be interested in the determination of the standard deviation because it is important in all aspects of statistical data analysis.

Example 3-2

The following readings are taken of a certain physical length. Compute the mean reading, standard deviation, variance, and average of the absolute value of the deviation.

Reading	x, ft
1	5.30
2	5 73
3	6.77
4	5.26
5	4 33
6	5.45
7	6.09
8	5.64
9	5 81
10	5.75

Solution. The mean value is given by

$$z_n = \frac{1}{n} \sum_{i=1}^{n} z_i = \frac{1}{10} (56.13) = 5613 \text{ ft}$$

The other quantities are computed with the aid of the following table:

Reading $d_i = x_i - x_m$ $(x_i - x_m)^2 \times 10^3$ 1 -0.313 9.797 2 0.117 1.369 3 1.157 133.864 4 -0.353 12.461 5 -1.283 164.866 6 -0.163 2.657 7 0.477 22.753 8 0.027 0.0729 9 0.197 3.881 10 0.137 1.877			
1	Reading	$d_i = x_i - x_m$	$\frac{(x_i-x_m)^3\times 10^3}$
	3 4 5 6 7 8	0.117 1.157 -0.353 -1.283 -0.163 0.477 0.027 0.197	1.369 133.864 12.461 164.866 2.657 22.753 0.0729 3.881

$$\sigma = \left[\frac{1}{n} \sum_{i=1}^{n} (x_i - x_m)^2\right]^{\frac{1}{2}} = \left[\frac{1}{10}(3.536)\right]^{\frac{1}{2}} = 0.595 \text{ ft}$$

$$\sigma^2 = 0.3536 \text{ ft}^2$$

$$|\overline{d_i}| = \frac{1}{n} \sum_{i=1}^{n} |d_i| = \frac{1}{n} \sum_{i=1}^{n} |x_i - x_m|$$
$$= \frac{1}{10} (4.224) = 0.4224 \text{ ft}$$

Isuppose an "honest" coin is flipped a large number of times. It will be noted that after a large number of tosses heads will be observed about the same number of times as tails. If one were to consistently bet on either heads or tails, the best he could hope for would be a break-even proposition over a long period of time. In other words, the frequency of occurrence of either heads or tails is the same for a very large number of tosses. It is common knowledge that a few tosses of a coin, say 5 or 10, may not be a break-even proposition, as in the case of a large number of tosses. This observation illustrates the fact that frequency of occurrence of an event may be dependent on the total number of events which are observed.

The probability that one will get a head when flipping an unweighted coin is $\frac{1}{2}$, regardless of the number of times the coin is tossed. The probability that a tail will occur is also $\frac{1}{2}$. The probability that either a head or a tail will occur is $\frac{1}{2} + \frac{1}{2}$ or unity. (We ignore the possibility that the coin will stand on edge.) *Probability* is a mathematical quantity which is linked to the frequency with which a certain phenomenon occurs after a large number of tries. In the case of the coin, it is the number of times heads would be expected to result in a large number of tosses divided by the total

number of tosses. In a similar manner, the toss of an unloaded die would be expected to result in the occurrence of any one side onesixth of the time in a large number of throws

Probabilities are expressed in numerical values less than 1, and a probability of unity corresponds to certainty. In other words, if the probabilities for all possible events are added, the result must be unity. If we know the probability that separate events will occur; the probability that one of the events will occur is the sam of the individual probabilities for the events. For the towing of a dig, the probability that any one side will occur is $\frac{1}{2}$. The probability that any one side will occur is $\frac{1}{2}$. The probability of getting either of two given numbers in a single throw of the due is $\frac{1}{2}+\frac{1}{2}+\frac{1}{2}$, or $\frac{1}{2}$, and so on. As another example, the probability of drawing the acc of spades from a deck of cards is $\frac{1}{2}$, but the probability of drawing the sace of spades from a deck of cards is $\frac{1}{2}$, but the probability of drawing any acc is $\frac{1}{2}$ (1).

Suppose two dice are thrown and we wish to know the probability that both will display a 6. The probability for a 6 on a single die is \$\frac{1}{2}\$. By a short calculation or listing of the possible arrangements that the dice may have, it can be seen that there are 36 possibilities and that the decired result of two 6s represents only one of these possibilities. Thus, the probability is \$\frac{1}{2}\$. The reader who has a gambling heart will naturally want to know the probability of getting a 7 or 11 on the throw of the dice. There are 36 possible ways that the dice may be arranged and 6 possible ways of getting a 7, thus the probability of getting a 7 is \$\frac{1}{2}\$, or \$\frac{1}{2}\$. There are only 2 ways of getting an 11, thus the probability is \$\frac{1}{2}\$, or \$\frac{1}{2}\$. The probability of getting as 11 is \$\frac{1}{2}\$, \$\frac{1}{2}\$, or \$\frac{1}{2}\$.

If several independent events occur at the same time such that case event has a probability p, the probability that all events will occur is given as the product of the probabilities of the individual events. Thus, $p=\Pi p$, where the Π sign designates a product. This rule could be applied to the problem of determining the probability of a double 6 in the throw of two dire. The probability of getting a 6 on each die is $\frac{1}{2}$, and the total probability is therefore ($\frac{1}{2}(\frac{1}{2})$), or $\frac{1}{2}$. This reasoning could not be applied to the problem of obtaining a 7 on the two diee, because the number on each die is not independent of the number on the other die since a 7 can be obtained in more than one way

As a final example we ask what the chances are of getting a royal flush in the first five cards drawn off the top of a deck. There are 20 suitable possibilities for the first draw (4 suits, 5 possible cards per aut) out of a total of 52 cards. On the second draw we have fixed the suits of that there are only 4 suitable cards out of the 51 remaining. There are three suitable cards on the third draw.

two on the fourth, and only one on the fifth draw. The total probability of drawing the royal flush is thus the product of the probabilities of each draw, or

$$\frac{20}{52} \times \frac{4}{51} \times \frac{3}{50} \times \frac{2}{49} \times \frac{1}{48} = \frac{1}{649,740}$$

In the above discussion we have seen that the probability is related to the number of ways a certain event may occur. In a sense we are assuming that all events are equally likely, and hence the probability that an event will occur is the number of ways the event may occur divided by the number of possible events. For our purposes it is sufficient that we recognize the link between probability and the mathematics dealing with permutations and combinations without pursuing the matter further. Our primary concern is the application of probability and statistics to the analysis of experimental data. For this purpose we need to discuss next the meaning and use of probability distributions. We shall be concerned with a few particular distributions which are directly applicable to experimental data analysis.

3-6 PROBABILITY DISTRIBUTIONS

Suppose we toss a horseshoe some distance x. Even though we might be playing a game such that every effort was made to toss the horseshoe the same distance each time, we would not always meet with success. On the first toss the horseshoe might travel a distance x_1 , on the second toss a distance of x_2 , and so on. If one is a good player of the game, there would be more tosses which have an x distance equal to that of the objective. Also, we would expect fewer and fewer tosses for those x distances which are further and further away from the target. Suppose the horseshoe is tossed a large number of times. We might compute the probability that it will travel a distance x by dividing the number traveling this distance by the total number of tosses. Since each x distance will vary somewhat from other x distances, we might find it advantageous to calculate the probability of a toss landing in a certain increment of x between x and $x + \Delta x$. When this calculation is made, we might get something like the situation shown in Fig. 3-1. For a good player, the maximum probability is expected to surround the distance x_m designating the position of the target.

The curve shown in Fig. 3-1 is called a probability distribution. It shows how the probability of success in a certain event is distributed over the distance x. Each value of the ordinate p(x) gives the




Fig. 3-1. Distribution of throws for a "good" horseshoes player.

probability that the horseshoe will land between x and $x + \Delta x$, where Δx is allowed to approach zero. We might consider the deviation from x_n as the error in the throw. If the horseshoes player has good aim, large errors are less likely than small errora. The area under the curve is unity, since it is certain that the horseshoe will land somewhere.

A particular probability distribution is the binomial distribution.

This distribution gives the number of successes n out of N possible independent events when each event has a probability of success n. The probability that n events will succeed is given in Ref. [2] as

$$p(n) = \frac{N!}{(N-n)!n!} p^{n} (1-p)^{N-n}$$
(3-8)

It will be noted that the quantity (1-p) is the probability of failure of each independent event.

Example 3-3

An unweighted com is supped three times Calculate the probability of getting zero, one, two, or three heads in these tosses

Solution. The binomial distribution applies in this case. The probability of getting a head on each throw is $p = \frac{1}{2}$ and N = 3, while n takes on the values 0, 1, 2, and 3. The probabilities are calculated as

$$p(0) = \frac{3!}{(3!)(0!)} \left(\frac{1}{2}\right)^{0} \left(\frac{1}{2}\right)^{1} = \frac{1}{8}$$

$$p(1) = \frac{3!}{(2!)(1!)} \left(\frac{1}{2}\right)^{1} \left(\frac{1}{2}\right)^{2} = \frac{3}{8}$$

$$p(2) = \frac{3!}{(1!)(2!)} \left(\frac{1}{2}\right)^{2} \left(\frac{1}{2}\right)^{1} = \frac{3}{8}$$

$$p(3) = \frac{3!}{(0!)(3!)} \left(\frac{1}{2}\right)^{3} \left(\frac{1}{2}\right)^{0} = \frac{1}{8}$$

Now suppose that the number of possible independent events N is very large and the probability of occurrence of each p is very small. The calculation of the probability of n successes out of the N possible events using Eq. (3-8) would be most cumbersome because of the size of the numbers. The limit of the binomial distribution as $N \to \infty$ and $p \to 0$, such that

Np = a = const

is called the Poisson distribution and is given by

$$p_a(n) = \frac{a^n e^{-a}}{n!} \tag{3-9}$$

The Poisson distribution is applicable to the calculation of the decay of radioactive nuclei, as we shall see in a subsequent chapter. It may be shown that the standard deviation of the Poisson distribution is

$$\sigma = \sqrt{a} \qquad (3-10)$$

3-7 THE GAUSSIAN OR NORMAL ERROR DISTRIBUTION

Suppose an experimental observation is made and some particular result recorded. We know (or would strongly suspect) that the observation has been subjected to many random errors. These random errors may make the final reading either too large or too small, depending on many circumstances which are unknown to us. Assuming that there are many small errors which contribute to the

final error and that each small error is of equal magnitude and equally likely to be positive or negative, the Gaussian or normal error distribution may be derived. If the measurement is designated by x_i the Gaussian distribution gives the probability that the measurement will be between x and x + dx and is written

$$P(z) = \frac{1}{\sigma \sqrt{2\pi}} e^{-(z-z_0)^2/2\sigma^2}$$
(3-11)

In this expression, x_r is the mean reading and σ is the standard deviation. A plot of Eq. (3-11) is given in Fig. 3-2. Note that the most probable reading is z_m . The standard deviation is a measure of the width of the distribution curve, the larger the value of σ_r the flatter the curve, and hence the larger the expected error of all the measurements Equation (3-11) is normalized so that the total area under the curve is unity. Thus,

$$\int_{-a}^{+a} P(x) dx = 1.0 \tag{3-12}$$

At this point we may note the similarity between the shape of the normal error curve and the expected experimental distribution for tossing horseshoes as shown in Fig. 3-1. This is what we would expect because the good horse-hoes player will have his throws bunched around the target. The better he is at the game, the more closely they will be grouped around the mean and the more probable will be the mean distance x_m. So, in the case of the horseshoes player, a smaller standard deviation would mean a larger percentage of "mayers".

We may quickly anticipate the next step in the analysis as one of trying to determine the precision of a set of experimental measurements through an application of the normal error distribution. One may ask; but how do you know that the assumptions perfaming to the derivation of the normal error distribution apply to experimental data? The answer is that for sets of data where a large number of measurements are taken, experiments indicate that the measurements do indeed follow a distribution like that shown in Fig. 3-2 when the experiment is under control. If an important parameter is not controlled, one gets just scatter, i.e., no senable distribution at all. Thus, as a matter of experimental verification the Gaussian distribution is believed to represent the random errors in an adequate manner for a properly controlled experiment.

By inspection of the Gaussian distribution function of Eq. (2-11) we see that the maximum probability occurs at $x = x_0$ and the x_0^2/x_0^2

Experimental methods for engineers




Fig. 3-2. The Gaussian or normal error distribution for two values of the standard deviation.

of this probability is

$$P(x_m) = \frac{1}{\sigma \sqrt{2\pi}} \tag{3-13}$$

It is seen from Eq. (3-13) that smaller values of the standard deviation produce larger values of the maximum probability, as would be expected in an intuitive sense. $P(x_m)$ is sometimes called a measure of precision of the data because it has a larger value for smaller values of the standard deviation.

We next wish to examine the Gaussian distribution to determine the likelihood that certain data points will fall within a specified deviation from the mean of all the data points. The probability that a measurement will fall within a certain range x_1 of the mean reading is

$$P = \int_{x_{m}-x_{1}}^{x_{m}+x_{1}} \frac{1}{\sigma \sqrt{2\pi}} e^{-(x-x_{m})^{2}/2\sigma^{2}} dx$$
 (3-14)

Making the variable substitution

$$\eta = \frac{x - x_m}{\sigma}$$

Table 3-1 Values of the Gaussian normal error distribution

Values of the function $(1/\sqrt{2\pi})e^{-y_{ij}}$ for different values of the argument η . (Each figure in the body of the table is preceded by a decimal point.)

v 0.00 0.01 0.02 0.03 0.04 0.05 0.06 0.07 0.08 0.00 0 0 30994 30946 30946 30946 30946 30944 30944 30973 30953 30943 30943 30944 30953 30933 30933 30943 30943 30943 30943 30943 30943 30943 30933 370333 370333 370333 370333 <	~~~			_	_			<u> </u>			
0 1 30695 30694 30698 30593 30505 3244 3257 3252 32533 32545 30 2 3014 3014 3014 3014 3014 3014 3014 3014	7	0.00	0 01	0.02	t) (13	004	0 05	0.06	0.07	0.08	0.03
0.2 30104 30604 30704 30704 30704 30702 30707 30705 30707 30701 30701 30703 30	0.0	39994	39592				33544	39422	39797	39767	39733
0 2 30104 30904 30903 37803 37805 37805 38406 3291 3255 3115 30973 30930 37803 37805 37805 37805 37805 38407 38608 3291 37255 3115 30973 3098 3115 30973 3098 3115 30973 3098 3115 30973 31	0 1	39695	33654	39609	39559	33563	33445	39397	39322	33253	39151
0 3 39139 39023 37903 37780 37644 37254 37291 37255 37115 30737 3074 3075	0.2	39104	39024	39940	35623	34762	39607	39569			
0 4 0.56827 26673 35526 35521 36241 26733 35590 35222 35533 35341	0.3	38139	35023	37903	37780	37654	37524	37321			
0.6 0.33322 33121 32918 32712 32960 32972 32960 31574 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 3	0.4	36827	36678	36526	36371	36213	30053	35449	35723		
0.6 0.33322 33121 32918 32712 32960 32972 32960 31574 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 31471 316.50 3	0.5	35207	35029	34849	34667	34492	34294	34105	23312	33715	33521
0.7 31225 31006 30785 30633 30320 30114 9947 7055 29491 7279 28491 7279 28491 7279 28491 7279 28491 7279 28491 7279 28491 7279 28491 7279 28491 29491 7279 28491 29491 29491 7279 28481 28491 28491 28491 28481 28491 28491 28491 28481 28491 28491 28491 28481 28491				32918							
0.8 29909 29737 29504 29209 2964 27794 27502 2724 2700-5 2548 2700-5 270											
0 9 26609 26309 26129 28341 25667 2740 25164 24023 24631 24437 1 0 24107 27355 27113 24411 23790 27985 22747 27206 27265 272023 1 1 21784 27355 27113 24411 23790 27985 22747 27206 27265 272023 1 2 19419 19185 18934 18724 18404 18725 17407 17535 17302 1 3 17137 1915 18904 18474 18456 18404 18725 18407 187410 17535 17302 1 4 14973 14764 14556 14350 14146 12943 13742 13342 13344 13147 1 5 172052 12734 12566 12735 12756 17255 15573 13152 13140 17535 13152 1 6 11092 19135 19741 19567 19560 10225 19504 18124 13147 1 7 09403 19245 19135 19741 19567 19560 10225 19504 18124 1450 11270 1 7 09403 19245 19135 19741 19567 19560 10225 19504 18145 11622 14450 11270 1 7 09403 19245 19135 19741 19567 19740 19256 19225 19740 19574 19574 1 9 00502 06438 06316 19185 19677 19740 1											
1 1 21783 21516 21307 21000 20831 2094 20357 20121 19-86 19525 1210 21 1919 1918 1939 1872 1816 1826 1826 1826 1826 1826 1826 182											
1 1 21783 21516 21307 21000 20831 2094 20357 20121 19-86 19525 1210 21 1919 1918 1939 1872 1816 1826 1826 1826 1826 1826 1826 182	٠.	04107		22712	 .	,,,,,,	20000	227.17	20100	m	2400.
1 2 19419 1918 1934 1724 1849 18755 1807 1710 1759 1720 1 1 3 17127 1915 1915 1907 1847 1847 1847 1847 1847 1847 1847 184											
1 17137 19115 19294 1444 19256 18203 18222 18204 18245 18245 18256 1											
1 1 1073											
1 5 12932											
1 6 1 1092 10914 1074 1074 1074 1074 1074 1074 1074 10	' 1	11973	14704	11330	11330	14140	10545	10/14	10.72	13311	
1 7 09403 09246 09489 0931 0759 0759 0759 0759 0759 0759 0759 0759	15	12952	12759	12566	12376	12155	12001	11516	11632	11450	
1 7 0 9403 09246 09489 0931 0759 0754 0751 0751 0751 0751 0751 0751 0751 0751	16	11092	10915	10741	10567	10396	10226	10039	09503	(9724	09566
1 0 00562 06439 06316 06195 06077 06939 08944 03730 05618 05509 2 0 03509 0522 03166 0692 0499 08920 08934 03730 05618 05509 2 1 04395 04377 04177 04128 0404 63955 36174 03750 04750	17	09405	09246	09059	05933	08780		05475	04324	(15153	D51135
2 0 0 0509	18	07895	07754	07614	07477	07341	07,206	07074	06743	06914	
2 1 04295	10	06562	06439	06316	96195	06077	05959	05914	0.5720	02414	อรรกฯ
2 1 0499	2.0	05200	05202	45186	05052	01380	0.820	04750	04552	04250	भाग
2 2 0.35347											03626
2 2 4 02233											
2 4 02239										02349	02294
2 5 01753	2 4										01797
2 5 01753						,	1 1				01201
2 7 01042 01014 00987 28 00792 00770 00748 2 9 00595 00578 00562 3 5 008727 4 0 0001335 4 5 00862 4 5 0001335 4 6 5 000145 4 5 0000160 4 5 000160 4 6 000160 4 6 000160 4 6 000160 4 6 000160 4 6 000160 4 6 000160 4								•			•
2 8 00792 00770 00744 00578 00562 00578 00562 0050727 4 0 0001333 4 0 00772 4 0 000140 00 001400											
2 9 10595 00578 00562 3 0 00443 3 5 008727 4 0 0001333 4 0 000135											
2 9 (0595 00578 00562 3 0 0043 3 5 (005727 4 0 (000135 4 5) (000160 1 0 000160 1						•	٠.	•		٠.	٠.
3 5 008727 4 0 0001335 4 5 0000160	29	90595	00578	00562		٠ .	, ' ',	• • • •	· i	· 1	
4 0 0001335 4 5 0000160	3 0	00443	,			,	1)	1	- 1	- 1	
4 5 0000160	3 5	008727	J					j	1	- 1	
	4 0	0001335		1 1		1 1	[ſ	ſ	- 1	
5 0 000001497	4.5	0000160					1	- 1	- 1	- 1	
	5 0	000001497						1	- 1		
	_		اا								

1




Fig. 3-2. The Gaussian or normal error distribution for two values of the standard deviation.

of this probability is

$$P(x_m) = \frac{1}{\sigma \sqrt{2\pi}} \tag{3-13}$$

It is seen from Eq. (3-13) that smaller values of the standard deviation produce larger values of the maximum probability, as would be expected in an intuitive sense. $P(x_m)$ is sometimes called a measure of precision of the data because it has a larger value for smaller values of the standard deviation.

We next wish to examine the Gaussian distribution to determine the likelihood that certain data points will fall within a specified deviation from the mean of all the data points. The probability that a measurement will fall within a certain range x_1 of the mean reading is

$$P = \int_{x_{m}-x_{1}}^{x_{m}+x_{1}} \frac{1}{\sigma \sqrt{2\pi}} e^{-(x-x_{m})^{2}/2\sigma^{2}} dx$$
 (3-14)

Making the variable substitution

$$\eta = \frac{x - x_m}{\sigma}$$

Table 3-1 Values of the Gaussian normal error distribution Volues of the function $(1/\sqrt{2r})e^{-\lambda t}$ for different values of the argument q. (Each figure in the body of the table is preceded by a decining point.)

	C III IIIE DOL	7 01 200	TODIE	2 prece	ued by	a occim	ai paint	.)		
7	0.00	0 01	0.05	0.03	0.04	nns	n 1/6	0.07	0.08	nm
0.0	39594	33992	39896	39976	37562	39944	39922	39797	39767	39733
0.1	39695	33654	39609	37559	39505	39444	39357	39322	39253	39151
0.2	39104	37024	39340	39953	35762	39667	38568	39466	38361	35251
0.3	35139	35023	37903	37780	37654	37524	37391	37255	37115	36973
0.4	36927	36678	36526	36371	36213	36053	35449	35723	35553	35381
		í l	[[1			i i	1 1	ĺ	1
0.5	35207	35029	34549	34667	34492	31294	34103	33912	33714	33521
0.6	33322	33121	32319	32713	32506	32297	320%	31874	31659	31443
0.7	31225	31006	30785	30563	30339	30114	20497	29658	29439	29200
8,9	28969	29737	24504	29269	25031	27793	27562	27324	27096	26545
0.0	26609	26369	26129	25999	25647	23406	25164	24923	24691	24439
10	24197	23955	23713	23471	23230	22988	22747	22506	22265	22025
ii	21785	21546	21307	21067	20531	20594	20357	20121	19886	19632
1 2	19419	19186	18954	18724	18494	18265	18037	17810	17555	17360
1 3	17137	16915	16694	16474	16256	16033	15922	15608	15395	15153
14	14973	14764	14556	14350	14146	13943	13742	13542	13344	13147
' '	**31.3	117.07	113.70	173 ~	,,,,,,	10.11	10174	13/12		1
15	12952	12759	12366	12376	[2188	12001	11816	11632	11450	11270
1.6	11092	10915	10741	10567	10396	10226	10059	09393	09729	00300
1.7	09405	00246	09089	09933	08780	09629	09478	05329	04183	05039
18	07895	07754	07614	07477	07341	07206	07071	06943	06514	06647
19	06862	06439	06316	06195	06077	05753	05414	0.5730	03618	กรรถจ
	ł	\ '		1				, ,		
20	05399	' '		1						
2.1	04394									
22	03547						•			
23	02833	(. "	. •	. '				
2 4	02239	02196	02134	02053	02033	01984	01936	01445	101-4-	
2 5	01753	Ι.	1	Ι.	ا ـــا			A1 450	01431	111 194
26	01358								01100	01071
27	01042	1 .	٠	٠					00537	00314
2.8	00792	Ι,	Ξ.		-				00631	00613
2.8		04576	00562	Lores	00570	00514	00499.1	0015a 1	00170	(x)457
2 9	00595	Gists.	50562	(00013	37330	100214	~~~~		- 1	
3 0	00443	í	ĺ	Ι.	ĺ		1	1	- 1	
3 5	008727	1 1	1	i 1	i i	1	- 1	- 1	- {	
4 0	0001339					i i		- 1	- 1	
4.5	0000160	i '	1	1	1	1	- 1	- }	- 1	
5 0	000001497	1 1				' 1	- 1	- 1	- 1	
		<u>. </u>								

Table 3-2 Integrals of the Gaussian normal error function

Values of the integral $(1/\sqrt{2\pi})\int_0^{\pi_1}e^{-\eta^2/2}\,d\eta$ are given for different values of the argu-

ment η_1 . It may be observed that

$$\frac{1}{\sqrt{2\pi}} \int_{-\eta_1}^{+\eta_1} e^{-\eta^2/2} d\eta = 2 \frac{1}{\sqrt{2\pi}} \int_0^{\eta_1} e^{-\eta^2/2} d\eta$$

The values are related to the error function since

$$\operatorname{erf} \eta_1 = \frac{1}{\sqrt{\pi}} \int_{-\eta_1}^{+\eta_1} e^{-\eta^2} \, d\eta$$

so that the tabular values are equal to $\frac{1}{2}$ erf $(\eta_1/\sqrt{2})$. (Each figure in the body of the table is preceded by a decimal paint.)

10010	, , .			·						
771	0.00	0.01	0.02	0.03	0.04	0.05	0.06	0.07	0.08	0.09
0.0	00000	00399	00798	01197	01595	01994	02392	02790	03188	03586
0.1	03983	04380	04776	05172	05567	05962	06356	06749	07142	07355
0.2	07926	08317	08706	09095	09483	09871	10257	10642	11026	11409
0.3	11791	12172	12552	12930	13307	13683	14058	14431	14803	15173
0.4	15554	15910	16276	16640	17003	17364	17724	18082	18439	18793
0.5	19146	19497	19847	20194	20450	20884	21226	21566	21904	22240
0.6	22575	22907	23237	23565	23891	24215	24537	24857	25175	25490
0.7	25804	26115	26424	26730	27035	27337	27637	27935	28230	28524
0.8	28814	29103	29389	29673	29955	30234	30511	30785	31057	31327
0.9	31594	31859	32121	32381	32639	32894	33147	33398	33646	33891
1.0	34134	34375	34614	34850	35083	35313	35543	35769	35993	36214
1.1	36433	36650	36864	37076	37286	37493	37698	37900	38100	38298
1.2	38493	38686	38877	39065	39251	39435	39617	39796	39973	40147
1.3	40320	40490	40658	40824	40988	41149	41308	41466	41621	41774
1.4	41924	42073	42220	42364	42507	42647	42786	42922	43056	43189
1.5	1	43448	43574	43699	43822	43943	44062	44179	44295	44408
1.6	1 -	44630	44738	44845	44950	45053	45154	45254	45352	45449
1.7		45637	45728	45818	45907	45994	46080	46164	46246	46327
1.8	5	46485	46562	46638	46712	46784	46856	46926	46995	47062
1.9	}	47193	47257	47320	47381	47441	47500	47558	47615	47670
2.0		47778	47831	47882	47932	47962	48030	48077	48124	48169
2.1	ş ·	48257	48300	48341	48382	48422	48461	48500	48537	48574
2.2	1	48645	48679	48713	48745	48778	48809	48840	48870	48899
2.3		48956	48983	49010	49036	49061	49086	49111	49134	49158
2.4	49180	49202	49224	49245	49266	49286	49305	49324	49343	49361
2.5	49379	49396	49413	49430	49446	49461	49477	49492	49506	49520
2.6		49547	49560	49573	49585	49598	49609	49621	49632	49643
2.7		49664	49674	49683	49693	49702	49711	49720	49728	49736
2.8		49752	49760	49767	49774	49781	49788	49795	49801	49807
2.9	49813	49819	49825	49831	49836	49841	49846	49851	49856	49861
3.0		[Ì					10000	10001
3. 5										
4.0		}	1	}						
4.5	(1	1	1						
5.0	4999997133	<u> </u>								
			~~~~			·	·		·	

Equation (3-14) becomes

$$P = \frac{1}{\sqrt{2\tau}} \int_{-\eta_1}^{+\eta_1} e^{-\eta_2} d\eta \qquad (3-15)$$

where

$$\eta_1 = \frac{x_1}{\sigma} \tag{3-16}$$

Values of the Gaussian normal error function

$$\frac{1}{\sqrt{2\pi}}e^{-v^{2/2}}$$

and integrals of the Gaussian function corresponding to Eq. (3-15) are given in Tables 3-1 and 3-2

If we have a sufficiently large number of data points, the error for each point should follow the Gaussian distribution and we rould determine the probability that certain data fall within a specified deviation from the mean value Example 3-4 illustrates the method of computing the chances of finding data points within one or two standard deviations from the mean. (Table 3-3 gives the chances for certain deviations from the mean value of the normal distribution curve.)

#### Example 3-4

Calculate the probabilities that a measurement will fall within one two, and three standard deviations of the mean value, and compare them with the values in Table 3-3

Solution. We perform the calculation using Eq. (3-15) with  $\eta_1=1$ , 2, and 3. The values of the integral may be obtained from Table 3-2 We observe that

$$\int_{-\eta}^{+\eta_1} e^{-q^2/2} d\eta = 2 \int_{0}^{\eta_1} e^{-q^2/2} d\eta$$

to that

$$P(1) = (2)(0.34134) = 0.683$$

$$P(2) = (2)(0.47725) = 0.954$$

# Table 3-3 Chances for deviations from mean value of normal distribution curve

Using the odds given in Table 3-3, we would calculate the probabilities as

$$P(1) = \frac{2.15}{2.15 + 1} = 0.683$$

$$P(2) = \frac{21}{21 + 1} = 0.954$$

$$P(3) = \frac{356}{356 + 1} = 0.007$$

In many circumstances the engineer will not be able to collect as many data points as might be desired and only an approximation to the Gaussian distribution may be obtained. [Generally speaking, it is desirable to have about 20 measurements in order to obtain reliable estimates of standard deviation and general validity of the data. For smaller sets of data it is recommended that the following relation be used as the best estimate for the standard deviation:

$$\sigma = \left[ \frac{\sum_{i=1}^{n} (x_i - x_m)^2}{n-1} \right]^{\frac{1}{2}}$$
 (3-17)

Note that the factor n-1 is used in Eq. (3-17) instead of n as in Eq. (3-7).

It is a rare circumstance indeed when an experimenter does not find that some of his data points look had and out of place in comparison with the bulk of the data. He is therefore faced with the task of deciding if these points are the result of some gross experimental blunder and hence may be neglected or if they represent some new type of physical phenomenon which is peculiar to a certain operating condition. The engineer cannot just throw out those points which do not fit his expectations—he must have some consistent basis for climination.

### Example 3-5

Calculate the best estimate of standard deviation for the data of Example 3-2 based on Eq. (3-17).

Solution. The calculation gives

$$\sigma = \left[\frac{1}{10 - 1} (3.536)\right]^{i} = (0.3929)^{i} = 0.627 \text{ ft}$$

Suppose n measurements of a quantity are taken and n is large enough that we may expect the results to follow the Gaussian cross distribution. This distribution may be used to compute the proability that a given reading will deviate a certain amount from the mean. We would not expect a probability much smaller than 1 > because this would be unlikely to occur in the set of a measure were Thus, if the probability for the observed desistion of a certa new ra is less than I/n, a suspicious eve would be east at that point with an idea toward eliminating it from the data Actually, a row restrictive test is usually applied to eliminate data po is in a known as Chaurenet's criterion and specifies that a val of their & rejected if the prohability of obtaming the partial at contact we was the mean is less than 1/2n Table 3-4 lists values on the 10 00 deviation to standard deviation for various values of a source of the this criterion.

In applying Chauvenet's criterion to eliminate School with a points one first calculates the mean value and stanson days we using all data points. The deviations of the manager points are then compared with the standard deviation in accession with the information in Table 3-4 (or by a direct app' server as a server) and the dubious points are channated for its the collapsements

Table 3-4 Chausenet's eritation for 'me.

lection & seasons	
	true manner per .
	Particularly profession 1
Norm ywast.	* A1
•	•
:	1.13
,	1
4	1
3	1.0
<del>6</del> 7	· ~
	1 .
19	; `
12	2.5
23	:
50	
200	
300	*
300	
1.000 -	_

# Experimental methods for engineers

tion a new mean value and standard deviation are computed with the dubious points eliminated from the calculation. Note that Chauvenet's criterion might be applied a second or third time to eliminate additional points; but this practice is unacceptable, and only the first application may be used.

### Example 3-6

Using Chauvenet's criterion, test the data points of Example 3-2 for possible inconsistency. Eliminate the questionable points, and calculate a new standard deviation for the adjusted data.

Solution. The best estimate of the standard deviation is given in Example 3-5 as 0.627 ft. We first calculate the ratio  $d_i/\sigma$  and eliminate data points in accordance with Table 3-4.

$d_i$				
σ				
0.499				
0.187				
1.845				
0.563				
2.046				
0.260				
0.761				
0.043				
0.314				
0.218				

In accordance with Table 3-4, we may eliminate only point number 5. When this point is eliminated, the new mean value is

$$x_m = \frac{1}{9}(51.80) = 5.756 \text{ ft}$$

The new value of the standard deviation is now calculated with the following table:

Reading	$d_i = x_i - x_m$	$(x_1-x_m)^2\times 10^2$
1	-0 436	19.010
2	-0.026	0.0676
3	1.034	106.916
4	-0.496	24.602
6	-0.306	9.364
7	0.334	11.156
8	-0.116	1.346
9	0.054	0.292
10	-0.006	0.0036

$$\sigma = \left[\frac{1}{n-1} \sum_{i=1}^{n} (x_i - x_n)^{\frac{1}{2}}\right]^{\frac{1}{2}} = \left[\frac{1}{4} (1.728)\right]^{\frac{1}{2}}$$
$$= (0.216)^{\frac{1}{2}} = 0.465 \text{ ft}$$

Thus, by the elimination of the one point, the standard deviation has been reduced from 0.627 to 0.465 ft. This is a 25 8 percent reduction

# 3-8 THE CHI-SQUARE TEST

In the previous discussion we have noted that random experimental errors would be expected to follow the Gaussian distribution, and the examples illustrated the method of calculating the probability of occurrence of a particular experimental determination. We might ask how it is known that the random errors or deviations do approximate a Gaussian distribution. In general, we may ask how we ran determine if experimental observations match some particular expected distribution for the data. As a simple example, consider the tossing of a coin. We would like to know if a certain coin is "honest," i.e., unweighted toward either heads or tails. If the coin is unweighted, then heads should occur half the time and tails should occur half the time. But suppose we do not want to take the time to make thousands of tosses to get the frequency distribution of heads and tails for a large number of tosses. Instead, we toss the com a few times and wish to infer from these few tosses whether the coin is unweighted or weighted. Common sense tells us not to expect exactly six heads and six tails out of, say, 12 tosses. But how much deviation from this arrangement could we tolerate and still expect the coin to be unweighted? The chi-square test of goodness of fit is a suitable way of answering this question. It is based on a calculation of the quantity chi squared defined by

$$\chi^{3} = \sum_{i=1}^{n} \frac{[(\text{observed value})_{i}, -(\text{expected value})_{i}]^{2}}{(\text{expected value})_{i}}$$
(3-18)

where n is the number of observations. The expected value is the value which would be obtained if the measurements matched the expected distribution perfectly.

The chi-squared test may be applied to check the validity of various distributions. Calculations have been made [2] of the ability that the actual measurements match the expected dist

Table 3-5 Chi-square. P is the probability that the value in the table will be exceeded for a given number of degrees of freedom Rt

0.995	0.090	0.975	0.950	0.900	0.750	0.500	0.250	0.100	0.050	0.023	0.01	a.
0.01393 0.0100 0.0717 0.207	0.0201 0.0201 0.115 0.297	0.07982 0.0506 0.216 0.484	0.01393 0.103 0.352 0.711	0.0158 0.211 0.584 1.06	0.102 0.575 1.21 1.92	0.455 1.30 2.37 3.36	1.32 4.11 5.30 6.63	2.71 4.61 6.25 7.78	3.84 5.99 7.81 9.49	5.02 7.38 9.35 11.1	6.63 9.21 11.3 13.3 15.1	7.88 10.6 12.8 14.9 16.7
0.472 0.989 1.34 1.73		0.551 1.69 2.70 3.25	3.33 3.33 3.33 3.94	2.20 2.20 2.49 4.17	2. 45 2.45 5.90 6.74 4.74	5.35 7.35 9.35 9.35	7.84 9.04 10.2 11.4	10.6 12.0 13.4 14.7 16.0	12.6 14.1 15.5 16.9 18.3	14.4 16.0 17.5 19.0 20.5	16.8 18.5 20.1 21.7 23.2	18.5 20.3 22.0 23.6 25.2
4.07 4.07		5.63 6.53 6.63 6.26 6.26	4.57 5.23 5.89 6.57 7.26	5.58 6.30 7.04 7.79 8.55	7.58 8.44 9.30 10.2	10.3 12.3 13.3 14.3	13.7 14.8 16.0 17.1 18.2	17.3 18.5 19.8 21.1 22.3	19.7 21.0 23.7 25.0	21.0 23.3 24.7 27.5 1.5	24.7 26.2 27.7 39.1	26.8 28.3 32.3 32.8
5.14 5.70 6.26 6.84 7.43			7.96 8.67 9.39 10.1 10.9	9.31 10.1 11.7 12.4	11.9 12.8 13.7 14.6 15.5	15.3 17.3 18.3 19.3	20.5 20.5 22.2 33.4 8.4 8.4	23.5 27.5 27.0 27.0 28.1	26.3 27.6 28.9 30.1 31.4	38.3 30.2 31.5 4.5 5.5 5.5	32.0 33.4 34.8 36.2 37.6	34.3 35.7 37.2 38.6 40.0
8.03 8.64 9.26 9.89	8 90 9.54 10 2 10 9 11.5	10.3 11.0 11.7 12.4 13.1	133 133 133 133 133 133 133 133 133 133	13.2 14.0 14.0 15.7 16.5	16.3 17.2 19.0 19.0	25222 25222 252223	24.9 26.0 27.1 28.2 29.3	22 23 23 23 24 24 24 24 24 24 24 24 24 24 24 24 24	33.9 35.2 36.2 37.7	35.5 36.8 39.4 40.6	38.9 40.3 43.0 43.0	4.24 45.6 46.9 6.9
11.8 12.5 13.1	22.22.22.23.25.25.25.25.25.25.25.25.25.25.25.25.25.	13.8 16.3 16.3 16.8	15.4 16.2 16.9 17.7 18.5	17 3 18.1 18.9 19.8 20.6	20.8 21.7 22.7 23.6 24.5	25.3 26.3 27.3 28.3	30.4 31.5 32.6 33.7 34.8	35.6 36.7 37.9 39.1 40.3	38.9 40.1 42.6 13.8	44.5 45.7 7.0	45.6 48.3 40.6 50.9	45.6 48.3 47.0 49.6 48.3 51.0 49.6 52.3 50.9 53.7

Turom C. M. thompson, Biomerina, 32 (1941), as abringed by McGraw-Hill Book Company, New York, 1963.

tion, and these probabilities are given in Table 3-5. In this table, F represents the number of degrees of freedom in the measurements and is given by

$$F = n - k \tag{3-19}$$

where n is the number of observations and L is the number of imposed conditions on the expected distribution. A plot of the chi-quared function is given in Fig. 3-3

While we initiated the discussion on the chi-squared test in terms of random error following the Gaussian distribution, the test is an important tool for testing any expected experimental distribution. In other words, we might use the test to analyze random errors or to check the adherence of certain data to an expected distribution. We interpret the test by calculating the number of degrees of freedom and  $\chi^2$  from the experimental data. Then, consulting Table 3-4, we obtain the probability P that this value of  $\chi^2$ , or higher values, could occur by chance. If  $\chi^2=0$ , then the assumed or expected distribution and measured distribution match exactly. The larger the value of  $\chi^2$ , the larger is the dissergement between the assumed distribution and the observed values, or the smaller the probability that the observed distribution matches the expected distribution.




Fig. 3-3. The chi-squared function.

for more specific information on the chi-squared test and the derivation of the probabilities associated with it.

One may note that the heading of this section includes the term "goodness of fit." We see that the chi-squared test may be used to determine how good a set of experimental observations fits an assumed distribution. In connection with this test we may remark that data may sometimes be "too good" or "too consistent," For example, we would be quite surprised if in the conduct of an experimental test, the results were found to check with theory exactly or to follow same well-defined relationship exactly. We might find, for instance, that a temperature controller maintained a ret point temperature exactly, with no measurable deviation whatsoever. Experienced laboratory people know that controllers usually do not operate this way, and would immediately suspect that the temperature recorder might be stuck or otherwise defective. The paint of this brief remark is that one must be suspicious of high values of P as well as A good rule of thumb is that if P lies between 0.1 and 0.9, the observed distribution may be considered to fallow the assumed distribution. If P is either less than 0.02 or greater than 0.08, the assumed distribution may be considered unlikely. The use of the chi-squared test is illustrated in the following examples.

## Example 3.7

Two dies are rolled 100 times, and the following results are noted:

Number	Number of occurrences
2	2)
3	3
-)	Ø
5	122
H	1.3
7	10
8	15
Ħ	13
10	S
13	4
12	)

Calculate the probability that the dice are unloaded.

Solution. Eleven observations have been made with only one restriction; the number of rolls of the dice is fixed. Thus, F=11=1-10. If the dice are unloaded, a short listing of the combinations of the dice will give the probability of accurrence for each number. The expected value

of each number is then the probability multiplied by 100, the total number of throws. The values of interest are tabulated below.

Number	Observed	Probability	Expected
2	2	1/36	2 778
3	3	1/18	5 556
4	9	1/12	8 333
5	12	1/9	11 (11
6	14	5/36	13 859
7	19	1/6	16 667
8	15	5/36	13 899
9	13	1/9	12 111
10	8	1/12	8 333
11	4	1/18	4 446
12	t	1/36	2 778

From these data the value of the squared is calculated as 3.754 If Table 3.5 is consulted, the probability is calculated as P = 0.957

### Example 3-8

A consistence of Dismes resulting in three leads and seven tails. Using the chi-aquared test, estimate the probability that the consistency is unweighted. Suppose another set of tosses of the same coin is made such that four heads and six tails are obtained. What is the probability of having an unweighted coin based on the information from both sets of data?

Solution. For each set of data we may make only two observations the number of heads and the number of tails. Thus, n=2. Furthermore, we impose one restriction on the data, the number of tosses is fixed. Thus k=1 and the number of degrees of freedom is

$$F = n - k = 2 - 1 = f$$

The values of interest are

	Observed	Expected
Heads Tails	3 7	5

For these values, x7 is calculated as

$$\chi^1 = \frac{(3-5)^2}{5} + \frac{(7-5)^2}{5} = 1.60$$

Consulting Table 3-5 we find P = 0.22, that is, there is a 22 percent chance that this distribution is just the result of random fluctuations and that the coin may be unweighted.

Now consider the additional information we gain about the coin from the second set of observations. We now have four observations: the number of heads and tails in each set. There are only two restrictions on the data; the total number of tosses is fixed in each set. Thus, the number of degrees of freedom is

$$F = n - k = 4 - 2 = 2$$

For the second set of data the values of interest are

	Observed	Expected
Heads	4	5
Tails	6	5

Chi-squared is now calculated on the basis of all four observations.

$$\chi^2 = \frac{(3-5)^2}{5} + \frac{(7-5)^2}{5} + \frac{(4-5)^2}{5} + \frac{(6-5)^2}{5} = 2.0$$

Consulting Table 3-5 again we find P = 0.39. So, with the additional information we find a stronger likelihood that the tosses are following a random variation and that the coin is unweighted.

### Example 3-9

A test is conducted to determine the effect of cigarette smoke on the eating habits and weight of mice. One group is fed a certain diet while being exposed to a controlled atmosphere containing cigarette smoke. A control group is fed the same diet but in the presence of clean air. The observations are given below. Does the presence of smoke cause a loss in weight?

	Gained weight	Lost weight	Total
Exposed to emoke Exposed to clean air	61 65	89 77	150 142
Total	126	166	292

Solution Clearly, there are four observations in this experiment, but we are faced with the problem of deciding on the expected values. We cannot just take the "clean-sir" data as the expected values because some of the behavior might be a result of the special diet which is fed to both groups of muc. Consequently, about the best retimate we can make is one based on the total sample of mice. Thus, the expected frequencies would be

Expected fraction to gain weight = ### Expected fraction to lose weight = ###

The expected values for the groups would thus be

	Gained weight	Lost weight
Exposed to emoke	111150 = 64 7	121150 - 85 3
Exposed to clean air	1:1142 - 61 3	111142 = 80 7

We observe that there are three restrictions on the data. (1) the number exposed to emoke, (2) the number exposed to clean air, and (3) the additional restriction involved in the calculation of the expected fractions which gain and lose weight. The number of degrees of freedom is thus

$$F = 4 - 3 = 1$$

The value of chi squared is calculated from

$$\chi^{2} = \frac{(61 - 64.7)^{2}}{64.7} + \frac{(89 - 85.3)^{2}}{853} + \frac{(65 - 61.3)^{3}}{61.3} + \frac{(77 - 807)^{3}}{807} = 0.767$$

From Table 3-5 we find  $P \sim 0.41$ , or there is a 41 percent chance that the difference in the observations for the two groups is just the result of random fluctuations. One may not conclude from this information that the presence of eigenetic smoke causes a loss in weight for the mire

### 3-9 METHOD OF LEAST SQUARES.

Suppose we have a set of observations  $x_1, x_2, \ldots, x_n$ . The sum of the squares of their deviations from some mean value is

$$S = \sum_{i=1}^{n} (x_i - x_{\sigma})^i$$
(3-20)

Now suppose we wish to minimize S with respect to the mean value  $x_m$ . We set

$$\frac{\partial S}{\partial x_m} = 0 = \sum_{i=1}^{n} -2(x_i - x_m) = -2\left(\sum_{i=1}^{n} x_i - nx_m\right)$$
 (3-21)

where n is the number of observations. We find that

$$x_m = \frac{1}{n} \sum_{i=1}^{n} x_i \tag{3-22}$$

or the mean value which minimizes the sum of the squares of the deviations is the arithmetic mean. This example might be called the simplest application of the method of least squares. We shall be able to give only one other application of the method, but it is of great utility in analyzing experimental data.

Suppose that the two variables x and y are measured over a range of values. Suppose further that we wish to obtain a simple analytical expression for y as a function of x. The simplest type of function is a linear one; hence we might try to establish y as a linear function of x. (Both x and y may be complicated functions of other parameters so arranged that x and y vary approximately in a linear manner. This matter will be discussed later.) The problem is one of finding the best linear function, for the data may scatter a considerable amount. We could solve the problem rather quickly by plotting the data points on graph paper and drawing a straight line through them by eye. Indeed this is common practice, but the method of least squares affords an opportunity to obtain a better functional relationship than by the guesswork of plotting. We seek an equation of the form

$$y = ax + b \tag{3-23}$$

We therefore wish to minimize the quantity

$$S = \sum_{i=1}^{n} \{y_i - (ax_i + b)\}^2$$
 (3-24)

This is accomplished by setting the derivatives with respect to a and b equal to zero. Performing these operations there results

$$nb + a\Sigma x_i = \Sigma y_i \qquad (3-25)$$

$$b\Sigma x_i + a\Sigma x_i^2 = \Sigma x_i y_i$$
 (3-26)

Solving Eqs. (3-25) and (3-26) simultaneously gives

$$a = \frac{n\Sigma x_i y_i - (\Sigma x_i)(\Sigma y_i)}{n\Sigma x^2 - (\Sigma x_i)^2}$$
(3-27)

$$b = \frac{(\Sigma y_i)(\Sigma x_i^4) - (\Sigma x_i y_i)(\Sigma x_i)}{n\Sigma x_i^4 - (\Sigma x_i)^4}$$
(3-28)

The method of feast squares may also be used for determining higher order polynomials for fitting data. One only needs to perform additional differentiations to determine additional constants. For example, if it were desired to obtain a least squares fit according to the quadratic function

$$v = ax^2 + bx + c$$

the quantity

$$S = \sum_{i=1}^{n} [y_i - (ax_i^2 + bx_i + c)]^2$$

would be minimized by setting the following derivatives equal to zero

$$\frac{\partial S}{\partial a} = 0$$
  $\frac{\partial S}{\partial b} = 0$   $\frac{\partial S}{\partial c} = 0$ 

The solution for the values of a, b, and c is more tedious than in the linear case but is equally straightforward. Example 3-10 gives a simple illustration of the application of the method of least squares to the determination of a linear function to approximate a set of experimental data

In the above discussion of the method of least squares no mention has been made of the influence of experimental uncertainty on the calculation. We are considering the method primarily for its utility in fitting an algebraic relationship to a set of data points. Clearly, the various x, and y, could have different experimental uncertainties. To take all these into account requires a rather tedious calculation procedure which we shall not present here; howver, we may state the following rules.

If the values of x, and y, are taken as the data value in y and the value of x on the fitted curse for the same ralue of y, then there is a presumption that the uncertainty in x is large compared with that in y.

- If the values of x; and y; are taken as the data value in y and the
  value on the fitted curve for the same value of x, the presumption
  is that the uncertainty in y dominates.
- If the uncertainties in x_i and y_i are believed to be of approximately equal magnitude, a special averaging technique must be used.

In Example 3-10, rule 2 is assumed to apply.

### Example 3-10

From the following data obtain y as a linear function of x using the method of least squares:

yı	1,
1.2	1.0
2.0	3 6
2.4	3.4
3.5	4 0
3.5	5.2
$\Sigma y_i = 12.6$	$\Sigma z_{*} = 15 2$

Solution. We seek an equation of the form

$$y = ax + b$$

We first calculate the quantities indicated in the following table:

$x_iy_i$	$x_1^2$
1.2	1 0
3.2	2.50
8.16	11 50
14.0	16.0
18.2	27.04
$\Sigma x_i y_i = 44.76$	$\Sigma x_i^2 = 58.10$

We calculate the value of a and b, using Eqs. (3-27) and (3-28) with n=5:


$$a = \frac{(5)(44.76) - (15.2)(12.6)}{(5)(58.16) - (15.2)^2} = 0.540$$

$$b = \frac{(12.6)(58.16) - (44.76)(15.2)}{(5)(58.16) - (15.2)^2} = 0.879$$

Thus, the desired relation is

$$y = 0.540x + 0.879$$

A plot of this relation and the data points from which it was derived is shown in the accompanying figure



### 3-10 STANDARD DEVIATION OF THE MEAN

We have taken the arithmetic mean value as the best estimate of the true value of a set of experimental measurements. Considerable discussion has been devoted to the Gaussian normal error distribution and to an examination of the various types of errors and deviations which may occur in an experimental measurement. But one very important question has not yet been answered, i.e., how good (or precise) is this arithmetic mean value which is taken as the best estimate of the true value of a set of readings? To obtain an experimental answer to this question it would be necessary to repeat the set of measurements and find a new arithmetic mean eral, we would find that this new arithmetic mean would differ from the previous value, and thus we would not be able to resolve the problem until a large number of sets of data were collected We would then know how well the mean of a single set approximated the mean which would be obtained with a large number of sets The mean value of a large number of sets is presumably the true value Consequently, we wish to know the standard deviation of the mean of a single set of data from this true value

It turns out that the problem may be resolved with a statistical analysis which we shall not present here. The result is

$$\sigma_{-} = \frac{\sigma}{\sqrt{n}}$$

(3-29)

where

 $\sigma_m = \text{standard deviation of the mean value}$ 

s = standard deviation of the set of measurements

n = number of measurements in the set

An example illustrates the use of Eq. (3-23).

### Example 3-11

For the data of Example 3-2, estimate the unvertainty in the calculated mean value of the readings.

Solution. We shall make this estimate for the original data and for the reduced data of Example 3-5. For the original data the standard deviation of the mean is

$$\sigma_{rr} = \frac{\sigma}{\sqrt{\pi}} = \frac{9.627}{\sqrt{10}} = 9.198 \text{ ft}$$

The arithmetic mean value calculated in Example 3-2 was  $x_{+}=5.613$  ft. We could now specify the uncertainty of this value by using the odds of Table 3-3:

Using the data of Erample 3-6, where one point has been eliminated by Chauvenet's orderion, we may make a better estimate of the mean value with less uncertainty. The standard deviation of the mean is calculated as

$$c_{\pi} = \frac{c}{\sqrt{\pi}} = \frac{0.455}{\sqrt{9}} = 0.155 \text{ ft}$$

for the mean raine of 5.75% ft. Thus, we would estimate the uncertainty as

$$r_{\pi} = 5.750 \pm 0.155 \,\text{ft}$$
 (2.15 to 1)

### 3-11 GRAPHICAL ANALYSIS And Curve Fitting

Engineers are well known for their ability to plot many curves of experimental data and to extract all sorts of significant facts from these curves The better one understands the physical phenomena involved in a certain experiment, the better he is able to extract a wide variety of information from graphical displays of experimental Because these physical phenomena may encompass all engineering science, we cannot discuss them here except to emphasize that the person who is usually most successful in analyzing experimental data is the one who understands the physical processes behind the data. Blind curve-plotting and cross-plotting usually generate an excess of displays which are confusing not only to the management or supervisory personnel who must pass on the experiments but are sometimes even confusing to the experimenter himself To be blunt, the engineer should give considerable thought to the kind of information that he is looking for before he ever takes the graph paper out of the package

Assuming that the engineer knows what he wants to examine with graphical presentations, the plots may be eatefully prepared and checked against appropriate theories Frequently, a correlation of the experimental data is desired in terms of an analytical expression between variables which were measured in the experiment. When the data may be approximated by a straight line, the analytical relation is easy to obtain, but when almost any other functional variation is present, difficulties are usually encountered. This lact is easy to understand since a straight line is casily recognizable on graph paper, whereas the functional form of a curve is rather doubtful The curve could be a polynomial, exponential, or complicated logarithmic function and still present roughly the same appearance to the eye. It is most convenient, then, to try to plot the data in such a form that a straight line will be obtained for certain types of functional relationships. If the experimenter has a good idea of the type of function that will represent the data, then the type of plot is easily selected. He frequently is able to estimate the functional form which the data will take on the bases of theoretical considerations and the results of previous experiments of a similar nature.

Table 3-6 summarizes several different types of functions and plotting methods which may be used to produce straight lines on graph paper. The graphical measurements which may be made to

Table 3-6 Methods of plotting various functions to obtain straight lines

Functional relationship	Method of plot	Graphical determination of parameters
y = ax + b	y versus x on linear paper	Slope = $a$
$y = ax^b$	log y versus log x on log-log paper	Slope = b $\log x = 0$ or $x = 1.0$ $\log x$
$y = ae^{bx}$	log y versus x on semilog paper	Slope = à log e log a 0 x
$y = \frac{x}{a + bx}$	$\frac{1}{y}$ versus $\frac{1}{x}$ on linear paper	Extrapolated $ \begin{array}{c} \frac{1}{y} \\ 0 \\ \frac{1}{x} \end{array} $

Table 3-6 Methods of plotting various functions to obtain straight lines (Continued)

(Continued)		
Functional relationship	Method of plot	Graphical Extermination of parameters
y = a + bz + cz*	y = y, version z od linear x = z, paper	Stope or been
$y - \frac{z}{a + \delta z} + c$	y - y, resuscon heres paper	$\begin{array}{c ccccccccccccccccccccccccccccccccccc$
y = ocheter	$\log \left[ \left( \frac{y}{y_1} \right)^{3/(e-y_1)} \right] \text{ ver}$ was z on seculog paper	$\log \left[ \left( \frac{1}{r_{i}} \right)^{r+1} \right]$ $Siope - r \log r$ $b - rr_{i} \log r$
		1

determine the various constants are also shown. It may be remarked that the method of least squares may be applied to all these relations to obtain the best straight line to fit the experimental data.

## **PROBLEMS**

- 3-1 The resistance of a resistor is measured 10 times, and the values determined are 100.0, 100.9, 99.3, 99.9, 100.1, 100.2, 99.9, 100.1, 100.0, and 100.5. Calculate the uncertainty in the resistance.
- 3-2 A certain resistor draws 110.2 volts and 5.3 amp. The uncertainties in the measurements are  $\pm 0.2$  volt and  $\pm 0.06$  amp respectively. Calculate the power dissipated in the resistor and the uncertainty in the power.
- 3-3 A small plot of land has measured dimensions of 50.0 by 150.0 ft. The uncertainty in the 50-ft dimension is ±0.01 ft. Calculate the uncertainty with which the 150-ft dimension must be measured to ensure that the total uncertainty in the area is not greater than 150 percent of that value it would have if the 150-ft dimension were exact.
- 3-4 Two resistors R₁ and R₂ are connected in series and parallel. The values of the resistances are

 $R_1 = 100.0 \pm 0.1 \text{ ohms}$ 

 $R_2 = 50.0 \pm 0.03$  ohms

Calculate the uncertainty in the combined resistance for both the series and the parallel arrangements.

- 3-5 A resistance arrangement of 50 ohms is desired. Two resistances of  $100.0 \pm 0.1$  ohms and two resistances of  $25.0 \pm 0.02$  ohms are available. Which should be used, a series arrangement with the 25-ohm resistors or a parallel arrangement with the 100-ohm resistors? Calculate the uncertainty for each arrangement.
- 3-6 The following data are taken from a certain heat-transfer test. The expected correlation equation is  $y = ax^b$ . Plot the data in an appropriate manner, and use the method of least squares to obtain the best correlation.

7	£
33.2	2040
32 0	2580
42.7	23%0
57 8	3220
125.0	3570
17 4	1690
21.4	2130
27.8	2423
52 1	2900
43.1	3310
15 8	1020
19 2	1240
15 1	1360
12 9	1710
78 5	2070

Calculate the mean deviation of these data from the lest correlation.

3-7 A horseshoes player stands 30 ft from his target. The results of the tosses are

Tota	Deviation from target, ft		
1	0		
2	+3		
3	-4 2		
4	0		
5	+15		
6	+2 4		
7	-2 6		
8	+3 5		
9	+2 7		
10	0		

On the basis of these data would you say that he is a good player or a poor player? What advice would you give in regard to improving his game?

- 3-8 Calculate the probability of drawing a full house (three of a kind and two of a kind) in the first 5 cards from a 52-card deck
- 3-9 Calculate the probability of filling an inside straight with one draw from the remaining 48 cards of a 52-card deck
- 3-10 A voltmeter is used to measure a known voltage of 100 volts. Forty percent of the readings are within 0.5 volt of the true value. Estimate the standard deviation for the incline What is the probability of an error of 0.75 volt?

3-11 In a certain mathematics course the instructor informs the class that grades will be distributed according to the following scale provided that the average class score is 75:

Grade	Score		
A	90-100		
В	80-90		
C	70-80		
D	60-70		
F	Below 60		

Estimate the percentage distribution of grades for 5, 10, and 15 percent failing. Assume that there are just as many A's as F's.

3-12 For the following data points y is expected to be a quadratic function of x. Obtain this quadratic function by means of a graphical plot and also by the method of least squares.

y	$\boldsymbol{x}$
1.9	1
9.3	2
21.5	3
42.0	4
115.7	5

3-13 It is suspected that the rejection rate for a plastic-cup-molding machine is dependent on the temperature at which the cups are molded. A series of short tests is conducted to examine this hypothesis with the following results:

ثغير

Temperature	Total production	Number rejected
T ₁ T ₂ T ₃ T ₄	150 75 120 200	12 8 10 13

On the basis of these data do you agree with the hypothesis?

3-14 A capacitor discharges through a resistor according to the relation

$$\frac{E}{E_0} = e^{-i/RC}$$

where

 $E_0 = \text{voltage at time zero}$ 

R = resistance

C = capacitance

The value of the capacitance is to be measured by recording the time necessary for the voltage to drop to a value E. Assuming that the resistance is known accurately, derive an expression for the percent uncertainty in the capacitance as a function of the uncertainty in the measurements of E₁ and E.

3-15 In heat-exchanger applications, a log mean temperature difference is defined by

$$\Delta T_m = \frac{(T_{k_1} - T_{e_1}) - (T_{k_2} - T_{e_1})}{\ln \left[ (T_{k_1} - T_{e_1}) / (T_{k_2} - T_{e_2}) \right]}$$

where the four temperatures are measured at appropriate inlet and outlet conditions for the heat-exchanger fluid. Assuming, that all four temperatures are measured with the same ab-olute uncertainty  $m_{T_1}$  derive an expression for the percentage uncertainty in  $\Delta T_n$  in terms of the four temperatures and the value of  $w_T$ . Recall that the percentage uncertainty is

$$\frac{w_{\Delta Tm}}{\Delta T} \times 100$$

3-16 A certain length measurement is made with the following results;

Reading	z, m.		
1	49 36		
2	50 12		
3	45 98		
4	49 24		
5	49 26		
6	50 56		
7	49.18		
8	48 89		
9	49 33		
10	49.33		

Calculate the standard deviation, the mean reading, and the uncertainty. Apply Chauvenet's criterion as needed

3-17 Devise a method for plotting the Gaussian normal error distribution such that a straight line will result (Ans.

 $(1/\eta)$  In  $[\sqrt{2\pi}P(\eta)]$  versus  $\eta$ .) Show how such a plot may be labeled so that it can be used to estimate the fraction of points which lie below a certain value of  $\eta$ . Subsequently show that this plot may be used to investigate the normality of a set of data points. Apply this reasoning to the data points of Example 3-2 and Probs. 3-6 and 3-7.

### REFERENCES

- Kline, S. J., and F. A. McClintock: Describing Uncertainties in Singlesample Experiments, Mech. Eng., p. 3, January, 1953.
- Mood, A. M., and F. A. Graybill: "Introduction to the Theory of Statistics," 2nd ed., McGraw-Hill Book Company, New York, 1953.
- Schenck, H.: "Theories of Engineering Experimentation," McGraw-Hill Book Company, New York, 1961.
- Wilson, E. B.: "An Introduction to Scientific Research," McGraw-Hill Book Company, New York, 1952.
- Young, H. D.: "Statistical Treatment of Experimental Data," McGraw-Hill Book Company, New York, 1962.

## Basic electrical measurements and sensing devices

### 4-1 INTRODUCTION.

A large majority of measuring device either use some basic electrical principle for their operation or rely on an electronic device for the intermediate modifying and final rendout stages. As a consequence, it is to our advantage to discuss some of the more important electric devices currently employed and to emphasize their relationship to the measurement oroces. We shall first consider the measurement of the basic electrical quantities of current and voltage. Next, we shall examine some simple circuits which may be used for modification and measurement of imput signals. The physical principles and operating characteristics of some of the more important electric transducers will then be studied and their application indicated.

In all the following discussions due consideration must be given to impedance matching. The principles of matching were discussed in Sec 2-9, and the reader should keep this discussion in mind as the exposition of the present chapter progresses.

### 4-2 THE MEASUREMENT OF CURRENT

If a point charge of q coulombs moving with a velocity r is seted upon by an electric and insgnetic field, the resultant force on the point charge is given by the basic relation

$$\hat{f} = q(\hat{E} + f \times \hat{B})$$
 newtons (4-1)

where

\(\bellet = \) electric field intensity, volts/m
\(\beta = \) velocity, m/sec

 $(1/\eta)$  ln  $[\sqrt{2\pi} P(\eta)]$  versus  $\eta$ .) Show how such a plot may be labeled so that it can be used to estimate the fraction of points which lie below a certain value of  $\eta$ . Subsequently show that this plot may be used to investigate the normality of a set of data points. Apply this reasoning to the data points of Example 3-2 and Probs. 3-6 and 3-7.

## REFERENCES

- Kline, S. J., and F. A. McClintock: Describing Uncertainties in Single-sample Experiments, Mcch. Eng., p. 3, January, 1953.
- Mood, A. M., and F. A. Graybill: "Introduction to the Theory of Statistics," 2nd ed., McGraw-Hill Book Company, New York, 1963.
- Schenck, H.: "Theories of Engineering Experimentation," McGraw-Hill Book Company, New York, 1961.
- Wilson, E. B.: "An Introduction to Scientific Research," McGraw-Hill Book Company, New York, 1952.
- Young, H. D.: "Statistical Treatment of Experimental Data," McGraw-Hill Book Company, New York, 1962.

## Basic electrical measurements and sensing devices

#### 4-1 INTRODUCTION.

Alarge majority of measuring devices either use some basic electrical practile for their operation or rely on an electronic device for the intermediate modifying and final readout stages. As a consequence, it is to our advantage to discuss some of the more important electric devices currently employed and to emphasize their relationship to the measurement process. We shall first consider the measurement of the basic electrical quantities of current and voltage. Next, we shall estamics some simple circuits which may be used for modification and measurement of input signals. The physical principles and operating characteristics of some of the more important electric transducers will then be studied and their application indicated.

In all the following discussions due consideration must be given to impedance matching. The principles of matching were discussed m Sec 2-9, and the reader should keep this discussion in mind as the appearance of the present chapter progresses

### 4-2 THE MEASUREMENT OF CURRENT

If a point charge of q coulombs moving with a velocity v is acted upon by an electric and magnetic field, the resultant force on the point charge is given by the basic relation

$$\hat{f} = q(\hat{E} + \hat{v} \times \hat{B})$$
 newtons (4-1)

where

£ = electric field intensity, volts/m

f = velocity, m/sec

B = magnetic flux density, webers/m2




Fig. 4-1. Current-carrying conductor in a magnetic field.

Now suppose that a current-earrying conductor is placed in a magnetic field as shown in Fig. 4-1. Let us consider the case where E=0. The electric current through the conductor is the time rate of motion of charge or

$$i = \frac{dq}{d\tau} \tag{4-2}$$

We could write

$$i ds = \frac{dq}{dr} ds = v dq (4-3)$$

and the force exerted on the charge is given by Eq. (4-1) as

$$dF = dq(\bar{v} \times \bar{B}) = i \, d\bar{s} \times \bar{B} \tag{4-4}$$

for E = 0. Integrating along the length of the conductor,

$$F = \int_0^L i \, d\bar{s} \times \bar{B} \tag{4-5}$$

If the magnetic flux vector and length vector are oriented at an angle of 90°, Eq. (4-5) becomes

$$F = BiL (4-6)$$

Equation (4-6) gives the magnitude of the force on a current-carrying conductor placed at a right angle with respect to a magnetic field. In order to integrate Eq. (4-5) and obtain Eq. (4-6) it has been assumed that end effects on the conductor are negligible and that the region L is sharply defined so that the magnetic field is zero outside this region and constant inside the region.




Fig. 4-2. Current-carrying coil in a magnetic field.

Clearly, the above principles may be used to construct an instrument to measure electric current. We construct a coil, as shown in Fig. 4-2, place it in a magnetic field, and measure the force extred on the coil as the result of the electric current. If the coil has N turns and the length of each turn in the magnetic field is L, the force on the coil is

$$F = NBiL$$
 (4-7)

The force is measured by observing the deflection of a force-restraining device such as a spring. The above principles form the bars of the construction of the mirror galvanometer shown in Fig. 4-3. A permanent magnet is used to produce the magnetic field, while the telescope arrangement and expanded scale improve the readability.



ment




Fig. 4-4. D'Arsonval movement used as a pointer-type instrument.

of the instrument. The meter shown in Fig. 4-3 is designated as the D'Arsonval moving-roil type. The metal ribbon furnishes the torsional-spring restraining force in this case, while a filamentary suspension would be used for a more sensitive instrument.

Instead of the mirror and light-beam arrangement shown in Fig. 4-3, the D'Arsonval movement could be used as a pointer-type instrument, as shown in Fig. 4-4; however, such an instrument has a lower sensitivity than the mirror galvanometer because of the addi-

Table 4-1 Typical galvanometer characteristics;

	Sensitivity per rem or coals division	Period,	Resistance, chine	
Construction type			External CDR	Coil
Elack suspension, one-reler ligid bearn	9,99991 #3 9,69994 #3 9,6995 #2 9,995 #5	49 20 6 1.5	199,999 79,999 19,999 2,599	899 800 639 899
	0.05 pt 0.2 pt 0.5 pt	7 5 1.5	19 40 40	15 15 21
Taul ruspension, self-contained optical system	9.0995 #2 9.095 #2 9.05 #2	3 3 2	25,000 5,000 2,500	550 -1,639 359
	0.5 μτ 2.5 μτ 2.5 μτ	3 2 2	59 12 59	17 13 13
Tout suspension, pointer type	9.029 p2 9.125 p2 1.0 pt.	5.3 3.5 3	42,000 10,000 950	1,999 1,999 259
	45 μν 259 μν	4.5 2	30 50	16 20

^{*} According to Sweeney [5].

tional mass of the pointer and decreased readability resulting from the relatively shorter scale length. The sensitivities of various commercial galvanometers as compiled by Sweeney [5] are given in Table 4-1. In this table the period is the undamped natural period of oscillation of the moving coil. The sensitivity values are those obtained with an external circuit resistance necessary to give critical damping.

It is clear that the D'Arsonval movement, in one form or another, may be used for the measurement of de-current. When this movement is connected to an a-c current, the meter will either vibrate or, if the frequency is sufficiently high, indicate zero. In either event, the D'Arsonval movement is not directly applicable to the measurement of a-c current. A detailed analysis of the response of galvanement of accourrents to various a-c waveforms is even by Frank [2].

The two most common types of movements used for ac current measurement are the iron-vane, or moving-iron, and electrody-nanometer arrangements. In the iron-vane instrument, as shown in Fig. 4-5, the current is applied to a fixed coil. The iron vane is movable and connected to a restraining spring as shown. The discrement of the vane is then proportional to the inductive force




Fig. 4-5. Principle of operation of the iron-vane or maying-iron instrument.




Fig. 4-6. Basic features of the electrodynamometer / movement.

exerted by the coil. The meter is subject to eddy-current losses in the iron vane and various hysteresis effects which hait its accuracy.

The features of the electrodynamometer movement are shown in Fig. 4-6. This movement is similar to the D'Arsonval movement except that the permanent magnet is replaced by an electromagnet which may be actuated by an a-c current. Consequently, the field in the electromagnet may be made to operate in synchronization with an a-c current in the moving coil. In order to use the electrodynamometer movement for a-c measurements, it is necessary to connect the electromagnet and moving coil in series as shown in Fig. 4-7.




Fig. 4-7. Electrodynamometer movement used as an ammeter.

Both the iron-vane and the electrodynamometer movements are normally used for low-frequency applications with frequences from 25 to 125 eps. Special designs of the electrodynamometer movement may be used to extend its range to about 2,000 cps Various theoretical considerations for these movements are discussed by Frank [2]. Both the iron-vane and the electrodynamometer instruments indicate the rins value of the alternating current, and the meter deflection varies with I_m, where

$$I_{rms} = \left(\frac{1}{T}\int_0^T \vec{v} dr\right)^{\dagger} \qquad (4-8)$$

The scale of the instrument is not necessarily based on a square law because the proportionality constant between Iim, and the meter deflection changes somewhat with the current

An important feature of the electrodynamometer instrument is that it may be calibrated with direct current and that the calibration will hold for ac- applications within the frequency range of the instrument. The iron-vane instrument is not as versatile because of the residual magnetism in the iron when direct current is used.

A rectifier arrangement may also be used for a-c measurements. In this device an a-c waveform is modified by some type of rectifier such that current is obtained with a steady d-c component. A D'Arsonval movement may then be used to measure the d-c component and thereby indicate the value of the alternating current which was applied to the rectifier.

For measurements of high-frequency alternating currents, a thromocouple meter is usually used. This type of meter is indicated in Fig. 4-8. The alternating current is passed through a heater element, and the temperature of the element is indicated by a thermocouple connected to a D'Arsonval meter. The thermocouple indicates the rims value of the current because the average power.



FIg. 4-8. Schematic of a thermocouple meter.

dissipated in the heater is equal to  $I_{\rm rms}^2R$ . The instrument reading is independent of waveform because of this relationship between the thermal emf generated in the thermocouple and the power dissipated in the heater. The thermal emf generated in the thermocouple varies approximately with the square of current, although slight deviations from the square law may be obtained because of change in heater resistance with temperature and other side effects. Alternating currents with frequencies up to 100 Mc may be measured with thermocouple meters.

### 4-3 VOLTMETERS

A d-c voltmeter may be constructed very easily by modifying a D'Arsonval movement, as shown in Fig. 4-9. In this arrangement, a large resistor is placed in scrics with the movement; thus, when the instrument is connected to a voltage source, the current in the instrument is an indication of the voltage. The range of the voltmeter may be altered by changing the internal series resistor. The voltmeter is usually rated in terms of the input voltage for full-scale deflection or in terms of the ratio of internal resistance to the voltage for full-scale deflection. A series-resistor arrangement may also be used with the iron-vane and electrodynamometer instruments for measurement of rms values of a-c voltages. For low frequencies up to about 125 eps the electrodynamometer meter may be calibrated with d-c voltage and the calibration used for a-c measurements.

Electrostatic forces may also be used to indicate electric potential difference. For this purpose two plates are arranged as shown in Fig. 4-10. One plate is fixed, and the other is mounted in jeweled bearings so that it may move freely. A spiral spring provides a restraining force on the movable plate. The electric potential difference to be measured is impressed on the two plates. If two complete disks were used instead of the sectoral plate arrangement, the




Fig. 4-9. D'Arsonval meter used as a voltmeter.




Fig. 4-10. Electrostatic voltmeter movement.

net torque would be zero, however, with the arrangement shown, the fringe effects of the electric field produce a net force in the indicated direction which is proportional to the equate of the rms voltage. As the movable plate changes position, the capacitance changes and hence the proportionality between the stored rnergy and the voltage varies with the impressed voltage.

The electrostatic voltmeter may be used for either a-c or devoltage measurements, but potentials above 100 volts are required in order to produce a sufficiently strong torque in the system. The neter may be calibrated with direct current and then used for measurement of rms values of a-c voltagers, regardless of the waveform. Electrostatic voltmeters are generally applicable up to frequencies of 50 Me. It may be noted that the electrostatic voltmeter has an extremely high input impedance for de-applications but a much lower a-c impedance as a result of the capacitance reactance. The capacitance may be about 20 pf for a 5,000-voltmeter.

In the preceding paragraphs we have discussed some of the more important devices which are used for measurement of electric current and voltage. We have not discussed electronic methods because they are generally considered as composite measurement systems and use one or more of the above devices for readout purposes.

## 4-4 BASIC INPUT CIRCUITRY

The output of an electric transducer is frequently of such a nature that it must be modified to produce a signal in a more usable form. At this point we wish to discuss the circuits which may be used as input-modifying circuits. The transducer may be of the active or passive type; an active element furnishes an energy input to the circuit, while a passive element merely modifies the electrical properties of the circuit through a change in some characteristic like resistance, capacitance, or inductance. A pressure transducer whose electrical resistance changes with pressure is a passive element, while a piezo-electric crystal or photoelectric cell is an example of an active element. The particular transducer must be connected to appropriate circuitry which will modify the signal so that it may eventually be displayed on an indicator or recorder. Clearly, there are many types of circuits which may be used, and we shall be able to discuss only a few representative cases.

We have already discussed the measurement of electric current with appropriate meter movements. A simple type of input circuit might use the current flow through a passive-resistance transducer as an indication of the value of the resistance. The schematic arrangement for this type of measurement is shown in Fig. 4-11. A change in the physical variable to be measured is represented in this case by a change in the resistance R, as indicated by the movable contact. The current is given by

$$i = \frac{E_i}{R + R_i} \tag{4-9}$$

Let the maximum resistance of the transducer be  $R_m$ . Then the current may be written in dimensionless form as

$$\frac{i}{E_i/R_i} = \frac{1}{(R/R_m)(R_m/R_i) + 1}$$
 (4-10)

It would be desirable to have the current output vary in a linear




Fig. 4-11. Current-sensitive input circuit.

Circuit senses change in resistance

R of the transducer.

manner with the resistance of the transducer. Unfortunately this is not the ease as shown in Eq. (4-10), although the output may be approximately linear for some ranges of operation.

The circuit shown above may be modified slightly by using a voltmeter as in Fig. 4-12. Let us assume that the internal impedance of the voltmeter is very large compared with the resistance in the circuit so that we may neglect the current drawn by the meter. The current flow is still eaven by

$$t = \frac{E_s}{R + R_s} \tag{4-11}$$

Let E be the voltage across the transducer, as indicated in Fig. 4-12. Then

$$\frac{E}{E_0} = \frac{iR}{i(R+R_0)} = \frac{(R/R_-)(R_-/R_0)}{1 + (R/R_0)(R_-/R_0)}$$
(4-12)

Now we have obtained a voltage indication as a measurement of the resistance R, but a nonlinear output is still obtained. The advantage of the circuit in Fig. 4-12 ever the one in Fig. 4-11 is that a voltage measurement is frequently easier to perform than a current inexamement. The voltages-ensitive circuit is called a boliate circuit.


We might define the sensitivity of the ballast eircuit as the rate of change of the voltage indication with respect to the resistance R Thus,

$$S = \frac{dE}{dR} = \frac{E_r R_r}{(R_r + R)^2}$$
(4-13)

We would like to design the circuit so that the sensitivity S is a maximum. The circuit design variable which is at our disposal is the fixed resistance R, so that we wish to maximize the sensitivity with respect to this variable. The maximizing condition

$$\frac{dS}{dR_i} = 0 = \frac{E_i(R - R_i)}{(R_i + R)^3}$$
(4-14)

Fig. 4-12. Voltage-sensitive input circuit. Change in resistance R is Indicated through change in veltage indication.






Fig. 4-13. Simple voltage-divider circuit.

is applied. Thus, for maximum sensitivity we should take  $R_i = R$ . But, since R is a variable, we may select the value of  $R_i$  only for the range of R where the sensitivity is to be a maximum.

In both of the above circuits a current measurement has been used as an indication of the value of the variable resistance in the transducer. In some instances it is more convenient to use a voltage-divider circuit, as indicated in Fig. 4-13. In this arrangement a fixed voltage  $E_0$  is impressed across the total transducer resistance  $R_n$  while the sliding contact is connected to the voltmeter with internal resistance  $R_n$ . If the impedance of the meter is sufficiently high, the indicated voltage E will be directly proportional to the variable resistance  $R_n$ , that is,

$$\frac{E}{E_0} = \frac{R}{R_n} \quad \text{for } R_1 \gg R \tag{4-15}$$

With a finite meter resistance a current is drawn which affects the voltage measurement. Considering the internal resistance of the meter, the current drawn from the voltage source is

$$i = \frac{E_c}{R_m - R + R_s R / (R + R_s)}$$
 (4-16)

The indicated voltage is therefore

$$E = E_0 - i(R_n - R)$$

or

$$\frac{E}{E_c} = \frac{R/R_n}{(R/R_n)(1 - R/R_n)(R_n/R_i) + 1}$$
(4-17)

As a result of the loading action of the meter the voltage does not vary in a linear manner with the resistance R. If Eq. (4-17) is

taken as the true relationship between voltage and resistance, then an expression for the loading error may be written as

Loading error = 
$$\frac{(E/E_t)_{true} - (E/E_t)_{true}}{(E/E_t)_{true}}$$

The true value is taken from Eq (4-17) and the indicated value from Eq (4-15). The error based on full-scale reading is

Loading error = 
$$-\frac{(R/R_n)^2(1-R/R_n)}{(R/R_n)(1-R/R_n)+R_n/R_n}$$
 (4-18)

The voltage-divider circuit shown in Fig. 4-13 has the dead-vantage that the indicated voltage is affected by the loading of the meter. This difficulty may be alleviated by utilizing a voltage-balancing potentiometer circuit, as shown in Fig. 4-14. In this arrangement a known voltage  $E_b$  is impressed on the resistor  $R_a$ , while the unknown voltage as impressed on the same resulter through the galvanometer with internal resistance  $R_a$  and the movable contact on the resistor  $R_a$ . At some position of the movable contact the galvanometer will indicate zero current, and the unknown voltage may be calculated from

$$\frac{E}{E_0} = \frac{R}{R_-}$$
(4-19)

Notice that the internal resistance of the galvanometer does not affect the reading in this case, however, it does influence the sensitivity of the circuit. The voltage-balaneing potentiometer circuit is widely used for precise measurements of small electric potentials particularly those generated by thermocouples. In order to a contract the particularly those generated by thermocouples for order to a contract the properties of the supply voltage F_c contracts the properties of the supply to the supply with the properties of the supply to th




Fig. 4-14. Simple voltage-balancing ometer circuit.




Fig. 4-15. Potentiometer circuit incorporating features for standardization of battery voltage.

voltage, but this represents an unreliable source because of aging characteristics. The aging problem is solved by using a standardcell arrangement to standardize periodically the battery voltage, as shown schematically in Fig. 4-15. When switch S: is in position A and switch S₁ is closed, the circuit is the same as Fig. 4-14. Then, when switch  $S_1$  is opened and switch  $S_2$  is placed in position  $B_1$ , the standard cell E, is connected in the circuit. The variable compensator resistance Re is adjusted until the galvanometer indicates balance conditions. The protective resistor  $R_1$  may then be bypassed by closing switch S1 and a fine adjustment of the compensator resistor effected. The protective resistor  $R_1$  is placed in the circuit to avoid excessive current drain on the standard cell and also to protect the galvanometer. Note that the standard-cell voltage is impressed on a fixed portion of the resistance R. Once the battery has been standardized, switch S₁ may be placed in the A position and the unknown voltage E measured. The battery may be standardized as often as necessary for the particular application.

## Example 4-1

The output of a transducer with a total resistance of 150 ohms is to be measured with a voltage-sensitive circuit like that shown in Fig. 4-12. The sensitivity is to be a maximum at the midpoint of the transducer. Calculate the sensitivity at the 25- and 75-percent positions, assuming a voltage source  $E_i$  of 100 volts.

Solution. For maximum sensitivity at the midpoint of the range we take

$$R_i = R = \frac{1}{9}R_m = 75 \text{ ohms}$$

At the 25-percent position, R = (0.25)(150) = 37.5 ohms, and the sensitivity is calculated from Eq. (4-13):

$$S = \frac{dE}{dR} = \frac{E_1 R_1}{(R_1 + R_1)^2} = \frac{(100)(75)}{(75 + 375)^3} = 0.592 \text{ volt/ohm}$$

At the 75-percent position the corresponding sensitivity is

$$S = \frac{(100)(75)}{(75 + 112.5)^2} = 0.213 \text{ volt/ohm}$$

#### Example 4-2

The voltage-divider circuit is used to measure the output of the transducer in Example 4-1 A 100-volt source is used  $(E_{\bullet} = 100 \text{ volts})$ , and the internal resistance of the meter  $R_{\bullet}$  is 10,000 ohms — Calculate the lossing error at the 25- and 75-percent positions

Solution We use Eq. (4-18) for the calculation with

$$\frac{R_1}{R} = \frac{10,000}{150} = 66.7$$

At the 25-percent position  $R/R_m = 0.25$  and

Loading error = 
$$-\frac{(0.25)^4(1-0.25)}{(0.25)(1-0.25)+66.7}$$
  
=  $-0.000703 = -0.0703.25$ 

At the 75-percent position  $R/R_m = 0.75$  and

Loading error = 
$$-\frac{(0.75)^2(1-0.75)}{(0.75)(1-0.75)+66.7}$$
  
=  $-0.00211 = -0.211\%$ 

#### 4-5 BRIDGE CIRCUITS

Bridge circuits are employed in a warsety of applications for the measurement of resistance, inductance, and capacitance under both steady-state and transient conditions. We shall be concerned with the characteristics of some of the more prominent types of circuits and their application to various measurements and control

The Wheatstone bridge is normally used for the comparison and measurement of resistances in the range of 1 ohm to 1 megohm. A




Fig. 4-15. Potentiometer circuit incorporating features for standardization of battery voltage.

voltage, but this represents an unreliable source because of aging The aging problem is solved by using a standardeharaeteristies. cell arrangement to standardize periodically the battery voltage, as shown schematically in Fig. 4-15. When switch S2 is in position A and switch S₁ is closed, the circuit is the same as Fig. 4-14. Then, when switch S₁ is opened and switch S₂ is placed in position B, the standard cell E, is connected in the circuit. The variable compensator resistance R_e is adjusted until the galvanometer indicates balance conditions. The protective resistor R₁ may then be bypassed by closing switch S1 and a fine adjustment of the compensator resistor effected. The protective resistor  $R_1$  is placed in the circuit to avoid excessive current drain on the standard cell and also to protect the galvanometer. Note that the standard-cell voltage is impressed on a fixed portion of the resistance R. Once the battery has been standardized, switch S₁ may be placed in the A position and the unknown voltage E measured. The battery may be standardized as often as necessary for the particular application,

#### Example 4-1

The output of a transducer with a total resistance of 150 ohms is to be measured with a voltage-sensitive circuit like that shown in Fig. 4-12. The sensitivity is to be a maximum at the midpoint of the transducer. Calculate the sensitivity at the 25- and 75-percent positions, assuming a voltage source  $E_i$  of 100 volts.

Solution. For maximum sensitivity at the midpoint of the range we take

$$R_i = R = \frac{1}{2}R_m = 75 \text{ ohms}$$

At the 25-percent position, R = (0.25)(150) = 37.5 ohms, and the sensitivity is calculated from Eq. (4-13):

$$S = \frac{dE}{dR} = \frac{E_i R_i}{(R_i + R)^2} = \frac{(100)(75)}{(75 + 37.5)^2} = 0.592 \text{ volt/ohm}$$

At the 75-percent position the corresponding consitivity as

$$S = \frac{(100)(75)}{(75 + 112.5)^3} = 0.213 \text{ volt/shm}$$

#### Example 4-2

The voltage-divider circuit is used to measure the output of the transducer in Example 4-1. A 100-volt source is used  $(E_a = 100 \text{ volts})$ , and the internal reustance of the meter  $R_i$  is 10,000 ohms—Calculate the loading error at the 25- and 75-percent positions.

Solution We use Eq. (4-18) for the calculation with

$$\frac{R_i}{R} = \frac{10,000}{150} = 66.7$$

At the 25-percent position  $R/R_{m} = 0.25$  and

Loading error = 
$$-\frac{(0.25)^4(1-0.25)}{(0.25)(1-0.25)+667}$$
  
=  $-0.000703 = -0.0703\%$ 

At the 75-percent position  $R/R_{-} = 0.75$  and

Loading error = 
$$-\frac{(0.75)^3(1-0.75)}{(0.75)(1-0.75)+65.7}$$
  
=  $-0.00211 = -0.211\%$ 

#### 4-5 BRIDGE CIRCUITS

Bridge circuits are employed in a variety of applications for the incasurement of resistance, inductance, and emperitance under both steady-state and transient conditions. We shall be concerned with the characteristics of some of the more pronuent types of circuits and their application to various measurements and control

The Wheatstone bridge is normally used for the comparison and measurement of resistances in the range of 1 ohm to 1 megohm A




Fig. 4-16. Schematic of basic Wheatstone bridge.

schematic of the bridge is given in Fig. 4-16. It is comprised of four resistances:  $R_1$ .  $R_2$ ,  $R_3$ ,  $R_4$ .  $R_1$  is a variable resistance, whereas  $R_x$  is some unknown. A voltage is applied to the bridge by closing the switch  $S_1$ , and by adjusting the variable resistance  $R_1$ , the bridge may be balanced so that the potential at B equals the potential at D. This balance condition may be attained by connecting the galvanometer in the circuit through  $S_2$  and adjusting the value of  $R_1$  until the galvanometer indicates zero-current flow. condition the voltage drop through resistance R2 must equal the voltage drop through  $R_1$ . Thus,

$$i_2R_2 = i_1R_1$$
Also,
$$i_2 = i_3 = \frac{E}{R_2 + R_2}$$
and
$$i_1 = i_z = \frac{E}{R_1 + R_2}$$

If the currents are climinated from these relations, we obtain

$$\frac{R_2}{R_3} = \frac{R_1}{R_z}$$
or
$$R = \frac{R_1 R_3}{R_z}$$
(4-20)

$$R_z = \frac{R_1 R_2}{R_2} \tag{4-21}$$

If the resistances  $R_1$ ,  $R_2$ , and  $R_3$  are known, then the value of the unknown resistance  $R_s$  is easily determined.

The term "rstio arms" is frequently used in describing two known adjacent arms in a Wheatstone bridge. The galvanometer is usually connected to the junction of these two known resistors. In Fig. 4-16, R₄ and R₅ would normally be called the ratio arms.

If accurate measurements are to be made with the bridge circuit, the values of the resistors must be precisely known and the gal-vanometer must be sufficiently sensitive to detect small degrees of imbalance in the circuit. When the unknown res stance R, is placed in the circuit, care must be taken to use feads which have a resistance which is small in comparison with the unknown.

#### Example 4-3

For the basic Wheatstone bridge in Fig. 4-16, determine the uncertainty in the measured resistance  $R_c$  as a result of an uncertainty of 1 percent in the known resistances. Repeat for 0.05 percent

Solution. We use Eq. (3-2) to estimate the uncertaints. We have

$$\frac{\partial R_s}{\partial R_i} = \frac{R_t}{R_t}$$
 $\frac{\partial R_s}{\partial R_s} = -\frac{R_1R_t}{R_s^3}$ 
 $\frac{\partial R_s}{\partial R_s} = \frac{R_s}{R_s}$ 

For a 1 percent uncertainty in the known resistances this gives

$$\frac{\omega_{8c}}{R_{\pi}} = (0.01^{2} + 0.01^{3} + 0.01^{3})^{\frac{1}{2}} = 0.01732$$

$$= 1.732\%$$

= 1.102%

For a 0.05 percent uncertainty in the known resistances the corresponding uncertainty in  $R_s$  is 0.0866 percent

The basic Wheatstone bridge circuit may also be employed for the measurement of a-c impedances. The main problem is that more than one balance condition must be made in order to obtain the null condition; one balance obtains the null on the real part of the waveform, while another obtains the null on the imaginary part. There are some types of a-c bridges which may be balanced with two independent adjustments. Several of these types are shown in Table 42 along with the balance conditions which may be used to determine values of the unknown quantities.

Since an alternating current is involved, the null condition may not be sensed by a galvanometer as in the case of the d-c Wheatstone




Fig. 4-16. Schematic of basic Wheatstone bridge.

schematic of the bridge is given in Fig. 4-16. It is comprised of four resistances:  $R_1$ ,  $R_2$ ,  $R_3$ ,  $R_z$ .  $R_1$  is a variable resistance, whereas  $R_z$  is some unknown. A voltage is applied to the bridge by closing the switch  $S_1$ , and by adjusting the variable resistance  $R_1$ , the bridge may be balanced so that the potential at B equals the potential at D. This balance condition may be attained by connecting the galvanometer in the circuit through  $S_2$  and adjusting the value of  $R_1$  until the galvanometer indicates zero-current flow. At this condition the voltage drop through resistance  $R_2$  must equal the voltage drop through  $R_1$ . Thus,

$$i_2R_2 = i_1R_1$$

Also,

$$i_2=i_3=\frac{E}{R_2+R_3}$$

and

$$i_1 = i_x = \frac{E}{R_1 + R_x}$$

If the currents are eliminated from these relations, we obtain

$$\frac{R_z}{R_3} = \frac{R_1}{R_z} \tag{4-20}$$

or.

$$R_x = \frac{R_1 R_3}{R_2} {4-21}$$

If the resistances R₁, R₂, and R₃ are known, then the value of the unknown resistance R_s is easily determined.

The term "ratio arms" is frequently used in describing two known adjacent arms in a Wheatstone bridge. The galvanometer is usually connected to the junction of these two known resistors. In Fig. 4-16, R. and R. would normally be called the ratio arms.

If accurate measurements are to be made with the hindge circuit, the values of the resistors must be precisely known and the galvanometer must be sufficiently sensitive to detect small degrees of imbalance in the circuit. When the unknown resistance R, is placed in the circuit, care must be taken to use leads which have a resistance which is small in comparison with the unknown.

#### Example 4-3

For the bane Wheatstone bridge in Fig. 4-16, determine the uncertainty in the measured resistance R. as a result of an uncertainty of 1 percent in the known resistance. Repeat for 0.05 percent

Solution We use Eq. (3-2) to estimate the uncertainty. We have

$$\frac{\partial R_s}{\partial R_1} = \frac{R_1}{R_t} = \frac{\partial R_s}{\partial R_t} = -\frac{R_1R_s}{R_s^2} = \frac{\partial R_s}{\partial R_s} = \frac{R_1}{R_t}$$

For a I percent uncertainty in the known resistances this gives

$$\frac{w_{s_s}}{R_s} = (0.01^3 + 0.01^3 + 0.01^3)^{\frac{1}{2}} = 0.01732$$
$$= 1.732\%$$

For a 0.05 percent uncertainty in the known resistances the corresponding uncertainty in R, is 0.0866 percent

The basic Wheatstone bridge circuit may also be employed for the measurement of a-c impedances. The main problem is that more than one balance condition must be made in order to obtain the null condition; one balance obtains the null on the imaginary part. There are some types of a-c bridges which may be balanced with two independent adjustments. Several of these types are shown in Table 4-2 along with the balance conditions which may be used to determine values of the unknown quantities.

Since an alternating current is involved, the null condition may not be sensed by a galvanometer as in the case of the d-c W heatstone

Table 4-2 Summary of bridge circuit	5		
Circuit	Balance relations	Name of bridge and remarks	
A	$C_x = \frac{C_1 R_2}{R_1}$ $R_x = \frac{R_1 R_1}{R_2}$	Basic Wheatstone bridge. Greatest sen- sitivity when bridge arms are equal.	
$C_x$ $R_3$ $C_3$	·		
B	C- R. R.	77.	
$R_1$ $C_2$ $R_3$ $R_4$ $C_3$ $R_4$ $C_4$ $R_5$	$\frac{C_z}{C_z} = \frac{R_1}{R_1} - \frac{R_1}{R_x}$ $C_zC_1 = \frac{1}{\omega^2 R_z R_x}$ If $C_1 = C_z$ and $R_1 = R_x$ $f = \frac{1}{2\pi R_1 C_2}$	Wien bridge. May be used for frequency measurement with indicated relations.	
C	$L_z = C_1 R_1 R_2$ $R_z = \frac{C_1 R_1}{C_2} - R_2$	Owen bridge	
32			

Table 4-2 Summary of bridge circuits (Continued)

Table 4-2 Summary of Dridge circuits (Continued)							
Circuil	Balance relations	Name of bridge and temarks					
D R. T.	$= \frac{MLC - 1}{R_s}$ $= \frac{R_s R_s}{R_s}$	Resonance bridge. At balance conditions may be used for frequency measurement with $f=\frac{1}{2\pi\sqrt{LC}}$					
E Rept to the first to the firs	$L_s = R_s R_s C$ $R_s = \frac{R_s R_s}{R_s}$	Mazwell bridge					
R, T,	$L_{*} = \frac{R_{*}R_{*}C}{1 + \omega \nabla R_{*}}$ $R_{*} = \frac{\omega \nabla R_{*}R_{*}R_{*}}{1 + \omega \nabla R_{*}}$	Hay bridge					




Fig. 4-17. Schematic for analysis of unbaianced bridge.

bridge; some type of a-c instrument must be used. This might be a vacuum-tube voltmeter, an oscilloscope, or a rectifier type of meter. A pair of headphones might also be used when audio-frequency signals are involved. For radio-frequency signals a communication receiver could be used as the detector in the bridge circuit.

It may be noted from Table 4-2 that for some types of a-c bridge circuits the balance condition is independent of frequency (types A, C, and E), while for others the frequency must be known in order to apply the balance conditions (types B, D, and F). Thus, with the capacitances and resistances known for the Wien bridge we could use the bridge as a frequency-measuring device.

Bridge circuits are very useful for experimental measurements. The d-c bridge is widely used for measuring the resistance of various transducers such as resistance thermometers, strain gages, and other devices which register the change in a physical variable through a change in resistance. The a-c bridge circuits are used for inductance and capacitance measurements. Numerous transducers operate on the principle of a change in capacitance or inductance with a change in the measured quantity, and the bridge circuits may be employed to detect these changes. Bridge circuits are also useful in an unbalanced condition because a rather small change in one of the bridge arms can produce a very large change in the detector signal which may be used to control other circuits.

Bridge circuits may operate on either a null or a deflection principle. The null condition has been described above as where the galvanometer or sensing device reads zero at balance conditions. At any other condition the galvanometer reading will be deflected from the null condition by a certain amount which depends on the degree of unbalance. Thus, the signal at the galvanometer or detector may be used as an indication of the unbalance of the bridge and may indicate the deviation of one of the arms from some specified balance condition. The use of the deflection bridge is particularly

important for the measurements of dynamic signals where insufficient time is available for achieving balance conditions.

Consider the bridge circuit shown in Fig. 4-17. R₁, R₂, R₃, and R₃ are the lour arms of the bridge; R₃ is the galvanometer revisance; and is and i, and i, are the battery and galvanometer currents, respectively. R₃ represents the resistance of the battery circuit. When the bridge is only shightly unbalanced, it can be shown that the value of R₃ does not appreciably influence the effective resistance of the bridge circuit as presented to the galvanometer (see Ref. [2], page 255). As a result, the following relation for the galvanometer current may be derived.

$$i_{\sigma} \approx \frac{E_{\sigma}}{R + R_{\sigma}}$$
(4.22)

where R is the effective resistance of the bridge circuit presented to the galvanometer and is given by

$$R = \frac{R_1 R_4}{R_1 + R_4} + \frac{R_1 R_1}{R_2 + R_4} \tag{4-23}$$

This effective resistance  $R \approx indicated$  in Fig. 4-18. The solitage presented at the terminals of the galvanometer  $E_r \approx$ 

$$E_s = E\left(\frac{R_1}{R_1 + R_4} - \frac{R_2}{R_2 + R_3}\right)$$
 (4-24)

The voltage impressed on the bridge E depends on the battery or external circuit resistance  $R_i$  and the resistance of the total bridge circuit as presented to the battery circuit, which we shall designate as  $R_i$ . It can be shown that for small unbalances the resistance  $R_i$  may be calculated by assuming that the galvanometer is not connected in the circuit. Thus

$$R_1 = \frac{(R_1 + R_1)(R_2 + R_1)}{R_1 + R_1 + R_2 + R_1}$$
(4-25)

Fig. 4-18. Equivalent circuit at bridge as presented to the galvanometer.

The voltage impressed on the bridge is then

$$E = E_b \frac{R_0}{R_0 + R_b} \tag{4-26}$$

Because the deflection described above and indicated by Eq. (4-22) is based on the determination of the galvanometer current, the circuit is said to be current-sensitive. If the deflection measurement were made with a vacuum-tube voltmeter, oscilloseope, or other high-impedance device, the current flow in the detector circuit would be essentially zero since, as  $R_s \to \infty$ ,  $i_s \to 0$  in Eq. (4-22). Even so, there is still an unbalanced condition at the galvanometer or detector terminals of the bridge. This condition is represented by the voltage between terminals A and C for the case of a high-impedance detector. Such an arrangement is called a voltage-sensitive deflection-bridge circuit. The voltage indication for such a bridge may be determined from Eq. (4-24).

For relatively large unbalances in a bridge circuit it may become necessary to shunt the galvanometer to prevent damage. Such an arrangement is shown in Fig. 4-19a. In this case the voltage across the galvanometer may still be given to a sufficiently close approximation by Eq. (4-24), but the current through the galvanometer must be computed by considering the shunt resistance  $R_p$ . The total resistance of the bridge and shunt combination as seen by the galvanometer circuit is given by

$$R_e = \frac{R_p R}{R_p + R} \tag{4-27}$$

and the galvanometer current is now given by

$$i_{\mathfrak{o}} = \frac{E_{\mathfrak{o}}}{R_{\mathfrak{o}} + R_{\mathfrak{o}}} \tag{4-28}$$




Fig. 4-19. (a) Galvanometer shunt arrangement for use with bridge of Fig. 4-18; (b) galvanometer with series resistance for use with bridge in Fig. 4-18.

The galvanometer current may also be reduced by using a series remator as shown in Fig. 4-19b. For this case the galvanometer current becomes

$$t_t = \frac{E_q}{R + R_- + R_-}$$
(4-20)

where R. is the value of the series resistor

#### Example 4.4

The Wheatstone bridge current of Fig. 4-16 has ratio arms (R, ind R) of 6,000 and 600 ohms. A galanometer a pith a resistance G 0 ohms and a sensitivity of 0.01  $\mu$ a, mm is connected between B and D, and the adjustable resistance R, reads 340 ohms. The galanometer deflection is 50 mm, and the battery voltage as 4 volts. Assuming no internal lattery resistance calculate the value of the unknown resistance R. Repeat for P, and R, having values of 600 and 60 ohms.

Solution. In this instance the bridge is operated on the defection principle. For purposes of analysing the circuit we use Figs. 4-17 and 4-15. The galls anometer current is calculated from the deflection and sensitivity as

In the circuit of Fig. 4-17 the resistances are

$$R_1 = 0$$
  $R_1 = 340$   $R_2 = 6,000$   $R_4 = 600$   $R_4 = R_4$   $R_4 = 70$ 

We also have E = 4.0 volts

Combining Eq. (4-22) to (4-24), we obtain

$$i_s = \frac{E[R_s/(R_1 + R_4) - R_s/(R_4 + R_4)]}{R_s + [R_1R_4/(R_1 + R_4) + R_3R_5/(R_5 + R_4)]}$$

Solving for Rt, we have

$$R_4 = \frac{ER_1R_3 - \iota_{e}[R_eR_1(R_0 + R_0) + R_0R_0R_0]}{\iota_{e}(1 + R_1 + R_0)(R_1 + R_0) + ER_0}$$

Using numerical values for the various quantities, we obtain

R. - 33 93 ohms

Taking  $R_1 = 600$  and  $R_1 = 60$ , we obtain

R. - 33 93 ohms

#### 4-6 FILTER CIRCUITS

It is often desirable to use only a certain range of frequencies which are obtained from a transducer input. Perhaps these frequencies represent the signal, while other frequencies may be unwanted harmonics and noise resulting from some sort of distortion in the input arrangement. If a relatively narrow range of frequencies is used, it is usually possible to operate with much simpler electronic circuits for amplification purposes than when a broad frequency range is used.

Various arrangements may be used for filter circuits, but they all fall into three eategories: (1) low-pass, (2) high-pass, and (3) bandpass circuits. The circuit may be constructed from passive elements or may involve electronic amplification to eliminate losses. The low-pass filter permits the transmission of frequencies below a certain cutoff value with little or no attenuation, while the high-pass filter permits the transmission of frequencies above a cutoff value. The bandpass filter permits the transmission of a certain range or band of frequencies while attenuating frequencies both above and below the limits of this range. The approximate performance curves for the three types of filters are shown in Fig. 4-20. The cutoff frequency is designated by fe for the high- and low-pass filters, and the limits of the frequency transmission in the bandpass filter are defined by the frequencies  $f_1$  and  $f_2$ . It must be noted that the various filter circuits do not provide a sharp cutoff frequency; i.e., there is a transmission of some frequencies above or below the eutoff value. ulthough the signal attenuation becomes more pronounced as the frequency becomes further removed from cutoff conditions.

A summary of several types of passive filter eirenits is given in Fig. 4-21, as recommended in Ref. [8]. The various filter sections




Fig. 4-20. Approximate performance curves for three types of filters.




Fig. 4-21. Basic filter sections and design formulas according to Ref. (8). In the for-

may be used separately or in combination to produce more desirable cutoff performance. In the m-derived sections the quantity m is defined by

$$m = \sqrt{1 - \left(\frac{f_c}{f_c}\right)^2} \tag{4-30}$$

for a low-pass filter and

$$m = \sqrt{1 - \left(\frac{f_{\infty}}{f_{\varepsilon}}\right)^2} \tag{4-31}$$

for a high-pass filter, where  $f_c$  is the desired cutoff frequency and  $f_{\infty}$  is a frequency having high attenuation. When only one m-derived section is used, a value of m=0.6 is recommended [8]. When a filter is designed for a particular application, it is usually important that the impedance of the filter circuit be matched with the connecting circuitry. A consideration of the matching of impedances in filter circuits is beyond the scope of our discussion, and the interested reader should consult Ref. [9] for more information.

A measurement of the degree of amplification or attenuation of a circuit is its gain or amplification ratio. Gain is defined as

$$Gain = \frac{output}{input}$$
 (4-32)

The output and input quantities may be voltage, current, or power, depending on the application. Gain usually is measured in decibel units, which are defined in terms of a logarithmic ratio.

Decibels = 
$$10 \log \frac{P_2}{P_1}$$
 (4-33)

where  $P_1$  and  $P_2$  are the input and output powers respectively. The voltage or current gain may be defined in a similar manner.

The filter circuits shown in Fig. 4-21 are the most commonly employed and are generally the most efficient passive element types. It is possible to construct filters in RC and RL arrangements instead of the LC designs given in Fig. 4-21; however, the circuits which employ resistive elements are generally not as efficient because they remove energy from the system. Some simple RL and RC filter sections are shown in Table 4-3, along with the appropriate equations describing their input-output voltage characteristics. The phase-lag angle  $\phi$  is also given.



may be used separately or in combination to produce more desirable cutoff performance. In the m-derived sections the quantity m is defined by

$$m = \sqrt{1 - \left(\frac{f_c}{f_\infty}\right)^2} \tag{4-30}$$

for a low-pass filter and

$$m = \sqrt{1 - \left(\frac{f_{\infty}}{f_{\epsilon}}\right)^2} \tag{4-31}$$

for a high-pass filter, where  $f_c$  is the desired eutoff frequency and  $f_{\infty}$  is a frequency having high attenuation. When only one m-derived section is used, a value of m=0.6 is recommended [8]. When a filter is designed for a particular application, it is usually important that the impedance of the filter circuit be matched with the connecting circuitry. A consideration of the matching of impedances in filter circuits is beyond the scope of our discussion, and the interested reader should consult Ref. [9] for more information.

A measurement of the degree of amplification or attenuation of a circuit is its gain or amplification ratio. Gain is defined as

$$Gain = \frac{\text{output}}{\text{input}}$$
 (4-32)

The output and input quantities may be voltage, current, or power, depending on the application. Gain usually is measured in decibel units, which are defined in terms of a logarithmic ratio.

Decibels = 
$$10 \log \frac{P_2}{P_1}$$
 (4-33)

where  $P_1$  and  $P_2$  are the input and output powers respectively. The voltage or current gain may be defined in a similar manner.

The filter circuits shown in Fig. 4-21 are the most commonly employed and are generally the most efficient passive element types. It is possible to construct filters in RC and RL arrangements instead of the LC designs given in Fig. 4-21; however, the circuits which employ resistive elements are generally not as efficient because they remove energy from the system. Some simple RL and RC filter sections are shown in Table 4-3, along with the appropriate equations describing their input-output voltage characteristics. The phase-lag angle  $\phi$  is also given.

Table 4-3 Some simple RL and RC fliter sections according to Ref. [9]

Drag	rd m	Tupe	Time constant or resonant freq	Formula and approximation
ο ε _{,η} (	E _{mi}	A low-pan RC	7 - RC	$\frac{E_{nt}}{E_{*}} = \frac{1}{\sqrt{1 + \omega^{2} / 1}} = \frac{1}{\omega T}$ $\theta \epsilon = -\tan^{-1}(P\omega C)$
E _o ,	R Emi	B high-pass RC	T - 20	$\frac{F_{in}}{F_{in}} = \frac{1}{\sqrt{1 + \frac{1}{\mu V Y^2}}}$ $\sigma_{\theta} = \tan^{-1} \frac{1}{E \omega_{i}^{\alpha}}$
E''	E _{nt}	C los-pass RL	$T = \frac{L}{R}$	$F_{a} = \frac{1}{\sqrt{1 + \sqrt{1 + u}}} = \frac{1}{uT}$ $\phi = -\tan^{-1} \frac{uL}{R}$
E _{IR}	£.	D) high-pses EL	τ - <u>t</u>	$\frac{E_{ni}}{E_{in}} = \frac{1}{\sqrt{1 + \frac{1}{\omega^{2}T^{4}}}} = \omega T$ $\phi_{in} = \tan^{-1} \frac{R}{\omega L}$

#### Example 4-5

A simple RC circuit is to be used as a low pass filer. It is desired that the output voltage be attenuated 3 db at 100 cps. Calculate the required

value of the time constant T ~ RC

Soldion, Network A of Table 4.3 is the desired examplement. We wish to have

$$\frac{\mathcal{E}_{mi}}{\mathcal{E}} = -3 \text{ db}$$

so that

$$-3 = 10 \log \frac{E_{ext}}{E_{ext}}$$

00

$$\frac{E_{min}}{F} = 0.501$$

## xperimental methods for engineers

Thus,

Thus,
$$\frac{E_{\text{out}}}{E_{\text{in}}} = \frac{1}{(1 + \omega^2 T^2)^3} = 0.501$$

where

'n

$$\omega^2 = (2\pi f)^2 = [2\pi (100)]^2$$

We find that  $T=2.75\times 10^{-3}$  sec. The circuit might be constructed  $\omega^2 = (2\pi f)^2 = [2\pi (100)]^2$ using a 0.1µf capacitor and a 2.75-kilohm resistor.

### 4-7 THE VACUUM-TUBE VOLTMETER (VTVM)

The vacuum-tube voltmeter is one of the most useful laboratory devices for the measurement of voltage. It may be used for both a-c and d-e measurements and is particularly valuable because of its high input-impedance characteristics, which make it applicable to the measurement of voltages in electronic circuits.

A block-diagram schematic of a simple VTVM is shown in Fig. 4-22. The input voltage is connected through appropriate terminals to the function switch. If a d-c voltage is to be measured, the signal is fed directly to the range-selector switch operating as a voltagedivider circuit where the signal is reduced to a suitable range for the




Fig. 4-22. Block-diagram schematic of a vacuum-tube voltmeter (VTVM).




Fig. 4-23. Photograph of a commercial vacuum-tube voltmeter. (Courtesy Hewlett-Packard Company.)

succeeding amplifier circuit. The voltage signal from the voltage divider is then impressed on the grid circuit of the vacuum-tube-amplifier stage whose voltage output is used to drive a conventional D'Arsonval movement for readout purposes. The output from the amplifier stage could also be connected to a recorder or oscillo-cope for the measurement of transient voltages.

For an a-c voltage measurement the eignal w fed through a voltage proportional to the nupta a-c signal. The d-c voltage is then impressed on the voltage-divider network of the range-selector which. The remainder of the eigenut is the same as in the case of the de-measurement.

Various modifications of the above arrangement may be used, depending on the range of voltages to be measured. For very low-voltage as signals an amplification stage may be added to the instead of the voltage-divider arrangement. For very low desegnals a chopper device mucht be used at the input to produce an ac-

#### Experimental methods for engineers

Thus, 
$$\frac{E_{\rm out}}{E_{\rm in}} = \frac{1}{(1 + \omega^2 T^2)^{\frac{1}{2}}} = 0.501$$
 where

$$\omega^2 = (2\pi f)^2 = [2\pi (100)]^2$$

We find that  $T=2.75\times 10^{-3}$  sec. The circuit might be constructed using a  $0.1\mu f$  capacitor and a 2.75-kilohm resistor.

## 4-7 THE VACUUM-TUBE VOLTMETER (VTVM)

The vacuum-tube voltmeter is one of the most useful laboratory devices for the measurement of voltage. It may be used for both a-e and d-c measurements and is particularly valuable because of its high input-impedance characteristics, which make it applicable to the measurement of voltages in electronic circuits.

A block-diagram schematic of a simple VTVM is shown in Fig. 4-22. The input voltage is connected through appropriate terminals to the function switch. If a d-e voltage is to be measured, the signal is fed directly to the range-scleetor switch operating as a voltage-divider circuit where the signal is reduced to a suitable range for the




Fig. 4-22. Block-diagram schematic of a vacuum-tube voltmeter (VTVM).




Fig. 4-23. Phetograph of a commercial vacuum-tube voltmeter. (Courtesy Hewlett-Packard Company.)

succeeding amplifier circuit. The voltage signal from the voltage divider is then impressed on the grid circuit of the vacuum-tube-amplifier stage whose voltage output is used to drive a conventional D'Arsonval movement for readout purposes

The output from the amplifier stage could also be connected to a recorder or oscilloscope for the measurement of transient voltage.

For an a-c voltage measurement the signal is fed through a voltage divider and then to a rectifier circuit which produces a decoulage proportional to the input a-c signal. The de-voltage is then impressed on the voltage-divider network of the range-selector switch. The remainder of the circuit is the same as in the case of the de-measurement.


Various modifications of the above arrangement may be used, depending on the range of voltages to be measured. For very low-voltage are signals an amplification stage may be added to the input instead of the voltage-divider arrangement. For very low de-signals a chopper device might be used at the input to produce an ac-

signal, which is more easily amplified to the voltage levels which may be handled with conventional circuitry.

The important point is that the input impedance of the VTVM is very high, usually greater than 10 megohms, so that the measured circuit is not loaded appreciably and the indicated voltage more closely represents the true voltage to be measured. Example 4-6 illustrates the influence which the meter can exert on a circuit and the reduction in error of measurement which can result when a VTVM is used. It may be noted that a correction may be made for the meter impedance when the impedance of the measured circuit is known. A photograph of a typical commercial VTVM is shown in Fig. 4-23.


#### Example 4-6

The voltage at points 4 and B is to be measured. A constant 100 volts is impressed on the circuit as shown. Two meters are available for the measurement: a small volt-ohimmeter with an internal impedance of 100,000 ohms and a range of 100 volts and a VTVM with an internal impedance of 17 megohms.



Compare the error in measurement with each of these devices.

Solution. The true voltage, by inspection, is 50 volts. With the volt-ohmmeter connected in the circuit there results



and the voltage at A and B is

$$\begin{split} E_{AB} &= 100 \, \frac{1/[(1/0.5) \, + (1/0.1)]}{1/[(1/0.5) \, + (1/0.1)] \, + \, 0.5} \\ &= 100 \, \left( \frac{0.0833}{0.0833 \, + \, 0.5} \right) = 14.3 \, \, \text{volts} \end{split}$$

or an error of -71 percent.

With the VTVM connected in the circuit there results



and the voltage at A and B is

$$E_{AB} = 100 \frac{1/[(1/0.5) + (1/17)]}{1/[(1/0.5 + 1/17)] + 0.5}$$
$$= 100 \left( \frac{0.4857}{0.4857 + 0.5} \right) = 49.27 \text{ solts}$$

or an error of -1 46 percent

#### 4-8 THE OSCILLOSCOPE

We have seen that the vacuum-tube voltmeter offers the advantage that it may be used to measure voltage without a substant is loading of the input circuit. The cathode-ray oscilloscope (CRO) is similar to the VTVM in that it has a high input impedance and is used as a voltage-measuring device. It offers the additional feature that it may be used for the measurement of rapidly varying transients with any type of waveform.

The heart of the oscilloscope is the cathode-ray tube (CRT), which is shown schematically in Fig. 4-24. Electrons are released from the hot cathode and accelerated toward the screen by the use of a positively charged anode. An appropriate grid arrangement then governs the focus of the electron beam on the screen. The exact position of the spot on the screen is controlled by the use of the horizontal and vertical deflection plates. A voltage applied on one set of plates produces the x deflection, while a voltage on the other set produces the y deflection. Thus, with appropriate voltages on the two sets of plates the electron beam may be made to fall on any particular spot on the screen of the tube The screen is coated with a phosphorescent material which emits light when struck by the electron beam. If the deflection of the beam against a known voltage input is calibrated, the oscilloscope may serve as a voltmeter. Since voltages of the order of several hundred volts are usually required to produce beam deflections across the entire diameter of the screen, the cathode-ray tube is not directly applicable for many low-level voltage measurements and amplification must be

#### Experimental methods for engineers




Fig. 4-24. Schematic diagram of a cathode-ray tube (CRT).

provided to bring the input signal up to the operating conditions for the CRT.

A schematic of the CRO is shown in Fig. 4-25. The main features are the CRT, as described above, the horizontal and vertical amplifiers, and the sweep and synchronization circuits. The sweep generator produces a sawtooth wave which may be used to provide a periodic horizontal deflection of the electron beam, in accordance with some desired frequency. This sweep then provides a time base for transient voltage measurements by means of the vertical deflection. Oscilloscopes provide internal circuits to vary the horizontal sweep frequency over a rather wide range us well as external connections for introducing other sweep frequencies. Internal switching is also provided which enables the operator of the scope to "lock" the sweep frequency onto the frequency impressed on the vertical input. Provisions are also made for external modulation of the intensity of the electron beam. This is sometimes called the z-axis input. This modulation may be used to cause the trace to appear on the screen during certain portions of a waveform and disappear during other portions. It may also be used to produce traces of a specified time duration on the screen of the CRT so that a time base is obtained along with the waveform under study.




Fig. 4-25. Block-diagram schomatic of an oscilloscope.





Fig. 4-26. Photograph of a commercial oscilloscope, (Courtesy Hewlett-Packard Company.)

photograph of a commercial single-beam oscilloscope is given in Fig 4-20

A dual-beam oscilloscope provides for amplification and display of two signals at the same time, thereby permitting direct emparison of the signals on the CRT screen. A single-beam nealloscope may be given a dual-beam function through the use of an electronic This device switches between two inputs and alternately impresses the two signals at the input terminals of the single-beam oscilloscope. The switching rate may be varied to accommodate different frequency input signals. A schematic of the system is given in Fig 4-27. Notice the chopped nature of the signal dis-



to a chieve a dual-beam function with a singlebeam oscilloscops.

plays on the CRT screen as a result of the switching process. The width of the gaps in the displays is determined by the switching rate in the electronic switch. Switching frequencies of electronic switches are usually limited to about 5,000 cps.

#### Phase-shift measurements

The CRO may be used to measure phase shift in an electronic circuit, as shown in Fig. 4-28. An oscillator is connected to the input of the circuit under test. The output of the circuit is connected to the CRO vertical input, whereas the oscillator signal is connected directly to the horizontal input. The phase-shift angle  $\phi$  may be determined from the relation

$$\phi = \sin^{-1} \frac{B}{A} \tag{4-34}$$

where B and A are measured as shown in Fig. 4-28. For zero phase shift the ellipse will become a straight line with a slope of 45° to the right; for 90° phase shift it will become a circle; and for 180° phase shift it will become a straight line with a slope of 45° to the left.

#### Lissajous diagrams

The CRO offers a convenient means of comparing signal frequencies through the use of Lissajous diagrams. Two frequencies are impressed on the CRO inputs, one in the horizontal input and one on the vertical input. One of these frequencies may be a known frequency as obtained from a variable frequency oscillator or signal generator. If the two input frequencies are the same, an ellipse will be displayed on the CRT screen. If the two input frequencies are




Fig. 4-28. Schematic illustrating use of oscilloscope for phase measurements.



Fig. 4-29. Lissajous diagrams for various frequency raties as indicated.

not the same, the patterns which are displayed on the CRT series. are called Lissajous diagrams. There is a distinct relationship which governs the shape of these diagrams at accordance with the input frequencies

#### Vertical input frequency

Horizontal input frequency

number of vertical maxima on Lissagous diagram

(4-35) number of horizontal maxima on Lissajons diagram

Some typical shapes for the Lissaions diagrams are shown in Fig. 4-29. It may be noted that these shapes can yars consenhat, depending on the phase relation between the input signife

Oscilloscope traces may be recorded by various photographic methods, and several cameras are manufactured especially for oscilloscope applications.

#### Example 4-7

An oscilloscope is used for a phase-shift measurement in accordance with the arrangement in Fig 4-25. The measurements are

Calculate the nominal value of the phase angle and estimate the uncertainty in the measurement

Solution. We calculate the nominal value with Eq. (4-34)

$$\phi = \sin^{-1}\frac{B}{A} = \sin^{-1}\frac{15}{25} = 369^{\circ}$$

We may estimate the uncertainty with the use of Eq. (3-2) that.

$$\frac{\partial [\sin^{-1}(B/A)]}{\partial (B/A)} = \frac{1}{\{1 - (B/A)^2\}^4}$$

We have

$$\frac{\partial \phi}{\partial B} = \frac{1}{[1 - (B/A)^2]^{\frac{1}{3}}} \frac{1}{A} = \frac{1}{(1 - 0.36)^{\frac{1}{3}}} \frac{1}{1.5} = 0.833 \text{ rad/cm}$$

$$\frac{\partial \phi}{\partial A} = -\frac{B}{[1 - (B/A)^2]^{\frac{1}{3}}} \frac{1}{A^2} = \frac{-1.5}{(1 - 0.36)^{\frac{1}{3}}} \left(\frac{1}{2.5}\right)^2 = -0.3 \text{ rad/cm}$$

Also,

 $w_{H} = 0.05 \text{ cm}$ 

 $w_A = 0.05 \text{ cm}$ 

so that the uncertainty in  $\phi$  is

$$w_6 = \{(0.833)^2(0.05)^2 + (0.3)^2(0.05)^2\}^{\frac{1}{2}}$$
  
= 1.4 × 10⁻² rad = 0.80°

or

$$\frac{w_{\phi}}{\phi} = \frac{0.8}{36.9} = 0.0215 = 2.15 \text{ percent}$$

#### 4-9 OSCILLOGRAPHS

The oscillograph is basically a recording D'Arsonval movement. Various input amplifiers are available for raising the signal to an acceptable level for driving the movement. Two types of galvanometer movements are used: the direct-writing, or stylus move-galvanometer deflection is recorded directly on recording paper by action of the stylus. Three types of stylus are in common use: inkwriting, pressure-writing, and heated styli. The latter two write on cither pressure- or heat-sensitive paper. The light-beam oscillograph uses a light-beam galvanometer, a light source to produce a fine beam, and light-sensitive paper for recording. The movement of a stylus oscillograph is similar to that of the indicating D'Arsonval movement shown in Fig. 4-4 except that the pointer is replaced by a stylus, which writes on the recording paper. The construction of the light-beam oscillograph is somewhat similar to that of the lightbeam galvanometer except that a lens system is used to focus the light beam to a small point in order to produce a fine trace on the recording paper. Since input amplification is provided, the galvanometer may be constructed in a more substantial fashion than in the system of Fig. 4-3. Typically, the mirror and coil are placed in an integral unit which may be inserted in the oscillograph instrument. The ends of the unit allow it to pivot freely and reflect the light beam onto the recording paper. This unit is frequently not

much larger than a matchetick. A photograph of a typical mirror or galvanometer for use in an oscillograph is shown in Fig. 4-302, and the construction details are shown in Fig. 4-302.

The frequency response of an oxillograph is primarily a function of the mechanical frequency response of the galvanometer,




Fig. 4-30. (a) Photograph of a typical accilingtaph gairsnometer. (The gaivanometer is approximately the size of matchillek.) (b) Schematic diagram of "matchillek" gairsnometer and electric connections. (Courtery Minne




Fig. 4-31. Photograph of a commercial eight-channel oscillograph system. (Courtesy Sanborn Company.)

which, in turn, is primarily dependent on its mass moment of inertia and damping characteristics. The smaller the mass of the galvanometer movement, the higher the frequency response. For this reason, the light-beam oscillograph has a much higher frequency response than the stylus type because of the higher mass associated with the stylus movement. In general, stylus-type oscillographs exhibit flat frequency responses from 0 to 100 cps, while light-beam oscillographs may be used up to 5,000 cps.

A multitude of preamplifiers, chart speeds, and remote operation facilities are available on commercial oscillographs. Commercial models are available with 1 to 50 separate channels. A photograph of a typical eight-channel light-beam oscillograph is shown in Fig. 4-31. The input preamplifiers and controls for each channel are shown at the top of the eahinet, while the chart magnitude is shown in the right-center portion of the cabinet.

#### 4-10 COUNTERS, TIME, AND FREQUENCY MEASUREMENTS

The engineer is called upon to perform counting-rate and frequency measurements over an extremely broad range of the intervals A determination of revolutions per minute on a clou-speed steam engine might involve a simple mechanical revolutions counter siel a hand-operated stopwatch In this case, the accuracy of the moreurement would depend on the human-response time in starting and stopping the watch. The same measurement performed on an automobile engine might utilize an electric transducer which generated a pulse for each revolution of the engine. The pulses could be fed to some type of counting device which established if a number of pulses produced for a given increment of time. The accuracy of measurement would again depend on the accuracy of the aperification of the time interval | In both of these simple cases a circular frequency measurement is being performed through the combination of a counting measurement and time-interval measurement Aside from the simple frequency measurements discussed with the CRO, most frequency measurements are performed by some type of counting operation

- A large variety of electronic counters are available commerciant. These instruments have internal circuitry which enables them to be used for measurement of frequency, period, or time intervals over a very wide range. These instruments usually contain four sets of internal circuits.
- Input-signal conditioning circuits which transform the input signal into a series of pulses for counting
- 2. The time base which provides precise time increments during which the pulses are counted
- 3 A signal "gate" which starts and stops the counting device
- 4 A decade counter and display which counts the pulses and provides a digital readout

A photograph of a typical commercial counter for measurements of frequencies between 10 cps and 1.2 Me is given in Fig. 4-32

The functions of the electronic counter are shown schematically in Fig. 4-33. In (a) a frequency measurement is performed. input signal is fed to the signal shaper which produces an equivalent pulse train which in turn is fed to the gate along with a predetermined time-base signal. The counters subsequently register the number of pulses in the given time which is interpreted in terms of frequency. A period measurement is indicated in (b). In this instance the time base is used to provide a known number of pulses per unit time, while the input signal is used to actuate the gate eircuit. The measured count is thus an indication of the period of the input signal. For time-interval measurements the arrangement in (c) is used. Again, the time base provides a known number of pulses per unit time. Either external or internal trigger eireuits provide the signals to the gate circuits to start and stop the count. These trigger eireuits may be made to actuate on certain polarities or peak values of a waveform, depending on the measurement which is desired.

Phase-angle measurements may be made by measuring the time interval between similar points on the two waveforms. Calibration of the time-base eircuits may be achieved by the use of special frequency standards based on tuning-fork or crystal oscillators, or with NBS standard broadcast frequencies. A very detailed discussion of frequency and time standards is given in Ref. [6].




Fig. 4-32. Photograph of a commercial electronic counter. (Courtesy Hewlett-Packard Company.)




Fig. 411. Block diagrams indicating functions of electronic counter. (e) Frequency measurements: Function selector is set to "frequency," and apprepting jail time is selected by time-base switch (combined with burchin relette on some counters). (b) Period measurement: Function selector is safety-pri-od," and counted frequency is chosen by time-base switch. (e) Time-interval measurements: Start and stop titgers may be durited train by separate sources, as shown, or from ditherat points of one swarthm by setting come-up switch to "com." (Courtery Meetit-Tachard Compent).

#### 4-11 TRANSDUCERS AND ELECTRIC Sensing Devices

A large number of devices operate on the principle of transforming as input representing a physical variable into an electric signal Sark devices are called transducers. In the following sections we shall discuss some of the more widely used transducers and their particular of transducer characteristics, and the render should consult this take throughout the following discussions to maintain an overall preperties. It may be noted that the subsequent paragraphs will be primarily concerned with principles of operation without repairs much of the detailed information contained in Table 4-1. Thus,

# le 4-4 Summary of transducer characteristics

Millerion		- abara	cteristics		
le 4-4 Summar		Input range of	Input-impedance characterietics	Input centificity	Error and noise characteristics
Type of transducer and principle of operation	Type of input	level as	Varies widely, de-	Lave Len a con	1 the order of the
jable recircance: Morement of entact on elide-arire; also called externer potentiametere.	Linear dipplace- ment or angular dipplacement	Minimum 19 0.1% of total registance	total resistance characteristics and physical size	of less than in at	n neglizible of the neglizible of the order of 10 µv at the contact. Noise increases with "chatter" of
pifferential transformer: Ber land lext discussion, Linear sa the differential transformer n the differential transformer acidely used. Conserts disph	Fig. Linear displace ment most doc-	Tetal range fr ±0,005 to ±3	rom Deiends on ri 3 in. Forces from 0 to 0.3 g usua required	ally	in- Deviation from timestity about 0.55%, generally accurate to ±1%
ridely used. ruent to rollage.  Capacitive transducer: Variable fance between these registers change in capacitance.	Displacement	nt be-	cm to requirement very small, term. order of a dynes	at the tivities of the	on the officers of the connections of the connection of the c
Presocladic effect: Force is on crystals with asymmetric distributions proportional difference at the of the crystal.	mpreceed Form or a	Varies wide crystal II See penni	itivity. relatively compared other tra-	y large d with an-duors   Construction   Constructi	galt 0.15  rton .007 .v.in/ tules:  Usepends on plate voltage but of or-
I photoelectric essecti Light motal cathode course is electrons which may be anote to produce electr Photoconductive transdu Photoconductive transdu	vic current.	depend tube el trotor materi letwe 0.8 m. Very 1: From	ds on plan- enclosure. emissive rials respond	prati Oge-fille 0.01-0 prati About pwati	atronic as, 15 µa/  309 µa/ t at man- tensitivity t device  accordated circuit
euch as evientum, me or germanium, produ in resistant of the r /Photocoltaic cell: Ligh a symiconducting m lact with a metal p potential.	material.  At falling upon haterial in con- plate produces a	Deperiment O.1 Deperiment O.2 O.5 ma	ends on mate- 1. Felenium 2 to 0.7 µ, CuO 5 to 1.4 µ, set- anium 1.0 to 1.7	applicators 10°1	0 volts/mm   Can be accurate to microinches
the time rate of	ch earl: Changing Climpressed on coil in proportional to change of the field.	thanging mag- netic field	0-2 persted to highest values distanable	ot approximated de d	epends on coil Accuracies of 0.05% have been been fitted on plate thickness and current; of the order of -1 × 10-3 volteen/e
Hall-ffect train a impressed on a electric current tial difference pendicular to letter magnetic fi	in a direction por-				lismuth

Fraguescy	Temperature efects	Type of output	Order of the	Output unpadrase statusmatus	Application	R-pres
Generally sot above 3 rps for commercial po- tratiometers	0 m2 to 0 13 % "Und do to a change in reset- tance. Also, some thermoelectric effects de- preding on 17 per of contacts med	Voltage or current depending on consecuting ex- curt	N also	Varatio	Find for manufactures and deplaces	* trie bernen nie tory to ne mary transetu- tio menusy- tio y
Frequency of ap- pirel voltage must be 10 sutner desput response Mechanical juni- tations also	Small influence of temperature may be reduced by tening a thermo- tor current	Voltage propue tennal to sepol dis, lacement	0 6 to 4 8 me/ 0 001 m/s sepu- depending on fre- quary Lawre frequency pro- dures lower out- put	Mandy result to bed to great to stapedance of low on 20 gains, depending on each	Cord for treatments of displace toral	".Type Paged, as styres on a gh suited property equipment is are shad to taken to claration over the claration over
Depends strongly on mechanical econtruction but may go to 50,000 tps	Not strong if de- nors actors for effects	Сарапіанн	Lanual for the transfer of the		pre-intellers, present and the ere branche marks and att en large, are persistences dame are are the for the ere	Ragnet of the I'ch owing the polaries may fin- quer medial non- mention of est- pul type, Jy
Depends on order- nal receivey and co-chan mi- mounting 20- 20 to maily ob- laimed, no re- trouse to stro-ly- state forces	Water senting in representation with properties	Lonal to most	White depends on crystal our and majoral on wa- stirrity can have entities of several voice	ligh, aithe aith ai 19 mag bea	the provided of free provided of fire provided made and the free me	Exis melon-
Linear 0-800 epe runrest response drope off 13 % at 10 000 epe	Generally are op- arable above 75 to 100°C	Currest	Of the order of 2 on	High, of the order of 10 mag-kins	post mental ba put mill fre	Instrument Left ectives
Rue time varies undely unit ma- terni and here- dest radiation from 80 pare to	Response to lon- ger unvelopths nervane with re- duction in tem- perature	Current draws as the external cu- cust	Deposit on pro- dest mires 17, nor most more territ	Hat, verse from the ID top-Am- to tomorrul detere	With'y good for religit from Jo- torn to at a., by miragine	Farly expenses man for precess rate try to the last their full per- tential
fine time of the arder of I pare response into the inegacycle range	Variations of 10 % over 40"(", pargo depending on en- ternal projectors	Voltage	109-250 mr m normal room ight folesammerly up to \$40 m/m at high discounters	2,000 to 10 mg at me Capert- tage of order of 5 to taral tem?	Walely and LF expanse active, more to will reproduce to X	largete or anti- later between notes by my of forte
6-2000 the	ked Small	Sultage	Depends on ever- ferious securit, for spect orwaterity	Il at the arter	Can be peed where propose these arranged of dis- plantment to	Relatively moreov- tive to imposely of etrifical co- takey
O rad to frequency	žmaži	Vidiage	Deposits on mill ear, see layed productly	Chrystolia sa sud sure	Measurement of Rappel of States	Engle plinned percent and di- tension must be been proving but proving
High	Large but one be outdressed	Toltage	NE role and Ex- envolu	Low of the sedent of \$20 shows for a 2 posseth detector	Magazarani al Raguno Bridi	Fare transfers until the le- nutrant le- tent is been- frant is non- coductes und let amplication

the verbal discussion and tabular presentation are complementary

and should be used jointly.

It should be noted that the discussions of transducers which follow are concerned primarily with electrical effects. Other transducers of a more specialized nature (thermocouples, strain gages, pressure transducers, and nuclear radiation transducers) will be discussed in subsequent chapters.

# 4-12 VARIABLE-RESISTANCE TRANSDUCER

The variable-resistance transducer is a very common device which may be constructed in the form of a moving contact on a slide-wire, a moving contact on a coil of wire, through either linear or angular movement, or a contact that moves through an angular displacement on a solid conductor like a piece of graphite. The device may also be called a resistance potentiometer or rheostat and is available commercially in many sizes, designs, and ranges. Costs can range from a few cents for a simple potentiometer used as a volume control in a radio circuit to hundreds of dollars for a precision device used for accurate laboratory work.

The variable-resistance transducer fundamentally is a device for converting either linear or angular displacement into an electric signal; however, through mechanical methods it is possible to convert force and pressure to a displacement so that the device may also be useful in force and pressure measurements.

# 4-13 THE DIFFERENTIAL TRANSFORMER (LVDT)

A schematic diagram of the differential transformer is shown in Fig. 4-34. Three coils are placed in a linear arrangement as shown with a magnetic core which may move freely inside the coils. The construction of the device is indicated in Fig. 4-35. An alternating input voltage is impressed on the center coil, and the output voltage from the two end coils depends on the magnetic coupling between the core and the coils. This coupling is, in turn, dependent on the position of the core. Thus, the output voltage of the device is an indication of the displacement of the core. As long as the core remains near the center of the coil arrangement, the output is very nearly linear, as indicated in Fig. 4-36. The linear range of commercial differential transformers is clearly specified, and the devices are seldom operated outside this range. When operating in the




Fig. 4-34. Schematic diagram of a differential transformer.

linear range the device is called a linear variable differential transformer (LVDT). Near the null position a slight nonlinearity condition is encountered, as illustrated in Fig. 4-37. It will be noted that Fig. 4-36 considers the phase relationship of the output voltage, while the "V" graph in Fig. 4-37 indicates the absolute magnitude of the output. There is a 180° phase shift from one side of the null position to the other.

The frequency response of LVDTs is primarily hunted by the inertia characteristics of the device. In general, the frequency of the applied voltage should be 10 times the desired frequency response.

Commercial LVDTs are available in a broad range of sizes and are videly used for displacement measurements in a variety of applications. Force and pressure measurements may also be made after a mechanical conversion. Table 4-4 indicates the




FIG. 4-35. Construction of a commercial linear variable differential transformer (LVDT)-(Courtery Schortiz Engineering Company-)




Fig. 4-36. Output characteristics of an LVDT according to Ref. [7].




Fig. 4-37. "V" graph for an LVDT showing slight nonlinear behavior in the null region [7].

120

general characteristics of the LVDT. The interested reader should consult Ref. [7] for more detailed information.

### 4-14 CAPACITIVE TRANSDUCERS

Consider the capacitive transducer shown in Fig. 4-38. The rapacitance (in picofarads) of this arrangement is given by

$$C = 0.225\epsilon \frac{A}{d}$$
(4-30)

where

d = distance between the plates, in.

A = merlapping area, la.

· - dielectric constant

This plate arrangement may be used to measure a rhange in the distance of through a change in capacitance. A change in capacitance, the state of the state of the coverapping area A resulting from a relative movement of the plates in a lateral direction or a change in the dielectric constant of the material between the plates. The rapacitance may be incasured with bridge circuits. The output impedance of a rapacitor is given by

$$Z = \frac{1}{2\pi fC} \tag{4-37}$$

where

Z = impedance, ohms

f = frequency, rps

C - caparitance, farada

In general, the output impedance of a capacitive transducer is high; this fact may call for eareful design of the output circuitry.

The rapacitive transducer may be used for displacement measurements through a variation of either the spacing distance d or the plate area. It is enumonly used for liquid-level measurements, as indicated in Fig. 4-30. Two electrodes are arranged as shown, and the dislective constant, varies between the electrode according

- In lectra

Fig. 4-38. Schematic of a capacitive trans-

# Experimental methods for engineers




Fig. 4-39. Diagram illustrating use of capacitive transducer for liquid-level measurement.

to the liquid level. Thus, the capacitance between the electrodes is a direct indication of the liquid level.

## Example 4-8

A capacitive transducer is constructed of two 1-in.² plates separated by a distance of 0.01 in. in air. Calculate the displacement sensitivity of such an arrangement. The dielectric constant for air is 1.0006.

Solution. The sensitivity is found by differentiating Eq. (4-36).

$$S = \frac{\partial C}{\partial d} = -\frac{0.225\epsilon A}{d^2}$$

Thus.

$$S = -\frac{(0.225)(1.0006)(1)}{(0.01)^2} = -2.25 \times 10^3 \text{ pf/in.}$$

## Example 4-9

For the capacitive transducer in Example 4-8 the allowable uncertainty in the spacing measurement is  $w_d = \pm 0.0001$  in., while the estimated uncertainty in the plate area is  $\pm 0.005$  in... Calculate the tolerable uncertainty in the capacitance measurement in order to achieve the allowable uncertainty in the spacing measurement.

Solution. Solving Eq. (4-36) for d, we have

$$d = 0.225 \frac{\epsilon A}{C} \tag{a}$$

Making use of Eq. (3-2), we obtain

$$\frac{v_d}{d} = \left[ \left( \frac{v_d}{C} \right)^2 + \left( \frac{v_A}{A} \right)^2 \right]^{\frac{1}{2}}$$
(b)

We have

$$\frac{w_4}{d} = \frac{0.0001}{0.01} = 0.01$$
  $\frac{w_4}{A} = \frac{0.005}{1.0} = 0.005$ 

so that

$$\frac{w_s}{G} = 0.00866 = 0.8866\%$$

The nominal value of C is

$$C = \frac{(0.225)(1.0006)(1.0)}{0.01} = 22.513 \text{ pf}$$

so that the tolerable uncertainty in C is

 $w_c = (22513)(0.00566) = \pm 0.195 \text{ pf}$ 

### 4-15 PIEZOELECTRIC TRANSDUCERS

Consider the arrangement shown in Fig 4-40. A piezoelectric crystal is placed between two plate electrodes. When a force is applied to the plates, a stress will be produced in the crystal and a corresponding deformation. With certain crystals this deformation will produce a potential difference at the surfaces of the crystal, and the effect is called the piezoelectric effect. The induced charge on the crystal is proportional to the impressed force and is given by

$$Q = dF (4-38)$$

where Q is in coulombs, F is in newtons, and the proportionality constant d is called the prezoelectric constant. The output voltage of the crystal is given by

$$E = glp (4-39)$$

Fig. 4-40. Diagram illustrating the piezo-electric effect.

Table 4-5 Plezoelectric constants

Material	Orientation	Charge sensitivity d, coulomb/m² newton/m²	Voltage sensitivity g, volt/m newton/m²
Quartz	X cut; length along Y length longitudinal	2 25 × 10 -12	0.055
	X cut; thickness	-2 04	-0.050
	longitudinal Y cut; thickness	4 4	0.108
Rocheile salt	. shear X cut 45°; length longitudinal	435 0	0.098
	Y cut 45°;	-78 4	-0.29
Ammonium dihydrogen phosphale	length longitudinal Z cut 0°; face shear	48.0	0.354
	Z cut 45°;	24.0	0.177
Commercial barium titanate ceramics	length longitudinal To polarization To polarization	130-160 -56 0	0.0106 0.0042-0.0053

[†] According to Lion [3].

where t is the crystal thickness in meters, p is the impressed pressure in newtons per square meter, and g is called voltage sensitivity and is given by

$$g = \frac{d}{\epsilon} \tag{4-40}$$

Values of the piezoelectric constant and voltage sensitivity for several common piezoelectric materials are given in Table 4-5.

The voltage output depends on the direction in which the crystal slab is cut in respect to the crystal axes. In Table 4-5 an X (or Y) cut means that a perpendicular to the largest face of the cut is in the direction of the x axis (or y axis) of the crystal.

Piezoelectrie crystals may also be subjected to various types of shear stresses instead of the simple compression stress shown in Fig. 4-40, but the output voltage is a complicated function of the exact crystal orientation. Piezoelectric crystals are widely used as inexpensive pressure transducers for descriptions are commonly employed as phonogra; the commonly employed employ

1.

Example 4-10

A quartz plezoelectric crystal having a thickness of 2 mm and a voltage sensitivity of 0.055 volt-m/newton is subjected to a pressure of 200 per. Calculate the voltage output

Solution We calculate the voltage output with Eq. (4-39):

$$p = (200)(6.895 \times 10^{4}) = 1.38 \times 10^{4} \text{ newtons/m}^{2}$$
  
 $t \approx 2 \times 10^{-3} \text{ m}$ 

Thus.

 $E = (0.055)(2 \times 10^{-9})(1.38 \times 10^{9}) = 151.8 \text{ volts}$ 

#### 4.16 PHOTOELECTRIC EFFECTS

A photoelectric transducer converts a light beam into a usable electric signal. Consider the circuit shown in Fig 4-41 Light strikes the photoemissive cathode and releases electrons which are attracted toward the anode, thereby producing an electric current in the external circuit. The cathode and anode are enclosed in a glass or quartz envelope which is either evacuated or filled with an inert gas. The photoelectric sensitivity is defined by

$$I = S\Phi$$
 (1-41)

where

I = photoelectric current

Φ ≈ illumination of the cathode

S = sensitivity

The sensitivity is usually expressed in units of amperes per watt

or amperes per lumen.

Photoelectric tube response to different wavelengths of light is influenced by two factors (1) the transmission characteristics of the glass-tube envelope and (2) the photoemissive characteristics of the cathode material. Photoemusave materials are available which will respond to light over a range of 02 to 0.8 µ Most glasses transmit light in the upper portion of this range, but many do not transmit below about 0.4 # Quartz, however, transmits down to 0.2 u. Various noise effects are present in photoelectric tubes, and the interested reader should consult the discussion by Lion [3] for more information.

Table 4-5 Piezoelectric constants†

Material	Orientation	Charge sensitivity d, coulomb/m² newton/m²	Vollage sensitivity g, volt/m newton/m²
Quartz	X cut; length along Y length longitudinal	2.25 × 10 ⁻¹³	0.055
	X cut; thickness	-2.04	-0.050
	longitudinal Y cut; thickness	4 4	0.108
Rochelle salt	, shear X cut 45°; length longitudinal	435 0	0.098
	Y cut 45°, length longitudinal	-78 4	-0,29
Ammonium dihydrogen phosphale	Z cut 0°, face shear	48.0	0.354
	Z cut 45°;	24.0	0.177
Commercial barium titanate ceramics	length longitudinal To polarization To polarization	130-160 56 0	0.0106 0.0042-0.0053

[†] According to Lion [3].

where t is the crystal thickness in meters, p is the impressed pressure in newtons per square meter, and g is called voltage sensitivity and is given by

$$g = \frac{d}{\epsilon} \tag{4-40}$$

Values of the piezoelectric constant and voltage sensitivity for several common piezoelectric materials are given in Table 4-5.

The voltage output depends on the direction in which the crystal slab is cut in respect to the crystal axes. In Table 4-5 an X (or Y) cut means that a perpendicular to the largest face of the cut is in the direction of the x axis (or y axis) of the crystal.

Piczoelectric crystals may also be subjected to various types of shear stresses instead of the simple compression stress shown in Fig. 4-40, but the output voltage is a complicated function of the exact crystal orientation. Piczoelectric crystals are widely used as inexpensive pressure transducers for dynamic measurements and are commonly employed as phonograph pickups. General information on the piczoelectric effect is given by Cady [1].

Exomple 4-10

A quartz piezoelectric crystal having a thickness of 2 mm and a voltage sensitivity of 0 055 volt-m/newton is subjected to a pressure of 200 pci. Calculate the voltage output.

Solution. We calculate the voltage output with Eq. (4-39):

 $p = (200)(6.895 \times 10^4) = 1.38 \times 10^4 \text{ newtons/m}^2$ 

 $t = 2 \times 10^{-4} \text{ m}$ 

Thus,

 $E = (0.055)(2 \times 10^{-4})(1.38 \times 10^{4}) \approx 151.8 \text{ volts}$ 

#### 4-16 PHOTOELECTRIC FFFECTS

A photoelectric transducer converts a hight beam into a usable electric signal. Consider the circuit shown in Fig. 4-41. Light strikes the photoemissive cathode and releases electrons which are attracted toward the anode, thereby producing an electric current in the external circuit. The esthode and anode are enclosed in a glass or quartz envelope which is either evacuated or filled with an inert gas. The photoelectric sensitivity is defined by

$$I = S\Phi$$
 (4-41)

where

I = photoelectric current

 $\Phi =$  illumination of the cathode

S = sensitivity

The sensitivity is usually expressed in units of amperes per watt or amperes per lumen

Photoelectric tube response to different wavelengths of light is influenced by two factors (1) the transmission characteristics of the glass-tube envelope and (2) the photoemissive characteristics of the cathode material Photoemissive materials are available which will respond to light over a range of 0 2 to 0 8  $\mu$  Most glasses transmit light in the upper portion of this range, but many do not transmit helow about 0.4  $\mu$ . Quartz, however, transmits down to 0.2  $\mu$ . Various noise effects are present in photoelectric tubes, and the interested reader should consult the discussion by Lion [3] for more information.




Fig. 4-41. Diagram illustrating the photoelectric effect.

Photoelectric tubes are quite useful for measurement of light intensity. Inexpensive devices can be utilized for counting purposes through periodic interruption of a light source.

# 4-17 PHOTOCONDUCTIVE TRANSDUCERS

The principle of the photoconductive transducer is shown in Fig. 4-42. A voltage is impressed on the semiconductor material as shown. When light strikes the semiconductor material, there is a decrease in the resistance, thereby producing an increase in the current indicated by the meter. A variety of substances are used for photoconductive materials, and a rather detailed discussion of the pertinent literature on the subject is given in Refs. [3] and [10].

Photoconductive transducers enjoy a wide range of applications and are useful for measurement of radiation at all wavelengths. It must be noted, however, that extreme experimental difficulties may be encountered when operating with long-wavelength radiation.

# 4-18 PHOTOVOLTAIC CELLS

The photovoltaic-cell principle is illustrated in Fig. 4-43. The sandwich construction consists of a metal base plate, a semiconductor material, and a thin transparent metallic layer. This transparent layer may be in the form of a sprayed, conducting lacquer. When light strikes the barrier between the transparent metal layer and the semiconductor material, a voltage is generated as shown.




Fig. 4-12. Schematic diagram of a photoconductive transducer.




Fig. 4-43. Schematic diagram of a photovoltaic cell.

The output of the device is strongly dependent on the load resistance R. The open-circuit voltage approximates a logarithmic function, but more linear behavior may be approximated by decreasing the load resistance.

Perhaps the most widely used application of the photovoltaic cell is the light exposure meter in photographic work. The logarithmic behavior of the cell is a decided advantage in such applications because of its sensitivity over a broad range of light intensities

### 4-19 IONIZATION TRANSDUCER

A schematic of the ionization transducer is shown in Fig 4-44. The tube contains a gas at low pressure which the RF generator impresses a field on this gas. As a result of the RF field a glow discharge is created in the gas and the two electrodes I and 2 detect a potential difference in the gas phasma. The potential difference is dependent on the electrode spating and the capacitive coupling




Fig. 4-44. Schematic diagram of an ionization displacement transducer.

between the RF plates and the gas. When the tube is located at the central position between the plates, the potentials on the electrodes are the same; but when the tube is displaced from this central position, a d-c potential difference will be created. Thus, the ionization transducer is a useful device for measuring displacement. Some of the basic operating characteristics are given in Table 4-4, and a detailed description of the output characteristics is given by Lion [4].

# 4-20 MAGNETOMETER SEARCH COIL

A schematic of the magnetometer search coil is shown in Fig 4-45. A flat coil with N turns is placed in the magnetic field as shown. The length of the coil is L, and the cross-sectional area is A. The magnetic field strength H and the magnetic flux density B are in the direction shown, where

$$B = \mu H \tag{4-42}$$

and  $\mu$  is the magnetic permeability. The voltage output of the coil E is given by

$$E = NA \cos \alpha \frac{dB}{dl} \tag{4-43}$$

where  $\alpha$  is the angle formed between the direction of the magnetic field and a line drawn perpendicular to the plane of the coil. The total flux through the loop is

$$\phi = A \cos \alpha B \tag{4-44}$$

so that

$$E = N \frac{d\phi}{dt} \tag{4-45}$$

Note that the voltage output of the device is dependent on the rate of change of the magnetic field and that a stationary coil placed in a steady magnetic field will produce a zero-voltage output. The search coil is thus a transducer which transforms a magnetic field signal into a voltage.

In order to perform a measurement of a steady magnetic field it is necessary to provide some movement of the search coil. A typical method is to use a rotating coil as shown in Fig. 4-46. The




Fig. 4-45. Schematic of a magnetometer search coil.



Fig. 4-46. Diagram illustrating use of a rotating search coil for measurement of steady magnetic fields.

rms value of the output voltage for such a device is

$$E_{rine} = \frac{1}{\sqrt{2}} NAB\omega \qquad (4-16)$$

where  $\omega$  is the angular velocity of rotation. Oscillating coils are also used

The accuracy of the search coil device depends on the accuracy with which the dimensions of the coil are known. The coil should he small enough that the magnetic field is constant over its area

In the above equations the magnetic flux density is expressed in webers per square meter, the area is in square meters, the time is in seconds, the magnetic fidux is in webers, the magnetic field strength (magnetic intensity) is in anyores per meter, and the magnetic permeability for free space is  $4\pi \times 10^{-5}$  henry/m An alternate set of units uses B in gauss, H in oersteds, A in centimeters equared, and  $\mu$  in abhenrys per centimeter. The magnetic permeability for free space in this instance is unity

### Exomple 4-11

A rotating search coil has 10 turns with a cross-sectional area of 5 cm². It rotates at a constant speed of 100 rpm. The output voltage is 40 mv. Calculate the magnetic field strength.

Solution. According to Eq (4-46),

$$B = \frac{\sqrt{2} E_{\text{rms}}}{NA\omega} = \frac{\sqrt{2} (0.04)}{(10)(5 \times 10^{-9})[(100)(2\pi)/60]}$$
  
= 1.08 webers/m²

$$H = \frac{B}{\mu} = \frac{1.08}{4\pi \times 10^{-7}}$$
= 8.6 × 10t amp/m

# 4-21 HALL-EFFECT TRANSDUCERS

The principle of the Hall effect is indicated in Fig. 4-47. A conductor or semiconductor plate of thickness t is connected as shown so that an external current I passes through the material. When a magnetic field is impressed on the plate in a direction perpendicular to the surface of the plate, there will be a potential  $E_H$  generated as shown. This potential is called the Hall voltage and is given by

$$E_{II} = K_{II} \frac{IB}{t} \tag{4-47}$$

where I is in amperes, B is in gauss, and t is in centimeters. The proportionality constant is called the Hall coefficient and has the units of volt-em/mmp-gauss. Typical values of  $K_H$  for several materials are given in Table 4-6.

## Example 4-12

A Hall-effect transducer is used for the measurement of a magnetic field of 5,000 gauss. A 2-mm slab of bismuth is used with a current of 3 amp. Calculate the voltage output of the device.

Solution. We use Eq. (4-47) and the data of Table 4-6.

$$E_{H} = K_{H} \frac{IB}{t}$$

$$= \frac{(-1 \times 10^{-8})(3)(5,000)}{(2 \times 10^{-1})}$$

$$= -7.5 \times 10^{-4} \text{ volt.}$$




Fig. 4-47. Diagram illustrating the Hall effect.

Table 4-6 Hall coefficients for different materials?

Material	Field strength,	Temp, °C	K _H , voll-em amp-gauss
As C Bi Cu Fe n-Ge Si Sn Te	4,000-8,000 4,000-11,000 1,130 8,000-22,000 17,000 100-8,000 20,000 4,000 3,000-9,000	20 Room 20 20 22 25 23 Room 20	4 52 × 10-11 ~1.73 × 10-11 ~1 × 10-1 ~5 2 × 10-11 1.1 × 10-1 ~8 0 × 10-4 4 1 × 10-1 ~2 0 × 10-1 5 3 × 10-1

t According to Lion [3]

### PROBLEMS

- 4-1 Expand Eq (4-10) in series form, and indicate the relation which may be used to obtain a linear approximation for the current Also, show the error which results from this approximation
- 4-2 Expand the equation for voltage in the ballast circuit [Eq (4-12)] in series form, and indicate the relation which may be used for a linear approximation. Show the error which results from this approximation.
- 4-3 Derive an expression for the sensitivity of the circuit in Fig 4-11, defined by


$$S = \frac{di}{dR}$$

Find the condition for maximum sensitivity

- 4.4 Obtain a linear approximation for the sensitivity of the ballast circuit of Fig 4-12 Under what conditions would this relation apply? Estimate the error in the approximation
- 4-5 A Wheatstone bridge circuit has reustance arms of 400, 40, 602, and 6,000 ohms taken sequentially around the bridge. The galvanometer has a resistance of 110 ohms and is connected between the junction of the 40- and 602-ohm reastors to the junction of the 400- and 5,000-ohm reastors. The battery has an emf of 3 volts and negligible internal resistance. Calculate the voltage across the galvanometer and the galvanometer current.

- 4-6 It is known that a certain resistor has a resistance of approximately 800 ohms. This resistor is placed in a Wheatstone bridge the other three arms of which have resistances of exactly 800 ohms. A 4-volt battery with negligible internal resistance is used in the circuit. The galvanometer resistance is 100 ohms, and the indicated galvanometer current is 0.08 μa. Calculate the resistance of the unknown resistor.
- 4-7 Two galvanometers are available for use with a Wheatstone bridge having equal ratio arms of 100 ohms. One galvanometer has a resistance of 100 ohms and a sensitivity of 0.05 μa/mm, whereas the other has a resistance of 200 ohms and a sensitivity of 0.01 μa/mm. A 4-volt battery is used in the circuit, and it has negligible internal resistance. An unknown resistance of approximately 500 ohms is to be measured with the bridge. Calculate the deflection of each galvanometer for an error of 0.05 percent in the determination. State assumptions necessary to make this calculation.
- 4-8 Two known ratio arms of a Wheatstone bridge are 4,000 and 400 ohms. The bridge is to be used to measure a resistance of 100 ohms. Two galvanometers are available: one with a resistance of 50 ohms and a sensitivity of 0.05 μa/mm and one with a resistance of 500 ohms and a sensitivity of 0.2 μa/mm. Which galvanometer would you prefer to use? Why? Assume that the galvanometer is connected from the junction of the ratio arms to the opposite corner of the bridge.
- 4-9 A Wheatstone bridge is constructed with ratio arms of 60 and 600 ohms. A 4-volt battery with negligible internal resistance is used and is connected from the junction of the ratio arms to the opposite corner. A galvanometer having a resistance of 50 ohms and a sensitivity of 0.05 μa/mm is connected between the other corners. When the adjustable arm reads 200 ohms, the galvanometer deflection is 30 mm. What is the value of the unknown resistance?
- 4-10 The four arms of a Wheatstone bridge have resistances of 500, 1,000, 600, and 290 ohms taken in sequence around the bridge. The battery of 3 volts connects between the 1,000-and 600-ohm resistors and the 500- and 290-ohm resistors. A galvanometer with a resistance of 50 ohms and a sensitivity of 0.05 μa/mm is connected across the other two terminals. The galvanometer is shunted by a resistance of 30 ohms. Calculate the galvanometer deflection. Repeat the calculation for a series resistance of 30 ohms connected in the galvanometer circuit instead of the shunt arrangement.

4-11 Suppose an end resistor is added to the curcuit of Fig. 4-12 so that there results



where R₁ is the end resistor. Derive an expression for the voltage output and loading error of such an arrangement What advantage does it offer over the circuit in Fig. 4-12? Suppose the end resistor were attached to the other end of the variable resistance. What would be the advantage in this circumstance? What would be the advantage if an end resistor were placed on each end of the variable resistor?

4-12 Design a bandpass filter to operate between the limits of

- 500 and 2,000 cps
- 4-13 Design a low-pass filter with a cutoff frequency of 500 cps.
- 4-14 Design a high-pass filter with a cutoff frequency of 1,000 cps
- 4-15 A voltage of 500 volts is impressed on a 150-kilohm resistor. The impedance of the voltage source is 10 kilohm. Two meters are used to measure the voltage across the 150-kilohm resistor: a volt-ohimmeter with an internal impedance of 1,000 ohms/volt and a VTVM with an impedance of 11 megohms. Calculate the voltage indicated by each of these devices.
- 4-16 Plot the gain of the filter circuit of Example 4-5
- 4-17 Five 1-in.¹ plates are arranged as shown. The plate spacings are 0.01 in The arrangement is to be used for a displacement transducer by observing the chauge in capacitance with the distance z. Calculate the sensitivity of the device in picofarads per inch. Assume that the plates are separated by air.



4-18 Calculate the voltage-displacement sensitivity for the LVDT whose characteristics are shown in Fig. 4-37.

# Experimental methods for engineers

- 4-19 The piezoelectric crystal of Example 4-10 is used for a pressure measurement at a nominal 100 psi. The uncertainty in the voltage measurement is ±0.5 volt, and the uncertainty in the crystal thickness is ±0.0003 in. Estimate the uncertainty in the pressure measurement.
- 4-20 A rotating search coil like that shown in Fig. 4-9 has a nominal area of 1 cm² with 50 turns of small-diameter wire. The rotational speed is nominally 180 rpm. Calculate the voltage output when the coil is placed in a magnetic field of 1 weber/m².

### REFERENCES

- Cady, W. G.: "Piezoelectricity," McGraw-Hill Book Company, New York, 1946.
- Frank E.: "Electrical Measurement Analysis," McGraw-Hill Book Company, New York, 1959.
- Lion, K. S.: "Instrumentation in Scientific Research," McGraw-Hill Book Company, New York, 1959.
- Lion, K. S.: Mechanic-electric Transducer, Rev. Sci. Instr., vol. 27, no. 2, pp. 222-225, 1956.
- Sweeney, R. J.: "Measurement Techniques in Mechanical Engineering," John Wiley & Sons, Inc., New York, 1953.
- 6. ——, "Frequency and Time Standards," Application Note 52, Hewlett-Packard Co., Palo Alto, Calif.
- "Notes on Linear Variable Differential Transformers," Bulletin AA-1a, Schaevitz Engineering Co., Camden, N.J.
- 8. ——, "The Radio Amateur's Handbook," 36th ed., Amateur Radio Relay League, West Hartford, Conn., 1959.
- "Reference Data for Radio Engineers," International Telephone and Telegraph Corp., New York, 1956.
- "International Conference on Photoconductivity," J. Phys. Chem. Solids, vol. 22, pp. 1-409, December, 1961.

# Displacement and area measurements

### 5-1 INTRODUCTION

Many of the transducers discussed in Chap 4 represent excellent devices for measurement of displacement. In this chapter we wish to examine the general subject of dimensional and displacement measurement and indicate some of the techniques and instruments which may be utilized for such purposes, making use, where possible, of the information in the preceding sections.

Dimensional measurements are eategorized as determinations in bise of an object, while a displacement measurement implies the measurement of the movement of a point from one position to another. An area measurement on a standard geometric figure is a combination of appropriate dimensional measurements through a correct analytical relationship. The determination of areas of irregular geometric shapes usually involves a mechanical, graphical, or numerical integration.

Displacement measurements may be made under both steady and transient conditions Transent measurements fall under the general class of subjects discussed in Chap 11. The present chapter is concerned only with statue measurements.

### 5-2 DIMENSIONAL MEASUREMENTS

The standard units of length have been discussed in Chap 2. All dimensional measurements are eventually related to these standards. Simple dimensional measurements with an accuracy of  $\pm 0.01$  in. may be made with graduated metal machinist's scales or wood scales which have accurate engraved markings? For large




Fig. 5-1. Vernler caliper.

dimensional measurements metal tapes are used to advantage. The primary errors in such measurement devices, other than readability errors, are usually the result of thermal expansion or contraction of the scale. On long metal tapes used for surveying purposes this can represent a substantial error, especially when used under extreme temperature conditions. It may be noted, however, that thermal expansion effects represent fixed errors and may easily be corrected when the measurement temperature is known.

Vernier calipers represent a convenient modification of the metal scale to improve the readability of the device. The caliper construction is shown in Fig. 5-1, and an expanded view of the vernier scale is shown in Fig. 5-2. The caliper is placed on the object to be measured and the fine adjustment rotated until the jaws fit tightly against the workpiece. The increments along the primary scale are 0.025 in. The vernier scale shown is used to read to 0.001 in. so that it has 25 equal increments (0.001 is  $\frac{1}{2.5}$  of 0.025) and a total length of  $\frac{2.5}{2.5}$  times the length of the primary scale graduations. Consequently, the vernier scale does not line up exactly with the primary scale, and the ratio of the last coincident number on the vernier to the total vernier length will equal the fraction of a whole primary scale division indicated by the index position. In the example shown in Fig. 5-2 the reading would be  $2.350 + (\frac{1}{2.5})(0.025) = 2.364$  in.

The micrometer calipers shown in Fig. 5-3 represent a more precise measurement device than the vernier calipers. Instead of using the vernier scale arrangement a calibrated screw thread and circumferential scale divisions are used to indicate the fractional




Fig. 5-2. Expanded view of vernier scale.




Fig. 5-3. Micrometer calipers.

part of the primary scale divisions. In order to obtain the maximum effectiveness of the micrometer, care must be exerted to ensure that a consistent contact pressure is maintained on the workpiece. The spring-loaded ratchet device on the handle enables the operator to maintain such a condition. When properly used the micrometer can be employed for the measurement of dimensions within 0,000 in.

Dial indicators are devices which perform a mechanical amplication of the displacement of a pointer or follower in order to measure displacements within about 0 001 in. The construction of such indicators provides a gear rack which is connected to a displacement-sensing shaft. This rack engages a pinion which in turn is used to provide a gear-train amplification of the movement. The output reading is made on a circular dial.

### Example 5-1

A 100-ft steel tape is used for a surveying instrument in the summer such that the tape temperature is  $105^{\circ}\mathrm{F}$ . A measurement indicates  $45.5\pm0.002\,\mathrm{ft}$ . The linear thermal coefficient of expansion is  $6.47\times10^{-4}$  per 'F at 60°F. Calculate the true distance measurement

Solution. The indicated tape length would be the true value if the measurement were taken at 60°F. At the elevated temperature the tape has expanded and consequently reads too small a distance. The actual length of the 100-ft tape at 105°F is

$$L(1 + \alpha \Delta T) = [1 + (6.47 \times 10^{-4})(45)](100)$$
  
= 100.029115 ft

Such a true length would be indicated as 100 ft. The true reading for the above situation is thus

(84 56)(1.00029115) = 84 585 ft

## 5-3 GAGE BLOCKS

Gage blocks represent industrial dimension standards. They are small steel blocks about  $\frac{3}{6}$  by  $1\frac{3}{6}$  in, with highly polished parallel surfaces. The thickness of the blocks is specified in accordance with the following tolerances:

Grade of block	Tolerance,† pin.
AA	2
A	4
В	8

Gage blocks are available in a range of thicknesses which make it possible to stack them in a manner such that with a set of 81 blocks any dimension between 0.1000 and 8.0000 in. can be obtained in increments of 0.0001 in. The blocks are stacked through a process of wringing. With surfaces thoroughly clean the metal surfaces are brought together in a sliding fashion while a steady pressure is exerted. The surfaces are sufficiently flat so that when the wringing process is correctly executed they will adhere together as a result of molecular attraction. The adhesive force may be as great as 30 times atmospheric pressure.

Because of their high accuracy, gage blocks are frequently used for calibration of other dimensional measurement devices. For very precise measurements they may be used for direct dimensional comparison tests with a machined item. A discussion of the methods of producing gage-block standards is given in Ref. [3]. The literature of manufacturers of gage blocks furnishes an excellent source of information on the measurement techniques which are employed in practice.

# 5-4 OPTICAL METHODS

An optical method for measuring dimensions very accurately is based on the principle of light interference. The instrument based on this principle is called an interferometer and is used for the calibration of gage blocks and other dimensional standards. Other optical instruments in wide use are various types of microscopes and telescopes, including the conventional surveyor's transit which is employed for measurement of large distances.

† Tolerances are for blocks less than 1 in. thick; for greater thickness the same tolerances are per inch.




Fig. 5-4. Interference principle. (a) Beams in phase; (b) beams out of phase.

Consider the two sets of light beams shown in Fig. 5-4. In (a) the two beams are in phase so that the hrightness at point P is augmented when they interest. In (b) the beams are out of phase by half a wavelength so that a cancellation is observed, and the light waves are said to interfere with each other. Thus is the essence of the interference principle. The effect of the cancellation is brought about by allowing two light waves from a single source to travel along paths of different lengths. When the difference in the distance is an integral multiple of wavelength, there will be a rainforcement of the waves, while there will be a cancellation when the difference in the distances is an odd multiple of half-wavelengths.

Now let us apply the interference principle to dimensional measurements

Consider the two parallel plates shown in Fig. 5-5
One plate is a transparent, strain-free glass accurately polished flat within a few nucronnches

The other plate has a reflecting metal surface. The glass plate is called an optical flat

Parallel




Fig. 5.5. Application of Interference principle.




Fig. 5-6. Schematic of interferometer.

light beams A and B are projected on the plates from a suitable collimating source. The separation distance between the plates d is assumed to be quite small. The reflected beam A intersects the incoming beam B at the point P. Since the reflected beam has traveled further than beam B by a distance of 2d, it will create an interference at point P if this incremental distance is an odd multiple of  $\lambda/2$ . If the distance 2d is an even multiple of  $\lambda/2$ , the reflected beam will augment beam B. Thus, for  $2d = \lambda/2$ ,  $3\lambda/2$ , etc., the screen S will detect no reflected light. Now consider the same two plates, but let them be tilted slightly so that the distance between the plates is a variable. Now, if one views the reflected light beams, alternate light and dark regions will appear on the screen indicating the variation in the plate spacing. The dark lines or regions are called fringes, and the change in the separation distance between the positions of two fringes corresponds to

$$\Delta(2d) = \frac{\lambda}{2} \tag{5-1}$$

The interference principle offers a convenient means for measuring small surface defects and for calibrating gage blocks. The use of a tilted optical flat as in Fig. 5-5 is an awkward method of utilizing the principle, however. For practical purposes the interferometer, as indicated schematically in Fig. 5-6, is employed. Monochromatic light from the source is collimated by the lens L onto the splitter plate  $S_2$ , which is a half-silvered mirror that reflects half of the light toward the optically flat mirror M and allows transmission of the other half toward the workpiece W. Both beams are reflected back and recombined at the splitter plate  $S_2$  and then

instituted to the screen. Fringes may appear on the screen resulting from differences in the optical path lengths of the two bears. If the instrument is properly constructed, these differences will arise from dimensional reminions of the workpiece. The undeference is premarily treated for californian of gap blocks and other applications where entermoly promes absolute dimensional measurements are required. For detailed information on experimental techniques used in interference by the resalts should conrall Res. [3] and [3]. The use of the undeference for flaidfor measurements will be discussed in Chap. 7

### Example 5-2

A mentary kind source employs a more interests that the wavelength is 500 A. This high is collimated and unweiled onto two tilled surfaces for those lower in Fig. 55. A tone on the entires are impressed entated. Between the print of emplant and a distance of 3,000 in., fire interference larger are observed. Calculate the expansion distance between the two surfaces and the fits made as this position.

Solution. The five fringe lines correspond to  $\lambda/2, 3\lambda/2, \dots, 9\sqrt{2},$  that is, for the fifth fringe line

$$2d = \frac{9\lambda}{2}$$

We have  $\lambda = 5450 \times 10^{-4}$  cm = 2 15 × 10⁻³ m. so that

d = ₹(2.15 × 10⁻⁴) ≈ 48.4 µm.

The tilt angle is

$$\phi = \tan^{-1} \frac{48.4 \times 10^{-4}}{3.000} = \frac{49.4 \times 10^{-4}}{3.000} = 16.1 \times 10^{-4} \text{ rad}$$

Mechanical displacement may also be measured with the aid of the electric transducers discussed in Chap 4. The LVDT, for example, can be used to sense displacements as small as 1 µin. Resistance transducers are primarily of value for measurement of lairly large displacements because of their poor resolution. Capacitairly large displacements because of their poor resolution. Capacitance and piezoelectric transducers, on the other hand, provide high resolution and are suitable for dynamic measurements.

# 5-5 PNEUMATIC DISPLACEMENT GAGE

Consider the system shown in Fig. 5-7. Air is supplied at a constant pressure p₁. The flow through the orifice and through the




Fig. 5-7. Pneumatic displacement device.

outlet of diameter  $d_2$  is governed by the separation distance x between the outlet and the workpiece. The change in flow with x will be indicated by a change in the pressure downstream from the orifice  $p_2$ . Thus, a measurement of this pressure may be taken as an indication of the separation distance x. For purposes of analysis we assume incompressible flow. (See Sec. 7-3 for a discussion of the validity of this assumption.) The volumetric flow through an orifice may be represented by

$$Q = CA \sqrt{\Delta p} \tag{5-2}$$

where

C = discharge coefficient

A =flow area of the orifice

 $\Delta p$  = pressure differential across the orifice

There are two orifices in the situation depicted in Fig. 5-7, the obvious one and the orifice formed by the flow restriction between the outlet and the workpiece. We shall designate the area of the first orifice  $A_1$  and that of the second  $A_2$ . Then, Eq. (5-2) becomes

$$Q = C_1 A_1 \sqrt{p_1 - p_2} = C_2 A_2 \sqrt{p_2 - p_0}$$
 (5-3)

where  $p_a$  is the ambient pressure and is assumed constant. Equation (5-3) may be rearranged to give

$$r = \frac{p_2 - p_a}{p_1 - p_a} = \frac{1}{1 + (A_2/A_1)^2}$$
 (5-4)

where it is assumed that the discharge coefficients  $C_1$  and  $C_2$  are equal. We may now observe that

$$A_1 = \frac{\pi d_1^2}{4} \tag{5-5}$$

$$A_2 = \pi d_2 x \tag{5-6}$$

Thus we see the relation between the pressure ratio r and the workpiece displacement x. Graneek and Evans [1] have shown experimentally that the relation between r and the area ratio  $A_3/A_1$  is very nearly linear for  $0.4 \le r \le 0.9$  and that

$$r = 1.10 - 0.50 \frac{A_2}{A_1} \tag{5-7}$$

for this range Introducing Eqs. (5-5) and (5-6), we have

$$r = \frac{p_1 - p_4}{p_1 - p_4} = 1 \ 10 - 2 \ 00 \left(\frac{d_2}{d_1^2}\right) z \qquad \text{for } 0.4 < r < 0.9$$
 (5-8)

### Example 5-3

A pneumatic displacement gase like the one shown in Fig 5.7 has  $d_1=0.030$  in and  $d_2=0.062$  in. The supply pressure is 10.0 pmg, and the differential pressure  $p_1=p_2$  is measured with a sater manometer which may be read with an uncertainty of 0.05 in HeO. Calculate the displacement range for which Eq. (5-8) applies and the uncertainty in this measurement, assuming that the stupply pressure remains constant.

Solution We have

$$\frac{d_1}{d_1^2} \approx \frac{0.062}{(0.030)^2} \approx 68.8$$

When r = 0.4, we have, from Eq. (5-8),

$$z = \frac{1.10 - 0.4}{(2.00)(68.8)} = 0.0509 \text{ in}$$

When r = 0.9, z = 0.0145 in

Utilizing Eq (3-2) as applied to Eq (5-8), we have

$$w_r = \left[ \left( \frac{\partial r}{\partial x} \right)^2 w_x^2 \right]^{\frac{1}{2}} = \pm \frac{\left| \frac{\partial r}{\partial x} \right|}{\left| \frac{\partial r}{\partial x} \right|} w_x$$

Furthermore,

$$w_r = \frac{w_{\Delta,r}}{p_1 - p_*}$$
  $\frac{\partial r}{\partial z} = -(2.00)(68.8) \approx -137.6$ 

The uncertainty in the measurement of  $p_1 - p_4$  is

Thus, the uncertainty in x is given by

$$w_x = \frac{1.805 \times 10^{-3}}{(137.6)(10.00)} = 1.313 \times 10^{-6} \text{ in.} = 1.313 \text{ µin.}$$

From this example we see that the pneumatic gage can be quite sensitive, even with modest pressure-measurement facilities at hand.

## 5-6 AREA MEASUREMENTS

There are many applications which require a measurement of a plane area. Graphical determinations of the area of survey plots from maps, the integration of a function to determine the area under a curve, and analyses of experimental data plots all may rely on a measurement of a plane area. There are also many applications for the measurement of surface areas, but such measurements are considerably more difficult to perform.

### 5-7 THE PLANIMETER

The planimeter is a mechanical integrating device which is used for measurement of plane areas. Consider the schematic representation shown in Fig. 5-S. The point 0 is fixed while the tracing point T is moved around the periphery of the figure whose area is to be determined. The wheel W is mounted on the arm BT so that it is free to rotate when the arm undergoes an angular dis-




Fig. 5-8. Schematic of a polar planimeter.

placement The wheel has engraved graduations and a vernier scale so that its exact number of revolutions may be determined as the tracing point moves around the curve. The planimeter and area are placed on a flat, relatively smooth surface so that the wheel W will only slide when the arm BT undergoes an axial translational movement. Thus the wheel registers zero angular displacement when an axial translational movement of arm BT is experienced. Let the length of the tracing arm BT be L and the distance from point B to the wheel be a. The diameter of the wheel is D The distance OB is taken as R. Now suppose the arm BT is rotated an angle ds and the arm OB through an angle ds as a result of movement of the tracing point. The area awept out by the arm BT and OB is

$$dA = \frac{1}{2}L^{2}d\theta + LR \sin \beta d\phi + \frac{1}{2}(R^{2} + L^{2} - 2aL) d\phi$$
 (5-9)

where  $\beta$  is the angle between the two arms. Similarly, the distance traveled by the rim of the wheel owing to rotation is

$$ds = a d\theta + R \sin \beta d\phi ag{5-10}$$

Equations (5-9) and (5-10) may now be integrated for a complete traverse of the tracing point around the area. There results

$$A = \frac{1}{2}L^{2} \int d\theta + LR \int \sin \theta \, d\phi + \frac{1}{2}(R^{2} + L^{2} - 2\alpha L) \int d\phi \qquad (5-11)$$

and

$$s = o \int d\theta + R \int \sin \beta \, d\phi$$
 (5-12)

Since the tracing arm comes back to its original position,

$$\int d\theta = 0$$

$$s = R \int \sin \phi \, d\phi$$

and

$$A = L_8 + \frac{1}{2}(R^2 + L^2 - 2\alpha L)(\phi_2 - \phi_2) \tag{5-13}$$

If the pole point 0 is outside the area, as shown in Fig. 5.8,  $\phi_1 = \phi_1$ If it is inside the area,  $\phi_1 = \phi_4 = 2\pi$ . Note that when the pole is outside the area, the distances R and a do not enter into the calculation of the area. The last term in Eq. (5-13) represents

# Experimental methods for engineers




Fig. 5-9. Construction of a polar planimeter.

the area of the zero circle, which is the area the tracing point would sweep out when the pivot point is inside the area and the wheel reading is zero.

The instrument described above is called a polar planimeter. Typical commercial devices have a wheel circumference of 2.50 in., and models are available with both fixed- and adjustable-length tracing arms. The area of the zero circle is frequently given by the manufacturer but may also be determined as in Example 5-4. The construction of the polar planimeter is indicated in Fig. 5-9.

The polar planimeter is not generally suitable for the measurement of long narrow areas because the pivot point must be fixed. The roller planimeter shown in Fig. 5-10 is suitable for these measurements. The two rollers R are connected through a bevel-gear arrangement to the table A. The wheel W is in contact with the table and rotates in accordance with the number of revolutions of the table. The tracing point T is connected to the mounting




Fig. 5-10. Roller planimeter.

for the wheel so that its movement causes the wheel to move inward and outward on the rotatiog table. The rotation of the wheel depends upon its distance from the center of the table so that it is, in turn, dependent on the displacement of the tracing point in a direction parallel to the axis of the two rollers Thus, the total indication of the wheel is a function of the distance moved by the rollers and the perpendicular displacement of the tracing point and is consequently a function of the area traversed. The device may be used for a large class of area measurements since it can move in two directions.

### Exomple 5-4

A planimeter with a fixed tracing arm 400 in, long has a wheel circumference of 250 in. The instruction sheet for the instrument is lost so that the area of the zero circle is not known. To determine the area of the zero circle, a certain area is measured with the pole both mode and outside the area. With the pole outside the area the wheel records 25 revolutions. With the pole inside the area the wheel records -1301 revolutions. Calculate the area of the zero circle and the reading of the planimeter when it is used to trace out a circle 9 in m radius.

$$A = Ls + A_{\bullet}$$

where A_e is the area of the zero circle. The true area is the value of Ls when the pole is outside the area. Thus,

$$A = (4.00)(2.55)(2.50) \approx 25.50 \text{ m}^3$$

and

When the planumeter is used to measure a 9-in.-radius circle we have

$$s \sim \frac{A - A_0}{L} = \frac{\pi(\theta)^s - 1556}{400} = 24717$$

The number of wheel revolutions is thus

$$n = \frac{1}{2.50} = \frac{24717}{2.50} = 9887$$

# 5-8 GRAPHICAL AND NUMERICAL METHODS FOR AREA MEASUREMENT

A very simple method of plane-area measurement is to place the figure on coordinate paper and count the number of squares enclosed by the figure. An appropriate scale factor is then applied to determine the area. Numerical integration is commonly applied to determine the area under an irregular curve. Perhaps the two most common methods are the trapezoidal rule and Simpson's rule. Consider the area shown in Fig. 5-11. The area under the curve is

$$A = \int y \, dx \tag{5-14}$$

If the figure is divided into equal increments  $\Delta x$  along the x axis, the trapezoidal rule gives for the area

$$A = \left(\frac{y_0 + y_n}{2} + \sum_{i=1}^{n-1} y_i\right) \Delta x \tag{5-15}$$

When the area is divided into an even number of increments, Simpson's rule gives

$$A = \frac{\Delta z}{3} \left\{ y_0 + y_n + \sum_{i=1}^{n-1} y_i [3 + (-1)^{i+1}] \right\}$$
 (5-16)

The trapezoidal rule is obtained by joining the ordinates of the curve with straight lines, while the result given by Eq. (5-16) is obtained




Fig. 5-11. Plane-area determination.

by joining three points at a time with a parabols. Both of the above equations are special cases of a general class of equations called the Newton-Cotes integration formulas. A derivation of these formulas is based on an approximation of the actual curve with a polynomial which agrees with it at n + 1 equally spaced points. The general form of the integration formulas is derived in Ref. [2] and may be written in the following way

$$\int_{x_1}^{x_1} f(x) dx = \Delta x \sum_{k=0}^{n} C_k f(x_k)$$
 (5-17)

where

$$\Delta z = \frac{z_1 - z_1}{n} \tag{5-18}$$

$$x_k = x_1 + k \Delta x \tag{5-19}$$

and the coefficients C. are given by

$$C_k = \int_0^n \frac{s(s-1) \cdot (s-k+1)(s-k-1)}{k(k-1) \cdot (k-k+1)(k-k-1) \cdot (k-n)} ds$$

The variable s is defined according to

$$s = \frac{x - x_1}{n} \tag{5-21}$$

Note that the Newton-Cotes formulas use a increments in the independent variable and that this requires a matching of a polynomial at n + 1 points in the region which is to be integrated. A discussion of the errors involved in the above formulas is given by Hildebrand [9].

### 5-9 SURFACE AREAS

Consider the general three-dimensional surface shown in Fig 5-12 The surface is described by the function

$$z = f(x,y)$$

and the surface area is given in Ref [4] as

$$A = \iiint \left[ \left( \frac{\partial z}{\partial x} \right)^{2} + \left( \frac{\partial z}{\partial y} \right)^{2} + 1 \right]^{2} dx dy$$
 (5-22)




Fig. 5-12. Surface-area determination.

If the function z is known and well-behaved, the integral in Eq. (5-22) may be evaluated directly. Let us consider the case where the function is not given, but specific values of z are known for incremental changes in x and y. The increments in x and y are denoted by  $\Delta x$  and  $\Delta y$ , while the value of z is denoted by  $z_n^p$  where the subscript n refers to the x increments and the superscript p refers to the y increment. We thus have the approximations

$$\frac{\partial z}{\partial x} \approx \frac{z_{n+1}^p - z_n^p}{\Delta x}$$

$$\frac{\partial z}{\partial y} \approx \frac{z_n^{p+1} - z_n^p}{\Delta y}$$

The integral in Eq. (5-22) is now replaced by the double sum

$$A = \sum_{p} \sum_{n} \left[ \left( \frac{z_{n+1}^{p} - z_{n}^{p}}{\Delta x} \right)^{2} + \left( \frac{z_{n}^{p+1} - z_{n}^{p}}{\Delta y} \right)^{2} + 1 \right]^{3} \Delta x \, \Delta y \qquad (5-23)$$

The surface area may be determined by performing this numerical summation.

### PROBLEMS

5-1 A 12-in. steel scale is graduated in increments of 0.01 in. and is accurate when used at a temperature of 60°F. Calculate the

error in an 11-in. measurement when the ambient temperature is 100°F. Should the person using the acale be concerned about this error? Why?

- 5-2 Calculate the temperature error in a 76-ft measurement with a steel surveyor's tape at -10°F when the tape is accurate at 60°F
- 5-3 Show that the spacing distance d in Fig. 5-5 can be represented by

$$d = \frac{2n-1}{4}\lambda$$

where n is the number of fringe lines.

- 5.4 A pneumatic displacement gage is designed according to the arrangement in Fig. 5.7 An air supply pressure of 20 pag is available, and displacements are to be measured over a range of 0.500 in. The orifice diameter is 0.250 in Calculate the maximum displacement which may be measured in the linear range of operation and the outlet tube diameter d.
- 5.5 A planimeter is used to measure the stea of an irregular plane figure. The wheel circumference is 250 m, and the tracing arm is adjustable. With a tracing arm length of 200 m, and the pole outside the area the wheel indicates 9.52 revolutions. With a tracing arm length of 400 m, and the pole outside the area the wheel indicates 470 revolutions. Do the two readings correspond to the asme area? If not, how do you explain the differences?
- 5-6 Plot the equation

$$y = 3 + 4x - 6x^2 + 28x^2 - 013x^4$$

for the range 0 < x < 5 Determine the area under the curve by counting squares and also by numerical integration using the trapezoidal relation and Simpson's rule. Calculate the error in each of these three cases by comparing the results with that obtained analytically

5-7 Use the trapezoidal rule and Simpson's method to perform the integration

$$A = \int_0^x \sin x \, dx$$

Use 4, 8, and 12 merements of x and calculate the error for each case

5-8 Consider the sphere given by

$$x^2 + y^2 + z^2 = 25$$

Using the summation of Eq. (5-23), calculate the surface area bounded by  $x = \pm 1$  and  $y = \pm 1$ . Use  $\Delta x = \Delta y = 0.5$ . Determine the error in the calculation by comparing it with the true value as calculated from Eq. (5-22).

5-9 By suitable numerical integration determine the surface area and volume of a right circular cone having a height of 5 in. and a base diameter of 6 in. Compare the result with that obtained by an exact calculation.

#### REFERENCES

- Graneek, M., and J. C. Evans: A Pneumatic Calibrator of High Sensitivity, Engineer, p. 62, July 13, 1951.
- Hildebrand, F. B.: "Introduction to Numerical Analysis," McGraw-Hill Book Company, New York, 1956.
- Peters, C. G., and W. B. Emerson: Interference Methods for Producing and Calibrating End Standards, J. Res. Natl. Bur. Std., vol. 44, p. 427, 1950.
- Sokolnikoff, I. S., and R. M. Redheffer: "Mathematics of Physics and Modern Engineering," McGraw-Hill Book Company, New York, 1958.
- Metrology of Gauge Blocks, Natl. Bur. Std. (U.S.), Circ. 581, April, 1957.

# Pressure measurements

#### 6-1 INTRODUCTION

Pressure is represented as a force per unit area. As such, it has the same units as alress and may, in a general sense, be considered as a type of streas. For our purposes we shall designate the force per unit area exerted by a fluid on a containing wall as the pressure. The forcea which arise as a result of strains in solds are designated as stresses and discussed in Chap. 10. Thus, our discussion of pressure measurement is one which is restricted to fluid systems. Absolute pressure refers to the absolute value of the force per unit area exerted on the containing wall by a fluid. Gage pressure represents the difference between the absolute pressure and the local atmospheric pressure. Vacuum represents the amount by which the atmospheric pressure exceeds the absolute pressure. From these definitions we see that the absolute pressure may not be negative and the vacuum may not be greater than the local atmospheric pressure. The three terms are illustrated graphically in Fig. 6-1. It is worthwifte to




Fig. 6-1. Relationship between pressure terms.

mention that local fluid pressure may be dependent upon many variables; elevation, flow velocity, fluid density, and temperature are parameters which are of frequent importance.

In the engineering system of units pressure is usually expressed in pounds per square inch absolute (psia). Gage pressure carrying the same units is designated with the symbol psig. Pressure is frequently expressed in terms of the height of a column of mercury which it will support at a temperature of 68°F. At standard atmospheric pressure of 14.696 psia this height is 760 mm with the density of mercury taken as 13.5951 g/cm³. Some other units which are commonly used are:

1 microbar = 1 dyne per square centimeter 1 millimeter = 1333.22 microbars 1 micron = 1  $\mu$  = 10⁻⁶ meter Hg = 10⁻³ millimeter Hg 1 torr = 1 millimeter Hg

Fluid pressure results from a momentum exchange between the molecules of the fluid and a containing wall. The total momentum exchange is dependent upon the total number of molecules striking the wall per unit time and the average velocity of the molecules. For an ideal gas, it may be shown that the pressure is given by

$$p = \frac{1}{3}nmv_{im}^2 \tag{6-1}$$

where

n = molecular density

m = molecular mass

 $v_{rms} = \text{root-mean-square molecular velocity}$ 

It may also be shown that

$$v_{\rm rms} = \sqrt{\frac{3kT}{m}} \tag{6-2}$$

where

T= absolute temperature of the gas  $k=1.3803 \times 10^{-23}$  joule/molecule-°K (Boltzmann's constant)

Equation (6-1) is a kinetic theory interpretation of the ideal gas law. An expression for the pressure in a liquid would not be so simple.

The mean free path is defined as the average distance a molecule travels between collisions. For an ideal gas whose molecules act approximately like billiard balls

$$\lambda = \frac{\sqrt{2}}{8\pi r^2 n} \tag{6-3}$$

where r is the effective radius of the molecule and \( \) is the mean free path. It is clear that the mean free path increases with a decrease in the gas density. At standard atmospheric pressure and temperature the mean free path is quite amail, of the order of 10-tem. At a pressure of 1 \( \) \( \) however, the mean free path would be of the order of 1 cm. At very low pressures the mean free path may be significantly greater than a characteristic dimension of the containing vessel.

A variety of devices are available for pressure measurement, as we shall see in the following sections. State, 1e, eteady-state pressure, is not difficult to measure with good accuracy Dynamic measurements, however, are much more perplexing because they are influenced strongly by the characteristics of the fluid which is studied as well as the construction of the measurement device. In many instances a pressure instrument which gives very accurate results for a static measurement may be entirely unsatisfactory for dynamic measurements. We shall discuss some of the factors which are important for good dynamic response in conjunction with the exposition associated with the different types of pressure-measurement devices.

#### 6-2 DYNAMIC RESPONSE CONSIDERATIONS

The transient response of pressure-measuring instruments is dependent on two factors: (1) the response of the transducer element which seeness the pressure and (2) the response of the pressure-transmitting fluid and the connecting tubing, etc. This latter factor is frequently the one which determines the overall frequency response of a pressure-measurement aystem, and, eventually, direct cabbration must be relied upon for determining this response. An estimate of the behavior may be obtained with the following analysis. Consider the system shown in Fig. 6-2. The fluctuating pressure has a frequency of a and an amplitude of  $p_0$  and is impressed on the tube of length L, and radius r. At the end of this tube is a chamber of volume V where the connection to the pressure-sensitive transducer is made. The mass of fluid vibrates under the influence of  $f^{\rm ext}$  friction in the tube which tends to dampen the motion. If the control of the pressure is the fore V is the control of the pressure sensative transducer ventional formula for lammar friction restance in tube V is the sense of the pressure sensative transducer ventional formula for lammar friction restance in tube V is the sense of V in the control of V in the control of V is the control of V in the control of V is the control of V in the control of V in the control of V is the control of V in the control of V in the control of V is the control of V in the control of V in the control of V is the control of V in the control of V in the control of V is the control of V in the control of V in the control of V in the control of V is the control of V in the control of V in the control of V is the control of V in the contr

× .

#### Experimental methods for engineers




Fig. 6-2. Schematic of pressure-transmitting system.

to represent this friction, the resulting expression for the pressure amplitude ratio is

$$\left|\frac{p}{p_0}\right| = \frac{1}{\{[1 - (\omega/\omega_n)^2]^2 + 4h^2(\omega/\omega_n)^2\}^{\frac{1}{2}}}$$
(6-4)

In this equation, p is the amplitude of the pressure signal impressed on the transducer. The natural frequency  $\omega_n$  is given by

$$\omega_n = \sqrt{\frac{3\pi r^2 c^2}{4LV}} \tag{6-5}$$

and the damping ratio h is

$$h = \frac{2\mu}{\rho c r^2} \sqrt{\frac{3LV}{\pi}} \tag{6-6}$$

In the above formulas, c represents the velocity of sound in the fluid,  $\mu$  is the dynamic viscosity of the fluid, and  $\rho$  is the fluid density. The phase angle for the pressure signal is

$$\phi = \tan^{-1} \frac{-2h(\omega/\omega_n)}{1 - (\omega/\omega_n)^2} \tag{6-7}$$

When the tube diameter is very small, as in a capillary, Eq. (6-4) becomes

$$\left| \frac{p}{p_0} \right| = \frac{1}{[1 + 4h^2(\omega/\omega_n)^2]^{i}}$$
 (6-8)

If the transmitting fluid is a gas, the entire system can act as a Helmholtz resonator with a resonant frequency of

$$\omega = \left[\frac{\pi r^2 c^2}{V(L + \frac{1}{2}\sqrt{\pi^2 r^2})}\right]^{\frac{1}{2}}$$
(6-9)

More complete information on the dynamic response of pressuremeasurement systems is given in Refs. [1], [7], and [11].

From Eq. (6-8) it is evident that a capillary tube may be used for effective damping of pressure signals with frequencies appreciably higher than the natural frequency. The tube is then said to act as an acoustical filter.

#### 6-3 MECHANICAL PRESSURE-MEASUREMENT DEVICES

Mechanical devices offer the simplest means for pressure measurement. In this section we shall examine the principles of some of the more important arrangements

The fluid manometer is a widely used device for measurement of fluid pressures under steady-state conditions. Consider first the U-tube manometer shown in Fig. 6-3. The difference in pressure between the unknown pressure p and the atmosphere is determined as a function of the differential height h. The density of the fluid transmitting the pressure p is  $\rho$ , and the density of the manometer fluid is designated as  $\rho$ . A pressure balance of the two columns dictates that

$$p_{\bullet} + \frac{g}{g_{\circ}} h \rho_{\bullet} = p + \frac{g}{g_{\bullet}} h \rho_{f}$$
 (6-10)

Or

$$p - p_* = \frac{g}{g_*} h(\rho_m - \rho_f) \qquad (6-11)$$

Equation (6-11) gives the basic principle of the U-tube manometer It is to be noted that the distance A is measured parallel to the




Fig. 6-3. U-tube manemeter.

# Experimental methods for engineers

gravitational force and that the differential pressure  $p - p_a$  is measured at the location designated by the dashed line. If the location of the pressure source is at a different elevation from this point, there could be an appreciable error in the pressure determination, depending upon the density of the transmitting fluid.

A well-type manometer operates in the same manner as the U-tube manometer except that the construction is as shown in Fig. 6-4. In this case the pressure balance of Eq. (6-10) still yields

$$p - p_a = \frac{g}{g_c} h(\rho_m - \rho_f)$$

This equation is seldom used, however, because the height h is not the fluid displacement which is normally measured. Typically, the well-type manometer is filled to a certain level at zero-pressure differential conditions. A measurement is then made of the displacement of the small column from this zero level. Designating this displacement by h', we have

$$h'A_2 = (h - h')A_1 (6-12)$$

since the volume displacements are the same on both sides of the manometer. Inserting Eq. (6-12) in (6-10) gives

$$p - p_{\alpha} = \frac{g}{g_c} h' \left( \frac{A_2}{A_1} + 1 \right) (\rho_m - \rho_f) \tag{6-13}$$

Commercial well-type manometers have the scale for the manometer column graduated so that the user need not apply the area correction factor to the indicated displacement h'. Thus, for an area ratio of  $A_2/A_1=0.03$ , a true reading of 10.0 in. for h' would be indicated as 10.3 as a result of the special scale graduation. The indicated value is then substituted for h in Eq. (6-11).




Fig. 6-4. Well-type manometer.



Fig. 6-5. Manometer used as a barometer.

Manometers may be oriented in an inclined position to lengthen the scale and improve readability, or special optical sightglasses and vernier scales may be employed to provide more accurate location and indication of the manometer-fluid height than could be obtained with the naked eye. When mercury is the manometer fluid, variable-reluctance pickups may be used to accurately sense the fluid height Special metal floats may also afford such a convenience with less dense fluids which are noncoductive.

When a well-type manometer is arranged as in Fig 6-5, it is commonly called a batometer. The top of the column is evacuated while the well is exposed to atmospheric pressure. The height h is thus a measure of the absolute atmospheric pressure. When  $p_s = 14\,696$  psia, the height of a column of mercury at 68°F would be 750 mm.

#### 6-4 DEAD-WEIGHT TESTER

The dead - · · · · ·	 J	I fam halan	MEN B HAND TEPRRITE	
with a k				
static ca				
actual p				

only with the use of the dead-weight tester as a calibration device.

Consider the schematic in Fig. 6-6. The apparatus is set up for call briston of the pressure gage G. The chamber and cylinder of the tester are filled with a clean oil by first moving the plunger to its most forward position and then slowly withdrawing it while the oil is poured in through the opening for the piston. The gage to be tested is installed and the piston inserted in the cylinder. The pressure exerted on the fluid by the piston is now transmitted to the Sage when the valve is opened. This pressure may be vice to the contract of the contract of the sage when the valve is opened. This pressure may be vice the contract of the contract of

gravitational force and that the differential pressure  $p - p_a$  is measured at the location designated by the dashed line. If the location of the pressure source is at a different elevation from this point, there could be an appreciable error in the pressure determination, depending upon the density of the transmitting fluid.

A well-type manometer operates in the same manner as the U-tube manometer except that the construction is as shown in Fig. 6-4. In this case the pressure balance of Eq. (6-10) still yields

$$p - p_a = \frac{g}{g_c} h(\rho_m - \rho_f)$$

This equation is seldom used, however, because the height h is not the fluid displacement which is normally measured. Typically, the well-type manometer is filled to a certain level at zero-pressure differential conditions. A measurement is then made of the displacement of the small column from this zero level. Designating this displacement by h', we have

$$h'A_2 = (h - h')A_1 (6-12)$$

since the volume displacements are the same on both sides of the manometer. Inserting Eq. (6-12) in (6-10) gives

$$p - p_a = \frac{g}{g_c} h' \left( \frac{A_2}{A_1} + 1 \right) (\rho_m - \rho_f)$$
 (6-13)

Commercial well-type manometers have the scale for the manometer column graduated so that the user need not apply the area correction factor to the indicated displacement h'. Thus, for an area ratio of  $A_2/A_1 = 0.03$ , a true reading of 10.0 in. for h' would be indicated as 10.3 as a result of the special scale graduation. The indicated value is then substituted for h in Eq. (6-11).




Fig. 6-4. Well-type manometer.



Fig. 6-5. Manometer used as a baromete

Manometers may be oriented in an inclined position to lengthen the scale and improve readability, or special optical sightglasses and vernier scales may be employed to provide more accurate location and indication of the manometer-fluid height than could be obtained with the naked eye. When mercury is the manometer fluid, variable-reluctance pickups may be used to accurately sense the fluid height. Special metal floats may also afford such a convenience with less dense fluids which are nononductive.

When a well-type manometer is arranged as in Fig. 6-5, it is commonly called a barometer. The top of the column is evacuated while the well is exposed to atmospheric pressure. The height b is thus a measure of the absolute atmospheric pressure. When  $p_* = 14.696$  psia, the height of a column of mercury at 68°F would be 760 mm

#### 6-4 DEAD-WEIGHT TESTER

only with the use of the dead-weight tester as a calibration device

Consider the schematic in Fig. 6-6. The apparatus is set up for calibration of the pressure gage G. The chamber and cylinder of the tester are filled with a clean oil by first moving the plunger to its most forward position and then slowly withdrawing it while the oil is poured in through the opening for the piston. The gage to be tested is installed and the piston inserted in the cylinder. The pressure exerted on the fluid by the piston is now transmitted to the gage when the valve is opened. This pressure may be varied by

# Experimental methods for engineers




Fig. 6-6. Schematic of a dead-weight tester.

adding weights to the piston or by using different piston-eylinder eombinations of varying areas. The viscous friction between the piston and the eylinder in the axial direction may be substantially reduced by rotating the piston-weight assembly while the measurement is taken. As the pressure is increased, it may be necessary to advance the plunger to account for compression of the oil and any entrapped gases in the apparatus. High-pressure-dead-weight testers have a special lever system which is used to apply large forces to the piston.

The accuracies of dead-weight testers are limited by two factors: (1) the friction between the cylinder and the piston and (2) the uncertainty in the area of the piston. The friction is reduced by rotation of the piston and use of long enough surfaces to ensure negligible flow of oil through the annular space between the piston and the cylinder. The area upon which the weight force acts is not the area of the piston nor the area of the cylinder; it is some effective area between these two which depends on the clearance spacing and the viscosity of the oil. The smaller the clearance, the more closely the effective area will approximate the cross-sectional area of the piston. It can be shown that the percentage error due to the clearance varies according to

Percent error 
$$\sim \frac{(\rho \Delta p)^{\frac{3}{2}b^{\frac{3}{2}}}{\mu DL}$$
 (6-14)

† See, for example, Ref. [10], p. 105.

#### where

- $\rho = \text{density of the oil}$
- $\Delta p$  = pressure differential on the cylinder
  - b = clearance spacing
  - $\mu = viscosity$
  - D = piston diameter
- L = piston length

At high pressures there can be an elastic deformation of the cylinder which increases the clearance spacing and thereby increases the error of the tester.

#### 6-5 BOURDON-TUBE PRESSURE GAGE

Sourdon-tube pressure gages enjoy a wide range of application where consistent, inexpensive measurements of static pressure are desired. ✓ They are commercially available in many sizes (1 to 16 in. dismeter) and accuracies. The Heise gage is an extremely accurate boundontube gage having an accuracy of 0.1 percent of full-scale reading

† Manufactured by Heise Gage Company, Newton, Conn.




Fig. 6-7. Schematic of a bourdon-tube pressure gage.

and is frequently employed as a secondary pressure standard in laboratory work.

The construction of a bourdon-tube gage is shown in Fig. 6-7. The bourdon tube itself is usually an elliptical cross-sectional tube having a "C"-shape configuration. When the pressure is applied to the inside of the tube, an elastic deformation results which, ideally, is proportional to the pressure. The degree of linearity depends on the quality of the gage. The end of the gage is connected to a spring-loaded linkage which amplifies the displacement and transforms it to an angular rotation of the pointer. The linkage is constructed so that the mechanism may be adjusted for optimum linearity and minimum hysteresis, as well as to compensate for wear which may develop over a period of time. Electrical-resistance strain gages (Sec. 10-7) may also be installed on the bourdon tube to sense the elastic deformation.

#### 6-6 DIAPHRAGM AND BELLOWS GAGES

Diaphragm and bellows gages represent similar types of elastic deformation devices useful for many pressure-measurement applications. Consider first the flat diaphragm subjected to the differential pressure  $p_1 - p_2$ , as shown in Fig. 6-8. The diaphragm will be deflected in accordance with this pressure differential and the deflection sensed by an appropriate displacement transducer. Electrical-resistance strain gages may also be installed on the diaphragm, as shown in Fig. 6-9. The output of these gages is a function of the local strain which, in turn, may be related to the diaphragm deflection and pressure differential. The deflection generally follows a linear variation with  $\Delta p$  when the deflection is less than one-third




Fig. 6-8. Schematic of a disphragm gage.




Fig. 6-9. Diaphragm gage using electricalresistance strain gages.




Fig. 6-10. Deflection cheracteristice of three diaphragm arrangements according to Ref. [9]. (a) Edges fixed, uniform load over entire surface; (b) outer edge fixed and eupported, inner edge fixed, uniform load evit entire actual surface; (c) outer edge fixed and supported, inner edge fixed, uniform load along inner edge.

the disphragm thickness Figure 6-10 compares the deflection characteristics of three disphragm arrangements as given by Roark [9]. Note that the first two disphragms have uniform pressure loading over the entire surface of the disk, while the third type has a load which is applied at the center boss. In all three cases it is assumed that the outer edge of the disk is rigidly fixed and supported. To facilitate linear response over a larger range of deflections than that imposed by the one-third thickness restriction, the disphragm may be constructed from a corrugated disk, as shown in Fig. 6-11. This type of disphragm is most suitable for those applications where

Fig. 6-11. Corrugated-disk diephragm.




Fig. 6-12. Schematic of a bellows pressure gage.




Fig. 6-13. Capacitance pressure gage.

a mechanical device is used for sensing the deflection of the diaphragm. Larger deflections are usually necessary with a mechanical amplification device than for electric transducers. A good summary of the properties of correspated diaphragms is given in Ref. [12].

The bellows gage is depicted schematically in Fig. 6-12. A differential pressure force causes a displacement of the bellows which may be converted to an electric signal or undergo a mechanical amplification to permit display of the output on an indicator dial. The bellows gage is generally unsuitable for transient measurements because of the larger relative motion and mass involved. The diaphragm gage, on the other hand, may be quite stiff, involves rather small displacements, and is suitable for high-frequency pressure measurements.

The deflection of a diaphragm under pressure may be sensed by a capacitance variation as shown in Fig. 6-13. Such pressure pick-




Fig. 6-14. Schematic of LVDT-diaphragm differential pressure gage. (Courtesy Sanborn Company.)

ups are well-mited for dynamic measurement since the natural frequency of disphragms can be rather high. The capacitance pickup, however, involves low sensitivity, and special care must be exerted in the construction of readout circuitry. A schematic disgram of a LVDT-disphragm differential pressure gaze is shown in Fig. 6-14. Commercial models of this type of gage permit measurement of pressures as low as 0 000035 ps.

The natural frequency of a circular draphragm fixed at its perimeter is given by Hetenyi [5] as

$$f = \frac{10.21}{a^2} \sqrt{\frac{g_e E t^2}{12(1 - \mu^2)\rho}} \quad \text{cps}$$
 (6-15)

where

E = modulus of elasticity, psi

! = thickness, in.

a = radius of the disphragm, in

a = density of the material, lb_/in.

g_e = dimensional conversion constant, expressed in units of inches (g_e = 385.9 lb_m-in./lb_msec*)

u = Poisson's ratio

Equation (6-15) may be simplified to the following relation for steel disphragms:

$$f = 1.934 \times 10^4 \frac{t}{\pi a^4}$$
 (6-16)

where I and a are in inches.

#### Example 6-1

A disphragm pressure gage is to be constructed of spring steel  $(E=29\times10^{\circ}\ ps)$ ,  $\mu=0.3$ ) z in, in dismeter and is to be designed to measure a maximum pressure of 200 psig. Calculate the thickness of the gage required so that the maximum defection is one-third this thickness Calculate the natural frequency of this disphragm.

Solution Using the relation from Fig 6-10, we have

$$V_{\text{max}} = \frac{3}{3}t = \frac{3\Delta p}{16Et^2}a^4(1-\mu^2)$$
  
 $t^4 = \frac{(9)(200)(1.0^4)}{(16)(29 \times 10^4)}[1-(0.3)^4] = 3.53 \times 10^{-4} \text{ in }^4$   
 $t = 0.0433 \text{ in.}$ 

We may calculate the natural frequency from Eq. (6-15)

$$f = \frac{10.21}{(1)^2} \left[ \frac{(385.9)(29 \times 10^6)(0.0433)^2(1,728)}{(12)(1 - 0.09)(490)} \right]^{\frac{1}{2}}$$
  
= 26,600 cps

# 6-7 THE BRIDGMAN GAGET

It is known that the resistance of fine wires changes with the pressure according to a linear relationship.

$$R = R_1(1 + b \Delta p) \tag{6-17}$$

 $R_1$  is the resistance at 1 atm, b is the pressure coefficient of resistance, and  $\Delta p$  is the gage pressure. This effect may be used for measurement of pressures as high as 100,000 atm [4]. A pressure transducer based on this principle is called a Bridgman gage. A typical gage employs a fine wire of Manganin (84 percent Cu, 12 percent Mn, 4 percent Ni) wound in a coil and enclosed in a suitable pressure container. The pressure coefficient of resistance for this material is about  $1.7 \times 10^{-7}$  psi⁻¹. The total resistance of the wire is about 100 ohms, and conventional bridge circuits are employed for measuring the change in resistance. Such gages are subject to aging over a period of time so that frequent calibration is required; however, when properly calibrated the gage can be used for high-pressure measurement with an accuracy of 0.1 percent. The transient response of the gage is exceedingly good. The resistance wire itself can respond to variations in the megacycle range. Of course, the overall frequency response of the pressure-measurement system would be limited to much lower values because of the acoustic response of the transmitting fluid. Many of the problems associated with high-pressure measurement are discussed more fully in Refs. [2], [6], and [13].

# 6-8 LOW-PRESSURE MEASUREMENT

The science of low-pressure measurement is a rather specialized field which requires considerable care on the part of the experimentalist. The purpose of our discussion is to call attention to the more prominent types of vacuum instruments and describe the physical principles upon which they operate. For those readers requiring more

† P. W. Bridgman, Proc. Natl. Acad. Sci., U.S., vol. 3, p. 10, 1917.

specialized information we refer them to the excellent monograph by Dushman and Lafferty [3] The reader may also consult this reference for information on the various techniques for producing and maintaining a vacuum.

For moderate vacuum messurements the bourdon gage, manometers, and various diaphragm gages may be employed. Our discussion in this section, however, is concerned with the measurement of low pressures which are not usually accessible to the conventional gages. In this sense, we are primarily interested in absolute pressures below 1 torr.

#### 6-9 THE MCLEOP GAGET

The McLeod gage is a modified mercury manometer which is constructed as shown in Fig 6-15. The movable reservoir is lowered

† H McLeod, Phil Mag, vol 48, p 110, 1874




Fig. 6-15. The McLeed gage.

# Experimental methods for engineers

until the mercury column drops below the opening O. The bulb B and capillary C are then at the same pressure as that of the vacuum source p. The reservoir is subsequently raised until the mercury fills the bulb and rises in the capillary to a point where the level in the reference capillary is located at the zero point. The volume of the capillary per unit length is denoted by a so that the volume of the gas in the capillary is

$$V_c = ay ag{6-18}$$

where y is the length of the capillary occupied by the gas.

We designate the volume of the capillary, bulb, and tube down to the opening as  $V_B$ . The pressure of the gas in the capillary is thus

$$p_{\epsilon} = p \frac{V_{\epsilon}}{V_{R}} \tag{6-19}$$

Now, the pressure indicated by the eapillary is

$$p_{\bullet} - p = y \tag{6-20}$$

where we are expressing the pressure in terms of the height of the moreury column. Combining Eqs. (6-18) to (6-20) gives

$$p = \frac{ay^2}{V_B - ay} \tag{6-21}$$

For most cases  $ay \ll V_B$  and

$$p = \frac{ay^2}{V_B} \tag{6-22}$$

Commercial McLeod gages have the capillary calibrated directly in microns. The McLeod gage is insensitive to condensed vapors which may be present in the sample and are generally applicable to the pressure range from  $10^{-2}$  to  $10^2 \mu$ .

## Example 6-2

A McLeod gage has  $V_B = 100 \text{ cm}^3$  and a capillary diameter of 1 mm. Calculate the pressure indicated by a reading of 3.00 cm. What error would result if Eq. (6-22) were used instead of Eq. (6-21)?

Solution. We have

$$V_s = \frac{\pi(1)^{\frac{1}{2}}}{4} (30.0) = 23.6 \text{ mm}^{\frac{1}{2}}$$
  
 $V_s = 10^4 \text{ mm}^{\frac{1}{2}}$ 

From Eq (6-21),

$$p = \frac{(23.6)(30.0)^2}{10^4 - 23.6} = 0.212 \text{ torr} = 212 \mu$$

The fractional error in using Eq. (6-22) would be

Error = 
$$\frac{ay}{V_{*}} = 2.36 \times 10^{-4}$$

or a negligibly small value.

# 6-10 PIRANI THERMAL-CONDUCTIVITY GAGE!

At low pressures the effective thermal conductivity of gaves decreases with pressure? The Pirani gage is a devoce which measures the pressure through the change in thermal conductance of the gas. The gage is constructed as shown in Fig. 6-16. An electrically heated filament is placed inside the vacuum space. The heat loss from the filament is dependent upon the thermal conductivity of the gas and the filament temperature. The lower the pressure, the lower the thermal conductivity and consequently the higher the filament temperature for a given electric-energy input. The temperature of the filament to the filament could be measured by a thermocouple, but in the Pirani-type gage the measurement is made by observing the variation in resistance of the filament material (lungsten, platinum, etc.) The resistance measurement may be performed with an appropriate bridge circuit. The heat loss from the filament is also a function of the ambient temperature, and in practice, the gages are connected.

† M. Pirsni, Verhandl, deut. physik Ges., vol 8, p 686, 1906



Fig. 6-16. Schematic of Pirani gage.

# Experimental methods for engineers




Fig. 6-17. Pirani-gage arrangement to compensate for change in ambient temperatures.

in series as shown in Fig. 6-17 to compensate for possible variations in the ambient conditions. The compensator gage is evacuated and enclosed in a constant-temperature bath in order to provide a satisfactory reference condition.

Pirani gages require an empirical calibration and are not generally suitable for use at pressures much below  $1\,\mu$ . The upper limit is about 1 torr. For higher pressures the thermal conductance changes very little with pressure. It must be noted that the heat loss from the filament is also a function of the conduction losses to the filament supports and radiation losses to the surroundings. The lower limit of applicability of the gage is the point where these effects overshadow the conduction into the gas. The transient response of the Pirani gage is poor. The time necessary for the establishment of thermal equilibrium may be of the order of several minutes at low pressures.

# 6-11 THE KNUDSEN GAGET

Consider the arrangement shown in Fig. 6-18. Two vanes V along with the mirror M are mounted on the thin filament suspension. Near these vanes are two heated plates P, each of which is maintained at a temperature T. The separation distance between the vanes and plates is less than the mean free path of the surrounding gas. Heaters are installed so that the temperature of the plates is higher than that of the surrounding gas. The vanes are at the temperature of the gas  $T_{\mathfrak{o}}$ . The molecules striking the vanes from the hot plates have a higher velocity than those leaving the vanes because of the difference in temperature. Thus, there is a net momentum imparted to the vanes which may be measured by observing the angular displacement of the mirror, similar to the technique used in a light-beam galvanometer. The total momentum exchange with the

† M. Knudsen, Ann. Physik, vol. 32, p. 809, 1910.




Fig. 6-18. Schematic of a Knudsen gage.

vanes is a function of molecular density, which, in turn, is related to the pressure and temperature of the gas. An expression for the gas pressure may thus be derived in terms of the temperatures and the measured force. For small temperature differences  $T-T_s$ , it may be shown that this relation is [3]

$$p = 4F \frac{T_{\bullet}}{T - T_{\bullet}} \tag{6-23}$$

where the pressure is in dynes per square centimeter when the force is in dynes. The temperatures are in °K.

The Knudsen gage furnishes an absolute measurement of the pressure which is independent of the molecular weight of the gas. It is suitable for use between 10⁻³ and 10  $\mu$  and may be used as a calibration device for other gages in this region

#### 6-12 THE IONIZATION GAGE

Consider the arrangement shown in Fig 6-19, which is similar to the ordinary triode vacuum tube. The heated cathode emits electrons which are accelerated by the positively charged grid. As the




Fig. 6-19. Schematic of an ionization gage.

electrons move toward the grid, they produce ionization of the gas molecules through collisions. The plate is maintained at a negative potential so that the positive ions are collected there, producing the plate current  $i_p$ . The electrons and negative ions are collected by the grid, producing the grid current  $i_p$ . It is found that the pressure of the gas is proportional to the ratio of plate current to grid current.

$$p = \frac{1}{\tilde{S}} \frac{i_p}{i_{\tilde{\sigma}}} \tag{6-24}$$

where the proportionality constant S is called the sensitivity of the gage. A typical value for nitrogen is S = 20 torr⁻¹, but the exact value must be determined by calibration of the particular gage. The value of S is a function of the tube geometry and the type of gas.

Conventional ionization gages are suitable for measurements between 1.0 and  $10^{-5} \mu$ , and the current output is usually linear in this range. At higher pressures there is the danger of burning out the cathode. Special types of ionization gages are suitable for measurements of pressures as low as  $10^{-12}$  torr. Very precise experimental techniques are required, however, in order to perform measurements at these high vacuums. The interested reader should consult Ref. [3] for additional information.

# 6-13 THE ALPHATRON†

The Alphatron is a radioactive ionization gage, which is shown schematically in Fig. 6-20. A small radium source serves as an  $\alpha$ -particle emitter. These particles ionize the gas inside the gage enclosure, and the degree of ionization is determined by measuring the voltage output  $E_0$ . The degree of ionization is a direct linear function of pressure for a rather wide range of pressures from  $10^{-3}$  to  $10^3$  torr. The output characteristies, however, are different for each type of gas used. The lower pressure limit of the gage is determined by the length of the mean free path of the alpha particles as compared with 1 National Research Corp., Cambridge, Mass.




Fig. 6-20. Schematic of an Alphatron gare.

the enclosure dimensions. At very low pressures the mean free path becomes so large that very few collisions are probable in the space and hence the ionization level is very small. The Alphation has the advantage that it may be used at atmospheric pressure as well as which vacuum and that there is no heated falment to contend with



Fig. 6-21. Summary of applicable range of pressure gages.

as in the conventional ionization gage. Consequently, there is no problem of accidently burning out a filament because of an inadvertent exposure of the gage to high (above 10⁻¹ torr) pressures.

#### 6-14 SUMMARY

Figure 6-21 gives a convenient summary of the pressure ranges for which the gages discussed are normally employed in practice.

#### PROBLEMS

- 6-1 A mercury harometer is constructed like that shown in Fig. 6-5. The column is a glass tube 0.250 in. ID and 0.375 in. OD, and the well is a glass dish 1.50 in. ID. Calculate the percent error which would result if an area correction factor were not used.
- 6-2 Derive an expression for the radius of a simple diaphragm as shown in Fig. 6-10 using the following restrictions:
  - a. The maximum deflection is one-third the thickness.
  - b. The maximum deflection must be 100 times as great as the uncertainty in the deflection measurement  $w_{\nu}$ .

Assume that the maximum pressure differential  $\Delta p$  is given as well as  $w_{\nu}$ .

- 6-3 Determine the factor to convert pressure in inches of water to pounds per square foot.
- 6.4 The effective radius of an air molecule is about 1.85  $\times$  10⁻⁸ cm. Calculate the mean free path at 70°F and the following pressures: 1 atm, 1 torr, 1  $\mu$ , 1 in. H₂O, and 10⁻²  $\mu$ .
- 6-5 Reduce Eq. (6-3) to an expression for mean free path in terms of pressure in microns, temperature in ^aK, molecular weight of the gas, and effective molecular diameter.
- 6-6 A dynamic pressure measurement is to be made with an apparatus similar to that shown in Fig. 6-2. The appropriate dimensions are:

$$L \approx 2.50 \text{ in.}$$

r = 0.005 in.

 $V \approx 0.10 \text{ in.}^*$ 

The fluid is air at  $70^{\circ}$ F and 14.7 psia. Plot the pressure amplitude ratio versus  $\omega/\omega_n$  according to both Eq. (6-4) and Eq. (6-8).

- 61 Plot the error in Eq. (6-8) serves of LT.
  64 Calculate the resonant frequency of the system in Prof. 64.
- assuming that it acts as a Helmholiz rescrate.
  69 A well-type manometer uses a special branish field having a
- specific gravity of 2.95. The well has a further of 4.00 in, and the tube has a dismeter of 0.000 in. The manuscre's to be used to measure a differential presume in a wine-fore system. The scale placed aburyth the tube has no correction factor for the area ratio of the manuscre. Calculate the value of a factor which may be unfurfied by the manuscret reading in inches to find the presume offerential in pounds per square inch.
- 61) A varuum gage is to use an LVDT-d aptrasm continuation lie that shown in Fig. 6-14. The LVDT has a senditivity of 0,0001 in n, and the displanger, a to be constructed of seel (E = 20 × 10° n = 0.3) with a factorer of 6 in. Calculus the displangem thickness in avariation with the restriction that the maximum deflection the system of condition this blokeness. What is the lowest pressure which may be sensed by this instrument?
- 6-11 Calculate the natural frequency of the disphragm in Prob. 6-10
- 512 A Bridgman gage uses a coil of Margania wire baring a nominal renotance of 100 ohms at atmospheric pressure. The Eagle is to be used to measure a pressure of 1,000 pdg with an uncertainty of 0.1 percent. What is the allowable uncertainty in the resistance measurement.
- 613 Suppose the Bridgman gage of Prob. 6-12 is connected to the bridge circuit of Fig. 4-17 so that the gage is R₁ and all testianness are equal to 100 ohms is a presence of 1 stim. The battery voltage is 40 volts and the detector is a high-impedance voltage-measuring device. The bridge is assumed to be in balance at p = 1 atm. Cal-ulate the voltage output of the bridge at p = 1,000 psig.
  - 6-14 Rework Example 6-2 assuming the diameter of the capillary to be 0.2 mm.
- 615 A Ennañsen gage is to be designed to operate at a maximum pressure of 1.0 µ. For this application the appring of the vane and plate is to be less than 0.3 mean free path at this pressure Calculate the force on the vames at pressures of 1.0 and 0.01 µ when the gas temperature is 20°C and the temperature difference is 5.00°E.
- 6-15 A capacitance-diaphragm pressure gage as shown in Fig. 6-13

is to be used to measure pressure differentials as high as 1,000 psi at frequencies as high as 15,000 cps. The diameter of the diaphragm is not to exceed 0.500 in. Calculate the thickness and diameter of a diaphragm to accomplish this (the natural frequency should be at least 30,000 cps). Choose a suitable gap spacing, and estimate the capacitance-pressure sensitivity of the device. Assume the dielectric constant is that of air.

6-17 A bourdon-tube pressure gage having an internal volume of 1.0 in.3 is used for measuring pressure in a fluctuating air system having frequencies as high as 100 cps. Design an acoustical filter which will attenuate all frequencies above 20 cps by 99 percent. Plot the frequency response of this filter.

#### REFERENCES

- Arons, A. B., and R. H. Cole: Design and Use of Piezo-electric Gages for Measurement of Large Transient Pressures, Rev. Sci. Instr., vol. 21, pp. 31-38, 1950.
- Bridgman, P. W.: "The Physics of High Pressure," The Macmillan Company, New York, 1931.
- Dushman, S., and J. M. Lafferty: "Scientific Foundations of Vacuum Technique," 2nd ed., John Wiley & Sons, Inc., New York, 1962.
- Hall, H. T.: Some High Pressure-High Temperature Apparatus Design Considerations, Rev. Sci. Instr., vol. 29, p. 267, 1958.
- Hetenyi, M. (ed.): "Handbook of Experimental Stress Analysis," John Wiley & Sons, Inc., New York, 1950.
- Howe, W. H.: The Present Status of High Pressure Measurements, ISA Journal, vol. 2, pp. 77 and 109, 1955.
- Iberall, A. S., Attenuation of Oscillatory Pressures in Instrument Lines, Trans. ASME, vol. 72, p. 689, 1950.
- Neubert, H. K. P.: "Instrument Transducers," Oxford University Press, Fair Lawn, N.J., 1963.
- Roark, R. J.: "Formulas for Stress and Strain," 3rd ed., McGraw-Hill Book Company, New York, 1954.
- 10. Sweeney, R. J.: "Measurement Techniques in Mechanical Engineering," John Wiley & Sons, Inc., New York, 1953.
- Taback, I.: The Response of Pressure Measuring Systems to Oscillating Pressure, NACA Tech. Note 1819, February, 1949.
- Wildhack, W. A., R. F. Dresslea, and E. C. Lloyd: Investigation of the Properties of Corrugated Diaphragms, Trans. ASME, vol. 79, pp. 65-82, 1957.
- Giardini, A. A. (ed.): "High Pressure Measurements," Butterworth & Co. (Publishers), Ltd., London, 1963.

# Flow measurement

#### 7-1 INTRODUCTION

The measurement of fluid flow is important in applications ranging from measurements of blood-flow rates in a human artery to the measurement of the flow of liquid oxygen in a rocket Many research projects and industrial processes depend upon a measurement of fluid flow to furnish important data for analysis. In some eases extreme precision is called for in the flow measurement, while in other instances only crude measurements are necessary selection of the proper instrument for a particular application is governed by many variables, including cost. For many industrial operations the accuracy of a fluid-flow measurement is directly related to profit. A simple example is the ensoline numb at the neighborhood service station, another example is the water meter at home. It is easy to see how a small error in flow measurement on a jarge natural gas or oil pipeline could make a difference of thousands of dollars over a period of time. Thus, the laboratory scientist is not the only person who is concerned with accurate flow measurement; the engineer in industry is also vitally interested because of the impact which flow measurements may have on the profit and loss statement of the company

Flow-rate-measurement devices frequently require accurate pressure and temperature measurements in order to calculate the output of the instrument. Chapters 6 and 8 consider these associated measurement topics in detail, and the reader should consult the appropriate sections from time to time to relate specific pressure and temperature measurement devices to the material in the present chapter. We may remark at this time, however, that the overall accuracy of many of the most widely used flow-measurement devices is governed primarily by the accuracy of some pressure or temperature measurement.

#### Experimental methods for engineers

Our objective in this chapter is to present a broad discussion of flow measurements and indicate the principles of operation of a number of devices which are commonly used. We shall also give the calculation methods which are connected with some of these devices and discuss some methods of flow visualization. In concluding the chapter a tabular comparison of the various methods will be presented, pointing out their range of applicability and expected accuracies.

## 7-2 POSITIVE-DISPLACEMENT METHODS

The flow rate of a nonvolatile liquid like water may be measured through a direct-weighing technique. The time necessary to collect a quantity of the liquid in a tank is measured, and an accurate measurement is then made of the weight of liquid collected. The average flow rate is thus calculated very easily. Improved accuracy may be obtained by using longer or more precise time intervals or more precise weight measurements. The direct-weighing technique is frequently employed for calibration of water and other liquid flowmeters and thus may be taken as a standard calibration technique. Obviously, it is not suited for transient flow measurements.

Positive-displacement flowmeters are generally used for those applications where consistently high accuracy is desired under steady flow conditions. A typical positive-displacement device is the home water meter shown schematically in Fig. 7-1. This meter operates on the nutating-disk principle. Water enters the left side of the meter and strikes the disk, which is eccentrically mounted. In order for the fluid to move through the meter, the disk must "wobble" or nutate about the vertical axis since both the top and the bottom of the disk remain in contact with the mounting chamber. A partition separates the inlet and outlet chambers of the




Fig. 7-1. Schematic of a nutating-disk meter.




Fig. 7-2. Schematic of rotary-vane flowmeter.




Fig. 7-3. Schematic of lobedimpeller flowmeter.

disk. As the disk nutates, it gives direct indication of the volume of liquid which has passed through the meter. The indication of the volumetric flow is given through a gearing and register atrangement which is connected to the nutating disk. The nutating-disk meter may give rehable flow measurements within 1 percent.

Another type of positive-displacement device is the rotary-wane meter shown in Fig. 7-2. The wanes are apring-loaded so that they continuously maintain contact with the easing of the meter. A fixed quantity of fluid is trapped in each section as the eccentric drum rotates, and this fluid eventually finds its way out the crit. An appropriate register is connected to the shaft of the eccentric drum to record the volume of the displaced fluid. The uncertainties of rotary-wane meters are of the order of 0.5 percent, and the meters are relatively insensitive to viscosity since the vanes always maintain good contact with the inside of the easing V

The lohed-impeller meter shown in Fig. 7-3 may be used for either gas- or liquid-flow measurements. The impellers and case are carefully machined so that accurate fit is maintained. In this way, the incoming fluid is always trapped between the two rotors and is conveyed to the outlet as a result of their rotation vThe number of revolutions of the rotors is an indication of the volumetric flow rate.

#### Example 7-1

A lobed-impeller flowmeter is used for measurement of the flow of nitrogen at 20 pais and 100°F. The meter has been calibrated so that it indicates the volumetric flow with an accuracy of ± one-half of one percent from 1,000 to 3,000 cfm. The uncertainties in the gas pressure and temperature measurements are  $\pm 0.025$  psi and  $\pm 1.0^{\circ}\mathrm{F}$  respectively. Calculate the uncertainty in a mass flow measurement at the given pressure and temperature conditions.

Solution. The mass flow is given by

$$m = pQ$$

where the density of nitrogen is given by

$$\rho = \frac{p}{R_N, T}$$

Using Eq. (3-2), we obtain the following equation for the uncertainty in the mass flow as

$$\frac{w_n}{\dot{m}} = \left[ \left( \frac{w_q}{Q} \right)^2 + \left( \frac{w_r}{p} \right)^2 + \left( \frac{w_r}{T} \right)^2 \right]^i$$

Using the given data,

$$\frac{w_{\dot{m}}}{\dot{m}} = \left[ (0.005)^2 + \left( \frac{0.025}{20} \right)^2 + \left( \frac{1}{560} \right)^2 \right]^{\frac{1}{3}} = 5.05 \times 10^{-3}$$

or 0.505 percent. Thus, the uncertainties in the pressure and temperature measurements do not appreciably influence the overall uncertainty in the mass flow measurements.

#### 7-3 FLOW-OBSTRUCTION METHODS

Several types of flowmeters fall under the category of obstruction devices. Such devices are sometimes called head meters because a head-loss or pressure-drop measurement is taken as an indication of the flow rate. Let us first consider some of the general relations for obstruction meters. We shall then examine the applicability of these relations to specific devices.

Consider the one-dimensional flow system shown in Fig. 7-4. The continuity relation for this situation is

$$\dot{m} = \rho_1 A_1 u_1 = \rho_2 A_2 u_2 \tag{7-1}$$

where u is the velocity. If the flow is adiabatic and frictionless and the fluid is incompressible, the familiar Bernoulli equation




Fig. 7-4. General one-dimensional flow system.

may be written

$$\frac{p_1}{\rho_1} + \frac{u_1^2}{2g_\epsilon} = \frac{p_2}{\rho_2} + \frac{u_2^2}{2g_\epsilon}$$
 (7-2)

where now  $\rho_1 = \rho_2$ . Solving Eqs (7-1) and (7-2) simultaneously gives for the pressure drop

$$p_1 - p_2 = \frac{u_1^* p}{2g_*} \left[ 1 - \left( \frac{A_1}{A_1} \right)^* \right]$$
(7-3)

and the volumetric flow rate may be written

$$Q = A_1 u_1 = \frac{A_1}{\sqrt{1 - \left(\frac{A_1}{A_1}\right)^2}} \sqrt{\frac{2g_2}{\rho}} (p_1 - p_2) \qquad (7-4)$$

where

Q = ft1/sec

 $A = ft^2$ 

 $\rho = lb_m/ft^4$   $p = lb_r/ft^2$ 

g. = 32.17 lb_-ft/lb_-sec2

Thus, we see that a channel like the one shown in Fig 7-4 could be used for a flow measurement by simply measuring the pressure drop  $(p_1 - p_2)$  and calculating the flow from Eq (7-4). No such channel, however, is frictionless, and some losses are always present in the flow. The volumetric flow rate calculated from Eq (7-4) is the ideal value, and it is usually related to the actual flow rate and an empirical discharge coefficient  $\hat{C}$  by the following relation:

$$\frac{Q_{\text{estual}}}{Q_{\text{ideal}}} = C \qquad (7-5)$$

The discharge coefficient is not a constant and may depend strongly on the flow Reynolds number and the channel geometry.

When the flow of an ideal gas is considered, the following equation of state applies:

$$p = \rho RT \tag{7-6}$$

where T is the absolute temperature and R is the gas constant for the particular gas. For reversible adiabatic flow the steady-flow energy equation is

$$c_p T_1 + \frac{u_1^2}{2g_c} = c_p T_2 + \frac{u_2^2}{2g_c} \tag{7-7}$$

where  $c_p$  is the specific heat at constant pressure and is assumed constant for an ideal gas. When Eqs. (7-1), (7-6), and (7-7) are combined, there results

$$\dot{m}^2 = 2g_* A_{2^2} \frac{\gamma}{\gamma - 1} \frac{p_1^2}{RT_1} \left[ \left( \frac{p_2}{p_1} \right)^{2/\gamma} - \left( \frac{p_2}{p_1} \right)^{(\gamma+1)/\gamma} \right]$$
 (7-8)

where the velocity of approach, i.e., the velocity at section 1, is assumed to be very small. This relationship may be simplified to


$$\dot{m} = \sqrt{\frac{2g_c}{RT_1}} A_2 \left[ p_2 \Delta p - \left( \frac{1.5}{\gamma} - 1 \right) \Delta p^2 + \cdots \right]^{\frac{1}{2}}$$
 (7-9)

with  $\Delta p = p_1 - p_2$  and  $\gamma = c_p/c_r$  is the ratio of specific heats for the gas. Equation (7-9) is valid for  $\Delta p < p_1/4$ . When  $\Delta p < p_1/10$ , a further simplification may be made to give

$$\dot{m} = A_2 \sqrt{\frac{2g_c p_2}{RT_1} (p_1 - p_2)} \tag{7-10}$$

Note that Eq. (7-10) reduces to Eq. (7-4) when the relation for density from Eq. (7-6) is substituted. Thus, for small values of  $\Delta p$  compared with  $p_1$ , the flow of a compressible fluid may be approximated by the flow of an incompressible fluid.

Three typical obstruction meters are shown in Fig. 7.5. The venturi offers the advantages of high accuracy and small pressure drop, while the orifice is considerably lower in cost. Both the flow nozzle and the orifice have relatively high permanent pressure drop.



Flow-rate calculations for all three devices are made on the basis of Eq. (7-4) with appropriate empirical constants defined as follows

$$M = \text{velocity of approach factor} = \frac{1}{\sqrt{1 - (A_2/A_1)^2}}$$
 (7-11)

$$K = \text{flow coefficient} = CM$$
 (7-12)

$$\beta = \text{diameter ratio} = \frac{d}{D} = \sqrt{\frac{A_2}{A_2}}$$
 (7-13)

When flow measurements of a compressible fluid are made, an additional parameter, the expansion factor Y, is used For venturis and nozzles this factor is given by

$$Y_{\bullet} = \left[ \left( \frac{p_1}{p_1} \right)^{1/\gamma} \frac{\gamma}{\gamma - 1} \frac{1 - (p_2/p_1)^{(\gamma - 1)/\gamma}}{1 - (p_2/p_1)} \frac{1 - (A_2/A_1)^2}{1 - (A_2/A_1)^2(p_1/p_1)^{2/\gamma}} \right]^{\frac{1}{\gamma}}$$
(7-1)

while for orifices an empirical expression for Y is given as

$$Y_1 = 1 - \left[0.41 + 0.35 \left(\frac{A_1}{A_1}\right)^2\right] \frac{p_1 - p_2}{\gamma p_1}$$
 (7-15)

when either flange taps or yena contracta taps are used. For orifices with pipe taps the following relation applies

$$Y_2 = 1 - [0.333 + 1 \, 145(\beta^1 + 0 \, 7\beta^4 + 12\beta^{18})] \frac{p_1 - p_2}{\gamma p_1}$$
 (7-16)

The empirical expansion factors given by Eqs. (7-15) and (7-16) are accurate within  $\pm 0.5$  percent for  $0.8 < p_2/p_1 < 1.0$ .

We thus have the following semiempirical equations which are conventionally applied to venturis, nozzles, or orifices:

Venturis, incompressible flow:

$$Q_{\text{set}} = CMA_2 \sqrt{\frac{2g_c}{\rho}} \sqrt{p_1 - p_2}$$
 (7-17)

Nozzles and orifices, incompressible flow:

$$Q_{\text{act}} = K A_2 \sqrt{\frac{2g_c}{\rho}} \sqrt{p_1 - p_2}$$
 (7-18)

The use of the flow coefficient instead of the product CM is merely a matter of convention. When compressible fluids are used, the above equations are modified by the factor Y and the fluid density is evaluated at inlet conditions. We then have

Venturis, compressible flow:

$$\dot{m}_{\rm act} = YCMA_2 \sqrt{2g_c\rho_1(p_1 - p_2)}$$
 (7-19)


Nozzles and orifices, compressible flow:

$$\dot{m}_{\rm set} = YKA_2 \sqrt{2g_e \rho_1 (p_1 - p_2)}$$
 (7-20)

Detailed tabulations of the various coefficients have been made in Ref. [1], some of which are presented in Figs. 7-9 through 7-15. Examples 7-2 and 7-3 illustrate the use of these charts for practical calculations.

# 7-4 PRACTICAL CONSIDERATIONS FOR OBSTRUCTION METERS

The construction of obstruction meters has been standardized by the American Society of Mechanical Engineers [1, 2]. The recommended proportions of venturi tubes are shown in Fig. 7-6. Note that the pressure taps are connected to manifolds which surround the upstream and throat portions of the tube. These manifolds receive a sampling of the pressure all around the sections so that a good average value is obtained. The discharge coefficients for such venturi tubes are shown in Fig. 7-9, with the tolerance limits indicated by the dashed lines. In general, the discharge coefficient



D = Fipe diameter interest and outlet d = Threat dameter as required a = 0.25D to 0.75D for  $4 \le D \le 6''$ , 0.25D to 0.50D for  $6' < D \le 32$  b = dc = d/2

8 = 3/16 in. to 1/2 in according to D Annular pressure chamber with at least four presonners vents.

r2 = 3.5d to 3 75d

 $r_1 = 0$  to 1 375D  $\alpha_1 = 21^{\circ} \pm 2^{\circ}$ 

or = 5° to 15°

Fig. 7-6. Recommended proportions of venturi tubes according to Ref. II.




Fig. 7-7. Recommended proportions of the ASME long-radius flow nozzle according to Ref. III.

## Experimental methods for engineers




Fig. 7-8. Recommended location of pressure taps for use with concentric, thin-plate, square-edged orifices according to Ref. [1].




Fig. 7-9. Discharge coefficients for the venturi tube shown in Fig. 7-6 according to Ref. [1]. Values are applicable for 0.25  $< \beta <$  0.75 and D> 2 in.




Fig. 7-10. Approximate venturi discharge coefficients for various throat diameters according to Ref. IISI.

is smaller for pipes less than 2 in. in diameter, and the approximate behavior is indicated in Fig 7-10. More precise values of the discharge coefficient for a ventum may be obtained by direct calibration, in which case accuracies of ±0.5 percent may be obtained fairly easily. The recommended dimensions for ASME flow nordes are shown in Fig 7-7, and the discharge coefficients are shown in Fig. 7-10.

The recommended installations for concentre, thin-plate orifices are shown in Fig 7-8. Note that three standard sets of pressure-tap locations are used

- 1. Both pressure taps are installed in the flanges as shown
- The inlet pressure tap is located one pipe diameter upstream, and the outlet pressure tap is located one-half diameter downstream of the orifice
- The inlet pressure tap is located one pipe diameter upstream, and the outlet pressure tap is located at the vena contracta of the orifice as given by Fig 7-12

Figure 7-13 gives the values of the onfice flow coefficient for pipe sizes 14 to 3 in with pressure taps located according to case 2 above. Flow coefficients for other cases are given in Ref. [1]




Fig. 7-11. Discharge coefficients for ASME long-radius nozzles shown in Fig. 7-7 according to Ref. [1],





Fig. 7-12. Location of outlet pressure connections for orlfices with vena contracts taps according to Ref. [1].






Fig. 7-14. Adiabatic expansion factors for use with venturis and flow nozzles as calculated from Eq. (7-14). From Ref. [2].

The various flow coefficients are plotted as a function of Reynolds number defined by

$$Re = \frac{\rho u_m d}{\mu} \tag{7-21}$$

where

 $\rho =$ fluid density

 $\mu = dynamic viscosity$ 

 $u_m = \text{mean flow velocity}$ 

d = diameter at the particular section for which the Reynolds number is specified

Note that some charts, viz., Fig. 7-13, base the Reynolds number on upstream conditions, while others, viz., Fig. 7-10, base it on throat conditions. The product  $\rho\nu_{-}$  may be calculated from the mass flow according to

$$m = \rho u_n A_n \tag{7-22}$$

where  $A_{\epsilon}$  is the cross-sectional area for the flow where  $u_{\sigma}$  is measured. For a circular cross-section,  $A_{\sigma} = \pi d^2/4$ .




Fig. 7-15. Espansion factors for square-edged orifices with pipe taps as calculated from Eq. (7-16). From Ref. (2),

## Example 7-2

A venturi tube is to be used to measure a maximum flow rate of water of 50 gpm at 70°F. The throat Reynolds number is to be at least 10⁵ at these flow conditions. A differential pressure gage is selected which has an accuracy of 0.25 percent of full scale, and the upper scale limit is to be selected to correspond to the maximum flow rate. Determine the size of the venturi and the maximum range of the differential pressure gage, and estimate the uncertainty in the mass flow measurement at nominal flow rates of 50 and 25 gpm. Use either Fig. 7-9 or Fig. 7-10 to determine the discharge coefficient.

Solution. The properties of water are

$$\mu = 62.4 \text{ lbm/ft}^3$$
  $\mu = 2.36 \text{ lbm/hr-ft}$ 

From the given maximum flow rate and throat Reynolds number we may calculate the maximum allowable throat diameter.

$$\text{Re}_d = \frac{\rho u_n d}{\mu} = \frac{ind}{(\pi d^2/4)\mu} = \frac{4in}{\pi d\mu} = 10^5$$

The maximum flow rate is

$$\dot{m} = (50)(8.33)(60) = 2.5 \times 10^4 \,\text{lb}_m/\text{hr}$$

so that

$$d_{\text{max}} = \frac{(4)(2.5 \times 10^4)}{\pi (10^4)(2.36)} = 0.135 \text{ ft} = 1.62 \text{ in.}$$

We shall select a venturi with a 1.0-in. throat diameter, since we have a discharge coefficient curve for this size in Fig. 7-10. The upstream pipe diameter is taken as 2.0 in. From Fig. 7-10 we estimate the discharge coefficient for this size venturi as 0.976 for  $8 \times 10^4 < \text{Re}_d < 3 \times 10^5$ . The uncertainty in this coefficient will be taken as  $\pm 0.002$  since Fig. 7-10 is a general set of curves. With this selection of venturi size the maximum throat Reynolds number becomes

$$(\text{Re}_d)_{\text{max}} = (10^5) \left(\frac{1.62}{1.0}\right) = 1.62 \times 10^5$$

The minimum Reynolds number is thus half this value or  $8.1 \times 10^4$ . The maximum pressure differential may be calculated with Eq. (7-17).

$$Q_{\rm act} = CMA_2 \sqrt{\frac{2g_c}{\rho}} \sqrt{\Delta p} \tag{7-17}$$

$$\frac{(50)(231)}{(60)(1728)} = \frac{(0.976)\pi(1.0)^2}{(4)(144)\sqrt{1-(\frac{1}{4})^2}} \sqrt{\frac{(2)(32.2)}{62.4}} \sqrt{\Delta p}$$

This yields

$$\Delta p = 948 \text{ psf} = 6.58 \text{ psi}$$

Let us assume that a differential pressure gage is at our disposal having a maximum range of 1,000 psf. In accordance with the problem statement the uncertainty in the pressure residing would be

When the flow is reduced to 25 gpm, the pressure differential will be antfourth of that at 50 gpm. To estimate the uncertainty in the flow measurement we shall assume that the dimensions of the venturi are known exactly, as well as the density of the water. For the calculation we utilize Eq. (3-2). The quantities of interest are

$$\frac{\partial Q}{\partial C} = MA_1 \sqrt{\frac{2q_2}{\rho}} \sqrt{\Delta p}$$

$$\frac{\partial Q}{\partial \Delta n} = \frac{CMA_1}{2\sqrt{\Delta n}} \sqrt{\frac{2g_*}{g_*}}$$

Thus,

$$\frac{w_Q}{Q} = \left[ \left( \frac{w_s}{C} \right)^2 + \frac{1}{4} \left( \frac{w_{d,p}}{\Delta p} \right)^2 \right]^{\frac{1}{4}}$$

For Q = 50 gpm,

$$\frac{w_0}{Q} = \left[ \left( \frac{0.002}{0.976} \right)^3 + \frac{1}{4} \left( \frac{2.5}{948} \right)^3 \right]^4$$

$$= 0.002435 \quad \text{or } 0.2435\%$$

For Q = 25 gpm,

$$\frac{w_0}{Q} = \left[ \left( \frac{0.002}{0.976} \right)^3 + \frac{1}{4} \left( \frac{2.5}{984/4} \right)^3 \right]^3$$

$$= 0.00566 \quad \text{or } 0.566\%$$

## Example 7-3

An orifice with pressure taps one diameter upstream and one-half diameter downstream is installed in a 2.00-in.-diam pipe and used to measure the same flow of water as in Example 7-2. For this orifice,  $\beta=0.50$ . The differential pressure gage has an accuracy of 0.25 percent of full scale, and the upper scale limit is selected to correspond to the maximum flow rate. Determine the range of the pressure gage and the uncertainty in the flow-rate measurements at nominal flow rates of 50 and 25 gpm. Assume that the uncertainty in the flow coefficient is  $\pm 0.002$ .

Solution. We first calculate the pipe Reynolds numbers. Using the properties from Example 7-2,

$$\text{Re}_d = \frac{(2.5 \times 10^4)(4)}{\pi(2.9/12)(2.35)} = 8.09 \times 10^4$$
 at 50 gpm

$$Re_c = 4.05 \times 10^4$$
 at 25 gpm

From Fig. 7-13 the flow coefficient is estimated as

$$K = 0.625$$
 at 50 gpm

$$K = 0.630$$
 at 25 gpm

The volumetric flow is

$$Q = \frac{(59)(231)}{(60)(1728)} = 0.1115 \text{ ft}^2/\text{sec}$$
 at 50 gpm

$$Q = 0.0558 \, \text{ft}^2/\text{sec}$$
 at 25 gpm -

The nominal values of the differential pressure are then calculated from Eq. (7-18) as

$$0.1115 \approx (0.625) \frac{\pi(1)^2}{(4)(144)} \sqrt{\frac{(2)(32.2)}{(62.4)}} \sqrt{\Delta p}$$
 at 50 gpm

$$\Delta p = 1,037 \text{ psf} = 7.21 \text{ psi}$$
 at 50 gpm

$$\Delta p = 255 \text{ psf} = 1.77 \text{ psi}$$
 at 25 gpm

A suitable differential pressure gage might be one with a maximum range of 1,200 psf. The same equation for uncertainty applies in this problem as in Example 7-2 except that the flow coefficient K is used instead of the discharge coefficient. Thus,

$$\frac{w_0}{Q} = \left[ \left( \frac{w_E}{K} \right)^2 + \frac{1}{4} \left( \frac{w_{dP}}{\Delta p} \right)^2 \right]^4$$

with 
$$w_E = 0.092$$
 and  $w_{2p} = (0.0925)(1,200) = 3.0 \text{ psf}$ 

For Q = 50 gpm,

$$\frac{w_0}{Q} = \left[ \left( \frac{0.002}{0.625} \right)^2 + \frac{1}{4} \left( \frac{3.0}{1,037} \right)^2 \right]^4$$

$$= 0.00351 \quad \text{or } 0.351\%$$

For Q = 25 gpm.

$$\frac{w_q}{O} = \left[ \left( \frac{0.002}{0.630} \right)^2 + \frac{1}{4} \left( \frac{3.0}{255} \right)^2 \right]^{\frac{1}{2}} = 0.00669$$
 or  $0.669\%$ 

#### 7-5 THE SONIC NOZZI F

All the obstruction meters discussed above may be used with gases when the flow rate is sufficiently high, the pressure differential becomes quite large and eventually sonic flow conditions may be achieved at the minimum flow area. Under these conditions the flow is said to be "choked," and the flow rate takes on its minimum value for the given inlet conditions. For an ideal gas with constant specific heats it may be shown that the pressure ratio for this choked condition, assuming is sentione flow. is

$$\left(\frac{p_2}{p_1}\right)_{\text{tritical}} = \left(\frac{2}{\gamma + 1}\right)^{\gamma/(\gamma - 1)}$$
(7-23)

This ratio is called the critical pressure ratio Inserting this ratio in Eq. (7-8) gives for the mass flow rate

$$m = A_5 p_1 \sqrt{\frac{2g_s}{RT_1}} \left[ \frac{\gamma}{\gamma + 1} \left( \frac{2}{\gamma + 1} \right)^{2/(\gamma - 1)} \right]^{\frac{1}{2}}$$
 (7-24)

Equation (7-24) is frequently applied to a nozzle when it is known that the pressure ratio  $p_1/p_1$  is less than the critical value given by Eq. (7-23). Under these conditions the ideal flow is dependent only on the inlet stagnation conditions  $p_1$  and  $T_1$ . These conditions are usually easy to measure so that the sonic north-offers a convenient method for measuring gas flow rates. It may be noted, however, that a large pressure drop must be toferated with the method. Upstream stagnation conditions must be used for  $p_1$  t.  $T_1$  in the calculation

The ideal some-nozzle flow rate given by Eq. (7-24) must modified by an appropriate discharge coefficient which is a functi of the geometry of the nozzle and other factors. There may several complicating conditions, but discharge coefficients of about 0.97 are usually observed. A comprehensive survey of critical flow nozzles is presented by Arnberg [3], and the interested reader should consult this discussion for more information.

The flow obstruction devices discussed above require the use of wall pressure taps. (Other devices also require the use of such taps.) Measurements with wall pressure taps can be subject to several influencing factors, which are discussed in detail by Rayle [19]. In general, the diameter of the pressure tap should be small in comparison with the diameter of the pipe.

## Example 7-4

A sonic nozzle is to be used to measure a flow of air at 300 psia and 100°F in a 3-in.-diam pipe. The nominal flow rate is 1 lb_m/sec. Calculate the throat diameter (nozzle size) such that critical flow conditions are just obtained.

Solution. We use Eq. (7-24) for this calculation with  $\gamma = 1.4$  for air. The only unknown in this equation is  $A_2$ . Thus, we have

$$\begin{split} \dot{m} &= CA_2 p_1 \sqrt{\frac{2 g_c}{RT_1}} \left[ \frac{\gamma}{\gamma + 1} \left( \frac{2}{\gamma + 1} \right)^{2 l (\gamma - 1)} \right]^{\frac{1}{2}} \\ 1 &= A_2(300)(144) \sqrt{\frac{(2)(32.2)}{(53.35)(560)}} \left[ \frac{(1.4)}{(2.4)} \left( \frac{2}{2.4} \right)^{2 l^{0.4}} \right]^{\frac{1}{2}} \end{split}$$

and

$$A_2 = 0.001078 \text{ fc}^2 = 0.1551 \text{ in.}^2$$

The diameter at the throat is

$$d = \sqrt{\frac{4}{\pi}(0.1551)} = 0.444 \text{ in.}$$

For the above calculation we have taken the given pressure and temperature as stagnation properties. The temperature would most likely be measured with a stagnation probe so that 100°F is probably the stagnation temperature. The pressure would probably be measured by a static tap in the side of the pipe upstream from the nozzle so that a static-pressure measurement is most likely the one which will be available. If the upstream pipe diameter is large enough, the static pressure will be very nearly equal to the stagnation pressure and the error in the above calculation will be small.

33

Let us examine the above situation, assuming that the 300 psix is a staticpressure measurement. The mass flow upstream is

$$\dot{m} \approx \frac{p_{1s}}{RT_s} A_1 u_1$$
 (a)

where the subscript s denotes static properties. The velocity upstream may be written in terms of the stagnation temperature as

$$u_1 = \sqrt{2g_c c_s(T_{1_c} - T_{1_c})}$$
 (b)

Combining Eqs. (a) and (b), we have

$$\dot{m} = \frac{p_{1a}}{RT_a} A_1 \sqrt{2q_a \epsilon_p (T_{1a} - T_{1a})} \tag{c}$$

Taking  $p_{1s} = 300$  psia and  $\tau_{1s} = 100^{\circ}\text{F} = 560^{\circ}\text{R}$ , we may solve Eq. (c) for  $T_{1s}$ . The result is

$$T_1 \approx 500^{\circ}R$$
 (d)

or the upstream velocity is so small that the stagnstion properties are very nearly equal to the state properties. This result may be checked by calculating the upstream velocity from Eq. (a) using the result from Eq. (d) We obtain

The pressure difference  $(p_{ii} - p_{ij})$  corresponding to this velocity would be only 0.031 pris, while the temperature difference  $(T_{ii} - T_{ij})$  would be 0.017°F. Both of these values are negligible. It may be noted, honever, that if the upstream pipe diameter were considerably smaller, say 10 in diameter, it imply the necessary to correct for a difference between the measured static pressure and the stagnation pressure which must be used in Eq. (7.24).

#### 7-6 FLOW MEASUREMENT BY DRAG EFFECTS

The rotameter is a very commonly used flow-measurement device and is shown schematically in Fig. 7-18. The flow enters the bottom of the tapered vertical tube and causes the bob or "float" to move upward. The bob will rise to a point in the tabe such

# Experimental methods for engineers




Fig. 7-16. Schematic of a rotameter.

that the drag forces are just balanced by the weight and buoyancy forces. The position of the bob in the tube is then taken as an indication of the flow rate. The device is sometimes called an area meter because the elevation of the bob is dependent on the annular area between it and the tapered glass tube; however, the meter operates on the physical principle of drag so that we choose to classify it in this eategory. A force balance on the bob gives

$$F_a + \rho_f V_b = \rho_b V_b \tag{7-25}$$

where  $\rho_f$  and  $\rho_b$  are the densities of the fluid and bob,  $V_b$  is the total volume of the bob, and  $F_d$  is the drag force which is given by

$$F_{\rm d} = C_{\rm d}A_{\rm b} \frac{\rho_{\rm f} u_{\rm m}^2}{2g_{\rm c}} \tag{7-26}$$

 $C_d$  is a drag coefficient,  $A_b$  is the frontal area of the bob, and  $u_m$  is the mean flow velocity in the annular space between the bob and the tube. Combining Eqs. (7-25) and (7-26) gives

$$u_n = \frac{1}{C_d} \sqrt{\frac{2g_c V_b}{A_b} \left(\frac{\rho_b}{\rho_f} - 1\right)} \tag{7-27}$$

or

$$Q = \frac{A}{C_d} \sqrt{\frac{2g_c V_b}{A_b} \left(\frac{\rho_b}{\rho_f} - 1\right)}$$
 (7-28)

where A is the annular area and is given by

$$A = \frac{\pi}{4} [(D + ay)^3 - d^3]$$
 (7-29)

D is the diameter of the tube at inlet, d is the maximum bob diameter, y is the vertical distance from the entrance, and a is a constant indicating the tube taper.

The drag coefficient is dependent on the Reynolds number and hence on the fluid viscosity, however, special bobs may be used which have an essentially constant drag coefficient and thus offer the advantage that the meter reading will be essentially independent of viscosity. It may be noted that for many practical meters the quadratic size relation given by Eq. (7-29) becomes nearly linear for the actual dimensions of tube and bob which are used. Assuming such a linear relation, the quastion for mass flow would become

$$m = C_{10} \sqrt{(p_0 - p_1)p_1} \tag{7-30}$$

where C1 is now an appropriate meter constant

It is frequently advantageous to have a rotameter which gives an indication that is independent of fluid density, i.e., we wish to have

$$\frac{\partial m}{\partial a} = 0$$

Performing the indicated differentiation, we obtain

$$\rho_0 = 2\rho_t \tag{7-31}$$

and the mass flow is given by

$$m = \frac{C_1 y_{P_0}}{2} \tag{7-32}$$

Thus, by special bob construction the meter may be used to compensate for density changes in the fluid. The error in En. (7-32) is less than 0.2 percent for a fluid-density deviation of 5 percent from that given in Eq. (7-31). A photograph of a commercial rotameter is given in Fig. 7-17.

A popular type of flow-measurement device is the turbine meter shown in Fig 7-18 As the fluid moves through the meter, it causes a rotation of the small turbine wheel In the turbine



Fig. 7-17. Photograph of a commercial rotameter. (Courtesy Fischer and Porter Company.)

wheel body a permanent magnet is enclosed so that it rotates with the wheel. A reluctance pickup attached to the top of the meter detects a pulse for each revolution of the turbine wheel. Since the volumetric flow is proportional to the number of wheel revolutions, the total pulse output may be taken as an indication of total flow. The pulse rate is proportional to flow rate, and the transient response of the meter is very good. A flow coefficient K for the turbine meter is defined so that

$$Q = \frac{f}{K} \tag{7-33}$$

where f is the pulse frequency. The flow coefficient is dependent on flow rate and the kinematic viscosity of the fluid  $\nu$ . A calibration curve for a typical meter is given in Fig. 7-19. It may be seen that this particular meter will indicate the flow accurately within  $\pm 0.5$  percent over a rather wide range of flow rates.




Fig. 7-18. Turbine flowmeter. (1) Meter body; (2) Inter-straightening vanes; (3) turbine blades; (4) downstream afterbody to maintain smooth flow; (5) pipe or tube connector; (6) refuctance pickup. (Courtesy Fischer and Porter Company.)




Fig. 7-19. Calibration curve for a 1-in. turbine flowmeter of the type shown in Fig. 7-13. Calibration was performed with water.

# 7-7 HOT-WIRE ANEMOMETER

The hot-wire anemometer is a device which is most often used in research applications to study varying flow conditions. A fine wire is heated electrically and placed in the flow stream. The heat-transfer rate from the wire has been shown [5] to be

$$q = (a + b\sqrt{\rho n})(T_w - T_w) \quad \text{Btn/(hr)(ft^2)}$$
 (7-34)

where

 $T_{\rm w} =$  wire temperature

T_m = fluid temperature

u =fluid velocity

a, b = constants which are obtained by a calibration of the device

The heat-transfer rate must also be given by

$$q = i^{2}R_{w} = i^{2}R_{0}[1 + \alpha(T_{w} - T_{0})]$$
 (7-35)

where

i = electric current

 $R_0$  = resistance of the wire at the reference temperature  $T_0$ 

 $\alpha$  = temperature coefficient of resistance

For measurement purposes the hot wire is connected to a bridge circuit as shown in Fig. 7-20. The current is determined by measuring the voltage drop across the standard resistance  $R_{\rm to}$ and the wire resistance is determined from the bridge circuit. For steady-state measurements the nill condition may be used, while an oscillograph output may be used for transient measurements. With i and Rw determined the flow velocity may be calculated with Eqs. (7-34) and (7-35). Hot-wire probes have been used extensively for measurement of transient flows, especially measurements of turbulent fluctuations. Time constants of the order of 1 msec may be obtained with 0.0001-in,-diam platinum or tungsten wires operating in air. A modification of the hot-wire method consists of a small cylinder which is coated with a thin metallic film a few microns thick. This film then serves as the variable resistance and is extremely sensitive to fluctuations in the fluid velocity. Such hot-film probes have been used for measurements involving frequencies as high as 50,000 eps.




Fig. 7-20. Schematic of hot-wire flow-measurement about

The calibration of hot-wire probes is quite complicated, and the interested reader is referred to the discussion by Konarnay N for more information. It may be noted, however, that somplete commercial setups are available for hot-wire and hossidal measurements.

#### 7-8 MAGNETIC FLOW METERS

Consider the flow of a conducting fluid through a magnetic tell as shown in Fig 7-21. Since the fluid represent a southern



Fig. 7-31, them at a communities for an meth Rolls




Fig. 7-23. Basic optical effects used for flow visualization.

tions, and n is the index of refraction which for gases may be written as

$$n = 1 + \beta \frac{\rho}{\rho_s} \tag{7-38}$$

 $\beta$  is a dimensionless constant having a value of about 0.000292 for air.

According to Eq. (7-37) the angular deflection of the light ray  $\epsilon$  is proportional to the density gradient in the flow. This is the basic optical effect which is used for flow-visualization work. It may be noted that the deflection of the light ray is a measure of the average density gradient integrated over the x coordinate. Thus, the effect is primarily useful for indicating density variations in two dimensions (in this case the y and z dimensions) and will average the variations in the third dimension.

In the following sections we shall discuss several optical methods of flow visualization for use in gas systems. For liquid flow visualization a typical experimental technique is to add a dye to the liquid in order to study the flow phenomena. Another technique which has received considerable attention for use with liquids is the so-called hydrogen-bubble method. The technique consists of using a fine wire, placed in water, as one end of a d-c circuit to electrolyze the water. Very small hydrogen bubbles are generated in the liquid. The motion of the bubbles may be studied by illuminating the flow. The application of this method has been given a very complete description by Schraub, Kline et al. [16].

# 7-10 THE SHADOWGRAPH

The shadoy technique is a method for direct viewing of flow phenomena. Imagine the flow field as shown in Fig. 7-24 with a




Fig. 7-24. Shedowgraph flow-visualization & vice.




Fig. 7-25. Direct shadowgram of flight of a ,220 caliber Remington "Swift" shell. Velocity - 4,100 tt/secfree-streem pressure is etmospheric. Exposure time. was 0.33 see. Note cleer definition of shock were and turbulent weke.

density gradient in the y direction. The parallel light rays enter the test section as shown. In the regions where there is no density gradient, the light rays will pass straight through the test section with no deflection. For the regions where a gradient exists the rays will be deflected. The net effect is that the rays will bunch together after leaving the test section to form bright spots and dark spots. The illumination will depend on the relative deflection of the light rays  $d\epsilon/dy$  and hence on  $d^2p/dy^2$ . The illumination on a screen placed outside the test section is thus dependent on the second derivative of the density at the particular point.

The shadowgraph is a very simple optical tool, and its effects may be viewed in several everyday phenomena using only the naked eye and local room lighting. The free-convection boundary layer on a horizontal electric hot plate is clearly visible when viewed from the edge. This phenomenon is visible because of the density gradients which result from the heating of the air near the hot surface. It is almost fruitless to try to evaluate local densities using shadow photography; however, the shadowgraph is exceedingly useful to view turbulent flow regions, and the method can be used to establish the location of shock waves with high precision. Figure 7-25 illustrates shock-wave and turbulent-flow phenomena as viewed with a shadowgraph.

# 7-11 THE SCHLIEREN

While the shadowgraph gives an indication of the second derivative of density in the flow field, the schlieren is a device which indicates the density gradient. Consider the schematic diagram shown in Fig. 7-26. Light from a slit source ab is collimated by the lens  $L_1$ and focused at plane I in the test section. After passing through lens L2 there is produced an inverted image of the source at the focal plane 2. Lens  $L_2$  then focuses the image of the test section on the screen at plane 3. Now let us consider the imaging process in more detail. The peneils of light originating at point a occupy a different portion of the various lenses than those originating from point b or any other point in the slit source. The regions in which these peneils overlap are shown in Fig. 7-26. Note that all peneils of light pass through the image plane cd in the test section and the source image plane b'a'. An image of the test section at d'c' is then uniformly illuminated since the image at b'a' is uniformly illuminated. This means that all points in the plane b'a' are affected in the same manner by whatever fluid effects may take place in the test section.




Fig. 7-26. (a) Schematic of Schileren flow visualization; (b) detail of knife edge,

If the test section is completely uniform in density, the pencils of light appear as shown in Fig. 7-26, a pencil originating at point c is deflected by the same amount as a pencil originating at point d. This is consistent with the observation that all pencils originating in plane dc completely fill the image plane b'c'. Now consider the effect of the introduction of an obstruction at plane b'c' under these circumstances. We immediately conclude that such an obstruction would uniformly decrease the illumination on the screen by a factor proportional to the amount of the area b'c' intercepted.

Suppose now that a density gradient exists at the test section focal plane cd. This means that all pencils of light originating in this plane would no longer fill the image plane b'a' completely If, now, an obstruction is placed at plane b'a', it will intercept more light from some points in the test section plane than from others, resulting in light and dark regions on the screen at plane 3. The obstruction is called a knife edge, and the resultant variation in illumination on the screen is called the Schheren effect.

Let us examine the variation in illumination in more detail. In Fig 7-265 the total height of the source image is y and the portion not intercepted by the knife edge is y₁. Thus, the general illumination on the screen 1 is proportional to y₁. An angular displacement of a pencil of light in plane 1 is 4. This produces a vertical deflection

density gradient in the y direction. The parallel light rays enter the test section as shown. In the regions where there is no density gradient, the light rays will pass straight through the test section with no deflection. For the regions where a gradient exists the rays will be deflected. The net effect is that the rays will bunch together after leaving the test section to form bright spots and dark spots. The illumination will depend on the relative deflection of the light rays  $d\epsilon/dy$  and hence on  $d^2\rho/dy^2$ . The illumination on a screen placed outside the test section is thus dependent on the second derivative of the density at the particular point.

The shadowgraph is a very simple optical tool, and its effects may be viewed in several everyday phenomena using only the naked eye and local room lighting. The free-convection boundary layer on a horizontal electric hot plate is clearly visible when viewed from the edge. This phenomenon is visible because of the density gradients which result from the heating of the air near the hot surface. It is almost fruitless to try to evaluate local densities using shadow photography; however, the shadowgraph is exceedingly useful to view turbulent flow regions, and the method can be used to establish the location of shock waves with high precision. Figure 7-25 illustrates shock-wave and turbulent-flow phenomena as viewed with a shadowgraph.

# 7-11 THE SCHLIEREN

While the shadowgraph gives an indication of the second derivative of density in the flow field, the schlieren is a device which indicates the density gradient. Consider the schematic diagram shown in Fig. 7-26. Light from a slit source ab is collimated by the lens  $L_1$ and focused at plane 1 in the test section. After passing through lens L2 there is produced an inverted image of the source at the focal plane 2. Lens L3 then focuses the image of the test section on the screen at plane 3. Now let us consider the imaging process in more detail. The pencils of light originating at point a occupy a different portion of the various lenses than those originating from point b or any other point in the slit source. The regions in which these pencils overlap are shown in Fig. 7-26. Note that all pencils of light pass through the image plane cd in the test section and the source image plane b'a'. An image of the test section at d'c' is then uniformly illuminated since the image at b'a' is uniformly illuminated. This means that all points in the plane b'a' are affected in the same manner by whatever fluid effects may take place in the test section.




Fig. 7-26. (a) Schematic of Schileren flow visualization; (b) detail of knife edge.

If the test section is completely uniform in density, the pencils of light appear as shown in Fig 7-20; a pencil originating at point c is deflected by the same amount as a pencil originating at point d. This is consistent with the observation that all pencils originating in plane completely fill the image plane b'a'. Now consider the effect of the introduction of an obstruction at plane b'a' under these circumstances. We immediately conclude that such an obstruction would uniformly decrease the illumination on the screen by a factor proportional to the amount of the area b'a' intercented.

Suppose now that a density gradient exist at the test section focal plane cd. This means that all pencils of light originating in this plane would no longer fill the image plane b'a' completely II, now, an obstruction is placed at plane b'a', it will intercept more light from some points in the test section plane than from others, resulting in light and dark regions on the screen at plane 3. The obstruction is called a knife edge, and the resultant variation in illumination on the screen is called the Schheren effect.

Let us examine the variation in illumination in more detail. In Fig. 7-26b the total height of the source image is y and the portion not intercepted by the knife edge is y. Thus, the general illumination on the screen I is proportional to y. An angular displacement of a penil of light in plant is . This produces a vertical deflection

# Experimental methods for engineers

at plane 2 of

$$\Delta v = f_2 \epsilon \tag{7-39}$$

where  $f_2$  is the focal length of lens  $L_2$ . As a result of this deflection, there is a fractional change in illumination on the screen. The contrast at any point on the screen may be defined as the ratio of the fractional change in illumination to the general illumination or

$$C = \frac{\Delta I}{I} = \frac{\Delta y}{y_1} = \frac{f_2 \epsilon}{y_1} \tag{7-40}$$

The angular deflection is given by Eq. (7-37) so that the expression for contrast may be written

$$C = \frac{f_2 L \beta}{y_1 \rho_s} \left( \frac{d\rho}{dy} \right)_{cd} \tag{7-41}$$

Thus, the contrast on the screen is directly proportional to the density gradient in the flow. It may be observed that the contrast may be increased by reducing the distance  $y_1$ , that is, by intercepting more light at the source image plane. This also reduces the general illumination so that the contrast may not be increased indefinitely and a compromise must be accepted. Schlieren photographs are used extensively for location of shock waves and complicated boundary-layer phenomena in supersonic flow systems. Some typical Schlieren photographs are shown in Figs. 7-27 and 7-28.




Fig. 7-27. Schlieren photograph of 1.75-in.-diam blunt cone and wake after separation of rear portion. Velocity = 5,878 ft/sec; free-stream pressure = 94 mm Hg; cone angle = 18°. (Courtesy ARO, Inc., Arnold Air Force Base, Tennessee.)




Fig. 7.23. Schilleren photograph of flow-separation phenomena. Plate Jength = 5 in.; flap angle = 30°, Note clear definition of shock wave and tha Jurbulent flow region at the intersection of the flap and horizontal plate. (Courtesy ARO, Inc., Aenold Air Force Base, Tennessee.)

#### 7-12 THE INTERFEROMETER

The Mach-Zehnder interferometer is the most precise instrument for flow visualization Consider the schematic representation in Fig. 7.29. The light source is collimated through lens Li onto the splitter plate Si. This plate permits half of the light to be transmitted to mirror M; while reflecting the other half toward mirror M. Beam 1 passes through the test section while beam 2 travels an alternate path of approximately equal length. The two beams are brought together again by means of the splitter plate S, and eventually focused on the screen Now, if the two beams travel paths of different optical lengths, either because of the geometry of the system or because of the refractive properties of any element of the optical paths, the two beams will be out of phase and will interfere when they are joined together at Sz. There will be alternate bright and dark regions called fringes. The number of fringes will be a function of the difference in optical path lengths for the two beams. for a difference in path lengths of one wavelength there will be one lunge, two franges for a difference of two wavelengths, and so on The interferometer is used to obtain a direct measurement of density variations in the test section. If the density in the test sec-

The interferometer is used to obtain a direct measurement of density variations in the test section. If the density in the test secuon (i.e., beam 1) is different from that in beam 2, there will be a change in the refractive properties of the fluid medium. If the

# perimental methods for engineers




Fig. 7-23. Schematic of Mach-Zehnder interferometer.




Fig. 7-30. Interferometer photograph of a freetion boundary layer on a vertical fi Fluid is zir. Ezch fringe line represen of constant density or a line of const perature. (Photograph courtesy E. S.




Fig. 7-31. Interferometer photograph of the Interaction of freconvection boundary layers on three horizontal heated cylinders. Full dis self, and each fringe line represents a line of constant temperatures. (Photograph courtesy E. Sochusch.)

medium in the test section has the same optical properties as the medium in beam 2, there will be no fringe shifts except those resulting from the geometric arrangement of the apparatus. These fringe shifts may be neutralized by appropriate movements of the intrors and splitter plates. Then, the appearance of fringes on the screen may be directly related to changes in density in the flow field within the test section utilizing the following analysis.

The change in optical path in the test section resulting from a change in refractive index is

$$\Delta L = L(n - n_0) \tag{7-42}$$

where L is the thickness of the flow field in the test section Using Eq. (7-38), the change in optical path may be related to change in density for gases by

$$\Delta L = \beta L \frac{\rho - \rho_0}{\rho_0} \tag{7-43}$$

The number of fringe shifts N is then given by

$$N = \frac{\Delta L}{\lambda} = \frac{\beta L}{\lambda} \frac{\rho - \rho_0}{\rho_0}$$
 (7-44)

where  $\lambda$  is the wavelength of the light. In Eq. (7-44) it is to be noted that  $\rho - \rho_0$  represents the change in density from the zero-fringe condition.

The interferometer gives a direct quantitative indication of density changes in the test section, but these changes are represented as integrated values over the entire thickness of the flow field. It is applicable to a wide range of flow conditions ranging from the low-speed (~1 ft/sec) flow in free-convection boundary layers to shock-wave phenomena in supersonic flow. Figures 7-30 and 7-31 show some typical interferometer photographs. The captions explain the flow phenomena.

## Example 7-5

An interferometer is used for visualization of a free-convection boundary layer in air similar to the one shown in Fig. 7-20. For this application the following data were collected:

Plate temperature  $T_w = 120^{\circ}\text{F}$ Free-stream air temperature  $T_w = 70^{\circ}\text{F}$  $\beta = 0.000293$ Depth of test section L = 18 in. Wavelength of light source  $\lambda = 5460$  A Reference density at  $70^{\circ}\text{F}$ Pressure = 14.7 peia

Calculate the number of fringes which will be viewed in the boundary layer.

Solution. We use Eq. (7-14) for this calculation. The reference density is the same as the zero-fringe density so that

$$N = \frac{\beta L}{\lambda} \left( \frac{\rho_w}{\rho_n} - 1 \right)$$

For air the density is calculated from the ideal gas equation of state.


$$\rho = \frac{p}{RT}$$

Thus,

$$N = \frac{\beta L}{\lambda} \left( \frac{T_{\bullet}}{T_{\bullet}} - 1 \right)$$

$$= \frac{(0.000293)(18.0)(2.54)}{(5460 \times 10^{-4})} \left( \frac{530}{580} - 1 \right)$$

$$= 21.15 \text{ fringes}$$






Fig. 7-32. (a) Smoka photograph showing secondary flow effects resulting from a standing sound wave in a tube; (b) flow streamlines for the system in (a) as obtained from the theoretical analysis of Ref. (12). (Photograph courtesy Dr. T. W. Jeckson.)

#### 7-13 SMOKE METHODS

A very simple flow-visualization method utilizes the injection of smoke traces in a gas stream to follow the flow streamlines. The method is primarily of qualitative utility in that direct measurements are difficult to obtain except for certain special phenomena. Figure 7-32 shows an example of a flow system where smoke visualization was used to verify an analytical calculation. In this case, smoke is used to view the complicated secondary flow patterns in a channel through which a forced flow is coupled with a standing sound wave. The smoke patterns in (a) agree well with the analytical predictions in (b).

In order for the smoke filaments to represent streamlines of the flow it is necessary that the individual smoke particles be of sufficiently small mass so that they are carried along freely at the flow velocity. Filtered smoke from burning rotten wood or cigars is

## Experimental methods for engineers

generally suitable for smoke studies as well as smoke from the chemical titanium tetrachloride when it reacts with moisture in air to form hydrochloric acid and titanium oxide. This latter substance, however, is corrosive to many materials used for the construction of containers. Reference [14] discusses the use of titanium tetrachloride for low-speed flow measurements.

### 7-14 PRESSURE PROBES

A majority of fluid dynamic applications involve a measurement of total flow rate by one or more methods discussed in the previous sections. These measurements ignore the local variation of velocity and pressure in the flow channel and permit an indication of only the total flow through a particular cross section. In applications involving external flow situations such as aircraft or wind-tunnel tests an entirely different type of measurement is required. In these instances probes must be inserted in the flow to measure the local static and stagnation pressures. From these measurements the local flow velocity may be calculated. Several probes are available for such measurements, and summaries of the characteristic behavior are given in Refs. [4], [7], [13], and [18]. We shall discuss some of the basic probe types in this section. The total pressure for isentropic stagnation of an ideal gas is given by

$$\frac{p_0}{p_{\infty}} = \left(1 + \frac{\gamma - 1}{2} M_{\infty}^2\right)^{\gamma/(\gamma - 1)} \tag{7-45}$$

where  $p_0$  is the stagnation pressure,  $p_\infty$  is the free-stream static pressure, and  $M_\infty$  is the free-stream Mach number given by

$$M_{\infty} = \frac{u_{\infty}}{a} \tag{7-46}$$

a is the acoustic velocity and may be calculated with

$$a = \sqrt{\gamma g_c RT} \tag{7-47}$$

for an ideal gas. It is convenient to express Eq. (7-45) in terms of the dynamic pressure g defined by

$$q = \frac{1}{2}\rho u_{m}^{2} = \frac{1}{2}\gamma p M_{m}^{2} \tag{7-48}$$

Equation (7-45) thus becomes

$$p_o - p_\sigma = \frac{2q}{\gamma M_\sigma!} \left[ \left( 1 + \frac{\gamma - 1}{2} M_\sigma! \right)^{\gamma/(\gamma - 1)} - 1 \right]$$
 (7-i9)

This relation may be simplified to

$$p_0 - p_w = \frac{2q}{\gamma M_w^2} \left( 1 + \frac{M_w^4}{4} + \frac{2 - \gamma}{24} M_w^4 + \right)$$
 (7-59)

when 
$$M_{\infty}^{1}\left(\frac{\gamma-1}{2}\right) < 1$$
.

For very small Mach numbers Eq. (7-50) reduces to the familiar incompressible flow formula

$$p_1 - p_n = \frac{1}{2}\rho u_n^2 \tag{7.51}$$

We thus observe that a measurement of the static and stagnation pressures permits a determination of the flow velocity, by either Eq. (7-51) or Eq. (7-49), depending on the fluid medium

A basic total pressure probe may be constructed in several different ways, as shown in Fig. 7-33. In each instance the opening in the probe is oriented in a direction exactly parallel to the flow when a measurement of the total stream pressure is desired. If the probe is




Fig. 7-33. Stagnation pressure response of various probes to changes in yaw angle. (a) Open-ended tube; (b) channel tube; (c) chamfered tube; (d) tube with orlice inside. From Ref. [7].

# Experimental methods for engineers




Fig. 7-34. Kiel probe (Model 3696) for measurement of stagnation pressure. (Courtesy Airilo Instrument Co., Glastonbury, Conn.)

inclined at an angle  $\theta$  to the free-stream velocity, a somewhat lower pressure will be observed. This reduction in pressure is indicated in Fig. 7-33 according to Ref. [7]. Configuration (a) represents an open-ended tube placed in the flow. Configuration (b) is called a shielded probe and consists of a venturi-shaped tube placed in the flow with an open-ended tube at the throat of the section to sense the stagnation pressure. It may be noted that this probe is rather insensitive to flow direction Configuration (c) represents an openended tube with a chamfered opening. The chamfer is about 15° and the ratio of OD to ID of the tube is about 5. Configuration (d) represents a tube having a small hole drilled in its side which is placed normal to the flow direction. This type of probe, as might be expected is the most sensitive to changes in yaw angle. Also indicated in Fig. 7-33 is a portion of the curve for a Kiel probe which is similar in construction to configuration (b) except that a smoother venturi shape, as shown in Fig. 7-34, is used. The Kiel probe is the least sensitive to yaw angle.

The measurement of static pressure in a flow stream is considerably more difficult than the measurement of stagnation pressure. A typical probe used for the measurement of both static and stagnation pressures is the *pitot tube* shown in Fig. 7-35. The opening in the front of the probe senses the stagnation pressure, while the small holes around the outer periphery of the tube sense the static pressure. The static pressure measurement with such a device is strongly dependent on the distance of the peripheral openings from the front opening as well as the yaw angle. Figure 7-36 indicates




Fig. 7-35. Schematic drawing of a pitot tube.




Fig. 7-36. Variation of static pressure along standard subsonic and supersonic probe types. From Ref. |6L




Fig. 7-37. Variation of static, stagnation, and dynamic pressures with yaw angle for a pitot tube. (Courtery Airlia Instrument Co., Glastonbury, Conn.)

...




Fig. 7-38. Yaw-angle climacteristics of various static-pressure probes. From Ref. [7].




Fig. 7-39. Mach-number characteristics of various static-pressure probes. From Ref. [7].

the dependence of the static pressure indication on the distance from the leading edge of the probe for both bluint subronic and conical supersonic configurations. To alleviate this condition, the static pressure holes are normally placed at least eight diameters downstream from the front of the probe. The dependence of the static and stagnation pressures on yaw angle for a conventional pitot tube is indicated in Fig. 7-37. This device is quite sensitive to flow direction.

The static pressure characteristics of three types of probes are shown in Fig. 7-38 and 7-39 as functions of Mach number and yaw angle. It may be noted that both the wedge and the Prandil tube indicate static pressure values that are too low, while the cone undicates a value that is too high. The wedge is least sensitive to yaw angle. All three probes have two static pressure boles located 180° apart.

#### Example 7-6

A pitot tube is inserted in a flowstream of air at 100°F and 147 pua. The dynamic pressure is measured as 1 12 in water when the tube is onented parallel to the flow. Calculate the flow velocity at that point

Solution We use Eq. (7-51) for this calculation. The air density is calculated as

$$p = \frac{p_d}{RT_n} = \frac{(14.7)(144)}{(53.35)(560)} = 0.071 \text{ lb}_n/\text{ft}^s$$

We also have

$$p_0 - p_m = 1.12 \text{ in water} = 5.82 \text{ psf}$$

so that the velocity is

$$u_n = \sqrt{\frac{2(p_0 - p_n)}{\rho}} = \sqrt{\frac{(2)(32.2)(5.82)}{(0.071)}}$$
  
= 72.6 ft/sec

#### 7-15 IMPACT PRESSURE IN SUPERSONIC FLOW

Consider the impact probe shown in Fig 7-40 which is exposed to a free stream with supersone flow that is. M. > 1 A shock wave will




Fig. 7-38. Yaw-angle characteristics of various static-pressure probes. From Ref. [7].




Fig. 7-39. Mach-number characteristics of various static-pressure probes. From Ref. [7].

the dependence of the static pressure indication on the distance from the leading edge of the probe for both blunt subsonic and conical supersonic configuration. To alleviate this condition, the static pressure holes are normally placed at least eight diameters downstream from the front of the probe. The dependence of the static and stagnation pressures on yaw angle for a conventional pitot tube is indicated in Fig. 7-37. This device is quite sensitive to flow direction.

The static pressure characteristics of three types of probes are shown in Figs 7-38 and 7-39 as functions of Mach number and yaw angle. It may be noted that both the wedge and the Prandil tube indicate static pressure values that are too low, while the cone undicates a value that is too high. The wedge is least sensitive to yaw angle. All three probes have two static pressure holes located 180° anart.

#### Example 7-6

A pitot tube is inserted in a flowstream of air at 100°F and 14.7 peix. The dynamic pressure is measured as 1.12 in, water when the tube is oriented parallel to the flow. Calculate the flow velocity at that point

Solution We use Eq (7-51) for this calculation. The air density is calculated as

$$\rho = \frac{p_*}{RT_*} = \frac{(14.7)(144)}{(53.35)(560)} = 0.071 \text{ lb}_*/\text{ft}^*$$

We also have

so that the velocity is

$$u_{-} = \sqrt{\frac{2(p_{4} - p_{-})}{\rho}} = \sqrt{\frac{(2)(322)(582)}{(0071)}}$$
  
= 72 6 ft/sec

#### 7-15 IMPACT PRESSURE IN SUPERSONIC FLOW

Consider the impact probe shown in Fig. 7-40 which is exposed to a free stream with supersonic flow, that is,  $M_1 > 1$  A shock wave will

# Experimental methods for engineers




Fig. 7-40. Impact tube in supersonic flow.

be formed in front of the probe as shown, and the total pressure measured by the probe will not be the free-stream total pressure before the shock wave. It is possible, however, to express the impact pressure at the probe in terms of the free-stream static pressure and the free-stream Mach number. The resulting expression as given in Ref. [10] is

$$\frac{p_{\infty}}{p_{0_1}} = \frac{\{[2\gamma/(\gamma+1)]M_1^2 - (\gamma-1)/(\gamma+1)\}^{1/(\gamma-1)}}{\{[(\gamma+1)/2]M_1^2\}^{\gamma/(\gamma-1)}}$$
 (7-52)

where  $p_{\pi}$  is the free-stream static pressure and  $p_0$ , is the measured impact pressure behind the normal shock wave. This equation is valid for Reynolds numbers based on probe diameter greater than 400. Equation (7-52) is called the Rayleigh supersonic pitot formula. We see that in order to determine the value of the Mach number it is necessary to have a measurement of the free-stream static pressure. It is possible to make this measurement with special calibrated probes.

### 7-16 SUMMARY

Comparisons of the operating range, characteristics, and advantages of several flowmeters have been presented by Miesse and Curth [11]. These comparisons are presented in Table 7-1 and may be taken as an appropriate summary of our discussions in this chapter. The reader should bear in mind that the stated accuracies for the various flowmeters may be improved with suitable calibration. Of course, the overall accuracy of a flow-rate determination is also dependent on the accuracy of the readout equipment. As an example, a venturi might be carefully calibrated within 0.5 percent, but if it were used with a crude instrument for differential pressure measurements, a much poorer precision would result than that for which it was calibrated.

Table 7-1

00 eret

## PROBLEMS

- 7-1 Using Eq. (7-8) as a starting point, obtain Eqs. (7-9) and (7-10). Subsequently, calculate the error in these equations when  $\Delta p = p_1/4$  for Eq. (7-9) and  $\Delta p = p_1/10$  for Eq. (7-10).
- 7-2 In the compressible flow equation for a venturi the velocity of approach factor M cancels with a like term in the expansion factor  $Y_a$ . Construct a graphical plot which will indicate the error which would result if the approach factor given by Eq. (7-11) were used in conjunction with Eq. (7-8). Use the parameter  $\Delta p/\gamma p_1$  as the abscissa for this plot.
- 7-3 A venturi is to be used for measuring the flow of air at 300 psin and 80°F. The maximum flow rate is 1.0 lb_m/sec. The minimum flow rate is 30 percent of this value. Determine the size of the venturi such that the throat Reynolds number is not less than 10°. Calculate the differential pressure across the venturi for mass flows of 0.3, 0.5, 0.7, and 1.0 lb_m/sec. Assume β = 0.5 for the venturi.
- 7-4 Work Prob. 7-3 for an orifice with pressure taps one diameter upstream and one-half diameter downstream.
- 7-5 Work Prob. 7-3 for an ASME long-radius flaw nozzle.
- 7-6 A sonic nozzle is to be used to measure a gas flow with an uncertainty of 1 percent. Assuming that the nozzle throat area and discharge coefficients are known exactly, derive an expression for the required relationship between the uncertainties in the stagnation pressure and temperature measurements. Which of the two measurements, pressure or temperature, is more likely to be the controlling factor?
- 7-7 Calculate the throat area for the sonic nozzle in Example 7-4 if the stated pressure is static pressure upstream, the temperature is total temperature upstream, and the pipe diameter is 1.0 in.
- 7-8 Show that the parameter which governs the use of a linear relation for a rotaneter as in Eq. (7-30) is

 $\widetilde{D}$ 

provided that d es D to the extent that

$$1 - \left(\frac{d}{D}\right)^{\sharp} \ll \frac{ay}{D}$$

Under these restrictions plot the error resulting from the linear approximation as a function of the parameter ay/D. Discuss the physical eignificance of this analysis, and interpet its meaning in terms of specific design recommendations for rotameters.

- 7.9 Verify that the error in flow rate for a rotameter calculated from Eq. (7-32) is less than 0.2 percent for density variations of ±5 percent when the float density is designated according to Eq. (7-31).
- 7-10 The turbine flowmeter whose calibration is shown in Fig. 7-19 is to measure a nominal flow rate of water of 25 gpm at 60°F. A single value of the meter constant K is to be used in the data reduction. What deviations from the nominal flow rate are allowable in order that the nominal value of K is accurate within ±0.25 percent.
- 7-11 A retameter is to be designed to measure a maximum flow of 10 gpm of water at 70°F. The bob is 1 in. in diameter and has a total volume of 1 in. * The bob is constructed so that the density is given in accordance with Eq. (7-31). The total length of the rotameter tube is 13 in., and the diameter of the tube at inlet is 1.0 in Determine the tube taper for drag coefficients of 0.4, 0.8, and 1.20. Plot the flow rate versus distances from the entrance of the tube for each of these drag coefficients. Determine the meter constant for use in Eq. (7-32), and estimate the error resulting from the use of this relation instead of the exact expression in Eq. (7-28).
- 7-12 A rotameter is to be used for measurement of the flow of air at 100 psia and 70°F. The maximum flow rate is 00 3lo/sec, the inlet diameter of the meter is 1 in, and the length of the meter is 12 in. The bob is constructed so that its density is five times that of the air, and its volume is 1 in. Calculate the tube taper for drag coefficients of 0 4, 0 8, and 1.2, and determine the meter constant for ure in Eq. (7-30). Plot the error resulting from the use of Eq (7-30) as a function of flow rate.
- 7-13 Derive an expression for the product of density and velocity across a hot-wire anemometer in terms of the wire resistance, the current through the wire, and the empirical constants a and b. Subsequently obtain an expression for the uncertainty in this product as a function of the measured quantities.
- in this product as a function of the measured quantities.

  7-14 The sensitivity of a schieren system is defined as the fractional deflection obtained at the knife edge per unit angular deflection of a light ray at the test section. Show that this

## Experimental methods for engineers

sensitivity may be calculated with

$$S = \frac{f_2}{y_1}$$

Derive an expression for the contrast in terms of the sensitivity, the density gradient, and the test section width.

7-15 Show that the sensitivity of an interferometer, defined as the number of fringe shifts per unit change of density, may be written as

$$S = \frac{\beta L}{\lambda \rho_*}$$

Show that the maximum sensitivity of an interferometer defined as the number of fringe shifts per unit change in Mach number will be about 30 when L=6 in.,  $\lambda=5400$  A,  $\beta=0.000293$ , and the stagnation density is that of air at standard conditions.

- 7-16 Calculate the temperatures corresponding to the four fringes nearest to the plate surface in Example 7-5.
- 7-17 The velocity in turbulent tube flow varies approximately as

$$\frac{u}{u_c} = \left(1 - \frac{r}{r_0}\right)^{\frac{1}{2}}$$

where  $u_c$  is the velocity at the center of the tube and  $r_0$  is the tube radius. An experimental setup using air in a 1-ft-diam tube is used to check this relation. The air temperature is 70°F, and pressure is 15 psia. The maximum flow velocity is 50 ft/sec, and a pitot tube is used to traverse the flow and obtain a measurement of the velocity distribution. Measurements are taken at radii of 0, 2, 4, and 5 in., and the uncertainty in the dynamic-pressure measurement is  $\pm 0.02$  in. water. Using the above relation and Eq. (7-51), calculate the nominal velocity and dynamic pressure at each radial location. Then calculate the uncertainty in the velocity measurement at each location based on the uncertainty in the pressure measurement. Assuming that the above relation does represent the true velocity profile, calculate the uncertainty which could result in a mass flow determined from the experimental data. The mass flow would be obtained by performing the integration

$$\dot{m} = \int_0^{r_0} 2\pi r \rho u \, dr$$

- 7.18 Calculate the dynamic pressure measured by a pitot tube in a flow stream of water at 70°F moving at a velocity of 10 ft/sec
- 7.19 Using the supersonic pitot-tube formula given by Eq. (7-52), obtain an expression for the uncertainty in the Mach number as a function of the percent uncertainty in the pressure ratio (p_e/p₀) and the nominal value of the Mach number. Plot the percent uncertainty in the Mach number as a function of Mach number for a constant uncertainty in (p_e/p₀) of I necent. Assume v_e = 1.4
- 7-20 A venturi with throat and upstream diameters of 8 and 16 in is used to measure the flow of water at 70°F. The flow rate is controlled by a motorated valve downstream from the centuri. The valve is operated so that a constant differential pressure of 12 in Hig is mainfained across the venturi. Suppose someone informs you that this type of control scheme is not very effective because it does not account for possible changes in temperature of the water. Reply to this criticism by plotting the error in the flow rate? The properties of the water temperature, taking the flow at 70°F as the reference value.
- 7-21 An obstruction meter is used for the measurement of the flow of moist air at low velocities Suppose that the flow rate is calculated taking the density as that of dry air at 90°F Plot the error in this flow rate as a function of relative humidate.

#### REFERENCES

- "Fluid Meters, Their Theory and Application," 5th ed., ASME, New York, 1959.
- 2. "Flowmeter Computation Handbook," ASME, New York, 1961.
- Arnberg, B. T.: Review of Critical Flowmeters for Gas Flow Measurements, Trans. ASME, vol. 84D, p. 447, 1962
- Gracey, W.: Measurement of Static Pressure on Aircraft, NACA Tech Note 4184, November, 1957.
- 5, King, L.
  Stream (
  Trans. R.
- Kovasanay, L. S. G.: Hot-wire Method, in "Physical Measurements in Gas Dynamics and Combustion," p. 219, Princeton University Press, Princeton, N.J., 1954.
- Krause, L. N., and C. C. Gettelman: Considerations Entering into the Selection of Probes for Pressure Measurement in Jet Engines, ISA Proc., vol. 7, p. 134, 1952

### Experimental methods for engineers

- Ladenburg, R. W. (ed.): "Physical Measurements in Gas Dynamics and Combustion," Princeton University Press, Princeton, N.J., 1954.
- Laurence, J. C., and L. G. Landes: Application of the Constant Temperature Hot-wire Anemometer to the Study of Transient Air Flow Phenomena, J. Instr. Soc. Am., vol. 1, no. 12, p. 128, 1959.
- Liepmann, H. W., and A. Roshko: "Elements of Gas Dynamics," John Wiley & Sons, Inc., New York, 1957.
- Miesse, C. C., and O. E. Curth: How to Scient a Flowmeter, Prod. Eng., p. 35, May 8, 1961.
- Purdy, K. R., T. W. Jackson, and C. W. Gorton: Viscous Fluid Flow under the Influence of a Resonant Acoustic Field, J. Heat Transfer, vol. 86C, p. 97, February, 1964.
- Schulze, W. M., G. C. Ashby, Jr., and J. R. Erwin: Several Combination Probes for Surveying Static and Total Pressure and Flow Direction, NACA Tech. Note 2830, November, 1952.
- Smith, E., R. H. Reed, and H. D. Hodges: The Measurement of Low Air Speeds by the Use of Titanium Tetraehloride, Texas Eng. Exp. Sta. Research Rpt. 25, May, 1951.
- Tuve, G. L.: "Mechanical Engineering Experimentation," McGraw-Hill Book Company, New York, 1961.
- Schraub, F. A., S. J. Kline, et al.: Use of Hydrogen Bubbles for Quantitative Determination of Time-dependent Velocity Fields in Low Speed Water Flows, ASME Paper no. 64-WA/FE-20, December, 1964.
- 17. "Flow Visualization Symposium," ASME, New York, 1960.
- 18. Dean, R. C. (ed.): "Aerodynamie Measurements," Eagle Press, 1953.
- Rayle, R. E.: An Investigation of the Influence of Orifice Geometry on Static Pressure Measurements, S.M. thesis, Dept. Mech. Eng., Massachusetts Institute of Technology, 1949. (See also Ref. 18.)

## The measurement of temperature

#### 8-1 INTRODUCTION

To most people, temperature is an intuitive concept which tells whether a body is "hot" or "cold" In the exposition of the second principle of thermodynamics, temperature is related to heat, for it 19 known that heat flows only from a high temperature to a low temperature, in the absence of other effects. In the kinetic theory of gases and statistical thermodynamics it is shown that temperature is related to the average kinetic energy of the molecules of an ideal gas Further extensions of statistical thermodynamics show the relationship between temperature and the energy levels in liquids and solids We shall not be able to discuss the many theoretical aspects of the concept of temperature but may only note that it is important in every branch of physical science, hence the experimental engineer should be familiar with the methods employed in temperature measurement. Detailed discussions of the thermodynamic meaning of temperature are given by Obert [8], Sears [10], Tribus [12], and Rossini [9]

Since pressure, volume, electrical resistance, expansion coefficients, etc. are all related to temperature through the fundamental molecular structure, they change with temperature, and these changes can be used to measure temperature. Calibration may be achieved through companison with established standards as discussed in Chap 2. The International Temperature Scale serves to define temperature in terms of observable characteristics of materials

#### 8-2 TEMPERATURE SCALES

The two temperature scales in use are the Fahrenheit and centigrade scales. These scales are based on a specification of the number of




Fig. 8-1. Relationship between Fahrenheit and contigrade temperature scales.

increments between the freezing point and boiling point of water at standard atmospheric pressure. The centigrade scale has 100 units between these points, while the Fahrenheit scale has 180 units. The absolute centigrade scale is called the Kelvin scale, while the absolute Fahrenheit scale is termed the Rankine scale. Both absolute scales are so defined that they will correspond as closely as possible with the absolute thermodynamic temperature scale. The zero points on both absolute scales represent the same physical state, and the ratio of two values is the same, regardless of the absolute scale used, i.e.,

$$\left(\frac{T_2}{T_1}\right)_{\text{Rankine}} = \left(\frac{T_2}{T_1}\right)_{\text{Kelvin}} \tag{8-1}$$

The boiling point of water is arbitrarily taken as 100° on the centigrade scale and 212° on the Fahrenheit scale. The relationship between the scales is indicated in Fig. 8-1. It is evident that the following relations apply:

$$^{\circ}F = 32.0 + {}_{\xi}^{\circ}C$$
 (8-2a)

$$^{\circ}R = ^{\circ}_{5}K$$
 (8-2b)

It may be noted that the name Celsius has been officially adopted to replace the name centigrade, but the adoption is not yet in wide-spread use.

#### 8-3 TEMPERATURE MEASUREMENT BY MECHANICAL EFFECTS

Several temperature-measurement devices may be classified as mechanically operative. In this sense we shall be concerned with those devices operating on the basis of a change in mechanical dimension with a change in temperature

The liquid-in-glass thermometer is one of the most common types of temperature-measurement devices. The construction details of such an instrument are shown in Fig. 8-2. A Feditively large bulb at the lower portion of the thermometer holds the major portion of the liquid, which expands when heated and rises in the capillary tube upon which are etched appropriate scale markings. At the top of the capillary tube another hulb is placed to provide a safety feature in case the temperature range of the thermometer is inadvertently exceeded. Alcohol and mercury are the most commonly used liquids. Alcohol has the advantage that it has a higher coefficient of expansion than mercury but it is bimited to low-temperature measurements because it tends to boil away at high temperatures. Mercury cannot be used below its fricang point of "38 78°F. The size of the capillary depends on the size of the




Fig. 8-2. Schematic of a mercury-in-glass thermemeter.

# Experimental methods for engineers




Fig. 8-3. The bimetallic strip.

sensing bulb, the liquid, and the desired temperature range for the thermometer.

In operation, the bulb of the liquid-in-glass thermometer is exposed to the environment whose temperature is to be measured. A rise in temperature causes the liquid to expand in the bulb and rise in the eapillary, thereby indicating the temperature. It is important to note that the expansion registered by the thermometer is the difference between the expansion of the liquid and the expansion of the glass. The difference is a function not only of the heat transfer to the bulb from the environment, but also of the heat conducted into the bulb from the stem; the more the stem conduction relative to the heat transfer from the environment, the larger the error. To account for such conduction effects the thermometer is usually calibrated for a certain specified depth of immersion. grade mercury-in-glass thermometers have the temperature scale markings engraved on the glass along with a mark which designates the proper depth of immersion. Very precise mercury-in-glass thermometers may be obtained from the National Bureau of Standards with calibration information for each thermometer.

Mereury-in-glass thermometers are generally applicable up to about 600°F, but their range may be extended to 1000°F by filling the space above the mereury with a gas like nitrogen. This increases

Table 8-1 Mechanical properties of some commonly used thermal materials

M aterial	Thermal coefficient of expansion per °C	Modulus of clasticity, psi	
Invar Yellow brass Monel 400 Inconel 702 Stainless-steel type 316	1.7 × 10 ⁻⁴ 2.02 × 10 ⁻² 1.35 × 10 ⁻³ 1.25 × 10 ⁻³ 1.6 × 10 ⁻³	21.4 × 10 ⁴ 14.0 × 10 ⁶ 26.0 × 10 ⁶ 31.5 × 10 ⁵ 28 × 10 ⁶	

the pressure on the mercury, raises its boiling point, and thereby permits the use of the thermometer at higher temperatures.

A very widely used method of temperature measurement is the bimetallic strip. Two pieces of metal with different coefficients of thermal expansion are bonded together to form the device as shown in Fig. 8-3. When the strip is subjected to a temperature higher than the bonding temperature, it will bend in one direction; when it is subjected to a temperature lower than the bonding temperature, it will bend in the other direction. Eskin and Fritze [3] have given calculation methods for bimetallic strips. The radius of curvature r may be calculated as

$$r = \frac{t[3(1+m)^2 + (1+mn)[m^2 + (1/mn)]]}{6(\alpha_1 - \alpha_1)(T - T_0)(1+m)^2}$$
(8-3)

where

t = combined thickness of the bonded strip

m = ratio of thicknesses of low-expansion to high-expansion materials

n = ratio of moduli of elasticity of low-expansion to highexpansion materials

at = lower coefficient of expansion

α₁ = higher coefficient of expansion

T = temperature

To = initial bonding temperature

The thermal-expansion coefficients for some commonly used materials are given in Table 8-1.

#### Example 8-1

A bimetallic strip is constructed of strips of yellow brass and Invarbonded together at 100°F. Each material has a thickness of 0014 in. Calculate the radius of curvature produced when the strip is subjected to a temperature of 200°F.

Solution We use Eq. (8-3) with properties from Table 8-1.

$$T - T_4 = 100^{\circ}F = 55 \, 6^{\circ}C$$
  
 $m = 1.0$   
 $n = \frac{21.4 \times 10^{\circ}}{14.0 \times 10^{\circ}} = 1.53$   
 $\alpha_1 = 1.7 \times 10^{-4} \, {}^{\circ}C^{-1}$   
 $\alpha_2 = 2.02 \times 10^{-4} \, {}^{\circ}C^{-1}$ 

t = (2)(0.014) = 0.028 in.

Thus,

$$r = \frac{(0.028)[(3)(1+1)^2 + (1+1.53)(1+1/1.53)]}{6(2.02-0.17)(10^{-5})(55.6)(1+1)^2}$$
  
= 18.35 in.

Fluid-expansion thermometers represent one of the most economical, versatile, and widely used devices for industrial temperature-measurement applications. The principle of operation is indicated in Fig. 8-4. A bulb containing a liquid, gas, or vapor is immersed in the environment. The bulb is connected by means of a capillary tube to some type of pressure-measuring device such as the Bourdon gage shown. An increase in temperature causes the liquid or gas to expand, thereby increasing the pressure on the gage; the pressure is thus taken as an indication of the temperature. entire system consisting of the bulb, capillary, and gage may be calibrated directly. It is clear that the temperature of the capillary tube may influence the reading of the device because some of the volume of fluid is contained therein. If an equilibrium mixture of liquid and vapor is used in the bulb, however, this problem may be alleviated, provided that the bulb temperature is always higher than the capillary-tube temperature. In this circumstance the fluid in the capillary will always be in a subcooled liquid state, while the pressure will be uniquely specified for each temperature in the equilibrium mixture contained in the bulb.

Capillary tubes as long as 200 ft may be used with fluid-expansion thermometers. The transient response is primarily dependent on the bulb size and the thermal properties of the enclosed fluid. Highest response may be achieved by using a small bulb connected to some type of electric pressure transducer through a short capillary.




Fig. 8-4. Fluid-expansion thermometer.

#### 8-4 TEMPERATURE MEASUREMENT BY ELECTRICAL EFFECTS

Electrical methods of temperature measurement are very convenient because they turnsh a signal which is easily detected, amplified, or used for control purposes. In addition, they are usually quite accurate when properly calibrated and compensated

#### Electrical-resistance thermometer

One quite accurate method of temperature measurement is the electrical-resistance thermometer. It consists of some type of reassitive element which is exposed to the temperature to be measured. The temperature is indicated through a measurement of the change in resistance of the element. Several types of materials may be used as resistive elements, and their characteristics are given in Table 8-2. The linear temperature coefficient of resistance are stefaned as defined by

$$\alpha = \frac{R_2 - R_1}{R_1 T_2 - R_2 T_1} \tag{S-4}$$

where  $R_1$  and  $R_1$  are the reassances of the material at temperatures  $T_1$  and  $T_1$  respectively The relationship in Eq. (8-4) is usually applied over a narrow temperature range such that the variation of reasstance with temperature approximates a linear relation. For

Table 8-2 Resistance-temperature coefficients α at room temperature, °C-1;

Nickel	0 0067
Iron (alloy)	0 002 to 0 006
Tungslen	0 0019
Aluminum	0 0043
	0 0043
Соррет	0.0042
Lead	0.0041
Silver	0.004
Gold	0 00392
Plaimum	0.00099
Mercury	+0 00002
Masganin	-0 0007
Carban	_8 02 to -0 09
Electrolytes	-0 069 to +0 14
Semiconductor (thermulari)	20 00 10 11
t According to Lion [6]	14-

wider temperature ranges the resistance of the material is usually expressed by a quadratic relation

$$R = R_0(1 + aT + bT^2) (8-5)$$

where

R = resistance at temperature T

 $R_0$  = resistance at 0°F

a, b = experimentally determined constants

It may be noted that the platinum resistance thermometer is used for the International Temperature Scale between the oxygen point and antimony point as described in Chap. 2.

Various methods are employed for construction of resistance thermometers, depending on the application. In all cases care must be taken to ensure that the resistance wire is free of mechanical stresses and so mounted that moisture cannot come in contact with the wire and influence the measurement.

The resistance measurement may be performed with some type of bridge circuit as described in Chap. 4. For steady-state measurements a null condition will suffice, while transient measurements will usually require the use of a deflection bridge. Some of the




Fig. 8-5. Methods of correcting for lead resistance with electrical-resistance thermometer. (a) Siemen's three-lead arrangement; (b) Callender four-lead arrangement; (c) floating-potential arrangement. Battery connections made at A and B.

primary sources of error in the electrical-revisions the momenter is the effect of the registance of the leads which connect the element to the bridge circuit. Several arrangements may be used to corner for this effect, as shown in Fig. 8-5. The Segren's three-lead arrangement is the simplest type of corrective circuit. At balance conditions the center lead carries no current and the effect of the resistance of the other two leads is canceled out. The Callender four-lead arrangement solves the problem by asserting two additional lead wires in the adjustable leg of the bridge so that the effect of the lead wires on the resistance thermometer is canceled out The floating-potential arrangement in (c) is the same as the Siemen's connection, but an extra lead is inserted. This extra lead may be used to check the equality of lead resistance. The thermometer reading may be taken in the position shown, followed by additional readings with the two right and left leads interchanged respectively. Through this interchange procedure the best average reading may be obtained and the lead error minimized

#### Example 8-2

A platinum resistance thermometer is used at room temperature Assuming a linear temperature variation with resistance, calculate the sensitivity of the thermometer in ohms per °F

Solution The meaning of a linear variation of resistance with tem-

$$R = RJ1 + \alpha(T - T_s)1$$

where  $R_{\phi}$  is the resistance at the reference temperature  $T_{\phi}$ . The sensitivity is thus

$$S = \frac{dR}{dt} = \alpha R_0$$

 $R_{\bullet}$  depends on the length and size of the resistance wire At room temperature,  $\alpha=0.00392$  °C⁻¹ = 0.00218 °F⁻¹ for platinum

#### Thermistors

The thermistor is a semiconductor device which has a negative temperature coefficient of resistance in contrast to the positive coefficient displayed by most metals. Purthermore, the resistance follows an exponential variation with temperature instead of a polynomial relation like Eq. (8-5). Thus, for a thermistor,

$$R = R_0 \exp \left[ \beta \left( \frac{1}{T} - \frac{1}{T_0} \right) \right] \tag{8-6}$$

where  $R_0$  is the resistance at the reference temperature  $T_0$  and  $\beta$  is an experimentally determined constant. The numerical value of  $\beta$  varies between 3500 and 4600°K, depending on the thermistor material and temperature. The resistivities of three thermistor materials as compared with platinum are given in Fig. 8-6 according to Ref. [1]. A typical static voltage-current curve is shown in Fig. 8-7, while a typical set of transient voltage-current characteristics is illustrated in Fig. 8-8. The numbers on the curve in Fig. 8-7 designate the degrees centigrade rise in temperature above ambient temperature for the particular thermistor.

The thermistor is an extremely sensitive device, and consistent performance within 0.01°C may be anticipated with proper calibration. A rather nice feature of the thermistor is that it may be used for temperature compensation of electric circuits. This is




Fig. 8-6. Resistivity of three thermistor materials compared with platinum according to Ref. [1].




Fig. 8-7. Static voltage-current curve for a typical thermistor according to Ref. Di.




Fig. 8-8. Typical set of transient voltage-current curves for a thermistor according to Ref. III. Circuit for measurement is shown in insert.

possible because of the negative temperature characteristic which it exhibits so that it can be used to counteract the increase in resistance of a circuit with a temperature merease

#### Example 8-3

Calculate the temperature sensitivity for thermistor No 1 in Fig. 8-6 at 100°C. Express the result in ohm-cm °C⁻¹ Take  $\beta = 4120$ °K at 100°C.

Solution. The sensitivity is obtained by differentiating Eq. (S-6).

$$S = \frac{dR}{dT} = R_t \exp\left[\beta \left(\frac{1}{T} - \frac{1}{T_t}\right)\right] \frac{-\beta}{T^t}$$

We wish to express the result in resistivity units; thus the resistivity at  $100^{\circ}$ C is inserted for  $R_{\rm b}$ . Also,

$$T = T_0 = 100^{\circ}\text{C} = 373^{\circ}\text{K}$$

so that

$$S = -\rho_{\text{torc}} \frac{4120}{(373)^2}$$
$$= -\frac{(110)(4120)}{(373)^2} = -3.26 \text{ obs.-m} \text{ °C}^{-1}$$

## Thermoelectric effects

The most common electrical method of temperature measurement uses the thermocouple. When two dissimilar metals are joined together as in Fig. 8-9, an emi will exist between the two points A and B which is primarily a function of the junction temperature. This phenomenon is called the Seebeck effect. If the two materials are connected to an external circuit such that a current is drawn. the emf may be altered slightly owing to a phenomenon called the Peltier effect. Further, if a temperature eradient exists along either or both of the materials, the junction emi may undergo an additional slight alteration. This is called the Thomson effect. There are, then, three emis present in a thermoelectric circuit: the Seebeck emf. caused by the junction of distiming metals; the Peltier emf, caused by a current flow in the current; and the Thomson emf, which results from a temperature gradient in the materials. The Seebeck emi is of prime concern since it is dependent on junction temperature. If the emf generated at the junction of two dissimilar metals is carefully measured as a function of temperature, then such a junction may be utilized for the measurement of temperature.






Fig. 8-9. Junction of two dissimilar metals indicating thermoelectric effect.





The main problem arises when one attempts to measure the potential. When the two dissimilar materials are connected to a measuring device, there will be another thermal emf generated at the junction of the materials and the connecting wires to the voltagemeasuring instrument. This emf will be dependent on the temperature of the connection, and provision must be made to take account of this additional potential.

Two rules are available for analysis of thermoelectric circuits

If a third metal is connected in the circuit as shown in Fig. 8-10, the net ent of the circuit is not affected as long as the new connections are at the same temperature. This statement may be proved with the aid of the second law of thermodynamics and is known as the law of intermediate metals.

Consider the arrangements shown in Fig. 8-11. The simple thermocouple circuits are constructed of the same materials but operate between different temperature limits. Circuit (a) develops an emf of E₁ between temperatures T₁ and T₂; circuit (b) develops an emf of E₂ between temperatures T₁ and T₁. The law of intermediate temperatures attacts that this same circuit will develop an emf of E₁ = E₁ + E₂ when operating between temperatures T₁ and T₂, as shown in (c)

It may be observed that all thermocouple circuits must involve at least two junctions. If the temperature of one junction is known, then the temperature of the other junction may be easily calculated with the thermoelectric properties of the materials. The known temperature is called the reference temperature  $\Lambda$  common arrangement for each ablishing the reference temperature is the ive both shown




Fig. 8-11. Circuits illustrating the law of intermediate temperatures.

in Fig. 8-12. An equilibrium mixture of ice and air-saturated distilled water at standard atmospheric pressure produces a known temperature of 32°F. When the mixture is contained in a Dewar flask, it may be maintained for extended periods of time. Note that the arrangement in Fig. 8-12 (a) maintains both thermocouple wires at a reference temperature of 32°F, whereas the arrangement in (b) maintains only one at the reference temperature. The system in (a) would be necessary if the binding posts at the voltage-measuring instrument were at different temperatures, while the connection in (b) would be satisfactory if the binding posts were at the same temperature. To be effective the system in (a) must have copper binding posts, i.e., the binding posts and leads must be of the same material.

It is common to express the thermoelectric emf in terms of the potential generated with a reference junction at 32°F. Standard thermocouple tables have been prepared on this basis, and a summary of the output characteristics of the most common thermocouple combinations is given in Table 8-3. These data are shown graphically in Fig. 8-13, along with the behavior of some of the more




Fig. 8-12. Conventional methods for establishing reference temperature in thermocouple circuit. Iron-constantan thermocouple illustrated.

Table 8-3 Thermal emf in absolute millivolts for commonly used thermocouple combinations according to Ref. [14]

(Bosed on reference junction at 32°F)

Tempera-	Copper-	Chromel-	Iton-	Chromel-	Platinum-
fure, *F	Constantan	Constantan	Constantan	Alumel	10% Rhod um
-300 -250 -200 -250 -150 -150 -50 50 50 150 200 350 350 350 350 350 1000 1500 1500 15	-5 294 -4 747 -4 111 -3 390 -1 654 -0 650 -0 389 1.517 2 711 3 947 5 290 6 9 525 11 2 713 12 773 19 703 19 703 19 703 19 703 10 703	-8 30 -6 40 -3 94 -1 02 2 27 5 87 9 71 13 75 17 95 22 25 25 65 30 00 40 06 40 06 40 07 40 07	-7 52 -6 71 -5 76 -4 63 -3 49 -2 22 -0 50 1 94 4 91 1 4 91 1 10 25 1 1 10 25 1 1 10 25 1 2 17 18 20 20 32 20 32 20 36 91	-5 51 -4 96 -4 20 -3 52 -1 70 -0 60 1 52 2 56 3 67 3 67 7 20 8 31 10 57 12 86 10 53 10 57 10 58 11 53 12 58 13 58 14 91 49 91 14 91 14 91 14 92	0 221 0 401 0 505 0 500 1 1 242 1 474 1 712 1 905 2 453 2 453 2 453 2 653 5 726 5 726 5 726 5 726 5 726 5 726 7 739 8 732 10 662 13 991

exotic thermocouple materials The output voltage E of a simple thermocouple circuit is usually written in the form

$$\int_{E} = AT + \frac{1}{2}BT^{3} + \frac{1}{2}CT^{3}$$
(8-7)

where T is the temperature in °C and E is based on a reference junction temperature of 0°C. The constants A, B, and C are dependent on the thermocouple material

The sensitivity, or thermoelectric power, of a thermocouple is given by


$$S = \frac{dE}{dT} = A + BT + CT^{2} \qquad (8-8)$$

Table 8-4 Thermoelectric sensitivity S = dE/dT of thermoelement made of materials listed against platinum, py °C-it

(Peterence function kept at a temperature of O°C)

*	-72	Saver	6.5
Ermuth Coortenies	-35	Copper	6.5
generalis. Neksi	-15	Gold	6.5
Petaerium	-3	Tungsten	7.5
Reform	-2	Cadmium	7.5
Meticum	G	Iron	18.5
Mercury	0.6	Nichrome	25
Carlesa	3	Antimony	47
Alaminum	3.5	Germanium	322
Icsi	4	Editon	440
Tentelum	4 5	Tellurium	570
Rhydian	ζ,	Felenium	600

† According to Lies [6].



## Lague 4 ومعمور فينس فالهامو سراع في to be in Consider the street As Buggers & rivere they be the Th A A'S marget \$1, may beggen \$14.

A December Program But in Alberta

E Plat - in Plat o in their in thep &.

#### Testation or me

A. Rhen on Motshderoon


B. Elbenora Tungaten.

C. Indian Indianal Adams

D. Turgeten Tungeten the neum

E. Plut the dear 47 it 10% the degree

Fig. E-11. Emf-temperature relations for thermocouple materials. (Courtesy Minneapolis-Reneywell Regulator Company.)



(Courtesy Minneapolis-Honeywell Regulator Company.) [See also Fig. (\$-15).]

le 8-3 gives the approximate values of the sensitivity of various erials relative to platinum at 0°C. A summary of the operating re and characteristics of the most common thermocouple erials is given in Figs 8-13 and 8-14.

The output of thermocouples is in the milivolt range and may

instruments can read potentials within 1 µv. It may be noted that the resistance of the lead wires is of no consequence when a potentiometer is used at balance conditions since the current flow is zero in the thermocouple circuit.

#### Example 8-4

An iron-constantan thermocouple is connected to a potentiometer whose terminals are at 75°F. The potentiometer reading is 3.59 mr. What is the temperature of the thermocouple junction?

Solution. The thermoelectric potential corresponding to 75°F is obtained from Table 8-3 as

$$E_{rs} = 1.22 \text{ my}$$

The emf of the thermocouple based on a 32°F reference temperature is thus

$$E_r = 1.22 + 3.59 = 4.81 \text{ mv}$$

From Table 8-3 the corresponding temperature is 197°F

In order to provide a more sensitive circuit, thermocouples are occasionally connected in a series or angement as shown in Fig. 8-16. Such an arrangement is called a thermopile, and for the three-junction situation, the output would be three times that of a single thermocouple arrangement provided that the temperatures of the hot and cold junctions are uniform. The thermopile arrangement is useful for obtaining a substantial emf for measurement, of a small temperature difference between the two junctions? In this way a




Fig. 8-15. Thermopile connection,




Fig. 8-17. Series connection of thermocouples.

relatively inexpensive instrument may be used for voltage measurement, whereas a microvolt potentiometer might otherwise be required. When a thermopile is installed, it is important to ensure that the junctions are electrically insulated from one another. have seen that the typical thermocouple measures the difference in temperature between a certain unknown point and another point designated as the reference temperature. The circuit could just as well be employed for the measurement of a differential temperature. For small differentials, the thermopile circuit is frequently used to advantage. Now consider the series thermocouple arrangement chown in Fig. 8-17. The four junctions are all maintained at different temperatures and connected in series. Since there are an even number of junctions, it is not necessary to install a reference junction because the same type of metal is connected to both terminals of the potentiometer. If we note that the current will flow from plus to minus, and assume that junction A produces a potential drop in this direction, then junctions B and D will produce a potential drop in the opposite direction and junction C will generate a potential drop in the same direction as junction A. Thus the total emf measured at the potentiometer terminals is

$$L = \epsilon_A - \epsilon_B + \epsilon_C - \epsilon_D \tag{8-9}$$

The reading will be zero when all the junctions are at the same temperature and will take on some other value at other conditions. Note, however, that the emf of this series connection is not indicative of any particular temperature. It is not representative of an average of the junction temperatures.

The parallel connection in Fig. 8-18 may be used for obtaining the average temperature of a number of points. Each of the four junctions may be at a different temperature and hence will generate a different emf. The bucking potential furnished by the potentiom-

eter will be the average of the four junction potentials. There can be a small error in this reading, however, because there is a small current flow in the lead wires as a result of the difference in potential between the junctions. Thus, the resistance of the lead wires will influence the reading to some extent.\(\frac{1}{2}\)

A more suitable way of obtaining an average temperature is to use the thermopile circuit in Fig. 8-16. Each of the "hot" junctions may be at a different temperature, while all the "cold" junctions may be maintained at a fixed reference value

The average emf is then given by

$$E_{\text{avg}} = \frac{E}{n} \tag{S-10}$$

where n is the number of junction pairs and E is the total reading of the thermopile. The average temperature corresponding to the average emf given in Eq. (8-10) may then be determined.

From the above discussion it is clear that the thermocouple measures the temperature at the last point of electric contact of the two dissimilar materials. Consider the situations shown in Fig. 8-19. The thermocouple installation in (a) is made so that only the junction bead makes contact with the metal plate whose temperature is to be measured. The installation in (b) allows contact at two




Fig. 8-18. Parallel connection of thermocouple

# Experimental methods for engineers




Fig. 8-19. Installation of thermocouples on a metal plate. (a) Only junction bead contacts plate; (b) contact at two points; (c) contact at bead and along wires.

points. If there is a temperature gradient in the metal plate, then the emf of the thermocouple will be indicative of the average of the temperatures of these two points. In Fig. 8-19c only the junction bead contacts the metal plate, but the two thermocouple wires are in electric contact a short distance away from the plate. The temperature indicated by the thermocouple will be that temperature at the shorted electric contact.

## Quartz-crystal thermometer

A novel and highly accurate method of temperature measurement is based on the sensitivity of the resonant frequency of a quartz crystal to temperature change. When the proper angle of cut is used with the crystal, there is a very linear correspondence between the resonant frequency and temperature. Commercial models of the device utilize electronic counters and digital readout for the frequency measurement. For absolute temperature measurements usable sensitivities of 0.001°C are claimed for the device. Since the measurement process relies on a frequency measurement, the device is particularly insensitive to noise pickup in connecting cables.

## Example 8-5

The thermopile arrangement of Fig. 8-16 uses copper-constant and thermocouples with  $T_1 = 300^{\circ}$ F and E = 3.2 mv for the three-junction pairs. Calculate the value of  $T_2$ .

Solution. We first calculate the thermoelectric sensitivity at 300°F using the values in Table 8-3.

$$S_{300} = \frac{dE}{dT}\Big)_{300} \approx \frac{E_{330} - E_{220}}{350 - 250} = \frac{8.064 - 5.280}{100} \approx 0.0278 \text{ my } ^{\circ}\text{F}^{-1}$$

The thermoelectric emf generated by each junction pair is

$$E = \frac{3.2}{3} = 1.067 \text{ my}$$

so that the temperature difference is

$$T_1 - T_1 = \frac{E}{S} = \frac{1.067}{0.0078} = 39.4$$
°F

and

$$T_{\bullet} = 300 + 384 = 3384$$
°F

#### Example 8-6

The thermoelectine effect has been used for electric power generation Calculate the thermoelectric rensitivity of a device using bismuth and tellurium as the dissimilar materials, and estimate the maximum solizare output for a 100°F temperature difference at approximately room temperature using one junction.

Solution The sensitivity is calculated from the data of Table 8-4 as

$$= 500 - (-72) = 572 uv *C^{-1}$$

The voltage output for a 100°F temperature difference is calculated as

$$E = S \Delta T \approx (572 \times 10^{-4})(5/9)(100)$$

#### 8-5 TEMPERATURE MEASUREMENT BY RADIATION

In addition to the methods described in the preceding sections, it is possible to determine the temperature of a body through a measurement of the thermal radiation emitted by the body Two methods are commonly employed for measurement (I) optical pyrometry and (2) emittance determination. Before we discuss these methods, it is necessary to describe the nature of thermal radiation.

✓ Thermal radiation is electromagnetic radiation emitted by a
body as a result of its temperature. This radiation is distinguished
from other types of electromagnetic radiation such as radio waves
and X rays, which are not propagated as a result of temperature
Thermal radiation lies in the wavelength region from about 0.1 to
100 µ (µ = 10⁻⁴ m). The total thermal radiation emitted by an
ideal blackbody (ideal radiation) is given as.

$$E_b = \sigma T^* \checkmark \tag{8-11}$$

where

 $\sigma = \text{Stefan-Boltzmann constant}$  and is equal to 0.1714  $\times$  10⁻² Btu/(hr)(ft²)(°R⁴)

T = absolute temperature, degrees Rankine

 $E_t = \text{emissive power, Btu/(hr)(ft}^2)$ 

The emissive power of the blackbody varies with wavelength according to the Planck distribution equation

$$E_{1\lambda} = \frac{C_1 \lambda^{-1}}{e^{C_2 DT} - 1} \tag{8-12}$$

where


 $\lambda =$ wavelength,  $\mu$ 

T = temperature, °R

 $C_1 = 1.187 \times 10^{-6} \text{ Btu-}\mu^4/(\text{hr})(\text{ft}^2)$ 

 $C_2 = 2.5896 \times 10^4 \,\mu\text{-}^{\circ}\text{R}$ 

 $E_{1\lambda}$  is called the monochromatic blackbody emissive power. A plot of Eq. (8-12) is given in Fig. 8-20 for two temperatures.



FIZ 8-20. Blackbody emissive power for two temperatures.

When thermal radiation strikes a material surface, the following relation applies:

$$\alpha + \rho + \tau = 1 \tag{8-13}$$

where

- α = absorptivity or the fraction of the incident radiation absorbed
- $\rho = \text{reflectivity or the fraction reflected}$
- τ = transmissivity or the fraction transmitted

For most solid materials  $\tau = 0$  so that

$$\alpha + \rho = 1$$
 (8-14)

The emissivity e is defined as

$$\epsilon = \frac{E}{E_b}$$
 (8-15)

where E is the emissive power of an actual surface and  $E_i$  is the emissive power of a blackbody at the same temperature Kirchhoff's identity furnishes the additional relationship

$$\epsilon = \alpha$$
 (8-16)

under conditions of thermal equilibrium. A gray body is one for which the emissivity is constant for all wavelengths, i.e.,

$$p_{\lambda} = \frac{E_{\lambda}}{E_{\delta\lambda}} = \epsilon$$
 (8-17)

Actual surfaces frequently exhibit highly variable emissivities over the wavelength spectrum. Figure 8-21 illustrates the distinctive features of blackbody and gray-body radiation. For purposes of analysis the real surface is frequently approximated by a gray body having an emissivity equal to the average total emissivity of the real surface as defined by Eq. (8-15)

Let us now consider the measurement of temperature through the use of optical pyrometry. This method refers to the identification of the temperature of a surface with the color of the radiation emitted. As a surface is heated, it becomes dark red, orange, and finally white in color. The maximum points in the blackbody




Fig. 8-21. Comparison of emissive powers of blackbody, ideal gray body, and actual surfaces.

radiation curves shift to shorter wavelengths with increase in temperature according to Wien's law

$$\lambda_{\text{max}}T = 5215.6 \ \mu\text{-}^{\circ}\text{R}$$
 (8-18)

where  $\lambda_{max}$  is the wavelength at which the maximum points in the curves in Fig. 8-20 occur. The shift in these maximum points explains the change in color as a body is heated; i.e., higher temperatures result in a concentration of the radiation in the shorter wavelength portion of the spectrum. The temperature-measurement problem consists of a determination of the variation of temperature with color of the object. For this purpose an instrument is constructed as shown schematically in Fig. 8-22. The radiation from the source is viewed through the lens and filter arrangement. The absorption filter at the front of the device reduces the intensity of the incoming radiation so that the standard lamp may be operated at a lower level. The standard lamp is placed in the optical path of the incoming radiation. By an adjustment of the lamp current the color of the filament may be made to match the color of the




Fig. 8-22. Schematic of optical pyrometer.

incoming radiation. The red filter is installed in the eyepiece to ensure that comparisons are made for essentially monochromatic radiation, thus eliminating some of the uncertainties resulting from variation of radiation properties with wavelength

Figure 8-23 illustrates the appearance of the lamp filament as wiewed from the eyepiece When balance conditions are achieved, the filament will seem to disappear in the total incoming radiation field. Temperature calibration is made in terms of the lamp heating current

The temperature of a body may also be measured by determining the total emitted energy from the body and then calculating the temperature from

$$E = \epsilon_0 T^4 \tag{8-19}$$

In order to determine the temperature, the emissivity of the material must be known so that

$$T = \left(\frac{E}{\epsilon \sigma}\right)^{i} \tag{8-20}$$

Fig. 8-23. Appearance of lamp filament in eyeplece of optical pyrometer.








Fig. 8-24. Temperature error due to non-blackbody-surface conditions,

The apparent blackbody temperature is the value as calculated from Eq. (8-20) with  $\epsilon=1$ , or

$$T_{a} = \left(\frac{E}{\sigma}\right)^{\frac{1}{4}} \tag{8-21}$$

If the apparent temperature is taken as the measured value, th error in temperature due to nonblackbody conditions is thus

Error = 
$$\frac{T - T_o}{T}$$
 =  $1 - \frac{T_o}{T}$  =  $1 - \epsilon^2$  (8-22)

Figure 8-24 gives this error as a function of emissivity.

Several methods are available to measure the emitted therms energy from a body, and these methods will be discussed in Chap. If For now, it is important to realize that temperature may be calculated from the above equations, once this measurement is made.

In practice the optical pyrometer is the more widely used of the two radiation temperature methods since it is relatively inexpensive.

and portable and the determination does not depend strongly on the surface properties of the material. The measurement of radiant energy from a surface can be quite accurate, however, when suitable instruments are employed. If the surface emissive properties are accurately known, this measurement can result in a very accurate determination of temperature. It will be noted that a total radia-

more importantion on thermal radiation and temperature measurements by the above methods

#### Example 8-7

The emitted energy from a piece of metal is measured, and the temperature is determined to be 1950°F, assuming a surface emissivity of 0.82. It is later found that the true emissivity is 0.75. Calculate the error in the temperature determination.

Solution The emitted energy is given by

$$\frac{q}{A} = e\sigma T^4$$

When  $T=1950^{\circ}\mathrm{F}=2410^{\circ}\mathrm{R},~\epsilon=0.82$  We wish to calculate the value of the true temperature  $T^{\circ}$  such that

$$\frac{q}{A} = \epsilon' \sigma(T')^4$$

where e' = 075

Thus 
$$(0.82)(2410)^4 \approx (0.75)(T')^4$$
 and  $T' = (2410)\left(\frac{0.82}{0.75}\right)^{41} \approx 210^4 H$ 

en that the temperature error is

$$\Delta T = 2464 - 2410 = 54^{\circ}F$$

#### 8-6 EFFECT OF HEAT TRANSFER ON TEMPERATURE MEASUREMENT

A heat-transfer process is associated with all temperature measurements. When a thermometer in exposed to an environment, the temperature is determined in accordance with the total heat energy




Fig. 8-24. Temperature error due to non-blackhed conditions.



Fig. 8-25. Schematic of general thermocouple installation in a fat plate.

whose temperature is to be measured. The plate is exposed to a convection environment on both sides, and the thermocouple wires are exposed to this same environment. The thermocouple wires are covered with insulating material as shown. If the plate temperature is higher than the convection environment, hast will be conducted out along the thermocouple wire and hence the temperature of the injection will be lover than the true plate temperature.




Fig. 8-25. Temperature-correction curves for instellation in Fig. 8-25. (From P. J. Schnelder, "Conduction Heat Transfer," Addition-Wesley Publishing Company, Inc., Reading, Mass., 1955.)

exchange with the temperature-sensing element. In some instances the temperature of the thermometer can be substantially different from the temperature which is to be measured. In this section we wish to discuss some of the methods which may be used to correct the temperature readings. It may be noted that the errors involved are classified as fixed errors.

Heat transfer may take place as a result of one or more of three modes: conduction, convection, or radiation. In general, all three modes must be taken into account in analyzing a temperature-measurement problem. Conduction is described by Fourier's law

$$q = -kA \frac{\partial T}{\partial x} \tag{8-23}$$

where

k =thermal conductivity

A = area through which the heat transfer takes place

q = heat-transfer rate in the direction of the decreasing temperature gradient

If a temperature gradient exists along a thermometer, heat may be conducted into or out of the sensing element in accordance with this relation.

Convection heat transfer is described in accordance with Newton's law of cooling

$$q = hA(T_{\bullet} - T_{\infty}) \tag{8-24}$$

where

h =convection heat-transfer coefficient

A =surface area exchanging heat with the fluid

T. = surface temperature

 $T_{\infty} = \text{fluid temperature}$ 

The radiation heat transfer between two surfaces is proportional to the difference in absolute temperatures to the fourth power according to the Stefan-Boltzmann law of thermal radiation.

$$q_{1-2} = \sigma F_0 F_1 (T_1^4 - T_2^4) \tag{8-25}$$

where  $F_0$  is a geometric factor and  $F_0$  is a factor which describes the radiation properties of the surfaces.

Consider the temperature-measurement problem illustrated in Fig. 8-25. A thermocouple junction is installed in the flat plate




Fig. 8-25. Schematic of general thermocouple installation in a fat plate.

whose temperature is to be measured. The plate is exposed to a convection environment on both sides, and the thermocouple wires are exposed to this same environment. The thermocouple wires are covered with insulating material as shown. If the plate temperature is higher than the convection environment, heat will be conducted out along the thermocouple wire and hence the temperature of the junction will be lower than the true plate temperature.




Fig. 2-26. Temperature-correction curves for installation in Fig. 2-25.

(From P. J. Schneider, "Conduction Heat Transfer," Addison-Wesley Publishing Company, Inc., Reading, Mass., 1955.)

An analytical solution to this problem has been presented by Schneider [11], and the results are given in Fig. 8-26. This solution neglects the radiation heat-transfer effects.

The nomenclature for the parameters in Fig. 8-26 is as follows:

 $h_1$ ,  $h_2$  = convection heat-transfer coefficients on the sides of the plate as indicated

 $h_t = \text{convection heat-transfer coefficient from each of the thermocouple wires}$ 

k = thermal conductivity of the plate material

 $\delta$  = plate thickness

 $T_f$  = fluid temperature surrounding the thermocouple wire

 $T_i$  = temperature indicated by the thermocouple

 $T_p$  = true plate temperature (temperature a large distance away from the thermocouple junction)

 $r_{*} = \sqrt{2} r_{*}$ , where  $r_{*}$  is the radius of each of the thermocouple wires

$$m = \left(\frac{h_1 + h_2}{k\delta}\right)^{\frac{1}{2}} \tag{8-26}$$

$$K = \sqrt{2} \pi (k_A^{i} + k_B^{i}) r_i^{i} \left( \frac{1}{h_i} + \frac{\delta_i}{k_i} \right)^{-1}$$
 (8-27)

where  $k_A$  and  $k_B$  are the thermal conductivities of the two thermocouple materials,  $\delta_i$  is the thickness of the thermocouple insulation, and  $k_i$  is the thermal conductivity of the insulation.

#### Example 8-8

A copper-constantan thermocouple is attached to a  $\frac{1}{6}$ -in-thick stainless-steel plate  $[k=35 \text{ Btu/(hr)(ft)(^cF)}]$  as shown in Fig. 8-25. The diameter of the wires is 0.04 in., and the following estimates are made of the significant heat-transfer parameters:

$h_1 = 4.0$	Btu/(hr)(ft2)(°F)	
$h_2 = 2.5$	Btu/(hr)(ft2)(°F)	
$h_1 = 20$	Btu(hr)(ft2)(°F)	
$k_A = 14$	Btu/(hr)(ft)(°F)	(constantan)
$k_B = 220$	Btu/(hr)(ft)(°F)	(copper)
$T_{\star} = 500^{\circ} \mathrm{F}$		,

The thermocouple wires are coated with an electrically insulating lacquer which may be considered negligibly thin insofar as heat transfer is concerned. The plate is cooled on the side opposite the thermocouple installa-

tion, and the thermocouple indicates a temperature of 300°F Calculate the true plate temperature

Solution. We observe that

$$\delta = \frac{1}{8}$$
 in. = 0.0142 ft

$$r_0 = 0.02 \text{ in.} \approx 0.00167 \text{ ft}$$

$$\delta_i \approx 0$$

$$T_t = 300^{\circ} F$$

$$m = \left[\frac{4.0 + 2.5}{(35)(0.0142)}\right]^{\frac{1}{2}} = 3.62$$

From Eq. (8-27),

$$K = \sqrt{2} \pi (14^{1} + 220^{1})(0.00167)^{1}(\frac{1}{10} + 0)^{-1}$$

$$= 0.251$$

The parameters for use with Fig 8-26 are thus

$$mr_4 = 2(0.00167)(3.62) \approx 0.00956$$

$$\frac{k\delta}{K} = \frac{(35)(0\ 0142)}{(0\ 251)} = 1.98$$

Using these values, we obtain from Fig 8-26


$$\frac{T_i-T_p}{T_i-T_p}=0.29$$

or

$$300 - T_p = (0.29)(500 - T_p)$$

The thermocouple conduction error is  $T_* = T_* \approx 82^\circ F$ . This error could be reduced by using smaller thermocouple wires or by insulating the wires

Now let us consider the general problem of the temperature measurement of a gas stream and the influence of radiation on this measurement. The situation is illustrated in Fig. 8-27. The temperature of the thermometer is designated as T_c, the true temperature of the sais T_c, and the effective radiation temperature.



of the surroundings is  $T_c$ . If it is assumed that the surroundings are very large, then the following energy balance may be made:

$$hA(T_{\mathfrak{g}} - T_{\mathfrak{t}}) = \sigma A \epsilon (T_{\mathfrak{t}}^{4} - T_{\mathfrak{t}}^{4}) \tag{8-28}$$

where


h = convection heat-transfer coefficient from the gas to the thermometer

A = surface area of the thermometer

 $\epsilon$  = surface emissivity of the thermometer

Equation (8-28) may be used to determine the true gas temperature In practice, the radiation error in a temperature measurement

is reduced by placing a radiation shield around the thermometer which reflects most of the radiant energy back to the thermometer A simple radiation-shield arrangement is shown in Fig. 8-28. The environment is assumed to be very large, and we wish to find the true gas temperature knowing the indicated temperature  $T_t$  and the other heat-transfer parameters such as the heat-transfer coefficients and emissivities. The thermometer size may vary considerably, from the rather substantial dimensions of a mercury-in-glass thermometer to a tiny thermistor bead embedded in the tip of a hypo-



5. 8-28. A simple radiation-shield arrangement for a thermometer.

dermic needle. An energy balance which neglects conduction effects may be made for both the thermometer and the shield using a radiation-network analysis to obtain expressions for the radiation heat transfer.! The results of the analysis are

Thermometer

$$h_t(T_t - T_t) = \frac{\epsilon_t}{1 - \epsilon_t} (E_M - J_t) \qquad (8-29)$$

Shield

$$2h_{\epsilon}(T_{\epsilon}-T_{\epsilon}) = \frac{E_{b\epsilon}-J_{\epsilon}}{(1/F_{b\epsilon})(A_{\epsilon}/A_{\epsilon})+1/\epsilon_{\epsilon}-1} + \frac{E_{b\epsilon}-E_{b\epsilon}}{1/\epsilon_{\epsilon}-1+1/F_{\epsilon\epsilon}}$$
(8-30)

where

$$J_{\ell} = \frac{\{E_{it}^{i}[\epsilon_{i}/(1 - \epsilon_{i})] + F_{i\nu}E_{is}\}A_{i}/A_{i} + E_{i\nu}/(1/F_{i\nu})(A_{i}/A_{i}) + 1/\epsilon_{i} - 1\}}{(A_{i}/A_{i})[F_{it} + \epsilon_{i}/(1 - \epsilon_{i})] + 1/[(1/F_{i\nu})(A_{i}/A_{i}) + 1/\epsilon_{i} - 1]}$$
(8-31)

*, and 4, are the emissivities of the thermonyeter and sheld, respectively, h, and h, are the convection heat-transfer coefficients from the gas to the thermometer and sizeld, respectively, A, is the surface area of the thermometer for convection and radiation, A, is the surface area of the radiation sheld on each side, and the blackbody emissive powers E_A are given by

$$E_{\rm M} = \sigma T_{\rm s}^4 \qquad (8-32)$$

$$E_{bi} = \sigma T_i^4 \qquad (8-33)$$

$$E_{bs} = \sigma T_s^4 \qquad (8-34)$$

The radiation-shape factors F are defined as

 $F_{ii}$  = fraction of radiation which leaves the thermometer and arrives

at the shield  $F_{ss} =$ fraction of radiation which leaves the outside surface of shield

and gets to the environment (This fraction is 10.)  $F_{te} =$  fraction of radiation which leaves the thermometer and gets to the environment

The analysis which arrives at Eqs. (8-29) and (8-30) has been simplified somewhat by assuming that all the radiation exchange between

f An explanation of the radiation-network method is given in Ref. [5]

the shield and environment may be taken into account by adjusting the value of  $F_n$  to include radiation from the inside surface of the shield. Some type of convection heat-transfer analysis must be used to determine the values of  $h_i$  and  $h_n$  depending on whether natural or forced convection is involved, etc. A trial and error solution must usually be performed on Eqs. (8-29) and (8-30) except in special cases. Some useful charts are given in Ref. [15] for correcting temperature measurements for the effects of conduction and radiation.

In general, the determination of convection heat-transfer coefficients requires very detailed consideration of the fluid dynamics of the problem and empirical relations must often be used for the calculation. For more information the reader should consult Reis. [2] and [7]. Some frequently used formulas for calculating convection heat transfer are summarized in Table S-5.

#### Example 8-9

A mercury-in-glass thermometer is placed inside a cold room in a frozen-food warehouse to measure the change in air temperature when the door is left open for extended periods of time. In one instance the thermometer reads 3½°F, while the automatic temperature-control system for the room indicates that the wall temperature of the room is 15°F. The convection heat-transfer coefficient for the thermometer is estimated at 2 Btu/(hr)(it²)(°F), and  $\epsilon = 0.9$  for glass. Estimate the true air temperature.

Solution. We use Eq. (S-28) to calculate the true air temperature  $T_{\rm r}$ :

$$h(T_r - T_t) = \epsilon \sigma(T_t^4 - T_t^4)$$
(2)  $(T_t - 494) = (0.1714 \times 10^{-4})(0.9)(4944 - 4759)$ 

Thus.

$$T_{\star} = 500.7^{\circ} R = 40.7^{\circ} F$$

# 8-7 TRANSIENT RESPONSE OF THERMAL SYSTEMS

When a temperature measurement is to be made under non-steadystate conditions, it is important that the transient response characteristics of the thermal system be taken into account. Consider the

Table 8-5

Table 8-5 Frequently used convection heat-transfer formulas	on heat-tra	nster formulas		
Physical estuation	Type of fine	Range of saleddy	Heal-transfor relation	Fluid properties evaluated of
Freed countries wer fest place, place bested wer enten iregel Gas or liquid Tradebastic Res 6 8 N 199	AA Ges or Hquid	Laminuer Res < 5 × 10 ⁴ Turbubed: Res > 5 × 10 ⁴ Laminar. Red < 5 × 10 ⁹ Turbubent: Res > 3 × 10 ⁹	Nu. = 0 332 Re.   Pri Shard = 0 0238 Re.   Nu. = 0 064 Re.   Pri Nu. = (0 035 Re. ! = 836) Pri	Film tempereture T,
Pered conrection in smooth cerealar tabs	Gas or liquid   Ras > 3000   Ras < 2100   Ras Fr ( )	$R_{44} > 3000$ $R_{44} < 21000$ and $R_{45} \cdot \left(\frac{d}{L}\right) > 10$	$N_{\rm LL}^{\rm a} = 0.023  {\rm Res}^2 \cdot {\rm Pr}^2$ $n = 0.4  {\rm for  batteng},  n = 0.3  {\rm for  cooling}$ $W_{\rm Ll}^{\rm a} = 1.86  {\rm (Res  Pr)}^2 \left(\frac{4}{L}\right)^4 \left(\frac{\mu}{L^4}\right)^{3.1}$	Average bulk temperature of fluid
Perced-connection erosifica sear extinder	Gae	40 < Res < 4000 40 < Res < 4000	N 0.818 Res	Visa temperature 7, Film temperature 7,
Pareed connection were opheres	Gas	(7 < Res < 70 000 ) < Res < 200 000	Nia + 0 37 Nat .	Pilm temperature Tr Presentenam temperature Ta
Pres consection from correct flat plate	Das or trusta	Gas or lequid 10' < Gre Fr < 10's 10' < Gre Fr < 10's	Nu - 0 89(0rs Pr) 1 Nas - 0 13(Gre Pr) 2	Film temperature Tr
Pres consection from harisenial extenders	Car or liquid	Cas or hquid 10! < Gra Pr < 10"	Na - 0 13(Gr. Pr)! No - 0 13(Gr. Pr)!	Film temperature Tr.
notities in consistent as	units so that Nn.	t of uals so that Ma, Re, Pr, Ot, and Pt are diverse for flow over sylladers or spheres, Res = """	to the is taken if $a_1 = \frac{m_0 a_1^2}{n}$ . For $a_1 = \frac{m_0 a_2^2}{n}$ , For $a_2 = \frac{m_0 a_2^2}{n}$ , $a_3 = \frac{m_0 a_2^2}{n}$ .	$\frac{1}{2} \left( \frac{1}{2} + \frac{1}{2} \right) \frac{1}{2} = \frac{1}{2} \left( \frac{1}{2} + \frac{1}{2} \right) \frac{1}{2}$
d = dismater of tube	ż	To well or surface temperature		

- d = demaker of tube

  d = exceleration of gravity

  d = local beat-transfer coefficient on flat plate

A – thermal cooductivity of fluid L – total length or heigh of this plate or length of tube  $T_f$  – film temperature  $\frac{T_f}{2} + \frac{T_f}{2}$ 

- l s. e. well of nutrae beinger saire.
  T. = free-stream tring-craute.
  T. = mean fluid velocity in table
  U. = free-stream velocity past flat plate, sylinder, or sphere.

so - elecority sendented at well tamperstore a - Getungs from leading wige of flat pluts # = professe coefficient of expansion of field blog to a departure a factority of fluid y = Suid density




Fig. 2-23. Simple thermal system subjected to a sudden change in ambient femperature.

simple system shown in Fig. 8-29. The thermometer is represented by the mass m and specific heat c and is suddenly exposed to a convection environment of temperature  $T_{\infty}$ . The convection heat-transfer coefficient between the thermometer and fluid is h, and radiation heat transfer is assumed to be negligible. It is also assumed that the thermometer is substantially uniform in temperature at any instant of time; i.e., the thermal conductivity of the thermometer material is sufficiently large in comparison with the surface conductance because of the convection heat-transfer coefficient. The energy balance for the transfert process may be written as

$$hA(T_{=}-T) = mc\frac{dT}{d\tau}$$
 (8-35)

The solution of Eq. (8-35) gives the temperature of the thermometer as a function of time.

$$\frac{T - T_{\pi}}{T_{\uparrow} - T_{-}} = e^{\langle -\lambda L m_{\pi} \rangle} \tag{8-36}$$

where  $T_0$  is the thermometer temperature at time zero. Equation (8-36) represents the familiar exponential decay behavior described in Sec. 2-7. The time constant for the system in Fig. 8-29 is

$$\tau = \frac{mc}{\hbar A} \tag{8-37}$$

When the heat-transfer coefficient is sufficiently large, there may be substantial temperature gradients within the thermometer itself and a different type of analysis must be used to determine the temperature variation with time. The interested reader should consult Ref. [2] for more information on this subject.

# 8-8 THERMOCOUPLE COMPENSATION

Suppose a thermocouple is used to measure a transient temperature variation. The response of the thermocouple will be dependent on

several factors as outlined above and will follow a variation like that of Eq. (8-36) when subjected to a step change is environment temperature. If a compensating electric network is applied to the system, it is possible to increase the frequency response of the thermocouple. The disadvantage of the compensating network is that it reduces the thermocouple output, however, if the measuring instrument is sufficiently sensitive this problem is not to critical.

A typical thermocouple-compensation network is shown in Fig 8-30. The thermocouple upm valtage is represented by E_n and the output voltage is represented by E_n. This particular network will attenuate low frequences more than high frequencies, and has a frequency response to a step upmit which is approximately opposite to that of a thermocouple. The network and thermocouple may thus be used in combination to produce a flat response over a wider frequency range. The output response of the network is given by

$$\frac{E_0}{E_1} = \alpha \frac{1 + j \omega \tau}{1 + \alpha j \omega \tau}$$
(8-39)

where

$$\alpha = \frac{R}{R + R}$$

$$r = R_c C$$


ω = frequency of the input signal

The amplitude response is given by the absolute value of the function in Eq. (8-38). Thus,

$$\left(\frac{E_1}{E_1}\right)_{\alpha = \alpha} \propto \sqrt{\frac{1 + \omega^2 r^2}{1 + \alpha^2 \omega^2 r^2}}$$
(8-39)

The high-frequency compensation of the network is improved as the value of  $\alpha$  is decreased, but this brings about a decreased output since the steady-state output is

$$\begin{pmatrix} E_1 \\ E_2 \end{pmatrix}_{\text{total const}} = \frac{R}{R + R} = \alpha$$
(8.40)



In practice, the compensating circuit is usually designed so that  $\tau$  is equal to the time constant for the thermocouple. Variable resistors may be used to change the compensation with a change in thermal environment conditions.

#### Example 8-10

A thermocouple head has the approximate shape of a sphere  $\gamma_n^{\dagger}$  in. in diameter. The properties may be taken us those of iron ( $\rho = 490 \text{ lh}_m/\text{ft}^2$ ,  $c = 0.11 \text{ Btu/lb}_m^{-0}\text{F}$ ). Suppose such a head is exposed to a convection environment where  $h = 15 \text{ Btu/(hr)(ft}^2)(^0\text{F})$ . Estimate the time constant for the thermocouple.

Solution. We use Eq. (8-37) to calculate the time constant with

$$m = \rho V = \rho_n^4 \pi r^2$$

$$A = 4\pi r^2$$

so that

$$\tau = \frac{(490)(0.11)}{(3)(15)(32)(12)} = 3.12 \times 10^{-4} \text{ hr}$$
  
= 11.2 sec

## Example 8-11

Design a thermocouple-compensation network like that shown in Fig. 8-30 having a steady-state attenuation of a factor of 10. Let the network have the same time constant as the thermocouple bead in Example 8-10.

Solution. We take

$$\alpha = \frac{R}{R + R_e} = 0.1$$
 and  $\tau = R_e = 11.2$ 

We must arbitrarily choose a value for one of the resistances. Let us choose a value of R, which will make C a reasonable number. Take

$$R_{\rm c} = 1 \text{ megohm} = 10^{\rm s} \text{ ohms}$$

Then 
$$C = \frac{11.2}{10^4} = 1.12 \times 10^{-4} = 11.2 \,\mu\text{f}$$
. Using the above value of  $R_e$  we

obtain

 $R = 1.11 \times 10^{4} \text{ ohms}$ 

A more practical set of values would be

C = 10uf

 $R_{\star} = 1.12$  megohms

R = 0.124 megohm

#### 8-9 HIGH-SPEED TEMPERATURE Measurements

The measurements of temperatures in high-peed gas-flow attrams are sometimes difficult because of the fact that a stationary probe must measure the temperature of the gas which is brought to treat at the probe surface. As the gas velocity is reduced to zero, the kinetic energy is converted to thermal energy and evidenced as an increase in temperature. If the gas is brought to rest adiabatically, the resulting stagnation temperature is given by

$$T_0 = T_m + \frac{u_m^4}{2c_0 a_0}$$
 (8-41)

where

 $T_0$  = stagnation temperature

 $T_m =$ free-stream or static temperature

u = flow velocity

c, = constant-pressure specific heat of the gas

The stagnation temperature of the gas may also be expressed in terms of the Mach number as

$$\frac{T_0}{T_n} = 1 + \frac{\gamma - 1}{2} M^{\tau} \tag{8-42}$$

where  $\gamma = c_p/c_r$  and has a value of 1.4 for air. An inspection of Eqs. (8-41) and (8-42) shows that the stagnation temperature is substantially the same as the static temperature for low-speed flow substantially the same as the static temperature for low-speed flow. The difference in these temperatures is only 41° for a velocity of 226 ft/sec in air.

For the actual case of a probe inserted in a high-epect flow




Fig. 8-31. A high-speed temperature probe according to Winkler [13].

stream, the temperature indicated by the probe will not, in general, be equal to the stagnation temperature given by Eq. (8-41). The actual temperature is called the recovery temperature and is strongly dependent on the probe configuration. The recovery factor is defined by

$$r = \frac{T_r - T_{\infty}}{T_0 - T_{\infty}} \tag{8-43}$$

where  $T_r$  is the recovery temperature. In practice, the recovery factor must be determined from a calibration of the probe at different flow conditions. It is usually in the range 0.75 < r < 0.99. One of the important objectives of a probe design is to achieve a configuration which produces a nearly constant recovery factor over a wide range of flow velocities.

A typical high-speed temperature probe is shown in Fig. 8-31 according to Winkler [13]. The gas stream enters the front of the probe and is diffused to a lower velocity in the enclosing shield arrangement. The flow subsequently leaves the probe through the side ventholes. The shield also serves to reduce radiation losses from the thermocouple-sensing element. The recovery factor for this probe is essentially 1.0.

## 8-10 SUMMARY

A summary of the range and application of the various temperature-measurement devices is given in Table 8-6. It will be noted that many of the devices overlap in their range of application. Thus, the selection of a device for use in a particular application is often a matter of preference. In many cases, the selection is based on a consideration of the type of readout equipment which is already available at the installation where the device is to be used.

Table 8-6 Summary of characteristics of temperature-measurement devices

Danca	Applicable temperature range, *P	Approximate activacy, *P	Transment transment	Coat	Ronaris
Liquid-in-gloss ther-				<b></b>	
a Alcohol	-90 to 150	±1	Poor	ia-	L'oni as indipensive fon-temperature
è Morcury	-35 to 600	±05	Pour	Variable	Accuracy of ±0 1"?
e Confiled mercury	- 25 to 1000	±0 8	Post	Variable	may be obtained with special calibrated the momentum
Fluid-expansion there mometer	{	,	ł	}	CHIPSELL I
a. Liquid or was	-150 to 1000	22	Peor	Low	Widely meet for in ton- trud temperature
6. Vaper pressure	20 to 400	\$3	Poor	Low	measurements
SimdoRic arrip	- 100 to 1000	±05	Pour	Low	Widely used in unspir temperature-control devices
Electrical resusigness thermometer	-300 to 1800	±0 005t	Fast to good, depending on Hea of element	Readout some- ment can be rather expenses for high-jugge-	Minst accurate of all methods
Thermissor	-100 to 500	±0 03†	Very good	mon work  Lew but readout equipment may be expressed for high-precision work	Unctal for tempera- ture-compensation mremia; thermator beeds may be ab- tuated in very amail
Copper-Considerian thermocourie	-300 to 550	±0 \$	Good, depends	Lov	Linear mountainty
Iron-Constantan ther- ma-touple	-\$00 to 1200	±0.4	Good, depends on ways use		Superior in reducing
Crand-Atund there mo-couple	-300 to 2200	±0 &	Good, depends on water man		Resultant to oxidation at high temperatures
Platenum-Platenum 10 7, rhodeum (hormocouple	0 to 2000	±0 \$	Good, dependa po wite mie	Hugh	Low output most re- metast to emperatures acturacy of ±0 15°F may be obtained to carefully controlled conditions
Optical pyrameter	1200 up	±20	Poor	Median	Widely used for mean urement of industrial furnace temperatures
Radiation pyrometer	ינט	±1 at low pages, ±5 to 20 at high isosperatures, depends on blackbody conditions and type of pyrometer, See Chap. 12.	Good, depend- ing on type of pyrometer	Medium to bigh	Increased applications resulting from new high-precision devices being daveloped

[†] Accuracy is that which may be achieved. Inexpensive versions of the davices may not give the

## PROBLEMS

- 8-1 Calculate the temperature at which the Fahrenheit and centigrade scales coincide.
- 8-2 A certain mercury-in-glass thermometer has been calibrated for a prescribed immersion depth. The thermometer is immersed too much, such that the extra depth is equal to a distance of 10° on the scale. The true temperature reading may be calculated with

$$T_{\text{true}} = T_{\text{ind}} - 0.000088 (T_{\text{ind}} - T_{\text{amb}})D$$

where

 $T_{\rm ind} = indicated temperature$ 

 $T_{amb} =$  ambient temperature of the exposed stem

D = extra immersion depth of the thermometer past the correct mark

Calculate the thermometer error for an indicated temperature of 210°F and an ambient temperature of 70°F.

- 8-3 The bimetallic strip material of Example 8-1 is to be used in an on-off temperature-control device which will operate at a nominal temperature of 200°F. Calculate the deflection at the end of a 4-in. strip for deviations of ±1 and 2°F from the nominal temperature.
- 8-4 Suppose the bimetallic strip in Prob. 8-3 is used to indicate temperatures of 150, 200, and 300°F. The tip of the strip is connected to an appropriate mechanism which amplifies the deflection so that it may be read accurately. The uncertainty in the length of the strip is ±0.01 in., and the uncertainty in the thickness of each material is ±0.0002 in. The perpendicular deflection from the 100°F position is taken as an indication of the temperature. Calculate the uncertainty in each of the above temperatures, assuming zero uncertainty in all the material properties; i.e., calculate the uncertainty in the deflection at each of these temperatures.
- 8-5 A bimetallic strip of yellow brass and Monel 400 is bonded at 120°F. The thickness of the yellow brass is  $0.014 \pm 0.0002$  in., and the thickness of the Monel is  $0.010 \pm 0.0001$  in. The length of the strip is 5 in. Calculate the deflection sensitivity defined as the deflection per degree Fahrenheit temperature difference. Estimate the uncertainty in this deflection sensitivity.
- 8-6 The specific volume of mercury is given by the relation

$$v = v_0(1 + aT + bT^2)$$

where T is in °C and

 $a = 0.1818 \times 10^{-2}$ 

b ≈ 0.0078 × 10~4

A high-temperature thermometer is constructed of a Monel-400 tube having an inside diameter of 0.032 ± 0.0020 in. After the inside is evacuated, mercury is placed on the inside such that a column height of 4.00 ± 0.01 in. is achieved when the thermometer temperature is 500°F. If the tube is to be used for a temperature measurement, calculate the uncertainty at 500°F if the uncertainty in the beight measurement is +0.01 in.

- 8-7 A fluid-expansion thermometer uses liquid Freon (C = 0.22 Bty/lba,*Fr, p = 85.2 lba,ft*) enclosed in a 0.25 in -ID copper (C = 0.022, p = 550) cylinder with a wall thickness of 0.321 in The thermometer is exposed to a crossflow of air at 400°F, 15 pais, and 20 ft/sec. Estimate the time constant for such a thermometer. Neglect all effects of the espillary tube. Repeat for a crossflow of liquid water at 180°F and 20 ft/sec Recalculate the time constant for both of these situations for a stanies-steel bulb (C = 0.11, a = 490).
- 8-8 It is desired to measure a temperature differential of 5°F using copper-constantan thermocouples at a temperature level of 200°F. A millivolt recorder is available for the emf measurement which has an uncertainty of 0.001 mv. Precision thermocouple wire is available which may be assumed to match the characteristics in Table 8-3 exactly. How many junction pairs in a thermopile must be used in order that the uncertainty in the temperature differential measurement does not exceed 0.05°F? Neglect all errors due to heat transfer.
- 8.9 A thermopile of chromel-aluned with four junction pairs is used to measure a differential temperature of 40°F at a temperature level of 400°F. The sensitivity of the thermocouple wire is found to match that in Table 8-3 within ±0 5 percent, and the millivolt potentiometer has an uncertainty of 0,002 my Calculate the uncertainty in the differential temperature measurement.
- 8-10 For a certain thermistor, \(\textit{\beta} = 3420^\text{c}\)K, and the resistance at 200°F is known to be 1,010 ± 3 nlms. The thermistor is used for a temperature measurement, and the resistances measured as 2,315 ± 4 ohms. Calculate the temperature and the uncertainty.

potentiometer.

8-11 Calculate the thermoelectric sensitivity for iron-constant and copper-constant at 0°C. Plot the error which would result if these values were assumed constant over the tempera-

ture range from -50 to +600°F.

- 8-12 A chromel-alumel thermocouple is exposed to a temperature of 1550°F. The potentiometer is used as the cold junction, and its temperature is estimated to be 83°F. Calculate the emitimated to be 83°F.
- indicated by the potentiometer.

  8-13 Four iron-constantan thermocouple junctions are connected in series. The temperatures of the four junctions are 200. 300, 100, and 32°F. Calculate the emf indicated by a
- 8-14 A millivolt recorder is available with a total range of 0 to 10 mv and an accuracy of ±0.25 percent of full scale. Calculate the corresponding temperature ranges for use with iron-constantan, copper-constantan, and chromel-alumel thermocouples, and indicate the temperature accuracies for each of these thermocouples.
- 8-15 When a material with spectral emissivity less than unity is viewed with an optical pyrometer, the apparent temperature will be somewhat less than the true temperature and will depend on the wavelength at which the measurements are made. The error is given by

$$T - T_e = \frac{1}{[C_2 T_e/\lambda \ln{(1/e_1)}] - 1}$$

where

T = true temperature, FR

 $T_e = \text{apparent temperature, }^T R$  $\alpha = \text{spectral emissivity at the particular value of } \lambda$ 

 $C_2 = \text{constant irom Eq. (8-12)}$ 

For a measurement at  $0.665 \mu$  and an apparent temperature of  $2400^{\circ}$ F, plot the error as a function of  $\alpha$ .

- A radiant energy measurement is made to determine the temperature of a hot block of metal. The emitted energy from the surface of the metal is measured as  $5010 \pm 80 \, \text{Btu/(hr)}$  (hr) and the surface emissivity is estimated as  $\epsilon = 0.90 \pm 0.05$ . Calculate the surface temperature of the metal, and estimate the uncertainty.
- 8-17 A radiometer is used to measure the radiant energy flux from a material having a temperature of  $542 \pm 1.0^{\circ}$ F. The emissivity of the material is  $0.95 \pm 0.03$ . The radiometer is then

used to view a second material having exactly the same geometric shape and orientation as the first material and an emissivity of  $0.72\pm0.0^\circ$ . The uncertainty in the radiant energy flux measurement is  $\pm40~\mathrm{Bm/(h^2)}$  for both measurements, and the second measurement is 2.23 times as large as the first measurement. Calculate the temperature of the second material and the uncertainty

8-18 Consider the thermometer-shield arrangement shown in Fig. 8-28. Assuming that the shield area is very large compared with the thermometer area and that all radiation leaving the thermometer is intercepted by the shield, calculate the true gas temperature using the following data.

 $h_t = 20 \text{ Btu/(hr)}(ft^2)(^{\circ}\text{F})$   $h_s = 15 \text{ Btu/(hr)}(ft^2)(^{\circ}\text{F})$   $t_s = 08$   $t_s = 02$   $T_t = 600^{\circ}\text{F}$  $T_c = 100^{\circ}\text{F}$ 

 $F_n = 1.0$ ,  $F_n = 1.0$ , and  $F_n = 0$ ) What temperature would the thermometer indicate if the shield were removed? Calculate the error reduction owing to the use of the radiation shield

(It is assumed from the statement of the problem that

8-19 Rework Prob. 8-18 assuming that A_s/A_s = 100 and that the radiation shape factors are given as F_{ts} = 0.9, F_{ts} = 01, and F_{ts} = 1.1 (recall the assumption pertaining to F_{ts})

F₁ = 1.1 (recall the assumption perfaming to Γ_{ct})

8-Q A platumum resistance thermometer is placed in a duct to measure the temperature of an airflow stream. The thermometer is placed unside a cylindrical shell 0.25 m. in diameter which has a polished outside surlace with ε = 0.03 ± 0.02. The airstream velocity is known to be 10 ft/sec, and the pressure is 14 peas. The thermometer indicates a temperature of 240°F. The duct wall temperature is measured at 350°F. Calculate the true air temperature, and estimate the uncertainty in this temperature. Assume that the uncertainty in the convection heat-transfer coefficient eleculated with the appropriate formula from Table 8-5 is ±15 percent. Assume that the uncertainty in the resistance-thermometer measurement is ±0.05°F.


8-21 Repeat Prob 8-20, but assume that the cylinder is a chromeplated copper rod with a thermocouple embedded in the sur-

face. The uncertainty in the thermocouple measurement is assumed to be  $\pm 0.5^{\circ}F$ .

- 8-22 A small copper sphere is constructed with a thermocouple embedded in the center and is used to measure the air temperature in an oven. The walls of the oven are at 1200 ± 20°F. The emissivity of the copper surface is 0.57 ± 0.04, and the temperature indicated by the thermocouple is 1015 ± 1.0°F. The convection heat-transfer coefficient is 5.0 Btu/(hr)(ft²)(°F) ± 15 percent. Calculate the true air temperature and the uncertainty. Calculate the true air temperature if the surface of the sphere had been chromeplated with ε = 0.06 ± 0.02. Estimate the uncertainty in this circumstance.
- 8-23 The thermocouple wires in Example S-S are coated with an insulation material having a thickness of 0.003 in, and a thermal conductivity of 0.1 Btu/(hr)(ft)(°F). Calculate the true plate temperature, assuming the other conditions are the same as in the example.
- 8-24 A 1/2 in. constantan strip is heated by the gas stream on one side and cooled on the other side as shown. Two bare 0.004-in.-diam copper wires are attached to the strip to indicate the temperature difference in the transverse direction. A potentiometer indicates 0.15 ± 0.001 mv, and the sensitivity of copper constantan may be taken as 0.0279 ± 0.0001 mv °F-1. Estimates of the significant heat-transfer parameters are as follows:

 $h_1 = 3.5 \text{ Btu/(hr)(ft^2)(°F)}$   $h_2 = 2.5 \text{ Btu/(hr)(ft^2)(°F)}$   $h_{t_1} = 15 \text{ Btu/(hr)(ft^2)(°F)}$   $h_{t_2} = 10 \text{ Btu/(hr)(ft^2)(°F)}$   $k_{ru} = 220 \text{ Btu/(hr)(ft)(°F)}$  $k_{ru} = 14 \text{ Btu/(hr)(ft)(°F)}$ 

Calculate the true temperature difference, and estimate the uncertainty.



- 8-25 Calculate the time constant for the copper-rod thermometer of Prob 8-21. Consider only the convection heat transfer from the gas in calculating this value.
- 8-26 A thermocouple is placed inside a 1-in.-OD, 3-in-ID copper tube. The tube is then placed inside a furnace whose walls are at 1500° F. The air temperature in the furnace is 1200°F Calculate the temperature indicated by the thermocouple, and estimate the time + to obtain

$$\frac{T-T_1}{T_1-T_2}=0.5$$

where

T. = initial temperature of the thermocouple before it is placed in the furnace

T_i = indicated temperature after a long time

T = temperature at time r

Assume e = 0 78 for copper

- A certain thermocouple has a time constant of 12 sec Design a compensation network like that shown in Fig. 8-30. having a steady-state attenuation factor of 8 Select the value of the resistance so that the capacitor has an even multiple value
- 8-28 A certain high-speed temperature probe having a recovery factor of 0.98 ± 0.01 is used to measure the temperature of air at Mach 3 00. The thermocouple installed in the probe is accurate within ±2.0°F and indicates a temperature of 715°F Calculate the free-stream temperature and the uncertainty.

#### REFERENCES

- 1. Becker, J. A., C. B. Green, and G. L. Pearson Properties and Uses of Thermistors, Trans AIEE, vol. 65, pp 711-725, November, 1946
- 2. Eckert, E R. G., and R M Drake "Heat and Mass Transfer," 2nd ed , McGraw-Hill Book Company, New York, 1959
- Eskin, S. G , and J R. Fritze. Thermostatic Bimetals, Trans ASME vol. 62, pp 433-442, July, 1940
- 4. Hackforth, H L. "Infrared Radiation," McGraw-Hill Book Company, New York, 1960.

- Holman, J. P.: "Heat Transfer," McGraw-Hill Book Company, New York, 1963.
- Lion, K. S.: "Instrumentation in Scientific Research," McGraw-Hill Book Company, New York, 1959.
- McAdains, W. H.: "Heat Transmission," 3rd ed., McGraw-Hill Book Company, New York, 1954.
- 8. Obert, E. F.: "Concepts of Thermodynamics," McGraw-Hill Book Company, New York, 1960.
- Rossini, F. D. (cd.): "Thermodynamics and Physics of Matter," Princeton University Press, Princeton, N.J., 1955.
- Scars, F. W.: "Thermodynamics," Addison-Wesley Publishing Company, Inc., Reading, Mass., 1953.
- Schneider, P. J.: "Conduction Heat Transfer," Addison-Wesley Publishing Company, Inc., Reading, Mass., 1955.
- Tribus, M.: "Thermostatics and Thermodynamics," D. Van Nostrand Company, Inc., Princeton, N.J., 1961.
- Winkler, E. M.: Design and Calibration of Stagnation Temperature Probes for Use at High Supersonic Speeds and Elevated Temperatures, J. Appl. Phys., vol. 25, p. 231, 1954.
- Reference Tables for Thermocouples, Natl. Bur. Std. (U.S.), Cir. 561, April, 1955.
- West, W. E., and J. W. Westwater: Radiation-conduction Correction for Temperature Measurements in Hot Gases, Ind. Eng. Chem., vol. 45, p. 2, 152, 1953.

# Thermal- and transportproperty measurements

#### 9-1 INTRODUCTION

Several types of thermal properties are essential for energy balance calculations in heat-transfer applications. Values of these properties for a variety of substances and materials are already available in tabular form in various handbooks; however, with the new materials which appear regularly, it is important that the engineer be familiar with some basic methods of measuring these properties.

Most thermal-property measurements involve a determination of heat flow and temperature. We have already discussed several types of temperature-measuring devices in Chap 8 and shall have oceasion to refer to them from time to time in discussing thermalproperty measurements Heat flow is usually measured by making an energy halance on the device under consideration. For example a metal plate might be heated with an electric heater and the plate immersed in a tank of water during this heating process. The convection heat loss from the plate could thus be determined by making a measurement of the electric power dissipated in the heater. As another example, consider the heating of water by passing it through a heated pipe. The convection heat transfer from the pipe wall to the water may be determined by measuring the mass flow rate of water and the inlet and exit water temperatures to the heated action of pipe The energy gamed by the water is therefore the hertransfer from the nine provided that the outside surface of the co is insulated so that no losses are mourred. The technical measurement of heat transfer by thermal radiation are discondetail in Chap 12.

Thermal conductivity may be classified as a transport in a field or

gases and liquids the transport of energy takes place by molecular motion, while in solids transport of energy by free electrons and lattice vibration is important. Fluid viscosity is also classified as a transport property because it is dependent on the momentum transport which results from molecular motion in the fluid. Mass diffusion is similarly classified as a transport process because it results from molecular movement. The diffusion coefficient is the transport property in this case. In this chapter we shall consider some simple methods for measurement of these transport properties.

The measurement of heat flow falls under the general subject of calorimetry. In this chapter we shall discuss some simple calorimetric determinations which may be performed. The broad subject of thermodynamic-property measurement is beyond the scope of our discussion.

# 9-2 THERMAL-CONDUCTIVITY MEASUREMENTS

Thermal conductivity is defined by the Fourier equation

$$q_r = -kA \frac{\partial T}{\partial x} \tag{9-1}$$

where

 $q_x$  = heat-transfer rate A = area through which the heat is transferred  $\partial T/\partial x$  = temperature gradient in the direction of the heattransfer

Experimental determinations of thermal conductivity are based on this relationship. Consider the thin slab of material shown in Fig. 9-1. If the heat-transfer rate through the material, the material thickness, and the difference in temperature are measured, then the




Fig. 9-1. Simple thermal-conductivity measurement.

í




Fig. 3-2. Schematic of guarded het-plate opparatus for measurement of thermal conductivity.

thermal conductivity may be calculated from

$$k = \frac{q \Delta x}{A(T_1 - T_2)}$$
(9-2)

In an experimental sctup the heat may be supplied to one side of the slab by an electric heater and removed from the other side by a cooled plate. The temperatures on each side of the slah may be measured with thermocouples or thermitions, whichever is more appropriate.

The main problem of the above method for determining thermal conductivity is that heat may escape from the edges of the slab, or if the edges are covered with insulation, a two-dimensional temperature profile may result which can cause an error in the determination This problem may be alleviated by the installation of guard heaters. as shown in Fig 9-2 In this arrangement the heater is placed in the center and a slab of the specimen is placed on each side of the heater plate. A coolant is circulated through the device to remove the energy, and thermocouples are installed at appropriate places to measure the temperatures. A guard heater surrounds the main heater, and its temperature is maintained at that of the main heater This prevents heat transfer out from the edges of the specimen and thus maintains a one-dimensional heat transfer through the material whose thermal conductivity is to be determined. The guarded hot plate, as it is called, is widely used for determining the thermal conductivity of nonmetals, se, solids of rather low thermal conductivity. For materials of high thermal conductivity a small temperature difference would be encountered which would require much more precise temperature measurement

A very simple method for the measurement of thermal conductivities of metals is depicted in Fig. 9-3 A metal rod A of known thermal conductivity is connected to a rod of the metal B whose




Fig. 9-3. Apparatus for measurement of thermal conductivity of metals.

thermal conductivity is to be measured. A heat source and heat sink are connected to the ends of the composite rod, and the assembly is surrounded by insulating material to minimize heat loss to the surroundings and to ensure one-dimensional heat flow through the rod. Thermocouples are attached, or embedded, in both the known and unknown materials as shown. If the temperature gradient through the known material is measured, the heat flow may be determined. This heat flow is subsequently used to calculate the thermal conductivity of the known material. Thus,

$$q = -k_A A \left(\frac{dT}{dx}\right)_A = -k_B A \left(\frac{dT}{dx}\right)_B \tag{9-3}$$

The temperatures may be measured at various locations along the unknown and the variation of thermal conductivity with temperature determined from these measurements. Van Dusen and Shelton [6] have used this method for the determination of thermal conductivities of metals up to 600°C.

## Example 9-1

A guarded hot-plate apparatus is used to measure the thermal conductivity of a metal having k=50 Btu/(hr)(ft)(°F). The thickness of the specimen is  $0.125\pm0.002$  in., and the heat flux may be measured within 1 percent. Calculate the accuracy necessary on the  $\Delta T$  measurement in

order to ensure an overall uncertainty in the measurement of k of 5 percent. If one of the piate temperatures is nominally 300°F, calculate the nominal value of the other plate temperature and the tolerable uncertainty in each temperature measurement, assuming a nominal heat flux of 20,000 BIO(hD)(ff)

Solution We use Eq. (9-2) to estimate the uncertainty in conjunction with Eq. (3-2)

$$k = \frac{(q/A)\Delta z}{\Delta T} \tag{a}$$

Equation (3-2) may be written as

$$\frac{\omega_R}{R} = \left[ \left( \frac{\partial R}{\partial z_1} \right)^t \left( \frac{w_1}{R} \right)^t + \left( \frac{\partial R}{\partial z_2} \right)^t \left( \frac{w_2}{R} \right)^t + \left( \frac{\partial R}{\partial z_2} \right)^t \left( \frac{w_2}{R} \right)^t \right]^{\frac{t}{2}}$$
(b)

We have

Inserting these expressions in Eq. (b) gives

$$0.05 = \left[ (0.01)^{s} + (0.002/0.125)^{s} + \left( \frac{w_{57}}{\Delta T} \right)^{3} \right]^{s}$$
or  $w_{37}/\Delta T = 0.0148 = 1.46$  percent.

We now calculate the nominal value of  $\Delta T$  as

$$\Delta T = \frac{(q/A) \Delta x}{\xi} = \frac{(2 \times 10^{\circ})(0.125)}{(12)(50)} = 4.1667^{\circ}F$$

Since  $\Delta T = T_1 - T_2$ , the nominal value of  $T_2$  is

The tolerable uncertainty in each temperature measurement is a multised

from

$$\frac{w_{\Delta T}}{\Delta T} = \left[ \left( \frac{\partial (\Delta T)}{\partial T_1} \frac{w_{T_1}}{\Delta T} \right)^2 + \left( \frac{\partial (\Delta T)}{\partial T_2} \frac{w_{T_1}}{\Delta T} \right)^2 \right]^{\frac{1}{2}}$$

$$w_{\Delta T} = (w_{T_1}^2 + w_{T_2}^2)^{\frac{1}{2}}$$

and we assume the uncertainties are the same for both temperatures so that

$$w_7 = \frac{1}{\sqrt{2}} w_{\Delta T} = 0.707 w_{\Delta T}$$
  
 $w_7 = (0.707)(0.0146)(4.1667) = \pm 0.043^{\circ} \text{F}$ 

We thus see that a very accurate measurement of temperature is necessary in order to give only a 5 percent accuracy in the determination of k.

#### Example 9-2

An apparatus like that in Fig. 9-3 is used to measure the thermal conductivity of the metal of Example 9-1. The same heat flux is used with a bar  $3.0 \pm 0.005$  in, long. Determine the accuracy necessary for the determination of  $\Delta T$  and the tolerable uncertainty in the temperature measurements. Assume the same conditions as in Example 9-1.

Solution. For a 5 percent uncertainty in k the uncertainty in  $\Delta T$  is given as

$$0.05 = \left[ (0.01)^2 + \left( \frac{0.005}{3.0} \right)^2 + \left( \frac{v_2 r}{\Delta T} \right)^2 \right]^{\frac{1}{4}}$$

$$\frac{v_4 r}{27} = 0.049 = 4.9\%$$

The nominal value of  $\Delta T$  is given as

$$\Delta T = \frac{(2 \times 10^{\circ})(3)}{(12)(50)} = 100^{\circ} F$$

The allowable uncertainty in the determination of the temperatures is

$$w_{\tau} = \frac{1}{\sqrt{2}} w_{\Delta \tau} = (0.707)(0.049)(100) = \pm 3.46^{\circ} F$$

This value is very easy to obtain. Even if the heat flux were reduced to  $2\times10^3$  Btu/(hr)(it²), the nominal temperature difference would be  $10^5$ F and the allowable uncertainty would be  $\pm0.346^5$ F. This is still a value which may be attained with careful experimental techniques.

#### 9-3 THERMAL CONDUCTIVITY OF LIQUIDS AND GASES

Kaye and Higgins [3] have used a guarded hot-plate method for determining thermal conductivity of fiquids. Their apparatus is shown in Fig. 9-4. The diameter of the plates is 5 cm, and the thickness of the liquid layer is approximately 0.05 cm. This layer must be sufficiently thin so that convection currents are minimized An annular arrangement as shown in Fig. 9-5 may also be used for the determination of liquid thermal conductivities. Again, the thickness of the liquid layer must be thin enough to minimize thermal-convection currents.

A concentra-cylinder arrangement may also be used for the measurement of the thermal conductivity of gases. Keyes and Sandeli [4] have used such a device for the measurement of thermal conductivity of water vapor, ox \$\text{gen}\$, untropen, and other gases. The inner and outer cylinders were both constructed of bit or suth a length of 5 in and an outside diameter of 14 in. The gip space for the gas was 0.025 in. Vines [7] has utilized such a device for the measurement of high-temperature gas thermal conductivities. A schematic of his apparatus is shown in Fig. 9-6. The cuntret serves as the heat source, while the heat stations on cuber end as tas guard heaters. The centret has an outside diameter of 6 una and a length heaters.




Fig. 5-4. Guarded het-plate apparatus for measurement af thermal conductivity of figuids, Ref. Di.




Fig. 9-5. Concentric-cylinder method for measurement of thermal conductivity of liquids.




Fig. 9-6. Apparatus for determining thermal conductivity of gases at high temperatures according to Vines [7].

of 50 mm, while the receiver has an invide diameter of 10 mm and a length of 125 mm with a wall thickness of 1 mm. For most of the tests it was possible to maintain a temperature difference of 5 to 10°C between the emitter and the receiver. The heat-transfer rate is measured by determining the electric-power input to the emitter, while thermocouples installed on the surface of the emitter and receiver determine the temperature differentiate the surface.

For the concentric-cylinder device the relation which is used to calculate the thermal conductivity is

$$k = \frac{q \ln (r_2/r_1)}{2\pi L(T_1 - T_2)}$$
(9-4)

where

g = heat-transfer rate

rs, rt = outside and inside radii of the annular space containing the fluid respectively

 $T_1$ ,  $T_1$  = temperatures measured at these radu

An investigation by Leidenfrost [8] proposes an apparatus for meauring thermal conductivities of gases and liquids from -180 to +500°C. Complete experimental data are not available, but accuracies of 0.1 percent are claimed for the device.

Thermal conductivities of several materials are given in the appendix.

#### 9-4 MEASUREMENT OF VISCOSITY

The defining equation for dynamic or absolute esecosity is

$$\tau = \mu \frac{du}{dv}$$
 (9-5)

where

τ = shear stress between fluid layers in laminar flow

 $\mu = viscosity$ 

du/dy = normal velocity gradient as indicated in Fig. 9-7

Various methods are employed for measurement of the viscosity. The two most common methods are the rotating concentric-cylinders method and the capillary-flow method. We shall discuss the rotating-cylinder method first




Fig. 9-7. Diagram indicating relation of viscosity to velocity gradient and fluid shear.

Consider the parallel plates as shown in Fig. 9-8. One plate is stationary, and the other moves with constant velocity u. The velocity profile for the fluid between the two plates is a straight line, and the velocity gradient is

$$\frac{du}{dv} = \frac{u}{b} \tag{9-6}$$

The system could be used to measure the viscosity by measuring the force required to maintain the moving plate at the constant velocity u. The system is impractical from a construction standpoint, however, and the conventional approach is to approximate the parallel flat-plate situation with the rotating concentric cylinders shown in Fig. 9-9. The inner cylinder is stationary and attached to an appropriate torque-measuring device, while the outer cylinder is driven at a constant angular velocity w. If the annular space b is sufficiently small in comparison with the radius of the inner cylinder, then the rotating-cylinder arrangement approximates the parallel-plate situation and the velocity profile in the gap space may be assumed to be linear. Then,

$$\frac{du}{dy} = \frac{r_{z\omega}}{b} \tag{9-7}$$




Fig. 9-8. Velocity distribution between large parallel plates.




Fig. 9-9. Rotating concentric-cylinder apparatus for measurement of viscosity.

where, now, the y distance is taken in the radial direction and it is assumed that  $b \ll r_1$ . Now, if the torque T is measured the fluid shear stress is expressed by

$$r = \frac{T}{2\pi r_s^2 L} \tag{9-8}$$

where L is the length of the cylinder. The viscosity is determined by combination of Eqs. (9-5), (9-7), and (9-8) to give

$$\mu = \frac{Tb}{2\pi r_1^2 r_1 L \omega} \qquad (9-9)$$

If the concentric-cylinder arrangement is constructed such that the gap space a is small, then the bottom disk will also contribute to the torque and influence the calculation of the viscosity. The torque on the bottom disk is

$$T_d = \frac{\mu r \omega}{2a} r_1^4 \tag{9-10}$$

where a is the gap spacing, as shown in Fig 9-9. Combining the torques due to the bottom disk and the annular space gives

$$T = \mu \pi \omega \tau_1^2 \left( \frac{r_1^2}{2a} + \frac{2L\tau_2}{b} \right) \tag{9-11}$$




Fig. 9-10. Laminar flow through a capillary tube.

Once the torque, angular velocity, and dimensions are measured, the viscosity may be calculated from Eq. (9-11).

Perhaps the most common method of viscosity measurement consists of a measurement of the pressure drop in laminar flow through a capillary tube. Consider the tube cross section shown in Fig. 9-10. If the Reynolds number defined by

$$Re_d = \frac{\rho u_m d}{\mu} \tag{9-12}$$

is less than 1,000, laminar flow will exist in the tube and the familiar parabolic-velocity profile will be experienced as shown. If the fluid is incompressible and the flow is steady, it can be shown that the volume rate of flow Q can be written as

$$Q = \frac{\pi r^4 (p_1 - p_2)}{8 \,\mu L} \tag{9-13}$$

A viscosity determination may be made by measuring the volume rate of flow and pressure drop for flow in such a tube. To ensure that laminar flow will exist, a small-diameter capillary tube is used; the small diameter reduces the Reynolds number as calculated from Eq. (9-12). In Eq. (9-12) the product  $\rho u_m$  may be calculated from

$$\rho u_m = \frac{\dot{m}}{\pi r^2} \tag{9-14}$$

where m is the mass rate of flow.

When a viscosity measurement is made on a gas, the compressibility of the gas must be taken into account. The resulting expression for the mass flow of the gas under laminar flow conditions in the

capillary is

$$m = \frac{\pi T^4}{16 \, \mu R T} (p_1^3 - p_2^3) \tag{9-15}$$

where R is the gas constant for the particular gas.

Care must be taken to ensure that the flow in the capillary is Ugaeveloped, i.e., the parabohe-velocity profile has been established. This means that the pressure measurements should be taken far enough downstream from the entrance of the tube to ensure that developed flow conditions persist. It may be expected that the flow will be fully developed when

$$\frac{L}{d} > \frac{\text{Re}_d}{8} \tag{9-16}$$

where L is the distance from the entrance of the tube.

The Saybolt viscosimeter is an industrial device which uses the capillary-tube principle for measurement of viscosities of injudic. A schematic of the device is shown in Fig. 9-11. A cylinder is filled to the top with the liquid and enclosed in a constant-tem-




Fig. 9-11. Schematic of the Sayboit viscosimeter.

perature bath to ensure uniformity of temperature during the measurements. The liquid is then allowed to drain from the bottom through the short capillary tube. The time necessary for 60 cc to drain is recorded, and this time is taken as indicative of the viscosity of the liquid. Since the capillary tube is short, a fully developed laminar velocity profile is not established and it is necessary to apply a correction to account for the actual profile. If the velocity profile were fully developed, the kinematic viscosity would vary directly with the time for drainage, i.e.,

$$\nu = \frac{\mu}{p} = c_1 t$$

To correct for the nonuniform velocity profile, another term is added to give

$$v=c_1t+\frac{c_2}{t}$$

With the constants inserted the relation is

$$\nu = \left(0.00237t - \frac{1.93}{t}\right) \times 10^{-3}$$
 ft²/sec (9-17)

The symbol t designates the drainage time in seconds for 60 cc of liquid, and it is common to express the viscosity in units of Saybolt seconds when this method of measurement is used. Equation (9-17) provides a method of converting to more explicit units for kinematic viscosity. Viscosities for several fluids are given in the Appendix.

## Example 9-3

A Saybolt viscosimeter is used to measure the viscosity of a certain motor oil. The time recorded for drainage of 60 cc is estimated at  $183 \pm 0.5$  sec. Calculate the percentage uncertainty in the viscosity.

Solution. Equation (3-2) is used in conjunction with Eq. (9-17) to estimate the uncertainty. We have

$$\frac{\partial \nu}{\partial t} = c_1 - \frac{c_2}{t^2} = \left(0.00237 + \frac{1.93}{t^2}\right) \times 10^{-1}$$

so that the uncertainty in the viscosity is given as

$$w_r = \frac{\partial v}{\partial t} w_r$$
  
=  $\left(0.00237 + \frac{1.93}{t^3}\right) (10^{-1})(0.5)$  ft²/eec

The nominal value of the viscosity is

$$\nu = \left(0.00237t - \frac{1.93}{1}\right)10^{-3} \quad \text{ft}^2/\text{sec}$$

At t = 183 sec

$$w_r = 1.21 \times 10^{-4}$$
 ft²/sec  
 $v = 4.22 \times 10^{-4}$  ft²/sec

#### 9-5 GAS DIFFUSION

Consider a container of a certain gas (2) as shown in Fig. 9-12. At one end of the container another gas (1) is introduced and allowed to diffuse into gas (2). The diffusion rate of gas (1) at any instant of time is given by Fick's law of diffusion as

$$n_1 = -D_{12}A \frac{\partial \hat{N}_1}{\partial x_2}$$
(9-18)

where  $n_1$  is the molal rate of diffusion, A is the cross-sectional area for diffusion,  $N_1$  is the molal concentration of component 1 at any point, and  $D_{11}$  is defined as the diffusion coefficient. It may be noted that Eq. (0-18) is similar to the Fourier law for heat conductions.



Fig. 9-12. Schematic of gas-diffusion proce-

duction. When a mass balance is made on an element, the one-dimensional diffusion equation results.

$$\frac{\partial \bar{N}_1}{\partial t} = D_{12} \frac{\partial^2 \bar{N}_1}{\partial x^2} \tag{9-19}$$

A solution to this equation may be used as the basis for an experimental determination of the diffusion coefficient  $D_{12}$ .

A simple experimental setup for the measurement of gasdiffusion coefficients is shown in Fig. 9-13. Two sections of glass tubing are connected by a flexible Tygon tubing connection which may be clamped as shown. The sections of tubing are charged with the two gases whose diffusion characteristics are to be investigated. After the initial charging process, the flexible connection is opened and the two gases are allowed to diffuse into one another. After a period of time the Tygon connection is closed again, the exact time recorded, and the two sections allowed to reach equilibrium concentrations. These equilibrium concentrations are then measured with appropriate analytical equipment. It is only necessary to measure the concentration of one of the gases in both sections since the concentration of the other gas will be obtained from a mole balance. However, measuring both gives a check and information about the accuracy of the experiment. Some check of this kind is always very desirable, although not always feasible.

A solution of Eq. (9-19) gives these concentrations in terms of the diffusion coefficient and dimensions of the tubes. Assuming that the lower portion is filled with gas (1) and the upper portion with gas (2) initially, the solution is

$$F = \frac{N_{1A} - N_{1B}}{N_{1A} + N_{1B}} = \frac{8}{\pi^2} \sum_{k=0} \frac{1}{(2k+1)^2} \exp\left[\frac{-\pi^2 D_{12} t (2k+1)^2}{4L^2}\right]$$
(9-20)

where the subscripts A and B refer to the lower and upper sections respectively, t is the time the two gases are allowed to diffuse, and L is the length of each tube.  $N_{1A}$  and  $N_{1B}$  represent the number of moles of component 1 in the lower and upper parts of the apparatus, respectively, after time t. For an experimental determination of  $D_{12}$  the optimum time to be allowed for the diffusion process is

$$t_{\rm opt} = \frac{4L^2}{\pi^2 D_{12}} \tag{9-21}$$

assuming that the only experimental errors are those involved in the determination of F. If the diffusion process is allowed to run for




Fig. 9-13. Loschmidt apparatus for measurement of diffusion coefficients in gases. (a) Apparatus; (b) detail of fiesible connection.

t_{opt} or longer, it is found that the first term in the series of Eq. (9-20) is the primary term and that the higher order terms are negligible. Then,

$$F = 0.2982$$
 at  $t = t_{out}$  (9-22)

If the second and higher order terms are neglected, it is easy to calculate the value of  $D_{12}$  once a determination of F and t have been made. Neglecting these higher order terms gives

$$F = \frac{8}{\pi^2} \exp \frac{-\pi^2 D_{12} t}{4L^2} \tag{9-23}$$

OL

$$D_{12} = \frac{-4L^2}{\pi^2 l} \ln \frac{\pi^2 F}{8} \tag{9-24}$$

It is necessary to know only an approximate value for  $D_{12}$  in order to calculate the value of  $t_{\rm opt}$  from Eq. (9-21). Then, the experiment is conducted using a diffusion time greater than this value. The exact value of  $D_{12}$  is then calculated from the experimental data using Eq. (9-24).

The simple experimental setup shown in Fig. 9-13 is called a Loschmidt apparatus. In the apparatus the heavier gas is usually contained in the lower section, while the lighter gas is placed in the upper section. Extreme care must be exerted to ensure that the system is free of leaks and that each section contains a pure component at the start of the experiment. Care must also be exerted to ensure that both gases are initially at the same temperature and pressure. The apparatus should be constructed so that the volume of the inlet tubing is negligible in comparison with the volume of the main apparatus. While the diffusion process is in progress, the temperature of the apparatus should be maintained constant. Diffusion coefficients for several gases are given in the Appendix.

## Example 9-4

An apparatus like that shown in Fig. 9-13 is constructed so that L=50 cm. CO₂ is placed in the lower tube and air in the upper tube. Both gases are at standard atmospheric pressure and 77°F. The diffusion coefficient for CO₂ in air is 0.164 cm²/sec. Calculate the mole fraction of CO₂ in each tube for (1) 5 min and (2) 2 hr after the connection between the tubes is opened.

Solution. The mole fractions are given be

$$x_{14} = \frac{N_{14}}{N_{16}} \qquad x_{17} = \frac{N_{14}}{N_{16}}$$

where  $N_{th}$  is the initial number of moles in each tube and e peak to  $\lambda_{th}$  is  $N_{th}$ . Gas I is the CO₂ in this case. From Eq. (9.79),

$$F \approx x_{14} - x_{18} \tag{4}$$

We calculate the optimum time as

$$I_{mei} = \frac{(4)(50)^2}{\pi^2(0.164)} = 6.180 \text{ sec}$$

The 5-min condition is far short of this so that the series solution of by (9-20) must be used to find F. Thus, with t = 300 ms.

$$F = \frac{3}{\pi^2} \left\{ e^{-10046 \cos t \cdot \theta} + \frac{1}{4} e^{-10046 \cos t \cdot \theta} + \frac{1}{4} e^{-10046 \cos t \cdot \theta} \right\}$$

$$= \frac{3}{\pi^2} \left( 0.9528 + 0.0718 + 0.0119 + \dots \right)$$

$$= 0.8400$$

Using Eq. (a) and

$$z_{14} + z_{12} = 1.0$$

gives  $z_{1A} = 0.92$  and  $z_{10} = 0.04$ For the 2-hr time, t = (2/(3/900) = 7.200 are, and only the tree in its series need be used. Thus, from Eq. (9.23).

Again, using Eqe (a) and (b) gives

#### 9-6 CALORIMETRY

The subject of ententionary to concerned with a decrease of the energy quantities. These quantities way he wise and a some




Fig. 9-14. Schematic of the Junkers flow calorimeter.

of the thermodynamic properties of a system, such as enthalpy, internal energy, specific heat, and heating value, or in terms of energy flow which results from a transport of mass across the boundaries of the thermodynamic system. Calorimetry is a very broad subject covering a majority of the experimental determinations which are used for measurement of thermodynamic properties. We shall give an example of calorimetry which shows the overall features of energy and mass balances and their importance; this is the flow calorimeter which is used for the measurement of heating values of gaseous or liquid fuels. The actual device which is usually used for the experiment is called the Junkers calorimeter. A schematic of the calorimeter is given in Fig. 9-14. The gaseous

fuel is burned inside the calorimeter where it gives up heat to the cooling water. The water flow rate is determined by weighing, and the inlet and outlet water temperatures are ineversed with precision mercury-in-glass thermometers as shown. The products of combustion are cooled to a sufficiently low temperature to that water vapor is condensed. This condensate is collected in the graduated flack as shown. The gas flow rate is usually measured with a positive-deplacement flowmeter. A detailed description of the calorimeter is given by Shoop and Tive [5], and the interested reader should consult their discussion for procedural information. We shall discuss the system in a general way and indicate an analysis which may be performed to determine the heating value of the fuel.

The flow schematic for the flow calonmeter is shown in Fig 9-15. For convenience, all streams entering the device are designated with the subscript 1, while all streams leaving the device are designated with the subscript 2. The fuel and air are burned inside the calonmeter, and the major portion of the heat of combustion is removed by the cooling water.

The following experimental measurements are made: the indeand exit cooling water temperatures T_n and T_n, the mass flow rate of fuel m_t, the mass flow rate of cooling water m_n, the condensate temperature T_n, the entering fuel and air temperatures T_t, and T_n, and the relative humidity of the inlet are is In addition, an analysis of the products of combustion is made to determine the crygen, earbon dioxide, and carbon monouse routent. From all these data, mass and energy balances may be made to determine the heating value of the fuel. Let us consider the simple case of the combustion of methanc Cfd. We write the chemical balance




Fig. 9-15. Flow schematic for calorimeter of Fig. 9-14.

equation as

$$aCH_4 + xO_2 + 3.76xN_2 + bH_2O$$
  
 $\rightarrow dCO_2 + eCO + fO_2 + gH_2O + 3.76xN_2$  (9-25)

An analysis of the products gives the values of d, e, and f for 100 moles of dry products. The mass balance then becomes

Carbon

$$a = d + e (9-26)$$

Hydrogen

$$4a + 2b = 2g \tag{9-27}$$

Oxygen

$$2x + b = 2d + e + 2f + g (9-28)$$

Equation (9-26) permits an immediate determination of a. The relative humidity of the incoming air  $\phi_1$  gives a relationship for b as

$$\frac{b}{4.76x} = \frac{p_{s_1}\phi_1}{p_1 - \phi_1 p_{s_1}} \tag{9-29}$$

where  $p_{q_1}$  is the saturation pressure of water vapor at the inlet air temperature and  $p_1$  is the total pressure of the incoming air-water-vapor mixture. We thus have three unknowns (b, g, and x) and three equations [(9-27) to (9-29)] which may be solved for the unknowns. With the mass balance now complete an energy balance may be made to determine the chemical energy constant of the incoming fuel. We observe that

$$\dot{m}_{f_1} = 16a$$
  $\dot{m}_{s_1} = 32x + (28)(3.76x)$   
 $\dot{m}_{\tau_1} = 18b$ 

The water vapor in the products of combustion is calculated from

$$\dot{m}_{\tau_1} = 18g - \dot{m}_{\epsilon} \tag{9-30}$$

The energy balance becomes

$$\dot{m}_{f_1}(h_{f_1} + E_{f_1}) + \dot{m}_{e_1}h_{e_1} + \dot{m}_{e_1}h_{e_1} - \dot{m}_{e_2}h_{e_2} - \dot{m}_{e_2}h_{e_3} = \dot{m}_{e_2}(h_{e_1} - h_{e_3})$$
(9-31)

where  $E_{f_1}$  is designated as the chemical energy of the fuel. The energy term for the products  $m_p h_{g_1}$  is calculated from the energies of the individual constituents. Thus

$$m_s h_{r_s} = m_{co} h_{co}$$
,  $+ m_{co} h_{co} + m_o h_o$ ,  $+ m_s h_s$ ,  $+ m_s h_s$ , (9-32)

The mass flow rate of these constituents is determined from the balance conditions in Eqs. (9-27) to (9-29).

The purpose of the above discussion is to illustrate the number of experimental measurements which must be made in even a simple calorimetric determination like the one shown and the fact that all




Fig. 3-16. Schematic of the nonflow bomb calorimeter.

these measurements influence the accuracy of the final result. Of course, the calculated value of heating value (or chemical energy content) will be more sensitive to some measurements than others. For details on the measurement techniques the reader should consult Ref. [5]. It may be noted that standardized procedures are available for this particular test which make it unnecessary to perform all of the analysis indicated above; nevertheless, this analysis indicates the theory behind the measurement process.

The bomb calorimeter is another device which is frequently used for heating-value determinations in solid and liquid fuels. In contrast to the flow calorimeter described above, the measurements are made under constant-volume, nonflow conditions as shown in Fig. 9-16. A measured sample of the fuel is enclosed in a metal container which is subsequently charged with oxygen at high pressure. The bomb is then placed in a container of water and the fuel ignited through external electric connections. The temperature of the water is measured as a function of time after the ignition process: and from a knowledge of the mass of water in the system, mass and specific heat of the container, and transient heating and cooling curves, the energy release during combustion may be determined. A motor-driven stirrer ensures uniformity in temperature of the water surrounding the bomb. In some circumstances external heating may be supplied to the jacket water to maintain a uniform temperature, while in other instances the jacket may be left empty in order to maintain nearly adiabatic conditions on the inner water container. A compensation for the heat lost to the environment may be made through an analysis of the transient heating and cooling curve. Doolittle [1] gives detailed procedures for use of the bomb calorimeter, and the interested reader should consult this reference for more information.

# 9-7 CONVECTION HEAT-TRANSFER MEASUREMENTS

Determinations of convection heat-transfer coefficients cover a very broad range of experimental activities. In this section we shall illustrate only two simple experimental setups: one for a forced-convection system and one for a free-convection system. The interested reader should consult Ref. [2] for more information.

Consider the experimental setup shown in Fig. 9-17. It is desired to obtain convection heat-transfer coefficients for the flow of water in a smooth tube. Heat is supplied to the tube by electric heating as shown. The tube is usually made of a high-resistance




Fig. 9-27. Schematic of apparatus for determination of forced-convection heat-tramfer coefficients in smooth tubes.

material like stainless steel to reduce the electric current inscessing for heating. The measure upon which of or connected to the outside surface of the tube to measure the wall temperature. Little thermocouples or the momenters are inserted in the flow to measure the water temperature at milet and outlet to the heated section. A voltimeter and ammeter measures the power input to the tube, while some type of flowmeter measures the water-flow rate. The electrically heated tube delivers a constain heat flux to the water (sonstain Bluy/(hr)(ft*) of tube surface) so that it is reasonable to assume a straight-line variation of water bulk temperature from milet to outlet. Thus the wall and bulk temperatures are known along the length of the tube, and the heat-transfer coefficient may be calculated at any axis location from.

$$q = hA(T_w - T_B) \tag{9-33}$$

where A is the total inside-heated surface area of the tube,  $T_{\sigma}$  and  $T_B$  are the wall and bulk temperatures at the particular location, and q is the total heat-transfer rate given by

$$q = EI (9-34)$$

E and I are the voltage and current impressed on the test section. The heated surface area is

$$A = \tau d_i L \qquad (9-35)$$

The outside surface of the tube must be covered with insulation to ensure that all the electric heating is dissipated in the water

## PROBLEMS

9-1 The following data are taken from Ref. [6] on an apparatus like that shown in Fig. 9-3. The measurements were made on a lead sample whose thermal conductivity is taken to be 0.352 watt/cm-°C at 0°C.

Thermocouple positions	Temperature,	Dielance between adjacent thermocouples, cm		
1	277.3	3.14		
2	231.6	3.14		
3	186.5	3.14		
4	143 0	3.15		
5	100.3			
6	78.6	3.16		
7	37.3			

Using these data construct a graph of the thermal conductivity of lead versus temperature.

- 9-2 The apparatus of Fig. 9-3 is used for measurement of the thermal conductivity of an unknown metal. The lengths of the unknown and known bars are the same, and five thermocouples are equally spaced on each bar. From the temperature and heat flux measurements the thermal conductivity of the unknown is to be established as a function of temperature. Design the apparatus to measure the thermal conductivity of a material, with  $k \sim 100 \, \text{Btu/(hr)(ft)(°F)}$ . Consider the influence of thermocouple spacing, dimensions of the bars, heat flux measurement, and temperature measurement on accuracy. Take the thermal conductivity of the known material as exactly 20  $\, \text{Btu/(hr)(ft)(°F)}$ .
- 9-3 A concentric-cylinder device like that in Fig. 9-5 is used for a measurement of the thermal conductivity of water at 100°F. Using the dimensions given in the text, discuss the influence of the heat flux and temperature measurements on the accuracy of the thermal-conductivity determination.
- 9.4 The viscosity of water is  $1.65 \text{ lb}_m/\text{hr}$ -ft at  $100^\circ \text{F}$ . A small capillary tube  $50 \pm 0.01$  ft long is to be used to check this value. Calculate the maximum allowable flow rate for an inside tube diameter of  $0.100 \pm 0.001$  in. Calculate the pressure drop for this flow rate, and estimate the allowable uncertainty in the pressure drop in order that the uncertainty in the

viscosity does not exceed 5 percent. Assume that the flow rate is measured within ±001 lb_m/hr.

- 9.5 The rotating concentric-tylinder apparatus of Fig. 9-9 is used to measure the viscosity of water at 100°F. The inner cylinder radius is 1.50 ± 0.001 in., and its lengthis 4 00 ± 0.002 in. The outer cylinder is rotated at a speed of 1,800 ± 2 rpm. The outer cylinder diameter is 1.60 ± 0.001 in., and the gap spacing at the bottom of the cylinder is 0.500 ± 0.005 in. Calculate the nominal torque which will be measured, and estimate the allowable uncertainty in this measurement in order that the overall uncertainty in the viscosity does not exceed 5 percent. Repeat the calculation for glycerine at 100°F.
- 9-6 The tolerance limits on the radii of the inner and outer cylinders of Fig. 9-9 exert a strong influence on the accuracy of the viscosity measurement. Establish a relation expressing the percent uncertainty in the viscosity measurement as a function of the uncertainty in these radius measurements. Assume that the torque, angular velocity, and bottom-epacing measurements are exact for this calculation. Assume that the uncertainty (tolerance) is the same for both cylinder.
- 9-7 The viscosity of a gas is to be determined by measuring the flow rate and pressure drop through a capillary tube. The experimental variables which are measured are.

Inlet pressure  $p_1$ Pressure differential  $\Delta p = p_1 - p_2$ Temperature TMass flow rate mTube diameter d = 2r

Derive an expression for the percent uncertainty in the viscosity measurement in terms of the uncertainties in these five primary measurements. In view of the information in Chaps 5 to 8 discuss the relative influence of each of the measurements, i.e., which primary measurement will probably have the most effect on the final estimated uncertainty in the viscosity.

- 9-8 The viscosity of an oil having a density of 51.9 ib_/ft¹ is measured as 200 Saybolt sec. Determine the dynamic viscosity in units of centipoise and ib_/hr-ft
- 9.9 A Loschmidt apparatus is used to measure the diffusion coefficient for benzene in air. At 25°C the diffusion coefficient is

0.088 cm²/sec for a pressure of 1 standard atmosphere. Both tubes have a length of 60 cm. Calculate the mole fraction of benzene in each tube 10 min and 3 hr after the connection between the tubes is opened.

- 9-10 A Loschmidt apparatus with L=50 cm is used to measure the diffusion coefficient for  $CO_2$  in air. After a time of 6.52 min the mole fraction of  $CO_2$  in the upper tube is 0.0912. Calculate the value of the diffusion coefficient.
- 9-11 For  $t = t_{\text{opt}}$ , calculate the relative magnitudes of the first four terms in the series expansion of Eq. (9-20). Repeat for  $t = \frac{1}{2}t_{\text{opt}}$  and  $t = 2t_{\text{opt}}$ .
- 9-12 Obtain a simplified expression for the heating value of methane as measured with a flow calorimeter with the following conditions:

$$T_{a_1} = T_{f_1} = T_{p_2} = T_{c_2}$$
  $\phi_1 = 0$ 

The incoming gaseous fuel is saturated with water vapor.

9-13 Design an apparatus like that shown in Fig. 9-17 to measure forced-convection heat-transfer coefficients for water at about 200°F in a range of Reynolds numbers from 50,000 to 100,000 based on tube diameter, i.e.,

$$Re_d = \frac{\rho u_m d}{\mu}$$

where  $u_m$  is the mean flow velocity in the tube. Be sure to specify the accuracy and range of all instruments required and estimate the uncertainty in the calculated values of the heat-transfer coefficients.

9-14 Design an apparatus like that shown in Fig. 9-18 to measure free-convection heat-transfor coefficients for air at atmospheric pressure and ambient temperature of 70°F. The apparatus is to produce data over a range of Grashof numbers from 10° to 10° where

Grashof number = Gr = 
$$\frac{\rho^2 g \beta (T_w - T_\infty) d^3}{\mu^2}$$

where

 $\beta$  = volume coefficient of expansion for air

d =tube diameter

 $T_w =$ tube surface temperature

 $T_{\infty}$  = ambient air temperature

The properties of the air are craiment at the time to continue defined by (see Table \$-5)

$$T_f = \frac{T_0 + T_0}{2}$$

The Grashof number is dimensionless when a consistent set of units is used. Be sure to specify the accuracy and range of all instruments used and estimate the uncertainty in the calculated values of the heat-transfer coefficient.

#### REFERENCES

- Doolittle, J. S.: "Mechanical Engineering Laboratory," McGraw-Hill Book Company, New York, 1957.
- Jakob, M.; "Hest Transfer," vol I, John Wiley & Sons, Inc., New York, 1949.
- Kaye, G. W. C., and W. F. Higgins The Thermal Conductivities of Certain Liquids, Proc. Roy. Soc. London, vol. 117, no. 459, 1928
- Keyes, F. G., and D. J. Sandell. New Measurements of Heat Conductivity of Steam and Nitrogen, Trans. ASME, vol. 72, p. 768, 1950
- Shoop, C. F., and G. L. Tuve: "Mechanical Engineering Practice," 5th ed., McGraw-Hill Book Company, New York, 1956.
- Van Dusen, M. S., and S. M. Sheiton: Apparatus for Measuring Thermal Conductivity of Metals up to 600°C, J. Res. Natl. Bur. Std., vol 12, no. 429, 1934.
- Vines, R. G: Measurements of Thermal Conductivities of Gases at High Temperatures, Trans. ASME, vol. 82C, p 48, 1960.
- Leidenfrost, W.: An Attempt to Measure the Thermal Conductivity of Liquids, Gases and Vapors with a High Degree of Accuracy over Wide Ranges of Temperature and Pressure, Intern. J. Heat and Mass Transfer, vol. 7, no. 4, pp 447-476, 1964.

0.088 cm²/sec for a pressure of 1 standard atmosphere. Both tubes have a length of 60 cm. Calculate the mole fraction of benzene in each tube 10 min and 3 hr after the connection between the tubes is opened.

- 9-10 A Loschmidt apparatus with L=50 cm is used to measure the diffusion coefficient for  $CO_2$  in air. After a time of 6.52 min the mole fraction of  $CO_2$  in the upper tube is 0.0912. Calculate the value of the diffusion coefficient.
- 9-11 For  $t = t_{opt}$ , calculate the relative magnitudes of the first four terms in the series expansion of Eq. (9-20). Repeat for  $t = \frac{1}{2}t_{opt}$  and  $t = 2t_{opt}$ .
- 9-12 Obtain a simplified expression for the heating value of methane as measured with a flow calorimeter with the following conditions:

$$T_{a_1} = T_{f_1} = T_{g_2} = T_{g_2} \qquad \phi_1 = 0$$

The incoming gaseous fuel is saturated with water vapor.

9-13 Design an apparatus like that shown in Fig. 9-17 to measure forced-convection heat-transfer coefficients for water at about 200°F in a range of Reynolds numbers from 50,000 to 100,000 based on tube diameter, i.e.,

$$Re_d = \frac{\rho u_m d}{\mu}$$

where  $u_m$  is the mean flow velocity in the tube. Be sure to specify the accuracy and range of all instruments required and estimate the uncertainty in the calculated values of the heat-transfer coefficients.

9-14 Design an apparatus like that shown in Fig. 9-18 to measure free-convection heat-transfor coefficients for air at atmospheric pressure and ambient temperature of 70°F. The apparatus is to produce data over a range of Grashof numbers from 105 to 107 where

Grashof number = 
$$Gr = \frac{\rho^2 g \beta (T_w - T_\infty) d^3}{\mu^2}$$

where

 $\beta$  = volume coefficient of expansion for air

d =tube diameter

 $T_w =$ tube surface temperature

 $T_{\infty}$  = ambient air temperature

The properties of the air are evaluated at the film temperature defined by (see Table 8-5)

$$T_f = \frac{T_* + T_*}{2}$$

The Grashof number is dimensionless when a consistent set of units is used. Be sure to specify the accuracy and range of all instruments used and estimate the uncertainty in the calculated values of the heatetranter coefficient.

#### REFERENCES

- Doolittle, J. S. "Mechanical Engineering Laboratory," McGraw-Hill Book Company, New York, 1957.
- Jakob, M., "Heat Transfer," vol. 1, John Wiley & Sons, Inc., New York, 1949
- Kaye, G. W C., and W. F Higgins The Thermal Conductivities of Certain Liquids, Proc. Roy Soc. London, vol. 117, no. 459, 1928.
- Keyes, F. G., and D. J. Sandell. New Measurements of Heat Conductivity of Steam and Nitrogen, Trans. ASME, vol. 72, p. 768, 1950.
- Shoop, C. F., and G. L. Tuve: "Mechanical Engineering Practice," 5th ed., McGraw-Hill Book Company, New York, 1958
- Van Dusen, M. S., and S. M. Shelton. Apparatus for Measuring Thermal Conductivity of Metals up to 600°C, J. Res. Natl. Bur. Sid., vol. 12, no. 429, 1934.
- Vines, R. G.: Measurements of Thermal Conductivities of Gases at High Temperatures, Trans. ASME, vol. 82C, p. 48, 1960
- Leidenfrost, W.: An Attempt to Measure the Thermal Conductivity of Liquids, Gases and Vapors with a fligh Degree of Accuracy over Wide Ranges of Temperature and Pressure, Intern. J. Heat and Mass Transfer, vol. 7, no. 4, pp. 447–476, 1964.

## Force, torque, and strain measurements

#### 10-1 INTRODUCTION

Some types of force measurements applicable to pressure-ensing devices have been discussed in Chap 6 We now wish to consider other methods for measuring forces and torques and relate these methods to basic strain measurements and experimental stress analysis.

Force is represented mathematically as a vector with a point of application. Physically, it is a directed push or pull. According to Newton's second law of motion, as written for a particle of constant mass, force is proportional to the product of mass and acceleration Thus,

$$F = \frac{1}{g_s} ma \tag{10-1}$$

where the  $1/\rho_c$  term is the proportionality constant. When force is expressed in lib, mass in  $\mathrm{lb_c}$  and acceleration in  $\mathrm{tf/sec}^2$ ,  $\rho_c$  has the value of  $32.1739~\mathrm{lb_m}$ - $\mathrm{tf/lb_c}$ -sec² and is numerically equal to the acceleration of gravity at sea level. The weight of a body is the force exerted on the body by the acceleration of gravity so that

$$F = W = \frac{mg}{g_s} \tag{10-2}$$

At sea level, the weight in lb, units is numerically equal to the mass in  $lb_m$  units.

Torque is represented as a moment vector formed by the cross product of a force and radius vector. In Fig. 10-1 the torque which




Fig. 10-1. Vector representation for torque.

the force F exerts about the point 0 is given mathematically as

$$T = r \times F = |r||F| \sin \theta \tag{10-3}$$

Mass represents a quantity of matter and is an inertial property related to force through Eq. (10-1). As such, mass is not a physical property which is measured directly; it is determined through a force measurement or by comparison with mass standards. Even with a comparison of two masses, as with a simple balance, a force equivalency is still involved.

In this chapter we shall be concerned with force measurements as related to mechanical systems. Forces arising from electrical and magnetic effects are not considered.

## **10-2 MASS BALANCE MEASUREMENTS**

Consider the schematic of an analytical balance as shown in Fig. 10-2. The balance arm rotates about the fulcrum at point 0 (usually a knife edge) and is shown in an unbalanced position as indicated by the angle  $\phi$ . Point G represents the center of gravity of the arm, and  $d_G$  is the distance from 0 to this point.  $W_B$  is the weight of the balance arm and pointer. When  $W_1 = W_2$ ,  $\phi$  will be zero and the weight of the balance arms will not influence the measurements. The sensitivity of the balance is a measure of the angular displacement  $\phi$  per unit unbalance in the two weights  $W_1$  and  $W_2$ . Expressed analytically this relation is

$$S = \frac{\phi}{W_1 - W_2} = \frac{\phi}{\Delta W} \tag{10-4}$$

We now wish to determine the functional dependence of this sensitivity on the physical size and mass of the balance. According to Fig. 10-2 the moment equation for equilibrium is

$$W_1(L\cos\phi - d_B\sin\phi) = W_2(L\cos\phi + d_B\sin\phi) + W_Bd_G\sin\phi$$

For small deflection angles  $\sin\phi\approx\phi$  and  $\cos\phi\sim1.0$  so that Eq. (10-5) becomes

$$W_1(L - d_B\phi) = W_2(L + d_B\phi) + W_B d_B\phi$$

or

$$\frac{\phi}{\Delta W} = \frac{L}{(W_1 + W_2)d_R + W_R d_Q}$$
(10-6)

Near equilibrium,  $W_1 \approx W_2$  and S becomes

$$S = \frac{\phi}{\Delta W} = \frac{L}{Weda + 2Wds}$$
 (10-7)

where, now, we have used the single symbol W to designate the loading on the balance. If the balance arm is constructed so that  $d_B = 0$ , we obtain

$$S = \frac{L}{W_B d_g}$$
 (10-8)




Fig. 10-2. Schematic of analytical belance.

an expression which is independent of the loading of the balance. Precision balances are available which have an accuracy of about 1 part in 10°. For precision instruments optical methods are usually employed to sense the deflection angle and determine the equilibrium position.

## Example 10-1

A balance is constructed with the following dimensions:

$$W_B = 50 \text{ g}$$

$$d_G = 0.3 \text{ cm}$$

$$L = 21.2 \text{ cm}$$

$$d_B = 0.01 \text{ cm}$$

The pointer scale is graduated so that readings may be taken within onequarter of a degree. Estimate the uncertainty due to sensitivity in determining the weight of a mass of 1,000 g. It may be noted that other uncertainties exist in the measurement, such as frictional effects, errors in reading, etc.

Solution. From Eq. (10-7) we have

$$S = \frac{\phi}{\Delta W} = \frac{L}{2Wd_B + W_E d_G}$$
$$= \frac{21.2}{(2)(1000)(0.01) + (50)(0.3)} = 0.606 \text{ rad/g}$$

For an uncertainty in  $\phi$  of 0.25° the uncertainty in W is then given by

$$\Delta W = \frac{\phi}{S} = \frac{0.25\pi}{(180)(0.606)} = 0.0072 \text{ g}$$

or about 1 part in 100,000.

When a balance is used for mass determinations, considerable errors may result if corrections are not made for buoyancy forces of the air surrounding the samples. Typically, an unknown mass is balanced with a group of standard brass weights. The forces which the instrument senses are not the weight forces of the unknown mass and brass weights but the weight forces less the buoyancy force on each mass. If the measurement is conducted in a vacuum or the unknown brass and mass weights have equal volume, the buoyancy forces will cancel out and there will be no error. Otherwise, the error may be corrected with the following analysis. The two forces

exerted on the balance arms will be

$$W_1 = (\rho_* - \rho_*)V_* \tag{10-9}$$

$$W_b = (\rho_s - \rho_b)V_s$$
 (10-10)

where

ρ_u = density of the unknown

ρ_s = density of the standard weights
 ρ_s = density of the surrounding air

 $V_u$ ,  $V_r = \text{volumes}$  of the unknown and standard weights

The true weights of the unknown and standard weights are

$$W_n \approx \rho_n V_n$$
 (10-11)

$$W_{\bullet} = \rho_{\bullet} V_{\bullet}$$
 (10-12)

At balance II'1 = IV, and there results

$$W_{\bullet} = W_{\bullet} \left(1 + \frac{\rho_{\bullet}}{\rho_{\bullet}} \frac{\rho_{\bullet} - \rho_{\bullet}}{\rho_{\bullet} - \rho_{\bullet}}\right)$$
(10-13)

#### Example 10-2

A quantity of a plastic maternal having a density of about 80 lb.//lt is weighed on a standard equal-arm balance. Balance conditions are achieved with brast weights totaling 132 g in a room where the ambient air is at 70°F and 14°7 psis. The density of the brass wrights may be taken as 50 lb.//lt. Calculate the true weight of the plastic material and the percent error which would result if the balance reading were taken without correction.

Solution. The true weight of the brass weights is 152 g. The density of the air may be calculated as

$$\rho_s = \frac{p}{RT} = \frac{(14.7)(144)}{(53.35)(530)} = 0.0749 \text{ lb}_{-}/\text{ft}^*$$

The true weight of the plastic is then calculated from Eq. (10-13) as

$$W_u = 153 \left( 1 + \frac{0.0749}{530} \frac{530 - 80}{80 - 0.0749} \right)$$
  
= 153.21

The error is 1.21/152 × 100 or 0 795 percent

# 10-3 ELASTIC ELEMENTS FOR FORCE MEASUREMENTS

Elastic elements are frequently employed to furnish an indication of the magnitude of an applied force through a displacement measurement. The simple spring is an example of this type of force-displacement transducer. In this case the force is given by

$$F = ky (10-14)$$

where k is the spring constant and y is the displacement from the equilibrium position. For the simple bar shown in Fig. 10-3 the force is given by

$$F = \frac{AE}{L}y \tag{10-15}$$

where

A = cross-sectional area

L = length

E =Young's modulus for the bar material

The deflection of the cantilever beam shown in Fig. 10-4 is related to the loading force by

$$F = \frac{3EI}{L^2}y\tag{10-16}$$

where I is the moment of inertia of the beam. Any one of the three devices mentioned above is suitable for use as a force transducer provided that accurate means are available for indicating the displacements. The differential transformer (Sec. 4-13), for example,




Fig. 10-3. Simple clastic element.



Fig. 10-4. Cantilerer elastic elament.



Fig. 16-5. Thin-ring elastic element.




Fig. 15-6. Proving rin

may be useful for measurement of these displacements, as well as capacitance and piezoelectric transducers (Secs. 4-14 and 4-15).

Another elastic device frequently employed for force measurements is the thin ring shown in Fig. 10-5. The force deflection relation for this type of elastic element is

$$F = \frac{16}{\pi/2 - 4/\pi} \frac{EI}{d^3} y \tag{10-17}$$

where d is the outside ring diameter and I is the moment of inertia about the centroidal axis of the ring section. The proving ring is a ring transducer which employs a sensitive micrometer for the deflection measurement, as shown in Fig. 10-6. To obtain a precise measurement, one edge of the micrometer is mounted on a vibrating-reed device R which is plucked to obtain a vibratory motion. The micrometer contact is then moved forward until a noticeable damping of the vibration is observed. Deflection measurements may be made within  $\pm 0.00002$  in. with this method. The proving ring is widely used as a calibration standard for large tensile-testing machines.

## Example 10-3

A small cantilever beam is constructed of spring steel having  $E=28.3\times10^6$  psi. The beam is 0.186 in. wide and 0.035 in. thick, with a length of 1.00  $\pm$  0.001 in. A LVDT is used for the displacement-sensing device, and it is estimated that the uncertainty in the displacement measurement is  $\pm$ 0.001 in. The uncertainties in the bar dimensions are  $\pm$ 0.0003 in. Calculate the indicated force and uncertainty due to dimension tolerances when y=0.100 in.

Solution. The moment of inertia is calculated with

$$I = \frac{bh^3}{12} \tag{a}$$

where b is the width and h is the thickness. Thus,

$$I = \frac{(0.186)(0.035)^3}{12} = 6.64 \times 10^{-7} \text{ in.}^4$$

Equation (10-16) may be rewritten as

$$F = \frac{3Ebh^2}{12L^2}y\tag{b}$$

Using Eq. (3-2) the uncertainty in the force measurement can be written

$$\frac{w_f}{F} = \left[ \left( \frac{w_b}{b} \right)^2 + 9 \left( \frac{w_b}{h} \right)^2 + 9 \left( \frac{w_b}{L} \right)^2 + \left( \frac{w_g}{y} \right)^2 \right]^2$$
(c)

The nominal value of the force becomes

$$F = \frac{(3)(28.3 \times 10^{\circ})(6.64 \times 10^{-\circ})}{(1.00)^{\circ}} 0.100$$

= 5.83 lb,

From Eq. (c) the uncertainty is

$$\frac{w_F}{P} = \left[ \left( \frac{0.0003}{0.156} \right)^4 + 9 \left( \frac{0.0003}{0.035} \right)^5 + 9 \left( \frac{0.001}{1.000} \right)^4 + \left( \frac{0.001}{0.100} \right)^2 \right]^4$$

$$= 0.0278 \text{ or } 2.78\%$$

In this instance 1.0 percent uncertainty would be present even if the dimensions of the beam were known exactly.

The surface strain (deformation) in elastic elements like three discussed above is, of course, a measure of the deflection from the no-load condition. This surface strain may be measured very readily by the electrical resistance strain gage to be discussed in subsequent paragraphs. The output of the strain gage to be discussed in subsequent paragraphs. The output of the strain game ty thus be taken as an indication of the impressed force. The man problem with the use of these gages for the force-measurement applications is that a moment may be impressed on the elastic element because of eccentric loading. This would result in an alteration of the base strain distribution as measured by the strain gage. Then are means for compensating for this effect through instalation of minute gages which are properly interconnected to careful out the deformation resulting from the impressed moment. The means of trades should consult Refs. 4(4) and [5] for a summary of their markets.

### 10-4 TORQUE MEASUREMENTS

Torque, or moment, may be remained by observing the angular deformation of a bar or house remains as sawn in Fig. 10-7. The moment is given by

$$M = \frac{\pi G(r_0^4 - r_*^4)}{2L} \pi$$

where

G = shear modulus of elasticity

 $r_i = inside radius$ 

 $r_0 =$ outside radius

L = length of the eylinder

 $\phi = \text{angular deflection}$ 

Strain gages attached at 45° angles as shown will indicate strains of

$$\epsilon_{45^{\circ}} = \pm \frac{Mr_0}{\pi G(r_0^4 - r_1^4)}$$
 (10-19)

Either the deflection or the strain measurement may be taken as an indication of the applied moment. Multiple strain gages may be installed and connected so that any deformation due to axial or transverse load is cancelled out in the final readout circuit.

A rather old device for the measurement of torque and dissipation of power from machines is the Prony brake.† A schematic diagram is shown in Fig. 10-8. Wooden blocks are mounted on a flexible band or rope which is connected to the arm. Some arrangement is provided to tighten the rope to increase the frictional resistance between the blocks and rotating flywheel of the machine. The torque exerted on the Prony brake is given by

$$T = FL ag{10-20}$$

The force F may be measured by conventional platform scales or other methods discussed in the previous paragraphs.

The power dissipated in the brake is calculated from

$$P = \frac{2\pi TN}{33,000} \qquad \text{hp} \tag{10-21}$$

† Named for G. C. F. M. Riche, Baron de Prony (1755-1839), French hydraulic engineer.




Fig. 10-7. Hollow cylinder as an elastic element for torque measurement.




Fig. 10-2. Schematic of a Prony brake.

where the torque is in ft-lb, and N is the rotational speed in revolutions per minute

Various other types of brakes are employed for power measurements on mechanical equipment. The water bride, for example, dissipates the output energy through flowd inction between a public wheel mounted unside a stationary chamber filled with water. The chamber is freely mounted on beamps so that the torque tranmitted to it can be measured through an appropriate moment arm rimilar to that used with the Provo brake.

The de-cradled dynamometer is perhaps the most widely used device for power and torque measurements on reternal combustion engines, pumps, small setam turbines, and offer nechanical equipment. The basic arrangement of this device is shown in Fig. 10-2. A de-motor-generator is mounted on bearings as shown, with a moment arm extending from the body of the ricitor to a forcemeasurement device which is usually a principle wide. When the device is connected to a power-producing grasslate, it arts as a degenerator whose output may be varied by disspiring the power in measured with the moment arm and the output power calculated with Eq. (10-21). The dynamometer may also be used as an elemenmotor to drive some power-absorbing deven Fix a primp. In that



case, it furnishes a means for measurement of torque and power input to the machine. Commercial dynamometers are equipped with controls for precise variation of the load and speed of the machine and are available with power ratings as high as 5,000 hp.

### 10-5 STRESS AND STRAIN

Stress analysis involves a determination of the stress distribution in materials of various shapes and under different loading conditions. Experimental stress analysis is performed by measuring the deformation of the piece under load and inferring from this measurement the local stress which prevails. The measurement of deformation is only one facet of the overall problem, and the analytical work which must be applied to the experimental data in order to determine the local stresses is of equal importance. Our concern in the following sections is with the methods which may be employed for deformation measurements. Some simple analyses of these measurements will be given to illustrate the reasoning necessary to obtain local stress values. For more detailed considerations the reader should consult Refs. [2] and [5] and the periodical publication [8].

Consider the bar shown in Fig. 10-10 subjected to the axial load T. Under no-load conditions the length of the bar is L and the diameter is D. The cross-sectional area of the bar is designated by A. If the load is applied such that the stress does not exceed the elastic limit of the material, the axial strain is given by

$$\epsilon = \frac{T/A}{E} = \frac{\sigma_a}{E} \tag{10-22}$$

where  $\sigma_a$  is the axial stress and E is Young's modulus for the material.




Fig. 10-10. Simple par in axial strain.

The unit axial strain & is defined by the relation

$$\epsilon_s = \frac{dL}{L}$$
(10-23)

i.e., it is the axial deformation per unit length. Resulting from the deformation in the axial direction is a corresponding deformation in the cross-sectional area of the bar. This change in area is evidenced by a change in the diameter or, more specifically, by a change in the transverse dimension. The ratio of the unit strain in the transverse direction to the unit strain in the axial direction is defined as Poisson's ratio and must be determined experimentally for various materials.

$$\mu = -\frac{\epsilon_t}{\epsilon_t} = -\frac{dD/D}{dL/L} \qquad (10.24)$$

A typical value for Poisson's ratio for many materials is 0.3. If the material is in the plastic state, the volume remains constant with the change in strain so that

$$dV = LdA + AdL = 0$$

OF

$$\frac{dA}{A} = -\frac{dL}{L}$$

Expressed in terms of the diameter this relation is

$$2\frac{dD}{D} = -\frac{dL}{L}$$

so that  $\mu=0.5$  under these conditions

#### 10-6 STRAIN MEASUREMENTS

Let us first consider some basic definitions. Any strain measurement must be made over a finite length of the workpiece. The smaller this length, the more nessly the measurement will approximate the unit strain at a point. The length over which the average strain measurement is taken is called the base length. The deformation sensitivity is defined as the minimum deformation which can't

indicated by the appropriate gage. Strain sensitivity is the minimum deformation which can be indicated by the gage per unit base length.

A simple method of strain measurement is to place some type of grid marking on the surface of the workpiece under zero-load conditions and then measure the deformation of this grid when the specimen is subjected to a load. The grid may be scribed on the surface. drawn with a fine ink pen, or photoetched. Rubber threads have also been used to mark the grid. The sensitivity of the grid method depends on the accuracy with which the displacement of the grid lines may be measured. A micrometer microscope is frequently employed for such measurements. An alternate method is to photograph the grid before and after the deformation and make the measurements on the developed photograph. Photographic paper can have appreciable shrinkage, so that glass photographic plates are preferred for such measurements. The grid may also be drawn on a rubber model of the specimen and the local strain for the model related to that which would be present in the actual workpiece. Grid methods are usually applicable to materials and processes having appreciable deformation under load. These methods might be applicable to a study of the strains encountered in sheet-metalforming processes. The grid could be installed on a flat sheet of metal before it is formed. The deformation of the grid after forming gives the designer an indication of the local stresses induced in the material during the forming process.

Brittle coatings offer a convenient means for measuring the local stress in a material. The specimen or workpiece is coated with a special substance having very brittle properties. When the specimen is subjected to a load, small cracks appear in the coating. These cracks appear when the state of tensile stress in the workpiece reaches a certain value and thus may be taken as a direct indication of this local stress. The brittle coatings are valuable for obtaining an overall picture of the stress distribution over the surface of the specimen. They are particularly useful for determination of stresses at stress concentration points which are too small or inconveniently located for installation of electrical resistance or other types of strain gages. In some instances, stress data obtained from brittlecoating tests may be used to plan more precise strain measurements with resistance strain gages. A popular brittle coating is manufactured by the Magnaflux Corporation under the trademark of Stresscoat. Strain sensitivities of this coating range from 400 to 2,000 µin./in. The theory and application of brittle coatings are discussed very completely by Durelli et al. [3], and the interested reader should consult this reference for additional information. We may mention, however, that residual stresses in the coating, differential thermal expansion between the coating and the workpiece, and curing procedure can influence the stress properties of the coating significantly.

#### 10-7 ELECTRICAL-RESISTANCE STRAIN GAGES

The electrical-resistance atrain gage is the most widely used device for strain measurement. Its operation is based on the principle that the electrical resistance of a conductor changes when it is subjected to a mechanical deformation. Typically, an electric conductor is bonded to the specimen with an insubling criment under no-load conditions. A load is then applied which produces a deformation in both the specimen and the resistance element. This deformation is indicated through a measurement of the change in resistance of the element and a calculation procedure which is described below.

Let us now develop the basic relations for the resistance strain gage. The resistance of the conductor is

$$R = \rho \frac{L}{A}$$
(10-25)

where

L = length

A ≈ cross-sectional area

p = resistivity of the material

Differentiating Eq. (10-25) we have

$$\frac{dR}{R} = \frac{d\rho}{\rho} + \frac{dL}{L} - \frac{dA}{A} \tag{10-26}$$

The area may be related to the square of some transverse dimension such as the diameter of the resistance wite — Designating this dimension by D, we have

$$\frac{dA}{A} = 2\frac{dD}{D}$$

Introducing the definition of the axial strain and Power's Tribin Eq. (10-23) and (10-24), we have

$$\frac{dR}{R} = \epsilon_*(1+2\mu) + \frac{d\rho}{\rho}$$

The gage factor F is defined by

$$F = \frac{dR/R}{\epsilon} (10-29)$$

so that

$$F = 1 + 2\mu + \frac{1}{\epsilon_0} \frac{d\rho}{\rho} \tag{10-30}$$

We may thus express the local strain in terms of the gage factor, the resistance of the gage, and the change in resistance with the strain.

$$\epsilon = \frac{1}{F} \frac{\Delta R}{R} \tag{10-31}$$

The value of the gage factor and the resistance are usually specified by the manufacturer so that the user need only measure the value of  $\Delta R$  in order to determine the local strain. For most gages the value of F is constant over a rather wide range of strains. It is worthwhile, however, to examine the influence of various physical properties of the resistance material on the value of F. If the resistivity of the material does not vary with the strain, we have, from Eq. (10-30),

$$F = 1 + 2\mu \tag{10-32}$$

Taking a typical value of  $\mu$  as 0.3 we would obtain F=1.6. In this case, the change in resistance of the material results solely from the change in physical dimensions. If the resistivity decreases with strain, the value of F will be less than 1.6. When the resistivity increases with strain, F will be greater than 1.6. Gage factors for various materials have been observed from -140 to +175. If the resistance material is strained to the point that it is operating in the plastic region,  $\mu=0.5$  and the resistivity remains essentially constant. Under these conditions the gage factor approaches a value of 2. For most commercial strain gages the gage factor is the same for both compressive and tensile strains.

A high gage factor is desirable in practice because a larger change in resistance  $\Delta R$  is produced for a given strain input, thereby necessitating less sensitive readout circuitry.

Three common types of resistance strain gages are shown in Fig. 10-11. The bonded wire gage is perhaps the most common with the wire size varying between about 0.0005 and 0.001 in. The foil gage usually employs a foil less than 0.001 in. thick. The semiconductor gage employs a silicon base material which is strain-sensitive and has




Fig. 10-11. Three types of resistance strain gages. (a) Wire gages (b) fall gages (c) semiconductor gage.

the advantage that very large values of F may be obtained ( $F \sim 100$ ). The material is usually produced in buttle scales having a thickness of about 0.01 in Semiconductor ages also have very high temperature coefficients of resistance. Table 10-1 presents a summary of characteristics of three atran-gape materials. Reference [7] furnishes additional information

Wire and foil gages may be manufactured in various ways, but the important point is that the resistance element must be security bonded to its mounting. It is essential that the bond between the resistance element and the cement joining it to the workpiece be stronger than the resistance were itself. In this way, the strength of the resistance element is the analler, and kneek the deformation of the entire gage is governed by the deformation of the resistance element. What wire strain gages employ either a nitrocclulose cement or a phenolic resist for the bonding agent with a thin paper backing

Table 10-1 Characteristics of some resistance strain-gage materials

Material	Approx gage factor, f	Approx, renst ance, ohms	Temp coef of resistance, of -1 × 100	Remarks
57% Cu, 43% No (Driver-Harris Ca, "Advance")	2 0	100	6.0	F constant over wide range of strain, low- temperature use (under 500°F)
Plainum alloys	4.0	50	1200	Suitable for high-temper- eture use above 1000°F
Bilicon semiconductor	-100 to +150	200	50,000	Brittle but has high gage factor, not suitable for large strain measure- ments

to maintain the wire configuration. Such gages may be used up to 300°F. A Bakelite mounting is usually employed for temperatures up to 500°F. Foil gages are manufactured by an etching process and use base materials of paper, Bakelite, and epoxy film. Epoxy cements are also employed for both wire and foil gages.

When strain gages are mounted on a specimen, two notes of caution should be observed: (1) The surface must be absolutely clean. Cleaning with an emery cloth followed by acctone is usually satisfactory. (2) Sufficient time must be allowed for the eement to dry and harden completely. Even though the cement is dry around the edges of the gage, it may still be wet under the gage. If possible, 24 hr should be allowed for drying at room temperature. Drying time may be reduced for higher temperatures.

Several different eements are available for mounting strain gages. These cements are discussed in Ref. [2] along with rather detailed instructions for mounting the various types of gages. The interested reader should consult this reference for more information as well as the literature of various manufacturers of strain gages.

Problems associated with strain-gage installations generally fall into three categories: (1) temperature effects, (2) moisture effects, and (3) wiring problems. It is assumed that the gage is properly mounted. Temperature problems arise because of differential thermal expansion between the resistance element and the material to which it is bonded. Semiconductor gages offer the advantage that they have a lower expansion coefficient than either wire or foil gages. In addition to the expansion problem there is a change in resistance of the gage with temperature which must be adequately compensated for. We shall see how this compensation is performed in a subsequent paragraph. Moisture absorption by the paper and cement can change the electrical resistance between the gage and the ground potential and thus affect the output resistance readings. Methods of moisture proofing are discussed in Refs. [1] and [2]. Wiring problems are those situations which arise because of faulty connections between the gage-resistance element and the external readout circuit. These problems may develop from poorly soldered connections or from inflexible wiring which may pull the gage loose from the test specimen or break the gage altogether. Proper wiring practices are . discussed in Refs. [2] and [6].

Electrical-resistance strain gages cannot be easily calibrated because once they are attached to a calibration workpiece removal cannot be made without destroying the gage. In practice, then, the gage factor is taken as the value specified by the manufacturer and a semicalibration effected by checking the bridge measurement and readout system.

# 11-1 MEASUREMENT OF CIRCLESCALL STRAIN-GAGE OPTIONS

Constitute bridge on the first the first of the first of

$$E_{P} = E\left(\frac{E_{1}}{E_{1} + K_{1}} - \frac{E_{1}}{E_{1} + E_{1}}\right)$$

$$(5)$$

If the bridge is in balance  $\beta_0 = 0$ . Is this images what it consists agree represents  $R_1$  in this contribute and a halo importance we have been device is employed so that the backgrope rate and when a contribute deflection circuit. We assume that the backer is obtained at least a strain order  $\alpha_0$  and  $\alpha_0$  and  $\alpha_0$  in resistance  $\Delta R_1$ .  $R_1$  will be used to reput out the instance of the range at zero-strain conditions. We immediately obtain a velope due to the strain as

$$\frac{\Delta E_D}{E} = \frac{R_1 + \Delta R_1}{R_1 + \Delta R_2 + R_2} + \frac{R_2}{R_1 + \Delta R_2 + R_2} + \frac{R_3}{R_4} + \frac{R_4}{R_4}$$

Solving for the rematance change give a

$$\frac{\Delta R_1}{R_2} = \frac{(R_4/R_1)[\Delta E_D/E + R_2/(H_2 + H_2)]}{1 - \Delta E_D/E - R_2/(H_2 + H_2)}$$
(33) (6)

Equation (10-35) expresses the reservoir express the spin of the voltage unbalance at the determ of the

The bridge circuit may also be used as a see the street of the see

Again, we execute the testing in the indirect indirect in a second distinct and taken to an other constraint of the pool indirect indirect in a second distinct. Thus,

The call tandmore exercise Sign of the control of t

shown that the denominator of Eq. (10-36) is not very sensitive to small changes in  $R_1$  and hence is very nearly a constant which we shall designate as C. Thus,

$$\Delta I_{\sigma} = \frac{E}{C} \left[ (R_1 + \Delta R_1) R_3 - R_2 R_4 \right] \tag{10-38}$$

Applying the balance conditions from Eq. (10-37) gives

$$\Delta I_{\sigma} = \frac{E}{C} R_3 \Delta R_1 \tag{10-39}$$

Introducing the gage factor from Eq. (10-31),

$$\Delta I_{\sigma} = \frac{E}{C} R_{3} R_{1} F \epsilon = \text{const} \times \epsilon$$
 (10-40)

Thus, the deflection current may be taken as a direct indication of the strain imposed on the gage.

### 10-9 TEMPERATURE COMPENSATION

It is generally not possible to ealculate corrections for temperature effects in strain gages. Consequently, compensation is made directly by means of the experimental setup. Such a compensation arrangement is shown in Fig. 10-12. Gage 1 is installed on the test specimen, while gage 2 is installed on a like piece of material which remains unstrained throughout the tests but at the same temperature as the test piece. Any changes in resistance of gage 1 due to temperature are thus cancelled out by similar changes in the resistance of gage 2, and the bridge circuit detects an unbalanced condition resulting only from the strain imposed on gage 1. Of course, care must be exerted to ensure that both gages are installed in exactly the same manner on their respective workpieces.

## Example 10-4

A resistance strain gage with R=120 ohms and F=2.0 is placed in an equal-arm bridge in which all resistances are equal to 120 ohms. The battery voltage is 4.0 volts. Calculate the detector current in microamperes per microinch of strain. The galvanometer resistance is 100 ohms.

Solution. The denominator of Eq. (10-36) is calculated as

$$C = (4)(120)^2 + (100)(240)^2 = 1.267 \times 10^7$$




Fig. 10-12. Temperature - compensation arrangement for electricalresistance etrain sages.

We calculate the current sensitivity from Eq. (10-40) as

$$\frac{\Delta I_s}{\epsilon} = \frac{E}{C} R_s R_1 F = \frac{(4.0)(120)^3 (2.0)}{1.267 \times 10^7} = 9.03 \times 10^{-3} \text{ smp/sn}$$
$$= 9.03 \times 10^{-3} \, \mu \text{s} / \mu \text{in}$$

### Example 10-5

For the gage and bridge in Example 10-4 calculate the voltage indication for a strain of 1 0 µm./m when a high-impedance detector is used

Solution. We have  $R_1=R_2=R_3=R_4=120$  ohres. Under these conditions Eq. (10-34) becomes

$$\frac{\Delta E_{D}}{E} = \frac{1 + (\Delta R_{1}/R_{1})}{2 + (\Delta R_{1}/R_{1})} - \frac{1}{2} = \frac{\Delta R_{1}/R_{1}}{4 + 2(\Delta R_{1}/R_{1})}$$

The resistance change is calculated from Eq. (10-31)

$$\frac{\Delta R_1}{R_1} = F\epsilon \approx 2.0 \times 10^{-4}$$

as that

$$\frac{4E_b}{E} = \frac{2.0 \times 10^{-4}}{4 + 4 \times 10^{-4}} = 0.5 \times 10^{-4}$$

and  $\Delta E_{\rho} = (4.0)(0.5 \times 10^{-6}) = 2.0 \,\mu\text{r}$ .

## 10-10 STRAIN-GAGE ROSETTES

The installation of a strain gage on a bar specimen like that shown in Fig. 10-10 is a useful application of the gage, but it is quite restricted. The strain which is measured in such a situation is a principal strain since we assumed that the bar is operating under only a tensile load. Obviously, a more general measurement problem will involve strains in more than one direction, and the orientation of the principal stress axes will not be known. It would, of course, be fortuitous if the strain gages were installed on the specimen so that they were oriented exactly with the principal stress axes. We now consider the methods which may be used to calculate the principal stresses and strains in a material from three strain-gage measurements. The arrangements for strain gages in such applications are called rosettes. We shall give only the final relations which are used for calculation purposes. The interested reader should consult Refs. [2] and [5] for the derivations of these equations.

Consider the rectangular rosette shown in Fig. 10-13. The three strain gages are oriented as shown, and the three strains measured by these gages are  $\epsilon_1$ ,  $\epsilon_2$ , and  $\epsilon_3$ . The principal strains for this situation are

$$\epsilon_{\max}$$
,  $\epsilon_{\min} = \frac{\epsilon_1 + \epsilon_3}{2} \pm \frac{1}{\sqrt{2}} [(\epsilon_1 - \epsilon_2)^2 + (\epsilon_2 - \epsilon_3)^2]^{\frac{1}{2}}$  (10-41)

The principal stresses are

$$\sigma_{\max}, \, \sigma_{\min} = \frac{E(\epsilon_1 + \epsilon_3)}{2(1 - \mu)} \pm \frac{E}{\sqrt{2} (1 + \mu)} [(\epsilon_1 - \epsilon_2)^2 + (\epsilon_2 - \epsilon_3)^2]^{\frac{1}{2}}$$
(10-42)

The maximum shear stress is designated by  $\tau_{max}$  and calculated from

$$\tau_{\max} = \frac{E}{\sqrt{2}(1+\mu)} [(\epsilon_1 - \epsilon_2)^2 + (\epsilon_2 - \epsilon_3)^2]^{\frac{1}{2}}$$
 (10-43)




Fig. 10-13. Rectangular strain-gage rosette.



Fig. 10-14. Deitz strain-gage rusette.

The principal stress axis is located with the angle # according to

$$\tan 2\theta = \frac{2\epsilon_1 - \epsilon_1 - \epsilon_2}{\epsilon_1 - \epsilon_4} \tag{10-44}$$

This is the axis at which the maximum stress  $\sigma_{max}$  occurs. A problem arises with the determination of the quadrant for  $\theta$  since there will be two values obtained as solutions to Eq. (10-44). The angle  $\theta$  will lie in the first quadrant  $(0 < \theta < \pi/2)$  if

$$\epsilon_1 > \frac{\epsilon_1 + \epsilon_2}{2}$$
 (10-45)

and in the second quadrant if ears less than this value,

Another type of strain-gage rosette in common use is the delta rosette shown in Fig. 10-14. The principal strains in this instance are given by

$$\epsilon_{\max}, \epsilon_{\min} = \frac{\epsilon_1 + \epsilon_2 + \epsilon_3}{3} \pm \frac{\sqrt{2}}{3} \left\{ (\epsilon_1 - \epsilon_2)^2 + (\epsilon_1 - \epsilon_4)^2 + (\epsilon_2 - \epsilon_2)^2 \right\}^4$$

$$+ (\epsilon_2 - \epsilon_2)^2 \int_0^1 (10.45)^2 dt dt$$

The principal stresses are

The maximum shear stress is calculated from

$$r_{\max} = \frac{\sqrt{2}E}{3(1+\mu)}[(\epsilon_1 - \epsilon_2)^2 + (\epsilon_1 - \epsilon_2)^2 + (\epsilon_1 - \epsilon_2)^2]$$
 (10-42)

The principal stress axis is located according to

$$\tan 2\theta = \frac{\sqrt{3}(\epsilon_1 - \epsilon_2)}{2\epsilon_1 - \epsilon_2 + \epsilon_2}$$
 (10-6).

The angle  $\theta$  will be in the first quadrant when  $\epsilon_3 > \epsilon_2$  and in the second quadrant when  $\epsilon_2 > \epsilon_3$ .

It is worthwhile to mention that resistance strain gages may be sensitive to transverse as well as axial strains. The resistance change produced by a transverse strain, however, is usually less than 2 or 3 percent of the change produced by an axial strain. For this reason, it may be neglected in many applications. If the transverse strain is to be considered, the above rosette formulas must be modified accordingly. We shall not present this modification but refer the reader to Refs. [1] and [5] for more information.

### Example 10-6

A rectangular rosette is mounted on a steel plate having  $E = 29 \times 10^6$ psi and  $\mu = 0.3$ . The three strains are measured as

$$\epsilon_1 = +500 \, \mu \text{in./in.}$$

$$\epsilon_2 = +400 \, \mu \text{in./in.}$$

$$\epsilon_3 = -100 \, \mu \text{in./in.}$$

Calculate the principal strains and stresses and the maximum shear stress. Locate the axis of principal stress.

Solution. As an intermediate step we calculate the quantities

$$A = \frac{\epsilon_1 + \epsilon_1}{2} = 200 \ \mu \text{in./in.}$$

$$B = [(\epsilon_1 - \epsilon_2)^2 + (\epsilon_2 - \epsilon_2)^2]^{\frac{1}{2}} = 510 \ \mu \text{in./in.}$$

Then,

$$\epsilon_{\text{max}} = A + \frac{1}{\sqrt{2}}B = 561 \,\mu\text{in./in.}$$

$$\epsilon_{\min} = A - \frac{1}{\sqrt{2}}B = -161 \,\mu\text{in./in.}$$

$$\sigma_{\text{thax}} = \frac{EA}{1-\mu} + \frac{EB}{\sqrt{2}(1+\mu)} = \frac{(29 \times 10^6)(200 \times 10^{-6})}{1-0.3} + \frac{(29 \times 10^6)(510 \times 10^{-6})}{\sqrt{2}(1+0.3)} = 8,280 + 8,050 = 16,330 \text{ psi}$$

$$\sigma_{\text{min}} = 8,280 - 8,050 = 230 \text{ psi}$$

$$\tau_{\text{max}} = \frac{EB}{\sqrt{2}(1+\mu)} = 8,050 \text{ psi}$$

$$\sigma_{\min} = 8,280 - 8,050 = 230 \text{ psi}$$

$$r_{\text{max}} = \frac{LB}{\sqrt{2}(1+\mu)} = 8,050 \text{ psi}$$

We also have

$$\tan 2\theta = \frac{2\epsilon_1 - \epsilon_1 - \epsilon_2}{\epsilon_1 - \epsilon_2} = \frac{(2)(400) - (500) - (-100)}{(500) - (-100)} = 0.607$$

 $2\theta = 33.7 \text{ or } 213.7^{\circ}$ 

 $\theta = 16.8 \text{ or } 106.8^{\circ}$ 

We choose the first quadrant angle ( $\theta = 16.8^{\circ}$ ) in accordance with Eq. (10-45).

#### 10-11 THE UNBONDED-RESISTANCE Strain gage

The bonded electrical-resistance strain gage discurred above is the most widely used device for atrain measurements. An alternate resistance gage is the unbonded type shown in Fig. 10-15. A spring-loaded mechanism holds the two plates in a close position while the fine wire filaments are stretched around the mounting pins as shown. The mounting pins must he rigid and also serve as electrical insulators. When plate A moves relative to B, a atrain is imposed on these filaments which may be detected through a measurement of the chaoge in resistance. The allowable displacement of commercial gages is of the order of ±0.0015 in , and the wire diameter is usually less than 0.001 in. The IM heating in the unbonded gage can be a problem because the wires have needly means for heat dissipation other than convection to the surrounding air. The principle of the unbooded gage has been applied to acceleration and diaphragm pressure transducers with road success.




Fig. 10-15. Schematic of unbonded-resistance strain gage.

### PROBLEMS

- 10-1 Many balances use brass weights ( $\rho_r = 530 \text{ lb}_p/\text{it}^2$ ) in atmospheric air ( $\rho_a = 0.075 \text{ lb}_p/\text{it}^2$ ). Plot the percent error in the balance determination as a function of  $\rho_u/\rho_r$ .
- 10-2 Using the conditions given in Example 10-1, calculate the required angular sensitivity in order that the uncertainty in the weight determination is of the order of 1 part in 10⁸.
- 10-3 An LVDT is used to measure the axial deformation of the simple bar of Fig. 10-3. The uncertainty in this measurement is ±0.001 in. A steel bar is to be used to measure a force of 250 lb, with an uncertainty of 1 percent. Determine a suitable diameter and length of rod for this measurement, assuming the rod dimensions will be known exactly.
- 10-4 The diaphragm of Fig. 6-10c is to be used as a force-measurement device with the load applied at the center boss. Steel is to be used as the diaphragm material, and the maximum displacement is not to exceed one-third the thickness. A load of 1,000 lb_f is to be measured with an uncertainty of 1 percent using an LVDT with an uncertainty of ±0.0001 in. Determine suitable diaphragm dimensions for this measurement.
- 10-5 A farmer decides to build a crude weighing device to weigh bags of grain up to 150 lb_f. For this purpose he employs a section of 1-in. steel pipe (1.315 in. OD, 0.957 in. ID) as a cantilever beam. He intends to measure the deflection of the beam with a metal carpenter's scale having graduations of  $\frac{1}{16}$  in. On the basis of these data what length of pipe would you recommend for the farmer's application?
- 10-6 A proving ring is constructed of steel  $(E=30\times10^6~\mathrm{psi})$  having a cross section with 0.250 in thickness and 1.000 in depth. The overall diameter of the ring is 6.000 in. A micrometer is used for the deflection measurement, and its uncertainty is  $\pm 0.0001$  in. Assuming that the dimensions of the ring are exact, calculate the applied load when the uncertainty in this load is 1.0 percent. Calculate the percent uncertainty in the load when y=0.01 in. and the uncertainty in the dimensions are

 $w_k = w_b = 0.0002 \text{ in.}$ 

 $w_2 = 0.01 \text{ in.}$ 

where b and h are the thickness and depth of the ring respectively.

10.7 A hollow steel cylinder (G = 12 × 10° psi) is subjected to a moment such that \$\phi\$ is 1.50°. The dimensions of the cylinder are

$$r_t = 0.500 \pm 0.0003$$
 in.  
 $r_t = 0.625 \pm 0.0003$  in.

$$L = 5000 \pm 0001$$
 in.

The uncertainty in the angular deflection is ±0.05°. Calculate the nominal value of the impressed moment and its uncertainty. Also calculate the 45° strains.

10-8 In a bridge circuit like that of Fig. 4-17, R₁ = 100 ohms. The galvanometer resistance is 50 ohms. The strain-gage resistance at zero strain is 120 ohms, and the value of R₁ is adjusted to bring the bridge into balance at zero-strain conditions. The gage factor is 20 Calculate the galvanometer current when ε = 400 μm./m. Take the battery voltage as 40 volts.

10-9 Calculate the voltage output of the bridge in Prob. 10-8, assuming a detector of very high impedance.

10-10 Show that Eq. (10-41) reduces to

when  $\theta = 0$  Obtain relations for the principal stresses and maximum shear stress in this instance

10-11 A delta rosette is placed on a steel plate and indicates the following strains:

$$\epsilon_1 = -250 \, \mu \text{in./in}$$

Calculate the principal strains and stresses, the maximum shear atress, and the orientation angle for the principal axes 10-12 Obtain simplified relations for the delta rosette under the conditions that  $e_1 = e_{max}$ , that is,  $\theta = 0$ 

10-13 Suppose a rectangular rosette is used to intessure the same stresses as in Prob 10-11. The bottom leg of this rosette it placed in the same location as the bottom aim of the delta rosette. Calculate the strains which would be indicated by the rectangular rosette under these conditions.

- 10-14 Calculate the percent uncertainty in the maximum and minimum stresses resulting from uncertainties of 2 percent in the strains as measured with a rectangular rosette. For this calculation assume E and  $\mu$  are known exactly.
- 10-15 Rework Prob. 10-14 for the delta rosette.
- 10-16 A rectangular rosette is placed on a steel plate and indicates the following strains:
  - $\epsilon_1 = 563 \, \mu \text{in./in.}$
  - $\epsilon_2 = -155 \, \mu \text{in./in.}$
  - $\epsilon_2 = -480 \, \mu \text{in./in.}$

Calculate the principal strains and stresses, the maximum shear stress, and the orientation angle for the principal axes.

10-17 A strip of steel sheet,  $\frac{1}{16} \times 2 \times 20$  in., is available for use as a force-measuring elastic element. The strip is to be used by cementing strain gages to its flat surfaces and measuring the deformation under load. The strain gages have a maximum strain of 2,000  $\mu$ in./in. and a gage factor of 1.90. A battery is available with a voltage of 4.0 volts, and the readout voltmeter has a high impedance and an accuracy of  $\pm 1$   $\mu$ v. The nominal resistance of the strain gages is 120 ohms. Calculate the force range for which the measurement system may be applicable.

### REFERENCES

- Desn, M. (ed.): "Semiconductor and Conventional Strain Gages," Academic Press, Inc., New York, 1962.
- Dove, R. C., and P. H. Adams: "Experimental Stress Analysis and Motion Measurement," Charles E. Merrill Books, Inc., Columbus, Ohio, 1964.
- Durelli, A. J., E. A. Phillips, and C. H. Tsao: "Introduction to the Theoretical and Experimental Analysis of Stress and Strain," McGraw-Hill Book Company, New York, 1958.
- Harris, C. M., and C. E. Crede (eds.): "Basic Theory and Measurements," vol. 1, "Shock and Vibration Handbook," McGraw-Hill Book Company, New York, 1961.
- Hctenyi, M. (ed.): "Handbook of Experimental Stress Analysis," John Wiley & Sons, Inc., New York, 1950.
- Perry, C. C., and H. R. Lissner: "The Strain Gage Primer," 2nd ed., McGraw-Hill Book Company, New York, 1962.
- 7. Stein, Peter K.: Material Considerations for Strain Gages, Inst. & Control Systems, vol. 37, no. 10, pp. 132-135, October, 1964.
- 8. Proc. Soc. Exptl. Stress Anal., published by the Society.

# Motion and vibration measurement

### 11-1 INTRODUCTION

Measurements of motion and vibration parameters are important in many applications. The experimental quantity which is desired may be velocity, acceleration, or vibration amplitude. These quantities may be useful in predicting the fatigue failure of a particular part or machine or may play an important role in analyses which are used to reduce structure vibration or noise level

The central problem in any type of motion or vibration measurement concerns a determination of the appropriate quantities in reference to some specified state, i.e., velocity, displacement, or acceleration in reference to ground. Ideally, one would hie to have a motion or vibration transducer which connects to the body in motion and furnishes an output signal proportional to the vibrational input. The ideal transducer should be independent of its location, i.e., it should function equally well whether it is connected to a vibrating structure on the ground, in an airplane, of in a space vehicle. In this chapter we shall see some of the compromises which are necessary to approach such behavior.

Sound may be classified as a vibratory phenomenon, and we shall indicate some of the important parameters necessary for specification of sound level. The measurement and analysis of sound levels are very specialized subjects which are becoming increasingly important in modern building and equipment design [8]

# 11-2 TWO SIMPLE VIBRATION INSTRUMENTS

Consider the simple wedge shown in Fig. 11-1 which is attached to a vibrating wall. When the wall is at rest, the wedge appears




Fig. 11-1. Simple wedge used as device for amplitude-displacement measurements. (a) At rest; (b) in motion.

as in (a); when the wall is in motion, the wedge appears as in (b). An observation is made of the distance x. At this distance the thickness of the wedge is equal to the double amplitude of the motion. In terms of x the amplitude is given by

$$a = x \tan \frac{\theta}{2} \tag{11-1}$$

where  $\theta$  is the total included angle of the wedge. The wedge-measurement device is necessarily limited to rather large amplitude motions, usually for  $a > \frac{1}{10}$  in.

Another simple vibration-frequency-measurement device is shown in Fig. 11-2. The small cantilever beam mounted on the block is placed against the vibrating surface, and some appropriate method is provided for varying the beam length. When the beam length is properly adjusted so that its natural frequency is equal to the frequency of the vibrating surface, the resonance condition shown in (b) will result. The natural frequency of such a beam is given by




Fig. 11-2. Cantilever beam used as frequency-measurement device. (a) No vibration or vibration other than  $\omega_n$ ; (b) vibration at  $\omega_n$ .

where

 $\omega_n = \text{natural frequency}$ 

E = Young's modulus for the beam material, per

I = moment of inertia of the beam, in.

m = mass per unit length, lb./in.

L = beam length, in.

#### Example 11-1

A  $\gamma_T$ -in-diam pring-steel rod is to be used for a vibration-frequency measurement as shown in Fig. 11-2. The length of the rod may be varied between 1 and 4 in. The density of this material is 480 lb_/ft, and the modulus of elasticity is 23.3 × 100 pm. Calculate the range of frequencies which may be measured with this device and the allow ship uncertainty in Lat L = 4 in, in order that the uncertainty in the frequency is not greater than 1 percent. Assume the material properties are known exactly

Solution. We have

$$I = \frac{\pi 7^4}{4} = \frac{\pi (1/32)^4}{4} = 7.49 \times 10^{-7} \text{ m}^4$$

$$m = \rho_0 \tau^4 = \frac{\pi (489)(1/32)^4}{(144)} \tau_0^4 = 8.69 \times 10^{-4} \, \text{lb}_0/\text{in}$$

$$\omega_n = 11.0 \left[ \frac{(28.3 \times 10^4)(7.49 \times 10^{-4})}{(8.69 \times 10^{-9})(1)^4} \right]^4 = 1.720 \text{ rad/sec}$$
  
= 273 cps

We use Eq. (3-2) to determine the allowable uncertainty in the length measurement in terms of the uncertainty in the frequency measurement

$$\frac{\partial \omega_n}{\partial L} = 11.0 \sqrt{\frac{EI}{m}} \left(\frac{-2}{L^2}\right)$$

$$\omega_m = \left[\left(\frac{\partial \omega_n}{\partial I} w_L\right)^2\right]^{\frac{1}{2}}$$

so that

$$w_L = \frac{w_u, L^4}{22.0 \sqrt{EI/m}}$$




Fig. 11-1. Simple wedge used as device for amplitude-displacement measurements. (a) At rest; (b) in motion.

as in (a); when the wall is in motion, the wedge appears as in (b). An observation is made of the distance x. At this distance the thickness of the wedge is equal to the double amplitude of the motion. In terms of x the amplitude is given by

$$a = x \tan \frac{\theta}{2} \tag{11-1}$$

where  $\theta$  is the total included angle of the wedge. The wedge-measurement device is necessarily limited to rather large amplitude motions, usually for a  $> \frac{1}{3\pi}$  in.

Another simple vibration-frequency-measurement device is shown in Fig. 11-2. The small cantilever beam mounted on the block is placed against the vibrating surface, and some appropriate method is provided for varying the beam length. When the beam length is properly adjusted so that its natural frequency is equal to the frequency of the vibrating surface, the resonance condition shown in (b) will result. The natural frequency of such a beam is given by

(b)

$$\omega_n = 11.0 \sqrt{\frac{EI}{mL^4}}$$

$$Vibration$$

$$s = s_0 \cos \omega_n t$$

$$\omega_n = 11.0 \sqrt{\frac{EI}{mL^4}}$$
(11-2)

Fig. 11-2. Cantilever beam used as frequency-measurement device. (a) No vibration or vibration other than  $\omega_n$ ; (b) vibration at  $\omega_n$ .

(a)

where

m = natural frequency

F = Young's modulus for the beam material, psi

I = moment of inertia of the beam in.4

m = mass per unit length th. /in.

I. = beam length, in.

### Example 11-1

measurement as shown in Fig. 11-2. The length of the rod may be varied between 1 and 4 in. The density of this material is 489 lb_/fts and the modulus of elasticity is 28 3 × 10° pss. Calculate the range of frequencies which may be measured with this device and the allowable uncertainty in Lat L = 4 in, in order that the uncertainty in the frequency is not greater than I percent. Assume the material properties are known exactly.

Solution. We have

$$I = \frac{\pi r^4}{l} = \frac{\pi (1/32)^4}{l} = 7.49 \times 10^{-7} \text{ m.}^4$$

$$m = \rho \pi \tau^4 = \frac{\pi (489)(1/32)^4}{(144)} \tau_3^2 = 8.69 \times 10^{-4} \, \text{lb}_{\gamma}/\text{in}$$

$$\omega_{\bullet} = 11.0 \left[ \frac{(28.3 \times 10^{\circ})(7.49 \times 10^{-9})}{(8.69 \times 10^{-9})(1)^{\circ}} \right]^{\circ} = 1.720 \text{ rad sec}$$

$$= 273 \text{ cps}$$

At 
$$x = 4$$
 in.,

$$\omega_* = 107.5 \text{ rad/sec} = 17.06 \text{ eps}$$

We use Eq. (3-2) to determine the allowable uncertainty in the length measurement in terms of the succrtainty in the frequency measurement.

$$\frac{\partial \omega_n}{\partial L} = 11.0 \sqrt{\frac{EI}{m}} \left( \frac{-2}{L^3} \right)$$

$$w_{u_{a}} = \left[ \left( \frac{\partial \omega_{a}}{\partial L} w_{L} \right)^{t} \right]^{i}$$

so that

$$w_L = \frac{w_{m_s}L^2}{22.0 \sqrt{EI/m}}$$

at 
$$L = 4$$
 in.  $w_{\omega_n} = (0.01)(107.5) = 1.075$  rad/sec
$$w_L = \frac{(1.075)(4)^3}{(22.0)(156.2)} = 0.02 \text{ in.}$$

# 11-3 PRINCIPLES OF THE SEISMIC INSTRUMENT

The seismic instrument is a device which has the functional form of the system shown in Fig. 2-3. A schematic of a typical instrument is shown in Fig. 11-3. The mass is connected through the parallel spring and damper arrangement to the housing frame. This frame is then connected to the vibration source whose characteristics are to be measured. The mass tends to remain fixed in its spatial position so that the vibrational motion is registered as a relative displacement between the mass and the housing frame. This displacement is then sensed and indicated by an appropriate transducer, as shown in the schematic diagram. Of course, the seismic mass does not remain absolutely, steady, but for selected frequency ranges it may afford a satisfactory reference position.

The seismic instrument may be used for either displacement or acceleration measurements by proper selection of mass, spring, and damper combinations. In general, a large mass and soft spring are desirable for vibrational displacement measurements, while a relatively small mass and stiff spring are used for acceleration indications. This will be apparent from the theoretical discussion which follows.




Fig. 11-3. Schematic of typical seismic instrument.




Fig. 11-4. Mechanical system for a saismic instrument.

Figure 2-3 is reproduced as Fig 11-4 to show the mechanical system to be analyzed. Using Newton's second law of motion, we have

$$m\frac{d^3x_1}{dt^2} + c\frac{dx_1}{dt} + kx_2 = c\frac{dx_1}{dt} + kx_1$$
 (11-3)

where it is assumed that the damping force is proportional to velocity. We assume that a harmonic vibratory motion is impressed on the instrument such that

$$x_1 = x_0 \cos \omega_1 t \tag{11-4}$$

and wish to obtain an expression for the relative displacement  $-x_1 - x_1$  in terms of this impressed motion. The relative displacement is that which is detected by the transducer shown in Fig. 11-3 Rewriting Eq. (11-3) and substituting Eq. (11-4) gives

$$\frac{d^{3}x_{1}}{dt^{3}} + \frac{c}{m}\frac{dx_{1}}{dt} + \frac{k}{m}x_{2} = x_{4}\left(\frac{k}{m}\cos\omega_{1}t - \frac{c}{m}\omega_{1}\sin\omega_{2}t\right)$$
(11-5)

The solution to Eq (11-5) is

$$x_3 - x_1 = e^{-(atm)t}(A \cos \omega t + B \sin \omega t) + \frac{mx_0\omega_1^2 \cos (\omega_1 t - \phi)}{[(k - m\omega_1^2)^2 + c^2\omega_1^2]}$$
(11-1)

where the frequency is given by

$$\omega = \left[ \left( \frac{c}{2m} \right)^3 - \frac{k}{m} \right]^3 \qquad (11-7)$$

and the phase angle by

$$\phi = \tan^{-1} \frac{\epsilon \omega_1}{k - m \omega_1^2}$$




Fig. 11-5. Displacement response of a seismic instrument as given by Eq. (11-9).

A and B are constants of integration determined from the initial or boundary conditions.

Note that Eq. (11-6) is composed of two terms: (1) the transient term involving the exponential function and (2) the steady-state term. This means that after the initial transient has died out a steady-state harmonic motion is established in accordance with the second term. The frequency of this steady-state motion is the same as that of the impressed motion, and its amplitude is

$$(x_2 - x_1)_0 = \frac{x_0(\omega_1/\omega_n)^2}{\{[1 - (\omega_1/\omega_n)^2]^2 + [2(c/c_c)(\omega_1/\omega_n)]^2\}^{\frac{1}{2}}}$$
(11-9)

where the natural frequency  $\omega_n$  and critical damping coefficient  $c_e$  are given by

$$\omega_n = \sqrt{\frac{k}{m}} \tag{11-10}$$

$$c_e = 2\sqrt{mk} \tag{11-11}$$

The phase angle may also be written

$$\phi = \tan^{-1} \frac{2(c/c_t)(\omega_1/\omega_n)}{1 - (\omega_1/\omega_n)^2}$$
(11-12)

A plot of Eq. (11-9) is given in Fig. 11-5. It may be seen that the output amplitude is very nearly equal to the input amplitude when

 $e/e_c = 0.7$  and  $\omega_s/\omega_s > 2$ . For low values of the damping ratio the amplitude may become quite large. The output becomes eventially a linear function of input at high-frequency ratios. Thus, a seismic-vibration pickup for measurement of displacement amplitude should be utilized for measurement of frequences sub-tantially higher than its natural frequency. The instrument constants  $e/e_c$  and  $\omega_s$  should be known or obtained from calibration. The anticipated accuracy of measurement may then be calculated for various frequencies.

The acceleration amplitude of the input vibration is

$$a_0 = \left(\frac{d^3x_1}{dt^2}\right)_0 = \omega_1^2x_0$$
 (11-13)

We may thus use the measured output of the instrument as a measure of acceleration. There are problems associated with this application, however. In Eq. (11-9) the bracketed term is the one which governs the linearity of the acceleration response since  $\omega$ , will be fixed for a given instrument. In Eq. 11-6 we have a plot of

$$\frac{(x_1-x_1)\omega_n^2}{a_0} \quad \text{versus} \quad \frac{\omega_1}{\omega_n}$$

which indicates the response. Generally unsatisfactory performance is observed at frequency ratios above 0.4. Thus, for accelera-




Fig. 11-6. Acceleration response of a seismic Instrument as given by Eq. (11-13).

tion measurements we wish to operate at frequencies much lower than the natural frequency, in contrast to the desirable region of operation for amplitude measurements. From the standpoint of instrument construction this means that we wish to have a low natural frequency (soft spring, large mass) for amplitude measurements and a high natural frequency (stiff spring, small mass) for acceleration measurements in order to be able to operate over a wide range of frequencies and still enjoy linear response.

The seismic instrument may also be used for vibration velocity measurements by employing a variable-reluctance magnetic pickup as the sensing transducer. The output of such a pickup will be proportional to the relative velocity amplitude, i.e., the quantity

$$\left[\frac{d}{dt}\left(x_2-x_1\right)\right]_0$$

From the above discussion it may be seen that the seismic instrument is a very versatile device which may be used for measurement of a variety of vibration parameters. For this reason, many commercial vibration and acceleration pickups operate on the scismic-instrument principle. Calibration methods for the scismic instrument are discussed in Refs. [1], [4], [6], and [7].

The transient response of the seismic instrument is governed partially by the exponential decay term in Eq. (11-6). The time constant for this term could be taken as

$$T = \frac{2m}{c} \tag{11-14}$$

or, in terms of the natural frequency and critical damping ratio,

$$T = \frac{1}{\omega_n(c/c_c)} \tag{11-15}$$

The specific transient response of the seismic-instrument system is also a function of the type of input signal, i.e., whether it is a step function, harmonic function, ramp function, etc. The linearity of a vibration transducer is thus influenced by the frequency ratio requirements which are necessary to give linear response as indicated by Eqs. (11-6) and (11-9). The design of a transducer for particular response characteristics must involve a compromise between these two effects, combined with a consideration of the sensitivity of the displacement-sensing transducer and its transient response characteristics. The response of the seismic instrument to different types of inputs is discussed by Dove and Adams [4].

#### Example 11-2

Using Eq. (11-9) and  $c/c_* = 0.7$ , calculate the value of  $\omega_1/\omega_*$  such that  $(x_1 - x_1)_0/x_1 = 0.99$ ; that is, the error is 1 percent.

Solution We have

$$0.99 = \frac{(\omega_1/\omega_n)^2}{[[1 - (\omega_1/\omega_n)^2]^2 + [2(0.7)(\omega_1/\omega_n)]^2]^2}$$

Rearranging this equation gives the quadratic relation

$$\left[\left(\frac{1}{0.99}\right)^2 - 1\right] \left(\frac{\omega_1}{\omega_a}\right)^4 + 0.04 \left(\frac{\omega_2}{\omega_a}\right)^2 - 1 = 0$$

which yields

$$\frac{\omega_1}{\omega_2} \approx 2.47$$

#### Example 11-3

A small seismic instrument is to be used for measurement of linear acceleration. It has  $\omega_s=100$  rad/see and a deplacement-screing transceleration detects a measurement of  $\pm 0$  in. The uncertainty in the displacement measurement is  $\pm 0$ 001 in. Calculate the maximum acceleration which may be measured with this instrument and the uncertainty in the measurement, assuming  $\omega_s$  is known exactly

Solution. From Eq. (11-9) with 
$$\omega_1/\omega_4=0$$
, we have

$$a_0 = \omega_a^{-1}(x_1 - x_1)_0$$
  
= 100¹(0.1/12) = 83.3 ft/sec²

The uncertainty is calculated from

$$w_a = \left[ \left( \frac{\partial a}{\partial x} w_a \right)^2 \right]^{\frac{1}{2}} = \omega_a^2 \omega_r = (100)^2 (0.001/12) = 0.833 \text{ ft/sec}^2$$

or an uncertainty of 1 percent. It may be noted that larger uncertainties would be present when smaller accelerations were measured

#### Example 11-4

Calculate the frequency ratio for which the error in acceleration measurement is 1 percent, with  $e/e_a = 0.7$ , that is,  $[(x_2 - x_3) \omega_a^2]/a_b = 0.99$ 

Solution. We have

$$0.99 = \frac{1}{\{[1 - (\omega_1/\omega_n)^2]^2 + [2(0.7)(\omega_1/\omega_n)^2]^{\frac{1}{2}}}$$

This gives the quadratic relation

$$\left(\frac{\omega_1}{\omega_n}\right)^4 - 0.04 \left(\frac{\omega_1}{\omega_n}\right)^2 + 1 - (1/0.99)^2 = 0$$

which yields

$$\frac{\omega_1}{\omega_2} = 0.306$$

### Example 11-5

Calculate the time required for the exponential transient term in Eq. (11-6) to decrease by 99 percent with  $\omega_n = 100 \text{ rad/sec}$  and  $c/c_c = 0.7$ . Compare this time with the period of an acceptable frequency  $\omega_1$  for displacement and acceleration amplitude measurements as calculated from the 99 percent relationships of Examples 11-2 and 11-4.

Solution. We have

$$e^{-(c/2\pi)t} = 0.01$$
 and  $\frac{ct}{2m} = 10.06$   
 $10.06 = \omega_n \left(\frac{c}{\pi}\right) t$ 

$$t = 0.1438 \text{ sec}$$

From Example 11-2,  $\omega_1/\omega_n=2.47$  and the corresponding period for  $\omega_1$  in the displacement measurement is

$$P = \frac{2\pi}{\omega_1} = \frac{2\pi}{247} = 0.0255 \sec$$

From Example 11-4,  $\omega_1/\omega_n = 0.306$  and the corresponding period for  $\omega_1$  in the acceleration measurement is

$$P = \frac{2\pi}{\omega_1} = \frac{2\pi}{30.6} = 0.205 \sec$$

No specific conclusions may be drawn from this comparison because the transient response depends on the manner in which the instrument is subjected to a change.

### 11-4 PRACTICAL CONSIDERATIONS FOR SEISMIC INSTRUMENTS

The previous paragraphs have shown the basic response characteristics of seismic instruments to an improved harronic vibrational motion. Let us now consider some of the ways that these instruments might be constructed in practice.

In Fig. 11-7 a seismic instrument is dustrated which uses a voltage-divider potentiometer for sensing the relative displacement between the frame and the seismic mass. To provide the damping for the system, the case of the instrument right be filled with a viscous liquid which would interact continuously with the frame and the mass. Because of the relatively large rease of the potentiometer such systems have rather loss natural frequencies (less than about 100 cps) and, as such, are limited to acceleration measurements at frequencies less than about 50 cps. Such acceleration transducers may weigh a pound of more

The linear variable differential transformer ILVDT, described in Sec. 4-13 offers another convenient in near for measurement of the relative displacement between the scenie mass and weekermeter housing. Such devices have corrected that the frequencies than potentiometer devices 200-200 epoch segments that are all restricted to applications with loss frequency response requirements. The differential transformer, houseser, has a mark house as water to motion than the potentiometers and acceptable of mich seem resolution. In addition, the seem a previous resolution as a considerably lighter in oper transforments in one as IVIVI can be considerably lighter in oper transforments in the first potention.

The electrocal reportance error gays domined in CP sp. 10 may also be used for a displacement error of tensers, a serior of entire ment. Counder the edemants in CP at 100 The entire indicates monomized on a confidence bear. On error of cities central streets




Fig. 12.7. Seismic bestrament uring a military divider patentiameter for sensing relative displacement.




Fig. 11-8. Seismic instrument utilizing an electrical-resistance strain gage for sensing relative displacement.

ance strain gage is mounted to sense the strain in the beam resulting from the vibrational displacement of the mass. Damping for the system is provided by the viscous liquid which fills the housing. The outputs of the strain gages are connected to an appropriate bridge circuit which is used to indicate the relative displacement between the mass and housing frame. The natural frequencies of such systems are fairly low and roughly comparable to those for the LVDT systems. The low natural frequencies result from the fact that the cantilever beam must be sufficiently large to accommodate the mounting of the resistance strain gages.

For high-frequency measurements the seismic instrument frequently employs a piezoelectric transducer (Sec. 4-15), as shown in Fig. 11-9. The natural frequency of such instruments may be as high as 100 kc, and the entire instrument may be quite small and light in weight. A total weight of 1 oz for a piezoelectric accelerometer is not uncommon. Piezoelectric devices have rather high electric outputs but are not generally suitable for measurements at frequencies below about 10 cps. Electrical impedance matching between the transducer and readout circuitry is usually a critical matter requiring careful design considerations.

Seismic vibration instruments may be influenced by temperature effects. Devices employing variable-resistance displacement sensors will require a correction to account for resistance changes due to temperature. The damping of the instrument is affected




Fig. 11-9. Seismic instrument utilizing a piezoelectric transducer.

by changes in viscosity of the fluid surrounding the seismic mass Silicone oils are frequently employed in such applications, and their viscosity is strongly dependent on temperature. It would not be uncommon for such oils to experience a change in viscosity by a factor of two for a temperature change of only 50°F. The viscosity-temperature effect could be eliminated, of course, if a fluid were used with a small change in viscosity with temperature. Unfortunately, fluids which have this desirable behavior, viz., gaze, have low viscosities as well, so that they are generally unsuitable for use as damping agents in the seismic matrument. One way of allevinting the viscosity-temperature problem is to install an electrical-resistance heater in the fluid to maintain the temperature at a constant value regardless of the surrounding temperature.

Obviously, vibration measurements are not always performed on large, massive pieces of equipment. It is frequently of interest to measure the vibration of a thin plate or other small, low-mass structures. The question immediately arises about the effect of the presence of the vibration instrument in such measurements If the mass of the instrument is not small in comparison with the mass of the workpiece on which it is to be justalled, the vibrational characteristics may be altered appreciably. In such cases a correct interpretation of the output of the vibrational instrument may only be obtained by analyses beyond the scope of our discussion. and the interested reader should consult Ref 161 for more information about this subject. A simple experimental technique, however, will tell the engineer whether the presence of the instrument has altered the vibrational characteristics of the structure under test. First, a measurement is made with the vibration instrument in place. Then, an additional mass is mounted on the structure along with the instrument and a second measurement taken under the same conditions as the first. If there is no appreciable difference between the two measurements, it may be assumed that the presence of the vibrometer has not altered the vibrational characteristics. If there is an appreciable difference in the measurements, an analysis will be necessary to determine the "free" vibrational characteristics in terms of the experimental measurements

### 11-5 SOUND MEASUREMENTS

Sound waves are a vibratory phenomenon and for this reason are appropriately discussed in this chapter. They might also be discussed in the chapter on pressure measurements because accountie effects are usually measured in terms of harmonic pressure fluctuations which they produce in a higher gaseous medium.

It is standard practice in acoustic measurements to relate sound intensity and sound pressure to certain reference values  $I_0$  and  $p_0$  which correspond to the intensity and mean pressure fluctuations of the faintest audible sound at a frequency of 1,000 eps. These reference levels are:

$$I_0 = 10^{-16} \text{ watt/em}^2$$
 (11-16)  
 $p_0 = 2 \times 10^{-4} \text{ dyne/em}^2$   
 $= 2 \times 10^{-6} \text{ newton/m}^2$  (11-17)  
 $= 2.9 \times 10^{-9} \text{ psi}$ 

Intensity and pressure levels are measured in decibels. Thus,

Intensity level (db) = 
$$10 \log_{10} I/I_0$$
 (11-18)

Pressure level (db) = 
$$20 \log_{10} p/p_0$$
 (11-19)

When pressure fluctuations and particle displacements are in phase such as in a plane acoustic wave, these levels are equal,  $10 \log_{10} I/I_0 = 20 \log_{10} p/p_0$ .

The magnitudes of the particle velocity and pressure fluctuations ereated by a sound wave are small. For example, a plane sound wave having an intensity of 140 db generates a maximum oscillation velocity of approximately 2.4 ft/sec and a root-mean-square pressure fluctuation of about 0.029 psi. A sound intensity of 90 db is considered the maximum permissible level for extended human exposure.

The human ear responds differently to different sound frequencies and to certain groups of frequencies which are called "noise." The acoustical engineer is responsible for designing rooms or systems such that unwanted frequencies or noise is filtered out while still allowing clarity of transmission of certain other sounds. An auditorium, for example, should be designed so that very little outside noise is transmitted through the walls, while the inside structure and fixtures should allow clear transmission of audio performances on the stage. The walls should have good sound insulation, while the inside surfaces should be properly designed so that unwanted reverberations are climinated without causing undue attenuation of sound from the stage. Almost all acoustical design problems involve the exercise of considerable judgment based on experience as well as a knowledge of some basic sound-level measurements.

Sound-level measurements are performed with some type of microphone, which may be considered a type of seismic vibration instrument. The electric output of the microphone is proportional to sound pressure level which may be used to calculate the sound intensity according to Eq. (11-18). Appropriate power amplifiers and readout meters or recorders indicate the sound level. In general, the microphone must be calibrated in a text facility with a source of known frequency and intensity. Even with careful calibration, accuracies of better than ±1 db may not be expected in sound pressure level measurements. The characteristics of some typical microphones are given In Table 11-1.

A typical practical application of sound-level measurements may call for an analysis of the noise spectrum in a certain sound source. For this purpose a noise analyzer with bandpass filter circuits is used Several sound-pressure-level measurements are taken to determine the sound intensity in various wavelength bands Based on experience, the acoustical engineer may then take steps to attenuate whatever frequencies he feels are necessary to achieve the design objective. For many commercial nove and vibration meters calibration may be achieved with a simple whistle or tuning fork in a quiet room. Sound-level readings will generally follow the inverse source law.

Table 11-1 Characteristics of microphones according to Ref. [9]

Mechanism	Frequency range	Approximate open-circuit zensitivity, db, below 1 volt/dynes/ cm³	Approximate impedance, ohms	Application and remarks		
Carbon microphone	Up to 5 ke	-40	100	Telephones		
Electrodynamic	Up to 20 kc	-85	19	Field measurements, com- munications, etc.		
Electrostatic	Up to 50 ke	-50	500,000	Preession measurements, atandards		
Psezoelectric Rochelle	Audio region	-50	100,000	Temperature-dependent Hygroscopic		
ADP crystal		-50		Uae in underwater sound, solids, etc		
Quartz	Mainly ultrasonic	-90 to −100	High			
Barıum tılanale	uttrasonse	-90	Low	High-intensity work in air water, measurements with amall probes		
Magnetostrictive	Mainly ultrasonse	-100	Low	Underwater sound		
Ribbon microphone	Audio region	-100	1	Directive		

A good summary of acoustical principles and materials for use in sound attenuation applications is given in Refs. [2], [3], and [8]. The following paragraphs present a summary discussion of some of the types of acoustical phenomena which are encountered in practice.

# Traveling plane wave

A plane acoustic wave may be described in terms of the displacement of a particle at a distance x from the wave source and at a time t. The analytical relation expressing the particle displacement as a function of distance and time for a harmonic wave is

$$\xi = \xi_m \cos \frac{2\pi}{\lambda} (ct - x) \tag{11-20}$$

where  $\xi$  is the particle displacement,  $\xi_m$  is the particle-displacement amplitude, c represents the sound velocity, and  $\lambda$  is the wavelength. An observer located at some particular distance  $x_1$  from a plane wave source will experience a periodic variation of the particle displacement and velocity. Another observer located at a distance  $x_2$  from the source will experience exactly the same relative periodic motion; however, the absolute time at which the maximum and minimum points in the motion occur will depend on the distance  $(x_2 - x_1)$  and the wave velocity c. The amplitude of the oscillatory motion will decrease with the distance from the wave source owing to viscous dissipation in the fluid. The plane wave described by Eq. (11-20) is called a traveling wave since the particle displacement is dependent on time and the distance from the wave source. Traveling waves may be described in a similar manner for cylindrical wave propagation.

The fluctuations in pressure due to the passage of a plane sound wave may be described in terms of the amplitude of the particle displacement through the relation

$$p = \beta \frac{\partial \xi}{\partial x} = -\beta \frac{2\pi}{\lambda} \, \xi_m \sin \frac{2\pi}{\lambda} \, (ct - x) \tag{11-21}$$

where  $\beta$  is the adiabatic bulk modulus of the fluid defined by

$$\beta = -V \frac{dp}{dV} \tag{11-22}$$

The intensity of a sound wave is defined as the flux of energy per unit time and per unit area. Several equivalent expressions for the intensity of a plane wave are given in Eq. (11-23).

$$I = \frac{1}{2}\rho_{s}c(\xi_{m})^{2}$$

$$= \frac{1}{2}\rho_{s}c\omega^{2}\xi_{m}^{4}$$

$$= \rho_{s}c(\xi_{rm})^{2}$$

$$= p_{rms}\xi_{rms}$$

$$= \frac{p_{s}^{2}cms}{2}$$
(11-23)

where

 $\rho_a = air density$ 

ω = frequency

Em = velocity amplitude of the wave

ξ_{rms} = rms value of the particle velocity ν_{rms} = rms pressure fluctuation

It is worthwhile to note that the intensity expressions containing the pressure terms do not apply for the case of cylindrical or spherical waves unless the radius of curvature of these waves is large enough that the wave front may be approximated by a plane

### Standing waves

Standing waves, like traveling waves, are described in terms of periodic particle displacements and the corresponding periodic particle velocities. For the case of traveling waves the amplitude of the particle displacement is the same regardless of the position x provided that viscous disapitation effects are neglected. For standing waves the amplitude of the particle displacement will follow a periodic variation with the distance x from the sound source. At even quarter-wavelengths the amplitude will be zero, and at odd quarter-wavelengths the particle-displacement amplitude will take on its maximum value. Consequently, the term "standing wave" is derived from the fact that the amplitude of the particle displacement has a periodic variation which is independent of time. Thus, we have the idea that the wave "stands" in a certain position. The particle motion in a standing wave may be represented by the relation.

$$\xi = 2\xi_m \sin\left(\frac{2\pi x}{\lambda}\right) \cos\left(\frac{2\pi ct}{\lambda} + \text{const}\right)$$
 (11-24)

### Constant-pressure sound field

Constant sound pressure waves are distinctly different from either traveling waves or standing waves and are encountered in rever-

berant chambers whose walls reflect the major portion of the wave energy striking them. For the ideal case, the energy of the sound source is distributed uniformly throughout the reverberant room so that the fluid will experience a uniform compression and expansion in all directions.

Traveling waves and standing waves represent a vector field, i.e., they depend on the direction in which the wave is propagating. Reverberant waves, for the ideal case, are independent of either distance or direction from the wave source; hence, they represent a scalar field. There is evidently no simple correlation between the pressure fluctuations and the particle displacements in the free space of a reverberant room.

### PROBLEMS

- 11-1 The vibrating wedge shown in Fig. 11-1 is used for an amplitude measurement. The length of the wedge is  $6.0 \pm 0.02$  in., and the thickness is  $1.0 \pm 0.01$  in. The x distance is measured as  $x = 2.2 \pm 0.05$  in. Calculate the vibration amplitude and its uncertainty in percent.
- 11.2 A small cantilever vibrometer is available for measurement of vibration frequency, but the specification sheet is lost so that the properties of the device are not known. The instrument is calibrated by placing it on a large compressor in the laboratory which is rotating at  $300 \pm 2.0$  rpm. The measured length for resonance conditions is  $2.2 \pm 0.01$  in. Calculate the frequency which the instrument will indicate when  $L=4.0 \pm 0.02$  in. Also calculate the uncertainty in the measurement at this length.
- 11-3 Consider the cantilever beam of Example 11-1. Suppose the uncertainties in the material properties and dimensions are

```
w_E = 2\%

w_r = 0.0005 in.

w_p = 5 \text{ lb}_m/\text{ft}^2

w_L = 0.01 in.
```

Calculate the resulting uncertainty in  $\omega_n$  at L = 1.0 and L = 4.0 in.

11-4 A cantilever beam is to be used for the measurement of frequencies between 100 and 1,000 cps. The beam is to be made from a rod of spring steel having the properties given in

Example 11-1. The maximum length of the rod is to be 5 in., and the uncertainties io material dimensions and properties are those given in Prob. 11-3. Calculate the nominal diameter of the rod and the uncertainty in the frequency at 100 and 1,000 cps.

- 11-5 A seismic accelerometer is to be used to measure linear acceleration over a range from 100 to 1,000 ft/sec¹. The natural frequency of the instrument is 200 cps, and this value may vary by ±2 cps owing to temperature fluctuations. Calculate the allowable uncertainty in the relative displacement measurement in order to ensure an uncertainty of no more than 5 percent in the acceleration measurement.
- 11-6 A seismic instrument is to be used to measure velocity. Show that the input velocity amplitude is

$$v_0 = \left(\frac{dx_1}{d\ell}\right)_0 = \omega_1 x_0$$

Subsequently show that this velocity amplitude may be expressed in terms of the steady-state relative displacement as

$$(x_2 - x_1)_0 = \frac{v_0(\omega_1/\omega_n)}{\omega_n [(1 - (\omega_1/\omega_n)^2]^2 + [2(c/c_c)(\omega_1/\omega_n)]^2]^2}$$

- 11-7 Calculate the value of the time constant for the instrument in Prob. 11-5 if  $c/c_c \approx 0.65$
- 11.8 Plot the error in acceleration measurement of a seismic instrument for c/c_e = 0.7 versus frequency ratio, i.e.,

$$1 - \frac{(x_2 - x_1)_0 \omega_n^4}{\alpha_0} \quad \text{versus} \quad \frac{\omega_1}{\omega_n}$$

11-9 A large seismic instrument is constructed so that m = 100 lb_m and c/c_e = 0.707. A spring with k = 200 lb_f/ft is used so that the instrument will be relatively insensitive to longerquency signals for displacement measurements and relatively insensitive to high-frequency signals for acceleration measurements. Calculate the value of linear acceleration which will produce a relative displacement of 0.1 m on the instrument. Calculate the value of ω/ω such that

$$\frac{(x_1-x_1)_0}{x_0}=0.99$$

11.10 A seismic accelerometer is to be designed so that the time constant calculated from Eq. (11-15) is equal to the period

- of the maximum acceptable frequency for a 1 percent error in measurement, that is,  $(x_2 x_1)_0/a_0 = 0.99$ . Plot  $\omega_n$  versus  $c/c_c$  in accordance with this condition.
- 11-11 Calculate the phase angle  $\phi$  for the conditions of Example 11-2.
- 11-12 Calculate the phase angle  $\phi$  for the conditions of Example 11-3.
- 11-13 Calculate the energy flux and rms pressure variation corresponding to a sound intensity of 100 db.
- 11-14 The estimated accuracy of a sound-intensity measurement is usually expressed in decibels. Calculate the uncertainties in intensity in watts per square centimeter corresponding to  $\pm 1$ ,  $\pm 2$ , and  $\pm 3$  db. Express these as percentage values at sound levels of 50, 80, and 120 db.
- 11-15 A standing sound wave is created in room air  $(70^{\circ}\text{F}, 14.7 \text{ psia})$  with a frequency of 1,000 cps. The peak sound intensity occurring in the wave is 120 db. Plot the sound intensity and pressure fluctuations as functions of x for one wavelength. Over what fractional portion of a wavelength could the intensity be considered constant, consistent with an estimated uncertainty of  $\pm 1$  db in the intensity measurement?

### REFERENCES

- Beckwith, T. G., and N. L. Buek: "Mechanical Measurements," Addison-Wesley Publishing Company, Inc., Reading, Mass., 1961.
- Beranek, L. L.: "Acoustics," McGraw-Hill Book Company, New York, 1954.
- Beranck, L. L., "Noise Reduction," McGraw-Hill Book Company, New York, 1960.
- Dove, R. C., and P. H. Adams: "Experimental Stress Analysis and Motion Measurement," Merrill, Columbus, Ohio, 1964.
- Gross, E. E.: Noise Measuring and Sound Control, Refrig. Eng., vol. 66, p. 49, 1957.
- Harris, C. M., and C. M. Crede (eds.): "Basic Theory and Measurements," vol. 1, "Shock and Vibration Handbook," McGraw-Hill Book Company, New York, 1961.
- Hetenyi, M.: "Handbook of Experimental Stress Analysis," John Wiley & Sons, Inc., New York, 1950.
- 8. "ASHRAE Guide and Data Book," Amer. Soc. Heating, Refrig., and Air Cond., 1963.
- Condon, E. U. (ed.): "Handbook of Physics," McGraw-Hill Book Company, New York, 1958.

# Thermal and nuclear radiation measurements

### 12-1 INTRODUCTION

In Chap, 8 we have already mentioned the importance of thermal radiation measurements in temperature determinations. In this chapter we shall examine the physical principles and operating characteristics of some of the more important thermal radiation detectors and indicate their range of applicability. For a rather complete survey of the field of infrared engineering and thermal radiation detectors the reader is referred to the monograph by Hackforth [7].

Radioactivity measurements comprise a broad field of activity or engineers and are becoming increasingly important in many applications. In this chapter we shall discuss some of the measurements which find wide application and indicate the devices used for performing these measurements. Our discussion is, of necessity, a cursory one, and the interested reader should consult the book by Price [10] for detailed information on detection of nuclear radiation.

### 12-2 DETECTION OF THERMAL RADIATION

The measurement of thermal raduation is basically a measurement of radiant energy flux. The detection of this energy flux may be accomplished through a measurement of the temperature of a tim metal strip exposed to the radiation. The strip is usually blackened to absorb most of the radiation mendent upon it and is constructed as thun as possible to minimize the heat capacity and thereby bring about the most described transpent characteristics. A schematic of

- of the maximum acceptable frequency for a 1 percent error in measurement, that is,  $(x_2 x_1)_0/a_0 = 0.99$ . Plot  $\omega_n$  versus  $c/c_c$  in accordance with this condition.
- 11-11 Calculate the phase angle  $\phi$  for the conditions of Example 11-2.
- 11-12 Calculate the phase angle  $\phi$  for the conditions of Example 11-3.
- 11-13 Calculate the energy flux and rms pressure variation corresponding to a sound intensity of 100 db.
- 11-14 The estimated accuracy of a sound-intensity measurement is usually expressed in decibels. Calculate the uncertainties in intensity in watts per square centimeter corresponding to  $\pm 1$ ,  $\pm 2$ , and  $\pm 3$  db. Express these as percentage values at sound levels of 50, 80, and 120 db.
- 11-15 A standing sound wave is created in room air  $(70^{\circ}\text{F}, 14.7 \text{ psia})$  with a frequency of 1,000 cps. The peak sound intensity occurring in the wave is 120 db. Plot the sound intensity and pressure fluctuations as functions of x for one wavelength. Over what fractional portion of a wavelength could the intensity be considered constant, consistent with an estimated uncertainty of  $\pm 1$  db in the intensity measurement?

### REFERENCES

- Beckwith, T. G., and N. L. Buck: "Mechanical Measurements," Addison-Wesley Publishing Company, Inc., Reading, Mass., 1961.
- Beranck, L. L.: "Acoustics," McGraw-Hill Book Company, New York, 1954.
- Beranek, L. L., "Noise Reduction," McGraw-Hill Book Company, New York, 1960.
- Dovc, R. C., and P. H. Adams: "Experimental Stress Analysis and Motion Measurement," Merrill, Columbus, Ohio, 1964.
- Gross, E. E.: Noise Measuring and Sound Control, Refrig. Eng., vol. 66, p. 49, 1957.
- Harris, C. M., and C. M. Crede (eds.): "Basic Theory and Measurements," vol. 1, "Shock and Vibration Handbook," McGraw-Hill Book Company, New York, 1961.
- 7. Hetenyi, M.: "Handbook of Experimental Stress Analysis," John Wiley & Sons, Inc., New York, 1950.
- 8. "ASHRAE Guide and Data Book," Amer. Soc. Heating, Refrig., and Air Cond., 1963.
- Condon, E. U. (ed.): "Handbook of Physics," McGraw-Hill Book Company, New York, 1958.

### Thermal and nuclear radiation measurements

#### 12-1 INTRODUCTION

In Chap. 8 we have already mentioned the importance of thermal radiation measurements in temperature determinations. In this chapter we shall examine the physical principles and operating characteristics of some of the more important thermal radiation detectors and indicate their range of applicability. For a rather complete survey of the field of infrared engineering and thermal radiation detectors the reader is referred to the monograph by Hackforth [7].

Radioactivity measurements comprise a broad field of activity measurements comprise a broad field of activity applications. In this chapter we shall discuss some of the measurements which find wide application and indicate the devices used for performing these measurements. Our discussion is, of necessity, a cutsory one, and the interested reader should consult the book by Price [10] for detailed information on detection of nuclear radiation.

### 12-2 DETECTION OF THERMAL RADIATION

The measurement of thermal radiation is basically a measurement of radiant energy flux. The detection of this energy flux may be accomplished through a measurement of the temperature of a thin metal strip exposed to the radiation. The strip is usually blackened to absorb most of the radiation incident upon it and is constructed as thin as possible to minimize the heat capacity and thereby bring about the most desirable transient characteristics. A schematic of




Fig. 12-1. Schematic of the general thermal radiation detector.

the general thermal radiation detector is given in Fig. 12-1. The temperature attained by the element is a function not only of the radiant energy absorbed but is also dependent on the convection losses to the surroundings and conduction to the mounting fixtures. Convection losses from the element may be reduced by enclosing the detector in an evacuated system with an appropriate window




Fig. 12-2. Infrared transmission characteristics of several optical materials according to Ref. [1] as arranged by Hackforth [7]. Sample thickness = 2 mm, long-wavelength cutoff at 10 percent transmittance.

for transmission of the radiation. The infrared transmission characteristics of several substances employed as window materials are given in Fig. 12-2 according to Ref. [1]. Conduction losses may be reduced with suitable insulating materials.

Either thermocouples or thermopiles may be used for detecting the temperature of the blackened radiation-sensitive element.




Fig. 12-3. A commercial radiometer utilizing a thermopile sensor. (a) Cutaway of Instrument; (b) detail of thermopile sensor. (Courtesy Minneapolis-Hongywell Co.)




Fig. 12-4. A commercial thermistor-radiation detector. (Courtesy Barnes Engineering Co., Stamford, Conn.)

Thermopiles offer the advantage that they produce a higher voltage output. Many ingenious methods of construction have been devised for such thermopiles, a commercial example of which is given in Fig. 12-3. The expanded view of the thermopile shows the blackened junction pairs surrounded by an annular ring of mica which serves as both electrical and thermal insulation. The thermopile registers the difference in temperature between the hot junctions and the ambient temperature surrounding the detector. The lens at the front of the device focuses the radiation on the thermopile junctions. Special circuitries are used to provide for compensation of ambient temperatures between 50 and 250°F.

Thermal radiation may also be sensed by a metal bolometer which consists of a thin strip of blackened metal foil such as platinum. The temperature of the foil is indicated through its change in resistance with temperature. An appropriate bridge circuit is used to measure the resistance.

Thermistors are widely used as thermal radiation detectors, and a cutaway drawing of a commercial detection device is given in Fig. 12-4. Two thermistors are enclosed in the detector case which is covered by an appropriate glass window having satisfactory transmission characteristics. One thermistor element is exposed to the incoming radiation which is to be measured, while the other element is shielded from this radiation. The shielded element is connected in the circuit so that it furnishes a continuous compensation for the temperature of the detector enclosure. A schematic of a commercial radiometer using thermistor detectors is given in Fig. 12-5. The incoming radiation is focused by the mirror system




Fig. 12-5. Schematic of a commercial radiometer utilizing a thermistor detector.
(Courtesy Barnes Engineering Co., Stamford, Conn.)

onto the thermistor detector. A motor-driven chopper periodically interrupts the radiation so that an alternating signal is produced which may be amplified more easily. The amplified signal is subsequently rectified to produce an output voltage proportional to the tradiant flux incident on the thermistor detector. In this system mirrors may be adjusted so that the optical system can be focused on an area as small as 1 mm. The movable mirror and focusing lamp are used for this purpose. The system is exceedingly sensitive and may even be used for detection of radiation from sources near room temperatures.

Thermal radiation detectors are calibrated directly by obtaining the output as a function of the known radiation from a blackbody source at various temperatures. A typical blackbody source
is constructed as shown in Fig 12-6. The conical cavity is constructed of some high-conductivity material such as aluminum or
copper, and the inside surface is blackened. An electric heater
maintains the cavity at a desired temperature which is indicated
and controlled through a sensitive electric-resistance thermometer
or thermistor. Baffles near the opening prevent stray radiation




Fig. 12-6. Typical construction of a blackbody source.

Table 12-1 Characteristics of thermal receivers;

Туре	Response time	Energy threshold, walls
Thermocouple	0.2 sec	3.0 × 10-6
Thermistor bolometer	3.0 msec	7.2 × 10 ⁻¹
Metal bolometer	4.0 msec	$3.3 \times 10^{-6}$

f According to Ref. [2].

from the surroundings from influencing the radiation output of cavity. The detailed construction of blackbody standards is cussed by Marcus [9]. It may be noted that cavities like the discussed above may give effective emissivities within 1 per of blackbody conditions.

A comparison of the approximate transient and energy throold characteristics of three types of thermal radiation receiver given in Table 12-1 according to Ref. [2]. The energy threst values are the minimum energy which may adequately be deter by such a device.

### Example 12-1

A certain thermistor radiation bolometer detector has characteris such that the minimum input power necessary to produce a signal-to-n ratio of unity is  $10^{-8}$  watt. Suppose such a detector is located 3 ft fro blackbody radiation source and is perfectly black. Calculate the tempeture of the source necessary to produce a signal-to-noise ratio of 10, assigned that the detector and surroundings are maintained at  $70^{\circ}$ F. Source is a black sphere, 2 in. in diameter, and the detector area is 1 m

Solution. The net energy absorbed by the detector is

$$q = \sigma A(T_{\bullet}^4 - 530^4)(\frac{1}{3.6})^2$$

where A is the detector area. For a signal-to-noise ratio of 10 the inpower must be  $10 \times 10^{-s} = 10^{-s}$  watt =  $3.413 \times 10^{-s}$  Btu/hr = q. Th

$$T_{\bullet}^{4} - 530^{4} = \frac{(3.413 \times 10^{-7})(36)^{2}}{(0.1714 \times 10^{-8})(0.01)(0.001076)}$$
$$= 240 \times 10^{8}$$

$$T_{\star} = 565^{\circ} R = 106^{\circ} F$$

For a signal-to-noise ratio of 100 the corresponding value of  $T_{\bullet}$  would 291°F. From the results of this example we see why optical systems li

those shown in Figs. 12-3 and 12-5 are used to collect the radiation over a fairly large area and focus it on the small surface area of the detector.

#### 12-3 MEASUREMENT OF EMISSIVITY

An apparatus for the measurement of total normal emissivity has been described by Snyder, Gier, and Dunkle [11] The apparatus uses a thermopile radiometer and is constructed as shown in Fig. 12-T. An electric heater is used to maintain the temperature of the sample, while thermocouples embedded in the sample furnish an indication of its temperature. A detailed drawing of the their mopule receiver is shown in (b). It is constructed of 160 junctions of silver-constants in mounted in a cylindrical housing which is blackened on the inside. Two blackened aluminum forf strips are attached to the junctions. The rear shield has a narrow slot which allows




Fig. 12-7. Apparatus for measurement of normal emissivity according to Ref. (a) Schematics (b) detail of thermopile comtraction.

exposure of the hot junction strip to the radiant flux from the sample while exposing the cold junction strip to the temperature of the thermopile enclosure. The temperature difference between the hot and cold junctions is thus taken as an indication of the radiant energy flux which, in turn, is related to the emissivity of the sample. The conical shield on the front of the device ensures a proper concentration of energy from the sample. According to Ref. [11] the device furnishes essentially a linear output of 0.1275 mv per Btu/(hr)(ft²) radiant flux. If the temperatures of the hot and cold junctions are assumed to be essentially the same as the inside temperature of the radiometer (this apparently is a good assumption because of the small total energy absorbed in the radiometer) and the sample is assumed gray, the total normal emissivity of the sample is

$$\epsilon_{\epsilon} = \frac{7.84 E}{F_{t\sigma}(T_{\epsilon}^{i} - T_{E}^{i})}$$
 (12-1)

where

E =voltage output of the thermopile, mv

 $T_{\bullet} = \text{sample temperature}$ 

The state of the s

The real of the control of the first of the control of the control

 $T_R = \text{radiometer temperature}$ 

The view factor  $F_{tt}$  is calculated from

$$F_{tr} = \frac{r_1^2}{r_1^2 + L^2} \tag{12-2}$$

In order for the measurement to be valid the temperature of the radiometer must be maintained at very nearly that of the surroundings.

Glaser and Blau [6] have presented a method for measurement of spectral emissivities, and the interested reader should consult their paper for additional information on spectral characteristics of surfaces. Gier et al. [5] discuss the measurement of spectral reflectivity.

### Example 12-2

A measurement of total emissivity is made with the apparatus shown in Fig. 12-7. L=14.25 in. and  $r_1=1.50$  in. The output is  $0.823\pm0.005$  mv,  $T_r=703\pm1.0^\circ\mathrm{F}$ , and  $T_R=70\pm0.5^\circ\mathrm{F}$ . Calculate the nominal value of the emissivity, and estimate the uncertainty in the measurement.

Solution. We first calculate the view factor Ft, as

$$F_{tr} = \frac{(1.50)^2}{(1.50)^2 + (14.25)^2} = 0.011$$

The emissivity is then calculated with the use of Eq. (12-t).

$$\epsilon_* = \frac{(7.84)(0.823)}{(0.011)(0.1714 \times 10^{-4})(1163^4 - 539^4)}$$
  
= 0.195

We use Eq. (3-2) to calculate the uncertaints The appropriate parameters

$$\begin{split} \frac{\partial \epsilon}{\partial E} &= \frac{7.84}{F_{eff}(T_s^4 - T_s^6)} = 0.237 \text{ my}^{-4} \\ w_F &= 0.005 \text{ mv} \\ \frac{\partial T_s}{\partial T_s} &= \frac{7(7.84)(4)T_s^4}{F_{eff}(T_s^4 - T_s^6)^4} = -8.68 \times 10^{-49} \text{R}^{-1} \\ w_{T_s} &= 1.0^9 \text{R} \\ \frac{\partial \epsilon}{\partial T_s} &= \frac{7(7.84)(4)T_s^4}{F_{eff}(T_s^4 - T_s^6)^4} = 8.18 \times 10^{-49} \text{R}^{-1} \end{split}$$

wr. = 0.5°R

and the uncertainty in the emissivity is calculated as

$$u_1 = \{[(0.237)(0.005)]^2 + [(-8.65 \times 10^{-4})(1.0)]^2 + [(8.18 \times 10^{-4})(0.5)]^2\}^3 = 0.00147 \text{ or } 0.755\%$$

If the uncertainty in the source temperature had been ±5°F, the resulting uncertainty in the emissivity would be 0 0045 or 2.3 percent

### 12-4 NUCLEAR RADIATION

In the following sections we shall be concerned with methods for detecting nuclear radiation. A detailed consideration of the original of such radiation is quite beyond the scope of this discussion, but a few introductory remarks are appropriate in order to categorize the Vypes of nuclear radiation and indicate some of their praticular characteristics. A detailed discussion of the principles of nuclear radiation is given by Kaplan [8]; Price [10] presents a comprehensive appraisal of the subject of nuclear radiation detection.

We shall be concerned with the detection of four kinds of nuclear radiation (1) alpha (e.g. particles, (2) beta (g) particles, (3) gamma (s) rays, and (4) neutrons. An alpha particle is a helium nucleus which has a positive charge of 2 and a relative mass of 4 A beta Particle is a negatively charged electron having a relative mass of 9000549. The neutron has a zero charge and a relative mass of

unity. Gamma rays are high-energy electromagnetic waves which result from nuclear transformations and, as such, do not have mass or charge in the elassical sense. They may, however, produce ionizing effects in their interaction with matter. Alpha partieles are absorbed rather readily in many materials, beta partieles are usually more penetrating, and neutrons and gamma rays are the most penetrating types of radiation because they usually have higher energies and do not interact with coulomb force fields when entering a material. The interaction of these nuclear radiations with particular materials is a very complicated subject and forms the basis for nuclear-shielding applications. Our concern is with the detection of these types of radiation.

## 12-5 DETECTION OF NUCLEAR RADIATION

Nuclear radiation is detected through an interaction of the radiation with the detecting device which produces an ionization process. The degree of ionization may be measured with appropriate electronic circuitry. Two types of detection operations are normally performed: (1) a measurement of the number of interactions of nuclear radiation with the detector and (2) a measurement of the total effect of the radiation. The first type of operation is a counting process, while the second operation may be characterized as a mean level measurement. The counting operation frequently ignores the energy level of the radiation, while the mean level measurement is used for determining the energy level of the irradiation. The popular Geiger-Müller counter is typically used for nuclear counting operations, while ionization chambers and photographie plates are used for energy-level measurements. Scintillation detectors may be used for both counting and energy-level measurements. We shall diseuss these different types of detectors and indicate their range of applicability.

# 12-6 THE GEIGER-MÜLLER COUNTER

A typical cylindrical-tube arrangement for a Geiger-Müller tube is shown in Fig. 12-8. The anode is a tungsten or platinum wire, while the cylindrical tube forms the eathode for the circuit. The tube is filled with argon with perhaps a small concentration of alcohol or some other hydrocarbon gas. The gas pressure is slightly below atmospheric. The ionizing particle or radiation is transmitted through the eathode material, or some window material




Fig. 12-8. Typical cylindrical-tube errangement for a Geiger-Muller counter.

installed therein, and through interaction with the gas molecules produces an ionization of the gas. If the voltage E is sufficiently high, each particle will produce a voltage pulse. The country performance of the tube is indicated in Fig. 12-9. The plateau region typically slopes slightly upward at a rate of from 1 to 10 percent per 100 volts. The tube must be operated in the plateau region which has a width of approximately 200 volts for commercial tubes. When the particle causes a discharge or pulse, three is a time delay before the tube can detect another particle and register another pulse. This delay is roughly the time required to recharge the anode and cathode system, i.e., to establish a new space charge




Fig. 12-9. (a) Counting performance of system in Fig. 12-8 as a function at pressed voltage; (b) detail of Gelger-caunter region.




Fig. 12-10. Construction of an end-type Geiger counter.

in the gas. The counting rate of the G-M tube is thus limited by this delay time. The maximum counting rates are of the order of 104 counts/sec.

An end-type Geiger counter tube may be constructed as shown in Fig. 12-10. This type of tube is used for counting  $\alpha$  and  $\beta$  particles and low-energy  $\gamma$  rays. For these low-energy radiations the window is usually a thin sheet of mica or Mylar.

### 12-7 IONIZATION CHAMBERS

An ionization chamber may be constructed in basically the same way as the Geiger counter shown in Fig. 12-8 except that the tube is operated at a much lower voltage. This region of operation is indicated in Fig. 12-9. The arrangement may be modified, however, to accommodate specific applications. A schematic of a typical parallel-plate ionization chamber is shown in Fig. 12-11 according to Price [10]. In operation, the chamber is charged with a voltage which is high enough to ensure that electrons produced by the ionizing radiation will be collected on the anode. The voltage is




Fig. 12-11. Parallel-plate ionization chamber according to Ref. [10].

not so high that it triggers excitation of other molecules by electrons produced in the contaction process. This is in contract to the operation of the G-Y counter which has a rufficiently high voltage that once contaction is effected by the incoming radiation, rule-quent ionization of other molecules also takes place in an avalanche fathion which produces the voltage pulse used for counting. To in everythe energy level of the incoming radiation, a measurement is rustle of the output current of the deven or a determination is runde of the charge released in the chamber over a period of time. The invitation chamber may also be used as a pulse-type device for the measurement of the pulse bright force of the incoming and energies of kinds-energy sights particles. In this application a measurement of the pulse bright force of his made in order to determine the energy bright of the disk a porticles.

# 12-8 PHOTOGRAPHIC DETECTION METHODS

When certain types of photograph of the are expected to cordere and auton and subsequently developed to open of the protings be taken as an indication of the total and are of reduced a credit of the limit of the produced files are available for nuclear and attention and the standard of the services of the primary one used for measuring the translation argument workers in atomic energy installation. The protographs has budge may be used for detecting and a protograph of the protograph of the compoure rates to the different types of the construction. In order to use a sunfa basis of increasing a first or windows, may be constructed to a take to the different types of the constructed to strike the photograph must be the opening of the developed file and the construction of the different types of the construction of the different rates.


circuit will include appropriate electronic counters. The scintillation counter may also be used for measuring the energy of the incoming radiation since, for certain crystals, the intensity of the flash of light is proportional to the energy of the radiation.

A number of scintillation materials are used, including both solids and liquids. The selection of the proper type of material for detection of specific radiations is discussed by Price [10] and Birks [3].

### 12-10 NEUTRON DETECTION

The three detection methods described above depend on an ionization process caused by an interaction of the  $\alpha$ ,  $\beta$ , or  $\gamma$  radiation with a gas or scintillation material. These detectors may not be used for neutrons because neutrons do not produce an ionizing effect. For this reason, the measurement of neutron flux is usually an indirect process which involves the utilization of an intermediate reaction to produce some type of ionizing radiation ( $\alpha$ ,  $\beta$ , or  $\gamma$  rays) which may then be used to indicate the incoming flux. A variety of neutron measurement devices are available, and the type which is used in practice depends strongly on the energy level of the neutrons to be measured and the total neutron flux. We shall discuss the principles of operation of only one type of detector which is applicable for the measurement of thermal neutron fluxes ( $E \sim 0.025cv$ ).

A typical reaction which is used for neutron detection is the interaction of neutrons with B¹⁰ to produce Li⁷ and an alpha particle. The alpha particles may subsequently produce ionizations in a gas and corresponding voltage pulses. The reaction is utilized in two ways: (1) The boron is present in the form of boron-trifluoride (BF₃) gas and placed in a chamber very similar to the G-M counter shown in Fig. 12-8. The potential difference between the central wire and the cylindical shell is about 1,300 volts. The wire diameter is about 0.002 in., while the cylinder diameter is about 1 in., with a length of about 6 in. (2) An alternate method of utilizing the B¹⁰  $(n,\alpha)$  reaction is shown in Fig. 12-13. The inside surface of the cylinder is coated with B¹⁰, while the volume is filled with helium



; 12-12. Schematic of a scintillation counter.




Fig. 12-13. Diagram of a B*-lined neutron counter. Filling gas is heilum plus 8 percent ether at 10 cm Hg pressure. From Ref. 1121.

and 5 percent other at 10 cm Hg pressure. The sensitivity of a typical BF, detector is about 10 counts see per unit neutron flux The sensitivity of the born-ceated chamber is about 5 to 10 counts/sec per unit neutron flux. Neutron flux is measured in neutron flux is measured in neutron flux.

Tube voltage v

If sufficiently high neutron fluxes are encountered, the detector may be operated as a current-sensitive device. The current output is then proportional to the incoming flux. Currents of about 0.1 ma may be obtained for neutron fluxes of 10th neutrons. "cmt. see

#### 12-11 STATISTICS OF COUNTING

We have already seen that many nuclear radiation measurements rely on a counting operation. In this section we wish to consider the statistics associated with such operations and indicate the possible errors involved.

In a given sample of radiosctive material there are a large number of atoms and the probability that each of these atoms will dear is quite small. The probability that n atoms will decay is given by the Poisson distribution [Eq. (3-9)) as

$$p(n) = \frac{n^n e^{-n}}{n!}$$

where

Np = n

N = total number of atoms

p = probability that each atom will decay

Equation (12-3) is generally valid for N > 100 and p < 0.01, and the standard deviation of the distribution may be shown to be†

$$\sigma = \sqrt{n} \tag{12-4}$$

The quantity n represents the average number of radioactive decays recorded in a series of observations. The radioactivity of a certain sample of material might be studied by observing the number of partieles or  $\gamma$  rays given off in specified increments of time. The counting operation could be performed with a G-M counter or other device. In general, the number of counts in a fixed interval of time, say 1 min, might vary considerably. Several counts would be taken, and the arithmetic average of the number of counts in each time interval is given by  $\bar{n}$ . The standard deviation of the measurement would be given by Eq. (12-4). In the above and following equations, n is taken to represent the average number of counts.

The parameter which is of interest in an experimental determination is the counting rate defined by

$$r = \frac{n}{l} \tag{12-5}$$

where t is the clapsed time for the average number of counts n. The accuracy of the determination of the counting rate depends on the number of counts and the time t.

When a counting measurement is made to determine the counting rate, the detector senses not only the signal from the radioactive source but also some background signal which is the result of spurious radioactivity of the environment. A separate measurement must be made of the background counting rate and this information used to determine the counting rate resulting from the radioactive source. The counting rate and its associated uncertainty is written as

$$r = r \pm w, \tag{12-6}$$

The counting rate for the source is

$$r_* = r_T - r_c$$
 (12-7)  
† See Ref. [10], p. 56.

(q)

where r₇ is the total counting rate and r₂ is the counting rate due to the background — The uncertainty in the source counting rate is time

$$w_i \approx (w_T^2 + w_b^2)^{\frac{1}{2}}$$
 (12-8)

where we and to are the uncertainties in the total and background counting rates respectively. The uncertainties for three counting rates may be estimated through the use of the standard deviation for the Poisson distribution given by Eq. (12-4) if the nuclear radiation satisfies the conditions for this distribution. The accuracy of the counting-rate measurement is clearly dependent on the length of time available for the measurement. A longer time affords the opportunity for observation of a larger number of counts and hence the establishment of a better average counting rate. Psample 12-5 illustrates the use of the above relations for determining counting rates.

#### Example 12-3

A certain radioactive sample is observed, and the total and background countrigrates are approximately 800 and 35 counts/mm respectively. If a total time of 45 mm is available for both counting measurements, estimate the apportionment of this total time such that there is minimum uncertainty in the source counting rate.

Salution. We may assume that both the source and background counts follow the Posson distribution so that the uncertainty is proportional to the standard deviation, i.e.,

$$\sigma_b = n_b^{\dagger}$$
 $\sigma_T = n_T^{\dagger}$ 

$$w_i = \frac{n_i!}{n_i!} \qquad w_i = \frac{n_i!}{n_i!} \qquad w_i = \frac{n_i!}{n_i!}$$

where  $t_i$ ,  $t_b$ , and  $t_T$  are the counting times for the source, background, and total respectively. We have also

$$n_i \approx r_{i}l_i$$
  $n_i \approx r_{i}l_i$   $n_T \approx r_{i}l_T$  (b)

so that

$$W_t^2 = \frac{\tau_s}{\tilde{t}_s} = \frac{r_b}{\tilde{t}_b} + \frac{r_T}{\tilde{t}_T}$$

in accordance with Eq. (12-8). We wish to optimize  $w_t$  by proportionment of the times  $t_t$  and  $t_T$  in accordance with

$$t_b + t_r = \text{const} = 45 \text{ min} \tag{d}$$

Thus, we optimize  $w_b$  by setting  $dw_b/dt_b = 0$  and obtain

$$2w_s \frac{dw_s}{dl_b} = 0 = -\frac{r_b}{t_b^2} - \frac{r_T}{t_T^2} \frac{dt_T}{dl_b}$$
 (e)

From Eq. (d),

$$\frac{dt_T}{dt_b} = -1$$

so that the optimum condition is

$$\frac{t_b}{t_T} = \left(\frac{r_b}{r_T}\right)^{\frac{1}{4}} \tag{f}$$

For the given counting rates,

$$l_5 + l_7 = 45$$

$$\frac{l_b}{l_T} = (\frac{35}{500})^{\frac{1}{2}} = 0.2091$$

and  $t_T = 37.2 \text{ min}$ ;  $t_b = 7.8 \text{ min}$ .

In the above calculations it has been assumed that the time interval is accurately determined and that the uncertainty for this determination is zero.

### Example 12-4

For the estimated counting rates given in Example 12-3 calculate the optimum total time necessary to give a standard deviation of the source counting rate of 1 percent. Repeat for total and background counting rates of 400 and 100 respectively.

Solution. The nominal value of the source counting rate is

$$r_* = r_T - r_b = 800 - 35 = 765$$
 counts/min

We have

$$\sigma_s^2 = \frac{r_b}{t_b} + \frac{r_T}{t_T} = [(0.01)(765)]^2 = 59.5$$

Also, from relation (/) of Example 12-3,

$$t_{i} = t_{r} \left(\frac{r_{b}}{r_{r}}\right)^{\frac{1}{2}}$$

so that

$$l_T = \frac{1}{\sigma_*^2} (r_0 l_{T_1} l_{+T_2})$$

$$= \frac{1}{58.5} [(35)^{\frac{1}{2}} (800)^{\frac{1}{2}} + 800] = 16.5 \text{ min}$$

The total counting time is 4 + tr. or

$$t_{\text{int}} = (1\ 209)(16\ 5) = 20\ \text{min}$$

For total and background counting rates of 400 and 100,

$$\sigma_*^* = \{(0.01)(300)\}^* = 0$$

$$t_r = \frac{1}{6}[(100)^{\frac{1}{2}}(400)^{\frac{1}{2}} + 400] = 66.7 \text{ min}$$

The total counting time is

#### Example 12-5

A radioactive sample is observed over a period of 30 min, and a total of 21,532 counts is recorded. The sample is then removed, and the background radiation is observed for another 30 min. The background produces 1,850 counts. Calculate the source counting rate and its uncertainty

Solution We have

$$r_r = 21,552/30 = 715.1 \text{ counts/min}$$

so that

The standard deviation of the source counting rate is calculated from Eq. (c) of Example 12-3.

$$v_r = \sigma_r = \left(\frac{r_b}{t_b} + \frac{r_T}{t_T}\right)^2 = 5.08$$
 counts. min

The odds on this uncertainty are 2.15 to 1 in accordance with Table 3-3.

### PROBLEMS

- 12-1 Consider the thermistor detector and radiation source of Example 12-1. Instead of the bare detector an optical system collects the radiation over a circular area of radius r and focuses it on the detector which is maintained at 70°F. Plot the source temperature necessary to maintain a signal-to-noise ratio of 200 as a function of the radius of the collecting optical system. Assume that the distance between the source and detector is 3 ft, as in Example 12-1. Neglect losses in the optical system for this calculation.
- 12-2 Repeat Prob. 12-1 for distances of 6 and 12 ft between the source and detector.
- 12-3 A thermocouple detector has characteristics such that the minimum input power necessary to produce a signal-to-noise ratio of unity is 3 × 10⁻⁴ watt. A 2-in.-diam optical system collects the input thermal radiation and focuses it on the thermocouple. The optical-thermocouple system is to be used to measure the temperature of a 2-in. black sphere 6 ft. away. The thermocouple bead is maintained at a temperature of 70°F. Estimate and plot the uncertainty in the temperature measurement as a function of the temperature of the sphere.
- 12-4 The apparatus of Example 12-2 is used for an emissivity determination between the temperature limits of 300 and 1000°F. Plot the percent uncertainty in emissivity as a function of T, for nominal emissivities of 0.2 and 0.8. Take the uncertainties in radiometer temperature and output voltage as

$$w_{T_R} = \pm 0.5^{\circ} \mathrm{F}$$

 $w_E = 0.005 \text{ my}$ 

The uncertainty in the source temperature is taken as  $\pm 1.0$ °F.

A radioactive sample is observed, and the total and back-

ground counting rates are 500 and 100 counts min respec-

tively. Estimate the total true necessary to produce a standard deviation of 2 percent in the normal source counting rate. Repeat for counting rates of 100 and 22.

12-6 The following counting data are collected on a radoactive sample. Each of the number of counts is taken in an exact time interval of I min. The background counting rate is known accurately as 23 counts min. Calculate the nominal value of the source counting rate and the uncertainty in this rate. Apply Chauvenet's enterior to climinate some of the data if necessary. Assume that the Powon distribution applies.

Interval number	No of counts
1	523
2	410
3	342
á	595
5	490
6	611
7	547
8	512

- 12-7 After a set of radioactive counting measurements has been made, it is found that the timing device has been pursons in operation. A set of calibration measurements on the timer has given the standard deviation of the time-interval measurements as \( \epsilon \). Using the approach taken in Example 12-3, derive an expression for the standard deviation of the source counting rate in terms of the standard deviations of the number of background and total counts and the standard deviations of the time interval.
- 12-8 Derive an expression for the optimum time tr under the conditions that r₁ = r₂. Express in terms of σ₂ and r₃.
- 12-9 Plot the optimum counting time from Prob 12-8 as

$$\frac{(t_T)_{\text{opt}\sigma_s^2}}{\tau_s}$$
 versus  $\frac{\tau_s}{\tau_s}$ 

12-10 Under the condition that the total number of counts for both the background and sample measurements is hunted, 1 e.,

 $n_b + n_T = K = \text{const}$ 

show that the minimum error condition is

$$\frac{n_b}{n_T} = \frac{r_b}{r_T}$$

and the total counting time for the background and sample measurements is

$$t_b + t_T = \frac{2K}{2r_b + r_a}$$

Plot

$$\frac{(t_b + t_T)r_*}{K}$$
 versus  $\frac{r_b}{r_*}$ 

### REFERENCES

- Ballard, S., and W. Wolfe: Optical Materials in Equipment Design, a Critique, ONR, Proc. Infrared Inform. Symposia, vol. 4, no. 1, p. 185, March, 1959.
- Billings, B. H., E. E. Barr, and W. L. Hyde: An Investigation of the Properties of Evaporated Metal Bolometers, J. Opt. Soc. Am., vol. 37, p. 123, 1947.
- Birks, J. B.: "Scintillation Counters," McGraw-Hill Book Company, New York, 1953.
- Fuson, N.: The Infrared Sensitivity of Superconducting Bolometers, J. Opt. Soc. Am., vol. 38, p. 845, 1948.
- Gier, J. T., R. V. Dunkle, and J. T. Bevans: Measurement of Absolute Spectral Reflectivity from 1.0 to 15 Microns, J. Opt. Soc. Am., vol. 44, p. 558, 1954.
- Glaser, P. E., and H. H. Blau: A New Technique for Measuring the Spectral Emissivity of Solids at High Temperatures, Trans. ASME, vol. 81C, p. 92, 1959.
- Hackforth, H. L.: "Infrared Radiation," McGraw-Hill Book Company, New York, 1960.
- Kaplan, I.: "Nuclear Physics," 2nd ed., Addison-Wesley Publishing Company, Inc., Reading, Mass., 1963.
- Marcus, N.: A Blackbody Standard, Instr. and Automation, vol. 28, March, 1955.
- Price, W. J.: "Nuclear Radiation Detection," 2nd ed., McGraw-Hill Book Company, New York, 1964.
- Snyder, N. W., J. T. Gier, and R. V. Dunkle: Total Normal Emissivity Measurements on Aircraft Materials between 100 and 800°F, Trans. ASME, vol. 77, p. 1,011, 1955.
- "Reactor Handbook," vol. 2, p. 951, U.S.A.E.C. Document, McGraw-Hill Book Company, New York, 1955.

# Basic industrial control arrangements

#### 13-1 INTRODUCTION

Previous chapters have described many devices which are used to measure physical variables such as temperature, frequency, vibration amplitude, etc. In Chap. 2 we indicated that these measurement devices would be important in control applications. The functions of a control device are to sense the output from the measurement device, compare this signal with some predetermined value or "set point," and then institute a control action which will bring the process variable in agreement with the desired condition. These functions are not simple if precise control is to be maintained.

In this chapter, it is our purpose to discuss some of the more conventional industrial control schemes and to acquant the reader with the terminology which describes these methods. The presentation is necessarily superficial but should serve as an aid in matching instruments for specific measurements with a desired control objective. The material in the previous chapters, particularly those discussions pertaining to transient response of the various instruments, may then be viewed in an overall perspective as it pertains to the control of process variables.

Let us first consider some of the terms which are important in control technology. Suppose a hetroneouple is subjected to an environment whose temperature is changing with time. In general, the thermocouple will not indicate the correct temperature of the environment at a particular instant of time but will respond in a manner like that shown in Fig. 13-1. There will be a certain log or log time necessary for the thermocouple to eatch up with the change in environment temperature. At any particular time the difference




Fig. 13-1. Diagram indicating dynamic error in measuring instrument.

between the actual temperature and the indicated temperature is ealled the dynamic error. At steady-state conditions there may still be a difference between the actual and indicated temperatures for reasons discussed in Chap. 8. Under these conditions the error is called a static error. In this chapter we shall be primarily concerned with dynamic errors and shall assume that the static errors either are zero or may be corrected by an appropriate analysis. The material in Chaps. 3 and 8 would be useful for making such corrections. Clearly, the speed of response of a control setup will be dependent on the lag and dynamic error of the primary measuring device.

The sensitivity of indicating or controlling instruments determines the dead time of a process change. For example, a self-balancing potentiometer circuit might be used to sense the output of the thermocouple discussed above. Such an instrument might have an equivalent millivolt sensitivity of  $\pm 1^{\circ}\mathrm{F}$ . Thus, the environment temperature would have to change by  $1^{\circ}\mathrm{F}$  in order for the instrument to indicate any change at all. The time necessary for the environment temperature to change by this amount would then be the dead time. In this example we say that the instrument has a dead zone of  $\pm 1^{\circ}\mathrm{F}$ .

The purpose of these introductory remarks is to indicate the fact that the lag, dynamic error, and dead time all influence the accuracy with which a certain variable may be controlled. The

smaller the values of these parameters, the bigher the accuracy of control.

### 13-2 ON-OFF OR TWO-POSITION CONTROL

The on-off or two-position control scheme is perhaps the simplest one available. Most thermostat control switches in the home operate on this principle. Typically, a bimetallic strip is used to sense the room temperature. When the temperature drops below a certain value, the strip bends and closes an electric contact which is connected to the room heater. When the room becomes sufficiently warm, the strip bends in the other direction and the contact is broken. The set-point or desired room temperature is established through a mechanical movement of the contact position with respect to the bimetallic strip. In this example we see that only the on or off operations are possible and that the temperature must be a certain number of degrees above or below the set point in order for one of the actions to take place. This region is called the neutral zone, and its width is dependent on many factors, including the thermostat construction, room size, and others. The ratio of the width of the neutral zone to the set point is called the regulation. The simple on-off control scheme has many applications where a simple, inexpensive control device is desired

On-off controls have the disadvantage that they may cycle quite of the under heavy-load conditions. In the case of the simple home thermostat we can see that the device would eyele much more olten in below-zero weather than in, say, 40°F weather. In some instances it is undesirable to have rapid cycling because of excessive electric power drain or excessive wear on numns, valves, etc.

As another example of two-position control consider the lollowing application. An outdoor tank at a chemical plant contains a liquid which must be maintained at a fixed temperature, say 85° F lor use in certain processes. The ambient air temperature may be above or below this value, depending on the time of day, time of year, etc. Thus, neither an on-off heating or an on-off cooling system can accomplish the control objective. Sometimes heating will be required, and sometimes cooling will be required. Suppose that water is used as a coolant along with steam as a heating fluid We might then install a two-position control which would open the water valve when the temperature rose above the set point and open the steam valve when the temperature dropped below the set point. As long as the temperature remained within the neutral zone neither

valve would be opened. Such a system is frequently called a high-lon control.

## 13-3 FLOATING CONTROL

Let us now consider a type of control system which is suitable for applications where gradual load changes occur. We shall take the home thermostat as an example again. Let the thermostat be connected so that there are two contacts which will control the fucl supply to the heating system through a motorized valve on the gas or fuel oil supply. The circuit is connected so that when the temperature falls below a certain set point a contact is energized which causes the valve to close. As long as the heating demand just matches the supply, no action is taken by the control and the valve remains in a fixed position. The range of temperature for which no action is taken is called the *dead zone*, as mentioned previously.

The name floating control arises from the fact that the control element (a valve in the above example) "floats" when there is no change in demand. This type of control system may be adapted to control processes where there are gradual load changes. When there are rapid load changes, the system reduces to a two-position control system. The speed of the valve or control element is an important factor in determining whether the system will cycle or "hunt." In many cases it is possible to vary the speed of a motorized valve to achieve optimum matching with the process which is to be controlled. Floating control is generally unsuitable to the control of systems with appreciable lag because it may produce cycling more severe than the simple two-position control.

# 13-4 PROPORTIONAL CONTROL

In the floating control system only a single-speed action is performed and the control valve only moves toward one of two positions: closed or open. The point at which the valve stops is dependent on the lag time of the primary indicating element and the lag time of the overall system which is being controlled. With proportional control the position of the control element is a linear function of the deviation of the controlled variable from the set point. For the thermostat system described above the control valve would be opened more if the room temperature dropped 10° below the set point than it would if the temperature dropped only 5°. The

range of operation over which the proportional control is exerted in called the proportional band. This band is usually expressed • « a percentage of the full-scale range of the indicating device. Proportional bands are usually variable with most commercial controllers.

A typical electrical proportional control system might use a bridge-potentiometer circuit to provide the proportional action with a manual adjustment on the set point. The deviation of the control variable from the set point is indicated with a toltage-divider slidewire. In the valve motor is a similar slide-wire which indicates the valve position. The deviation from the set point and the valve position are then compared with a bridge circuit. This circuit then actuates appropriate relays which open or close the valve in accordance with the desired proportional band. It may be noted that the wider the proportional band, the smaller the valve movement for a given deviation from the set point.

The advantage of proportional control is that there is matching of controller position with specific changes in the indicated variable For each deviation from the set point a specific controller setting 15 called for This advantage, however, becomes a disadvantage when one examines the controller response to change in load, i.e , a change in the process variable which is being controlled. Consider a certain temperature-control system which is in balance with the set point maintained hy a proportional controller. Non let there he a change in the temperature so that the controller must move a control valve to a new position which is determined by the deviation from the set point. The temperature change has resulted from some change in load requirements. The controller can act to compensate for this change by moving the valve to a new position; however, it may be noted that for each temperature, ie, each deviation from the set point, there is only one corresponding valve position. Thus, while the proportional controller can react to the change in process load, it could never bring the temperature back into agreement with the set point because the valve position corresponding to the set-point temperature will not match the load requirements. As a result of this behavior there will be an offset between the set point and the controlled variable when proportional controllers are used in situations where there is a sustained process-load change

The offset characteristic may be alleviated through the use of reset action. Manual reset provides a control whereby the proportional band may be shifted to account for the offset due to processional changes. In the above example the proportional band could be shifted so that the valve position corresponding to the set point would be either greater or lower, depending on whether the load has intereased or decreased




Fig. 13-2. Diagram illustrating proportional-plus-reset control action. (Courtesy Minneapolis-Honeywell Co.)

We now see that proportional control can eliminate the cycling which is present with the two-position control but that the problem of offset is encountered. This may be alleviated with the manual reset but is generally undesirable when rapid load changes are present. Thus, the proportional control with manual reset is best suited to those processes which have rather slow and moderate load changes.

The proportional-plus-reset control is one which provides automatic reset to compensate for offset due to load change. In a typical controller the amount of reset is governed by two things: the deviation of the controlled variable and the time duration of the deviation. Thus, the greater the deviation and the longer it persists, the greater the reset action will be. When the controlled variable again returns to the reset-point value, the reset action stops. Figure 13-2 indicates the effects of proportional and proportional-plus-reset action resulting from the change in the controlled variable shown.

It is seen that the proportional-plus-reset control takes the smooth control features of the proportional control and combines them with reset action to climinate offset. This combination control is thus an effective means for compensating for process-load changes without cycling, provided that the system lag time is small. The system lag time is a combination of the lag time of the primary indicator device and the speed of response of the control element. If system lag time is too large, the proportional-plus-reset control may develop overshoot and cycle to such an extent that effective control is not maintained.






Fig. 13-3. Diagram lilustrating proportional-plus-rate control action. (Courtesy Minneapolis-Honeywell Co.)




Fig. 13-4. Diagram illustrating effects of three types of control action.

Table 13-1 Summary of applicability of various control modes, (Courtesy Minneapolis-Honeywell Co.)

.Mode of control	Process-reaction rate	Transfer lag or dead time	Process-load changes
Two-position	Slow	Slight	Small and slow
Proportional	Slow or moderate	Small or moderate	Small
Proportional-plus-rate action	Slow or moderate	Unlimited	Small
Proportsonal-plus reset	Unlimited	Small or moderate	Slow, but any amount
Proportional plus-reset, plus-rate action	Unlimited	Unlimited	Unlimited

methods described above In general, the simplest control system which will do the job is the one which should be used Invariably, the selection of a control system is influenced by economic considerations so that desirable control objectives may be relaxed in deference to a consideration of the funds which are available. An elaborate control system could be devised to maintain the air temperature in an office within ±1°F However, the cost would be much higher than that for a system to maintain the temperature within ±4°F. The one-degree control would be desirable, but the prudent businessman will probably decide that the four-degree system will be satisfactory in view of the money he will save On the other hand, a delicate chemical process might require temperature control within ±1°F in order to avoid excessive rejections in the final product In this case, a less accurate and less expensive control system, though least expensive from the standpoint of capital expenditure, might result in less economical operation on a long-term herie

#### PROBLEMS


- 13-1 The heating system for a building uses steam which is supplied st a constant pressure and temperature regardless of load. Discuss the operation of the system using each of the control systems in Table 13-1. Consider the following situations.
  - a. Normal operation, day and night, with only about 50 percent of the available steam capacity required up 3 -- the coldest nighttime condition.

- Same as a but with 90 percent of steam required under most severe conditions
- c. Same as a but a "blue norther" hits in the afternoon and suddenly lowers the outside temperature by 40°F
- d. Same as c but the system is already operating near capacity
- c. Same as a but with only 20 percent of steam required under most severe conditions
- 13-2 A simple liquid-level control on a water-supply tank uses a float-operated switch which actuates a solenoid valve to supply additional water to the tank. When the level drops below a certain point, the float closes the switch and water is added at a constant rate. When the level rises to the specified value, the float breaks the switch contact. Discuss this control system considering the following factors as they relate to the accuracy of control, i.e., accuracy with which the liquid level may be maintained:
  - a. Tank capacity and size. Capacity ≈ cross-sectional area × depth.
  - b. Dead zone in the float-netnated switch.
  - c. Water-supply rate.
  - d. Water-drainage rate or loss rate.

Under what conditions would you think that a more sophisticated control system would be desired? Describe a possible physical setup for each of the control systems in Table 13-1, and indicate the conditions under which they would be needed.

- 13-3 A water heater is constructed as shown in the accompanying figure. The inlet water temperature and water flow may vary over a rather broad range, but the outlet water temperature is to be maintained at a constant value within certain tolerance limits. The coolant may be used to lower the water temperature when the inlet temperature is above the set point, and the electric heater may be used to raise the temperature, when the temperature at inlet is too low. Describe suitable physical setups for each of the types of control systems indicated in Table 13-1, and indicate their respective applicability to the problem considering the influence of the following factors:
  - a. The coolant enpacity of the tank
  - b. The response time of the powerstat and electric heater
  - c. The response time of the motorized valve
  - d. The rate of change of the inlet water flow and water temperature

 The degree to which either the electric heater or the coolant is operating at its maximum capacity



#### REFERENCES

- Doebelin, E. O.: "Dynamic Analysis and Feedback Control," McGraw-Hill Book Company, New York, 1962
- Harrison, H. L., and J G Boilinger "Introduction to Automatic Controls," International Textbook Company, Scranton, Pa, 1963
- Kallen, H. P. (ed.) "Handbook of Instrumentation and Controls," McGraw-Hill Book Company, New York, 1961
- 4 Truxal, J. C (ed.), "Control Engineers' Handbook," McGraw-Hill Book Company, New York, 1958



# Data acquisition and processing

#### 14-1 INTRODUCTION

All the previous chapters have illustrated, in one way or another, the manner in which an experiment can be planned to collect meaningful data. Selection of proper instrumentation and analyses of experimental uncertainties are all part of the planning process But, nothing has been said about the manner of collecting data and later processing of these data to produce the desired results of the experiments. The acquisition of data might consist simply of several people (or perhaps only one person) reading a number of instruments and recording the observations on a data sheet. The processing of data could be done in many ways, from simple slider rule calculations to a complexed digital-computer routine.

There are systems available today for rapidly collecting a great in printed form. The purpose of this chapter is to present a brief qualitative description of such systems and the functions of the elements which go together to make up an overall data-acquisition and processing installation.

#### 14-2 THE GENERAL ACQUISITION SYSTEM

The essential element in a modern data-acquisation system is the instrument transducer which furnishes an electric signal that is indicative of the physical variable being measured. The signal may be voltage, current, resistance, frequency, or electric pulses. Our discussion assumes that suitable transducers are available to convert the physical variables of interest into electric signals. As examples of such transducers we may recall that a thermecouple gives a

		•	
			c. <del>(</del> F)
			•

# Data acquisition and processing

#### 14-1 INTRODUCTION

All the previous chapters have illustrated, in one way or another, the manner in which an experiment can be planned to collect meaningful data. Selection of proper instrumentation and analyses of experimental uncertainties are all part of the planning process. But, nothing has been said about the manner of collecting data and later processing of these data to produce the desired results of the experiments. The acquisition of data might consist simply of several people (or perhaps only one person) reading a number of instruments and recording the observations on a data sheet. The processing of data could be done in many ways, from simple aliderule calculations to a complexed dictal-computer routine.

There are systems available today for rapidly collecting a great but of data, processing it, and displaying the desired results in printed form. The purpose of this chapter is to present a biref qualitative description of such systems and the functions of the elements which go together to make up an oversil data-acquisition and processing installation.

#### 14-2 THE GENERAL ACQUISITION SYSTEM

The essential element in a modern data-acquisition system as the instrument transducer which furnishes an electric aignal that is indicative of the physical variable being measured. The signal may be voltage, current, resistance, frequency, or electric pulses. Our discussion assumes that suitable transducers are available to convert the physical variables of interest into electric signals. As examples of such transducers we may recall that a thermocouple gives a

voltage representation of temperature, a strain gage gives a resistance representation of strain, and so on.

The object of a data-aequisition system is to collect the data and record them in a form suitable for processing or presentation. Thus, a recording potentiometer is a simple data-aequisition system which may be used for collecting temperature data from thermocouples. In this case, the data points must be read from the recorder chart. A more complicated system might convert the voltage signal from the thermocouple to a digital signal which could be used to operate a printing recorder so that the numerical value of the temperature is printed on a sheet of paper. Such a system is much more complicated than the simple voltage recorder because of the digital-conversion process. It is easy to see, however, that the digital output has many advantages.

The general data-acquisition system has three stages:

- 1. The input stage which consists of appropriate transducers and signal-conditioning circuits (amplifiers, filters, etc.).
- 2. A signal-conversion stage which converts the input signal to a voltage and subsequently expresses this voltage in digital form. The conversion to digital form is made by converting the voltage to frequency which, in turn, may be used to drive electronic counting circuits. The conversion is essentially a frequency-modulation process.
- 3. An output stage which takes the digital signal and expresses it in printed form on a sheet of paper, plots the data on graph paper, punches the data on cards, or stores the data on magnetic or punched tape. The output stage must include suitable eoupling circuits to express the digital signal in a form for driving a printer, card punch, magnetic tape, etc.

A schematic of this general system is shown in Fig. 14-1. The analog to digital converter is the conversion stage.

It is a rare eircumstance when data in only one variable are to be collected. The data-acquisition system, then, should include provisions for collecting multiple channels of data inputs. This collection process could be accomplished by having a channel like the one shown in Fig. 14-1 for each variable to be studied. The cost of such a system, however, would be quite high so that a scanner/programmer is normally employed for multiple-channel work. The scanner is a device which samples the data channels in rapid sequence so that only one conversion and output stage is necessary. Commercial devices are constructed so that any particular sequencing of 1 to 100 channels may be used at the discretion of the laboratory personnel. Thus, the system may be programmed to collect any




Fig. 14-1. Schematic of a general data-acquisition system.

desired range of variables, and the device is called a scanner/ programmer. The scanner may be considered as part of the input section of the general data-acquisition system

Many experimental programs involve the collection of data at regular time intervals or in some particular time sequence. The acquisition system may perform this timing function automatically by incorporating a digital clock and time standard in the scanner and/or converter stages.

Finally, it may be advantageous to apply signal conditioning to the output of the scanner/programmer. This conditioning might be amplification, voltage to frequency conversion for only a few of the channels, filtering, distortion or harmonic analysis of the waveform of some of the signals, etc. When all the above elements are combined, a very flexible data-acquisition system results, as shown in Fig. 14-2. It may be noted that the programmable feature of the scanner is normally used in the converter stage as well. This is essential since some channels may require signal conditioning while others may not.

The use of a flexible data-acquisition system like the one described above depends on many factors, not the least of which is cost. Such systems are expensive The expense may be entirely justified however in an installation where large quantities of data are to be collected.

#### 14-3 DATA PROCESSING

The digital computer is undoubtedly the most suitable means for processing large quantities of data. By processing, we mean the




Fig. 14-2. Schematic of a multichannel data-acquisition system.




Fig. 14-3. Combined data-acquisition and processing system.

calculation of results from the raw data and/or analysis of these data for consistency using statistical methods or other means. The computer must be programmed to perform the desired calculations and print out or feed the results to some suitable output device.

In the above section we have seen that a firstile data-acquisition system can collect and present data in many output forms. The punched card, punched tape, and magnetic-tape forms are all suitable for use as inputs to a digital computer, provided that the systems use coding which is compatible with the computer installation. It is easy to see that a complete data-acquisition and processing installation might be organized something like the schematic shown in Fig 14-3. Such large-scale systems are used, of course, in many industrial and soace applications.

#### 14-4 SUMMARY

What are the advantages of a flexible data-acquisition system like the one described above? There are several

- The output of the acquisition system can be obtained in a form which is ready for immediate input to a digital computer.
- 2. A large amount of data can be collected very quickly, thereby freeing personnel and instrumentation for other projects
- The multichannel system may be able to collect data for some particular transient process which could not be obtained otherwise.
- 4. Since the collection of data can be accomplished very rapidly with such systems, instrument transducers may enjoy more varied use in a laboratory because they are used for a shorter period of time on each project
- 6. The rapid collection of data coupled with rapid data processing by means of a computer can speed the overall experimental program so that men, money, and machines are not wasted because of excessive waiting periods between data collection, processing, and analysis

Offsetting these advantages are the high cost of the dataacquisition system and the absolute necessity that all measurements be made with electric transducers, e.g., we cannot use a simple manometer for a differential pressure measurement; some type of transducer must be employed

The decision of whether or not to purchase a data acquisition system is clearly dependent on the economics of the situation The author has no desire to belabor this point, but a statement

which has been made by many people in the past years in regard to digital computers may also be applicable to data-acquisition systems. The statement is

You can never economically justify the cost of a digital computer before you buy one. After you buy it you cannot get along without it because you find yourself solving problems you were never able to solve before.

# Appendix

#### TABLE A-1 Conversion factors Length 12 in. = 1 ft 2.54 cm = 1 in. 1u = 10-m = 10-4 cm Mass 1 kg = 2.205 lb_ 1 slug = 32 16 lb. 454 g = 1 lb. Force l dyne = 2 248 × 10-4 lb, 1 lb, = 4 448 newtons 104 dynes = 1 newton Energy 1 ft-lb/ = 1 356 joules 1 kwhr = 3413 Btu 1 hp-hr = 2545 Btu I Btu = 252 cal 1 Btu = 778 ft-lb, Pressure 1 atm = 14 696 lb//in. = 2,116 lb//ft2 1 atm = 10132 newtons/m2 1 in. Hg = 70.73 lb./ft2 Vsecositu 1 centipoise = 2 42 lb./hr-ft $1 \text{ lb_r-sec/ft}^2 = 32.16 \text{ lb_m/sec-ft}$ Thermal conductivity 1 cal/sec-cm-°C = 242 Btu/(hr)(ft)("F) I watt/cm-°C = 57 79 Btu/(hr)(ft "°F)

Table A-2 Properties of metals at 70°F

Metal	Density, lb_n/fl1	Specific heat C, Btu/lb _m -°F	Linear coef. of expansion, °F-1 × 104	Electrical conductivity relative to copper	Thermal conductivity k _r Blu/(hr)(ft)(°F)
Aluminum, pure	167	0.22	0.13	0.66	118
Red brass: 85% Cu, 9% Sn, 6% Zn Copper, pure Iron, pure Lead Magnesium Nickel Platinum Silver	544 555 493 710 109 556 1,335 657	0.092 0.095 0.108 0.031 0.242 0.106 0.032 0.056	0.10 0.09 0.065 0.16 0.145 0.07 0.05 0.107	1.00 0.18 0.08 0.40 0.25 0.18 1.15	35 223 42 20 99 52 40 235
Stainless steel: 18% Cr. 8% Ni	488 485	0.11	0 003 0.07	0.0234 0.12	9.4 33
Sicel, structural Tin Tennatan	456 1,208	0 054 0 032	0 11 0 02	0.16 0.33	37 94
Tungsten Zinc	446	0.092	0 18	0.31	37

Table A-3 Thermal properties of some nonmetals at 70°F

Material	Density, lb _m /ft ¹	Specific heat, Blu/lbn-°F	Thermal conductivity k, Btu/(hr)(ft)(°F)
Ashestos sheet	60	0.2	0.083
Brick, common	110	0.22	0.042
Concrete	140	0.16	1.0
Fiberboard	15	0.5	0.027
Fiberglass	6	0.5	0.022
Glass, window	160	0.16	0.50
85% magnesia pipe covering	15	0.2	0.042
Plaster	95	0.25	0.27

Table A-4 Properties of some saturated liquids at 68°F

Fluíd	Chemical formula	Density, lb=/fl2	Specific heat C, Btu/lb _m -°F	Kinematic viscosity r, ft*/sec	Thermal conductivity k, Btu/(hr)(fl)(°F)	Prandil No. Pr, c _r µ k
Ammonia	NH ₁	38.2	1.15	0.386 × 10-1	0.301	2.02
Carbon diexide	CO,	48.2	1,2	0.98 × 10-1	0.0504	4.10
Freon-12	CCl,F,	83.0	0.231	0.213 × 10-1		2.17
Glycerine	$C_1H_1(OH)$ ,	78.9	0.57	0.0127	0.165	12.5
Mercury	Hg	\$47.7	0.033	0.123 × 10-1		0.025
Motor oil						0.0
(typical)		55.0	0.45	0.010	0.08	10,000
Water	H ₂ O	62.4	1.0	1.08 × 10-1		7.02

Table A-5 Properties of gases at atmospheric pressure and 68°F

Gas	Chemical formula	Malecular verght	Btu/B°F	γ = <del>c,</del>	conductivity k	Viscosity, centipoise
Air		28 95	0 24	1.40	0 025	0.018
Acetylene	C,H,	26 02	0 38	1,25	0.0124	0 010
Ammonia	NH.	17 03	0.52	1,30	0.0142	0.010
Corbon diazide	L CO.	44 00	0 20	1,30	0 0095	0 015
Freon-12	CC1 ₂ F ₂	120 9	0 15	1.14	0 0053	0.013
Hydrogen	H.	2.01	3 4	1,40	0 103	0 0089
Methane	CH.	16 03	0.54	1,30	0 0196	0 011
Nutrogen	N.	28 02	0 245	1,40	0.0150	0 018
Ozygen	0,	32 00	0 215	1 40	0 0153	0 020

Table A-6 Properties of dry air at atmospheric pressure

Ť, 'F	$\mu$ , $\frac{tb_m}{hr \cdot ft}$	$k_* \frac{Btu}{(hr)(ft)(^*F)}$	en Btu Ibm. F	Pr
-100	0 0319	0 0104	0 239	0 739
~50	0 0358	0 0118	0 239	0 729
0	0 0394	0 0231	0 240	0 718
50 t	0 0427	0 0143	0 240	0 712
100	0 0459	0 0157	0 240	0 706
150	0 0484	0 0167	0 241	0 699
200	0.0519	0 0181	0 241	0 693
250	0 0547	0 0192	0 242	0 690
300	0 0574	0 0203	0 243	0 686
400	0 0626	0 0225	D 245	0 681
500	0 0675	0 0246	0 248	0 680
600	0 0721	0 0265	0 250	0 680
700	0 0765	0 0284	0 254	0 682
800	0 0806	0 0303	0 257	D 684
900	0 0846	0 0320	0 260	D 687
1000	0 0584	0 0337	0 263	0 690

† From Natl Bur Std (U S.), Circ 564, 1955

Table A-7 Properties of water (saturated liquid)†

	• • • • • • • • • • • • • • • • • • • •				
°F	$c_r, \frac{Btu}{tb_m - {}^c F}$	$F, \frac{lb_n}{ft^3}$	$\rho, \frac{lb_n}{fl-h\tau}$	$k, \frac{Btu}{(hr)(fl)(^2F)}$	$Pr, \frac{c_{\tau}\mu}{k}$
32	1.009	62,42	4.33	0.327	13.35
40	1 005	62,42	3.75	0.332	11.35
50	1.002	62.3S	3 17	0.33\$	9,40
60	1.000	62.34	2.71	0.344	7.88
70	0 998	62,27	2.37	0.349	6.78
92	0.998	62.17	2 08	0.355	5.85
90	0.997	62.11	1.85	0.360	5.12
100	0.997	61.99	1.65	0.364	4.53
110	0.997	61.S4	1.49	0.36\$	4.04
120	0.997	61.73	1.36	0,372	3.64
130	0.925	61.54	1.24	0.375	3,30
140	0.998	61.39	1.14	0.378	3.01
150	0.999	61.20	1.04	0.381	2.73
160	1,000	61.01	0.97	0.331	2,53
170	1.001	60.79	0.90	0.356	2,33
170	1.001	00.19	0.90	0.030	2,00
150	1.002	60.57	0.\$4	0.359	2.16
190	1 003	60.35	0.79	0.390	2.03
200	1.004	60.13	0.74	0.392	1.90
220	1.007	59.63	0.65	0.395	1.66
240	1 010	59.10	0.59	0.396	1.51
260	1.015	58.51	0,53	0.000	
280	1.020	57.94	0.33	0.396	1.36
300	1.026	57.31	0,45	0.395	1,24
350	1.044	55.59	0.45	0.395	1.17
400	1.067	53.65	0.33	0.391	1.02
450	1.00,	33.03	0.33	0.384	1.00
450	1.095	51.55	6,29	0.373	0.85
500	1.130	49.02	0.26	0 356	0.83
550	1.200	45.92	0.23		
600	1.352	42.37	0.21		

[†] From A. I. Brown and S. M. Marco, "Introduction to Heat Transfer," 3d ed., McGraw-Hill Book Company, New York, 1958.

Table A-8 Diffusion coefficients of some gases and vapors in air at 25°C and 1 atmi


Substance	$D_s \frac{cm^2}{sec}$
Ammonia	0.28
Benzene	0 053
Carbon dioxide	0 164
Hydrogen	0 410
Methanol	0.159
Water	0.256
† From R H. Per "Chemical Engineer	Ty (ed ),
book," 3d ed , McC Book Company, No	Faw-Hill

#### Table A-9 Approximate total normal emissivities of various surfaces at 70°F

Surface	Emissionly
Aluminum, heavily oxidized	0 20-0 30
Aluminum, polished	0 09
Asbestos sheet	0 93-0 96
Brass, polished	0.06
Brick	0 93
Carbon, lampblack	0.96
Copper, heavily axidized	0.75
Copper, polished	0 03
Enamel, white fused on tron	0 90
Iron, oxidized	0 74
Paint, aluminum	0 27-0 67
Paint, flat black lacquer	0 97
Steel, polished	0 07
Steel plate, rough	0 95
Tin, bright	0 06
Water	0.95

# Table A-10 Area moments of Incrtia for some common geometric shapes


## Rectangle



$$I_{sc} = \frac{3.5^{5}}{12}$$

$$I_{sc} = \frac{3.5^{7}}{12}$$


#### Right triangle




$$I_{x0} = \frac{bh^3}{35}$$

$$I_{y0} = \frac{hb^3}{35}$$

### Quadrant of circle




#### Circle




$$I_{x0} = I_{y0} = \frac{x\alpha^4}{4} = \frac{xd^4}{64}$$
 (Polar) 
$$J = \frac{x\alpha^4}{4} \approx \frac{xd^4}{32}$$

## Quadrant of ellipse



#### Ellipse





#### Index

Absolute performance, 26 Ballard, S. 390 Accuracy, general discussion, 8 Ballast circuit, 85 Adams, P. H., 338, 358 Batr, E. E , 380 Air, properties of, 401 Base length for strain gage, 323 Alpha particle detection, 368 Becker, J. A., 277 Alphatron vacuum gage, 172 Beckwith, T. G. 358 Alternating current, high-frequency Bellows gage, 162-164 measurement, 81 Beranek, L. L., 358 measurement, 79 Beta particle detection, 368 rms value, 81 Bevans, J. T., 380 Amplification ratio, 100 . Billings, B. H., 380 Amplitude response, definition, 20 Bimetallic strip thermometer, 232 Analog-to-digital converter in data Binomial distribution, 45 acquisition, 394 Birks, J. B , 372, 380 Analysis of data, 33-40 Blackbody, 251 graphical, 67-70 apparent temperature, 256 statutical, 40-45 source, 363 chi-square test, 55-61 Blau, H. H., 366, 380 Gaussian distribution, 46-53 Bollinger, J. G. 391 method of least squares, 61-64 Bomb calorimeter, 301 probability distribution, 47 Boron used for neutron detection, 372 standard deviation, 65-67 Bourdon-tube pressure gage, 161 Analytical balance, 313 Bridges, 89-97 influence of buoyancy forces, 315 a-c, 92-93 sensitivity, 313 Hay, 93 Apparent blackbody temperature, 256 Maxwell, 93 Area measurement, graphical methods, Owen, 92 resonance, 93 numerical methods, 149 Wheatstone, 90 Planimeter, 144-146 Wien, 92 Arithmetic mean, definition, 40 Bridgman, P. W. 176 Araberg, B. T., 196, 227 Bridgman gage, 166 Arons, A B., 176 Brown, A I., 402

Buck, N. L., 358

Ashby, G. C., Jr., 228

Cady, W. G., 124, 134 Calibration, general discussion, S Calorimetry, 297-302 Cantilever beam, as force transducer, 316 vibrating, 340 Capacitance pressure gage, 164 Capacitive transducer, 121 Cathode-ray oscilloscope, 105 Celsius temperature scale, 230 Centigrade temperature scale, 230 Chauvenet's criterion, 53 Chi-square test, 55-61 Cigars as smoke generators, 215 Cole, R. H., 176 Commonsense analysis, 36 Condon, E. U., 358 Conduction error in temperature measurement, 259 Consistency, importance, 34 Constant, F. W., 12, 31 Constant-pressure sound field, 355 Contrast in flow visualization, 210 Control, relation to measurement process, 3 Control systems, summary, 389 Convection heat-transfer formulas, summary, 265 Convection measurements, forced convection, 303 free convection, 304 Conversion factors, 399 Corrugated-disk diaphragm, 163 Counting rate, 374 Counting statistics, 373 Crede, C. M., 338, 358 Current measurement, a-c, 79 d-c, 75-78 high-frequency, \$1 Current-sensitive input circuit, 84 Curth, O. E., 222, 228 Curve fitting, 67 Cycling in control systems, 384

D'Arsonval movement, 77
Data acquisition, general system, 394
advantages of, 397
Data collection, 26, 394

Dead time, 382 Dead-weight tester, 159 Dead zone, 3S2 Dean, M., 338 Dean, R. C., 228 Decibels, related to gain, 100 sound wave, 352 Deformation sensitivity, 323 Delay, definition, 20 Density related to interferometer, 214 Deviation, definition, 40 standard, 41 Dial indicators, 137 Diaphragms, corrugated-disk, 163 deflection characteristics, 163 natural frequency, 165 pressure gage, 162 Differential transformer, principles, 118 used with pressure measurements, 164 Diffusion coefficient, definition, 293 measurement, 294 tabulated values, 403 Dimensional measurements, definition, 135 optical methods, 139 Discharge coefficient, definition, 181 (See also Flowmeters) Displacement measurement, capacitive transducer, 121 definition, 135 ionization transducer, 127 LVDT, 118 pneumatic gage, 141 resistance transducer, 118 Distortion related to frequency and phase-shift response, 22 Doebelin, E. O., 391 Doolittle, J. S., 302, 309 Dove, R. C., 338, 358 Drag flowmeters, 197 Drake, R. M., 277 Dresslea, R. F., 176 Dunkle, R. V., 365, 380 Durelli, A. J., 324, 338 Dushman, S., 167, 176 Dynamic error, 382 Dynamometer, 321

Eckert, E. R. G., 277	Filters, electrical, basic discussion, 98
Elastic elements as force transducers, 316	design formulas, 99
Electrical filters (see Filters, electrical)	passive networks, 101
Electrical resistance, variation with	Fixed errors, 35
temperature, 236	Floating control, 384
Electrical-resistance strain gage, 325	Flow calorimeter, 298
bridge circuits, 329	Flow measurement (see Flowmeters)
gage factor, 326	Flow visualization, basic optical effect
installation, 328	205
materials, 327	hydrogen-bubble method, 206
problems, 328	interferometer, 211-214
temperature compensation, 330	schlieren, 208-210
Electrical-resistance thermometer, 235	shadowgraph, 206-208
correction of lead resistance, 236	smoke method, 215
Electrical standards, 10	Flowmeters, drag, 197
Electrodynamometer movement, 80	flow nozzle, 185
Electronic counter, 113	lobed-impeller, 179
Electronic switch, 107	magnetic, 203
Emerson, W B., 152	nutating-disk, 178
Emissivity, definition, 253	obstruction, 180
measurement, 365	onfice, 184, 189
apectral, 366	positive-displacement, 178
tabulated values, 403	rotameter, 198
Errors, conduction, 259	rotary-vane, 170
in controls, 382	sonic-nozile, 195
dynamie, 382	summary, 222
fixed, 35	turbine, 200
radiation, 262	uncertainty in, 193
random, 35	ventura, 183
related to uncertainty, 35	Fluid-expansion thermometer, 234
systematic, 35	Frank, E., 79, 81, 134
Erwin, J. R., 228	Frequency, relation to probability, 42
Eshbach, O. N. 12, 31	Frequency measurement, electronic
ESKIB, S. G., 233, 277	counter, 114
Evans, J. C., 143, 152	oscilloscope, 109
Expansion factor, charts, 190	Frequency response, definition, 17
definition, 183	Fringes for interferometer, 213
Experiment planning, general discussion,	Pritze, J. R , 233, 277
25-28	Fuson, N , 380
Experimentation, relation to theoretical	
work, 2	
	Gage blocks, 138
	Gage factor, 326
Fahrenheit ton	Gam, 100
Pahrenheit temperature scale, 230	Galvanometer, principles, 77
Feedback in general measurement sys-	tabulation, 78

as used in bridge circuits 95

Garnma rays, detection, 368

tem, 14

Fick's faw, 293

Gases, properties of, 401 Gaussian distribution, 46-53 values of, 49, 50 Geiger-Müller counter, 368 counting performance, 369 Generalized measurement system, 13-15 Gettelman, C. C., 227 Giardini, A. A., 176 Gier, J. T., 365, 366, 380 Glaser, P. E., 365, 380 Gorton, C. W., 228 Gracey, W., 227 Graneck, M., 143, 152 Graphical analysis, 67-70 Gray body, 253 Graybill, F. A., 74 Green, C. B., 277 Gross, E. E., 358 Guarded hot-plate apparatus, 281

Hackforth, H. L., 277, 359, 360, 380 Hall, H. T., 176 Hall coefficients, 131 Hall-effect transducers, 130 Harris, C. M., 338, 358 Harrison, H. L., 391 Heise gage, 161 Helmholtz cavity, resonant frequency, 156 Hetenyi, M., 165, 176, 338, 358 Higgins, W. F., 285, 309 High-low control, 384 High-speed temperature probe, 270 Hildebrand, F. B., 149, 152 Hedges, H. D., 228 Holman, J. P., 278 Hot-wire probe, 202 Howe, W. H., 176 Hyde, W. L., 350 Hysteresis, 7

Iberall, A. S., 176
Ideal gas flow, 182
Illumination measurement, 125, 126
Impedance matching, general discussion,
23
Incompressible fluid, flow, 180

Index of refraction, 206
Input circuitry, 84-88
Intensity of sound wave, 352
Interference principle, 139
Interference principle, 139
Interferometer, density related to, 214
for dimensional measurements, 140
as flow-visualization device, 211-214
International Temperature Scale, 11
Ionization chambers, 370
Ionization displacement transducer, 127
Ionization vacuum gage, 171
Iron-vane instrument, 79

Jackson, T. W., 228 Jakob, M., 309 Junker's calorimeter, 298

Kallen, H. P., 391
Kaplan, I., 367, 380
Kaye, G. W. C., 285, 309
Kelvin temperature scale, 230
Keyes, F. G., 285, 309
Kiel probe, 218
King, L. V., 227
Kline, S. J., 37, 74, 206, 228
Knudsen gage, 170
Kovasznay, L. S. G., 203, 227
Krause, L. N., 227

Ladenburg, R. W., 228
Lafferty, J. M., 167, 176
Lag, 381
Landes, L. G., 228
Laurence, J. C., 228
Least count, 7
Least squares, method of, 61-64
Leidenfrost, W., 287, 309
Length standards, 9
Liepmann, H. W., 228
Linear variable differential transformer,
119
characteristics of, 120
Linearity, definition, 18

Lion, K. S., 125, 128, 134, 244, 278

Liquid-in-glass thermometer, 231 Liquid level measurement, 122 Liquids, properties of, 400 Lessjous diagrams, 108 Lesner, H. R., 338 Uoyd, E. C., 176 Loading error, 86 Lobed-impeller flowmeter, 179 Loschmidt apparatus, 295

McAdams, W. H , 278 McChatock, F. A , 37, 74 McLeod gage, 167 Magnetic field measurements, Hall effect, 130 search coil, 128

Magnetic flowmeters, 203 Magnetometer search coil, 128 Manometers, 157 Marco, S M , 402 Marcus, N , 380, 384 Mass balance, 312 Mass atandards, 9 Mean free path, 155 Mean molecular velocity, 154 Mean solar day, 10 Measurement system, dynamic, 15-20 generalized, 13-15 response, 20-22

Metals, properties of, 400 Micrometer calipers, 137 Microphones, characteristics of, 353 Miesse, C. C , 222, 228

Moments of inertia, 404 Mood, A. M., 74

Multisample data, 24

(See also Seismic instrument) Neubert, H. K. P., 176 Neutron detection, 372 Newton-Cotes integration formulas, 149 Noise, 353 Nonmetals, properties of, 400 Normal error curve (see Gaussian distribution)

Natural frequency of tube cavity, 156

Nozzle, sonic, 195 Nozzle flowmeter, 183, 185, 187 Nuclear radiation measurement, 368-378 Numerical integration, plane areas, 148 surface areas, 149 Nutating-disk meter, 178

Obert, E. F., 12, 31, 229, 278 Obstruction flowmeter, 180 Offset in control systems, 385 On-off control, 383 Optical pyrometer, 255 Orifice flow meter, 184, 189 Oscillograph, 110 Oscilloscope, 105 dual-beam, 107 measurement, frequency, 108 phase-shift, 103

used with electronic awatch, 107

Pearson, G. L. 277 Performance testing distinguished from research, 4 Perry, C. C. 338 Perry, R. H., 403 Peters, C G , 152 Phase shift, definition, 17 measurement, electronic counter, 114 oscilloscope, 103 in seismic instrument, 313 Phillips, E. A., 338

Photoconductive transducer, 126 Photoelectric transducer, 125 Photographic methods for nuclear radio ation detection, 371 Photovoltane cells, 125

Piezoelectric constants, 124 Prezoelectric transducers, 123 Pirani gage, 169 Pitot tube, 218

Plan for general experiment, 25, 28 Planck distribution, 252 Planimeter, polar, 144 145 zero zirele of, 146

roller, 146 Pasumatic displacement page, 141

Poisson distribution, definition, 46 standard deviation, 374 used with nuclear radiation, 373 Poisson's ratio, 323 Positive-displacement meter, 178 Potentiometer, with battery standardization, SS simple, 87 Power measurement, 320 Precision, 8 Pressure, absolute, 153 gage, 153 units, 154 Pressure gage, dynamie response, 156 Pressure measurements, bellows gage, 162-164 bourdon gage, 161 diaphragm gage, 162 dynamie response, 155-157 for high pressures, 166 for low pressures, 167 manometer, 157 Pressure probes, basic relations, 216 effect of yaw angle, 217 Mach number effects, 220 Price, W. J., 359, 367, 370, 372, 380 Probability, definition, 42 relation to frequency, 42 rules for calculating, 43 Probability distributions, binomial, 45 definition, 44 Gaussian, 46 Poisson, 46 Programming in data acquisition, 395 Prony brake, 320 Proportional band, 385 Proportional control, 384 Proving ring, 319 Pulse counters in nuclear measurements, 369 Purdy, K. R., 228

Quartz-crystal thermometer, 250

Radiation error in temperature measurement, 262 Radiation shield in temperature measurements, 263 Radiometer, with thermistor, 362 with thermopile, 361 Random errors, 35 Rankine temperature scale, 230 Rate action in control systems, 387 Rate time in control systems, 387 Ratio arms in bridge eircuits, 91 Rayle, R. E., 196, 228 Readability, 7 Recovery factor, 270 Recovery temperature, 270 Redheffer, R. M., 152 Reed, R. H., 228 Refractive index, 206 Regulation, 383 Relative performance, 26 Report writing, 29 Research distinguished from performance testing, 4 Reset action, 385 Resistance thermometer, 235 Resistance transducer, 118 Reynolds number for flowmeters, 190 Rise time, definition, 20 Roark, R. J., 163, 176 Rosettes for strain gages, 332 Roshko, A., 228 Rossini, F. D., 229, 278 Rotameter, influence of density, 199 principles, 198 Rotary-vane flowmeter, 179

Sandell, D. J., 285, 309
Saybolt seconds, 292
Saybolt viscosimeter, 291
Scanner programmer, 394
Schenck, H., 74
Schlieren, 208
knife edge in, 209
Schneider, P. J., 260, 278
Schraub, F. A., 206, 228
Schulze, W. M., 228
Scintillation counter, 372
Scars, F. W., 229, 278



Thermometers, electrical-resistance, 235 fluid expansion, 234 for high speed flow, 270 liquid-in-glass, 231 optical, 255 quartz-crystal, 250 summary of characteristics, 271 thermistor, 237-240 thermocouple, 243 transient response of, 264 Thermopile, 247 used in radiometer, 361 Time constant, definition, 21 for thermocouples, 267 Time interval measurements, 114 Time standards, 10 Titanium tetraehloride as smoke generstor, 216 Torque measurement, 320 Transducers, capacitive, 121-123 differential (LVDT), 118-119 general definition, 13 Hall-effect, 130 ionization, 127 photoconductive, 126 photoelectrie, 125 piezoeleetrie, 123 summary of characteristics, 116-117 variable-resistance, 118 Trapezoidal rule, 148 Traveling sound wave, 354 Tribus, M., 229, 278 Truxal, J. C., 391 Tsao, C. H., 338 Tube-cavity arrangement, natural frequency, 156 Turbine flowmeter, 200 Tuve, G. L., 228, 299, 309 Two-position control, 383

Unbonded strain gage, 335
Uncertainty, calculation, 38
general discussion, 35
in nuclear radiation measurements, 375
Unit strain, axial, 323
transverse, 323

Vacuum, definition, 153 Vacuum gages, Alphatron, 172 ionization, 171 Knudsen, 170 McLeod, 167 Pirani, 169 Vacuum-tube voltmeter, 102 Van Dusen, M. S., 282, 309 Variance, definition, 41 Venturi flowmeter, 183, 185, 187 Vernier calipers, 136 Vibrating cantilever beam, 340 Vibrating wedge, 340 Vibration measurements (see Seismic instrument) Vines, R. G., 285, 286, 309 Viscosity, definition, 287 related to fluid shear, 288 Viscosity measurement, capillary, 290 rotating cylinder, 289 Saybolt method, 291 Voltage-divider circuit, 86 Voltage-sensitive input circuit, 85 Voltmeter, D'Arsonval, 82 electrostatie, 83 vacuum-tube, 102

Water, properties of, 402
West, W. E., 278
Westwater, J. W., 278
Wheatstone bridge, basic circuit, 90
deflection analysis, 95
Wien's law, 254
Wildhack, W. A., 176
Wilson, E. B., 33, 74
Winkler, E. M., 270, 278
Wolfe, W., 380

Yaw angle, influence on pressure probes, 218 Young, H. D., 74 Young's modulus, 316

Zero circle of planimeter, 146

